

ANNUAL HOME-IDEA ISSUE

POPULAR SCIENCE

SEPTEMBER • 35¢ *Monthly*

Compact Workshop

**Shares
Garage
with
Compact
Car**

PAGE 152



SPECIAL:

PAGE 45

Let's Get Rolling on Car Safety!

Stop envying the other fellow's "Lucky Breaks"— AND START TO MAKE YOUR OWN!

Chances are there's at least one fellow you know who keeps right on moving ahead. The one who never seems plagued by financial worries. Who drives a new car... owns a luxurious home... takes nice vacation trips.

Maybe you've even caught yourself thinking: "Boy, how I wish I had his lucky breaks!"

Well, you can start right now to make your own "breaks"! Not through wishful thinking, but through your own ability and determination—coupled with specialized training to set yourself apart from the ordinary worker. Because these days, the "breaks" come to men who are prepared for them.

And that's where International Correspondence Schools can help you, as it has helped so many hundreds of thousands of able, ambitious men and women. By preparing you now for a successful, rewarding future in any



one of more than 250 important job categories.

Here's what you get. Personalized instruction prepared by experts. Practical facts and theory you can start to apply at once on the job. The opportunity to progress at your own pace, at home, in spare time. And equally important, the coveted I.C.S. diploma—universally recognized as the mark of a man who's on his way up!

Think it over. Don't you owe it to yourself to at least find out how I.C.S. can help you? Fill in the coupon and mail it now, while you're still thinking about it. By return mail you'll receive a FREE Career Kit with 3 famous booklets: (1) a Career Guide Handbook, (2) a complete catalog of job opportunities in your field of interest, (3) a sample lesson to demonstrate the success-proven I.C.S. method.

Don't keep on envying "the other fellow"... mail that coupon!

For Real Job Security—Get an I. C. S. Diploma!

I. C. S., Scranton 15, Penna.

Accredited Member,
National Home Study Council

INTERNATIONAL CORRESPONDENCE SCHOOLS



BOX 24085J, SCRANTON 15, PENNA.

(In Reply, reply P.O. Box 422, Montreal)

(Partial list of courses)

Without cost or obligation, send me "HOW TO SUCCEED" and the opportunity booklet about the field BEFORE which I have marked X (plus sample lesson):

ARCHITECTURE and BUILDING CONSTRUCTION

- ☐ Air Conditioning
- ☐ Architecture
- ☐ Arch. Drawing and Designing
- ☐ Building Contractor
- ☐ Building Estimator
- ☐ Carpenter Builder
- ☐ Carpentry and Millwork
- ☐ Heating
- ☐ Painting Contractor
- ☐ Plumbing
- ☐ Reading Arch. Blueprints

ART

- ☐ Commercial Art
- ☐ Magazine Illustr.
- ☐ Sign Painting and Design's
- ☐ Sketching and Painting

AUTOMOTIVE

- ☐ Automobile
- ☐ Auto Body Rebuilding and Refinishing
- ☐ Auto Engine Tuning
- ☐ Auto Electrical Technician
- ☐ Diesel Engines

AVIATION

- ☐ Aero-Engineering Technology
- ☐ Aviation Engine Mech.
- ☐ Reading Aircraft Blueprints

BUSINESS

- ☐ Accounting
- ☐ Advertising
- ☐ Bookkeeping and Cost Accounting
- ☐ Business Administration
- ☐ Business Management
- ☐ Clerk Typist
- ☐ Creative Salesmanship
- ☐ Managing a Small Business
- ☐ Professional Secretary
- ☐ Public Accounting
- ☐ Purchasing Agent
- ☐ Real Estate Salesmanship
- ☐ Salesmanship
- ☐ Salesmanship and Management
- ☐ Traffic Management

CHEMICAL

- ☐ Analytical Chemistry
- ☐ Chemical Engineering
- ☐ Chem. Lab. Technician
- ☐ General Chemistry

- ☐ Oil Field Technology
- ☐ Pulp and Paper Making

CIVIL ENGINEERING

- ☐ Civil Engineering
- ☐ Construction Engineering
- ☐ Highway Engineering
- ☐ Professional Engineer (Civil)
- ☐ Reading Struc. Blueprints
- ☐ Sanitary Engineer
- ☐ Sewage Plant Operator
- ☐ Structural Engineering
- ☐ Surveying and Mapping
- ☐ Water Works Operator

DRAFTING

- ☐ Aircraft Drafting
- ☐ Architectural Drafting
- ☐ Drafting & Machine Design
- ☐ Electrical Drafting
- ☐ Electrical Engineer Drafting
- ☐ Industrial Piping Drafting
- ☐ Mechanical Drafting
- ☐ Sheet Metal Drafting

ELECTRICAL

- ☐ Electrical Appliance Servicing
- ☐ Electrical Engineering

- ☐ Electric Motor Repairman
- ☐ Elec. Engr. Technician
- ☐ Elec. Light and Power
- ☐ Practical Electrician
- ☐ Practical Lineman
- ☐ Professional Engineer

HIGH SCHOOL

- ☐ Good English
- ☐ High School Diploma
- ☐ High School General
- ☐ H. S. College Prep.
- ☐ (Eng'g & Science)
- ☐ High School Math
- ☐ High School Science
- ☐ Short Story Writing

LEADERSHIP

- ☐ Industrial Foremanship
- ☐ Industrial Supervision
- ☐ Personnel-Labor Relations
- ☐ Supervision

MECHANICAL and SHOP

- ☐ Diesel Engines
- ☐ Gas-Elec. Welding
- ☐ Heating and Air Conditioning
- ☐ Industrial Engineering
- ☐ Industrial Instrumentation

- ☐ Industrial Safety
- ☐ Machine Shop Practice
- ☐ Mechanical Engineering
- ☐ Plumbing and Heating
- ☐ Professional Engineer
- ☐ Quality Control
- ☐ Reading Shop Blueprints
- ☐ Refrigeration and Air Conditioning
- ☐ Tool Design
- ☐ Tool Making

RADIO, TELEVISION

- ☐ General Electronics Tech.
- ☐ Industrial Electronics
- ☐ Practical Radio-TV Eng'g
- ☐ Radio-TV Servicing
- ☐ TV Technician

RAILROAD

- ☐ General Railroad

STEAM and DIESEL POWER

- ☐ Combustion Engineering
- ☐ Power Plant Engineer
- ☐ Stationary Diesel Engr.
- ☐ Stationary Steam Engineer

TEXTILE

- ☐ General

Name _____ Age _____ Home Address _____

City _____ Zone _____ State _____ Working Hours _____ A.M. to P.M. _____

Occupation _____


Canadian residents send coupon to International Correspondence Schools, Canadian, Ltd., Montreal, Canada. ... Special low monthly tuition rates to members of the U. S. Armed Forces.

ARMSTRONG SAFETY DISCS CAN SAVE YOUR LIFE!



**ONLY ARMSTRONG TIRES HAVE
THIS PATENTED SAFETY DISC TREAD**
— Makes them grip the road to stop
deadly skids as no other tires can.


When you hit your brakes, the weight of your car is thrown on the tires. Their tread can be squeezed together into a smooth, slippery surface. To overcome this danger, Armstrong engineers invented the famous Safety Disc tread design, which holds the tread ribs open, always ready to grip the road to stop deadly skids.



OVER 1000 SAFETY DISCS

are *molded* between the tread ribs of the Armstrong tire. Just as the discs in hand at left keep the fingers apart, so Safety Discs keep the tire's gripping edges apart. They can't squeeze smooth, no matter how hard you brake. But the tread of ordinary tires, lacking discs, can squeeze together, go smooth . . . and you skid!

**Patented Interlocking Sipes
ADD GRIP in ALL DIRECTIONS**



Sipes are slots put in tire tread to add gripping edges. Armstrong's S-shape interlocking siping gives sharply improved traction to protect against both forward and side skids.

ARMSTRONG EXCLUSIVE UNI-CUSHION CONTOUR



Puts more rubber on the road — where it counts!
Gives greater traction, more even wear.

Diagrams show Armstrong tread is flatter when inflated and rolling. Gives more road contact, greater stability and traction — vital for today's high-power cars and express highways. Armstrong Tires grip the road to stop deadly skids as no other tires can!

**GET EXTRA SAFETY AT NO EXTRA COST WITH
ARMSTRONG TIRES!**

ARMSTRONG RUBBER COMPANY, Home Office, West Haven, Conn.

AS LOW AS
\$10⁹⁵
(6.70 x 15)

plus tax and your
recappable tire



Radar spotter: A squeal says "cops ahead." P. 61



Renault R14: How come no grease fittings? P. 58



Lefties: Pity the poor southpaw. P. 103

Founded in 1872 Vol. 179 No. 3

Mechanics and Handicraft REG. U.S. PAT. OFF.

Popular Science

September, 1961

Cover photo by W. W. Morris and R. D. Borst

CARS AND DRIVING

First of a PS series on auto safety reveals the shocking truth about—
Why Cars Aren't Made Safe..... 45

- The Car You Can't Grease..... 58**
- Gadget Spots Radar Trap—But.... 61**
- Inside the New and Bigger VW.... 74**
- The President Gets a New Car..... 90**

SCIENCE AND INDUSTRY

- A-Blast That Couldn't Happen..... 52**
- Jet Hydro Tests Model Hulls..... 56**
- How a Player Piano Works..... 94**

DISCOVERIES AND INVENTIONS

- Why Inventing Is a One-Man Job.. 70**
- What's New in Photography..... 92**

SPECIAL FEATURES

- Starlings: Public Nuisance No. 1.. 66**
- M60—World's Toughest Tank.... 82**
- Civil War Weapons: Balloons..... 86**
- Remember the B-36?..... 98**
- It's a Clumsy World for Lefty..... 103**
- Adventures of Secret Service: II.. 108**

PICTURE NEWS

- Blimp Serves as Wind Tunnel..... 51**
- How to Pack Swimming Goldfish.. 60**
- Trailer Becomes Boat or Tent..... 64**
- Space Probe to Fly Past Venus.... 73**
- More Bite for the Sprite..... 97**
- His Car Is an Eight-Wheeler..... 102**
- Fire Trucks Control Traffic..... 106**

AUTO UPKEEP

- Hints from the Model Garage.... 198**
- Gus Makes a Fast Getaway..... 202**

Editor HOWARD ALLAWAY

Assistant Managing Editors
Kandall W. Goodwyn, Robert P. Stevenson

Senior Editors
Alden P. Armagnac, Devon Francis
Martin Mann, Everett H. Ormer

Technical Editor
Hubert Luckett

West Coast Editor
Wesley S. Griswold

Managing Editor FRANK ROWSOME JR.

Associate Editors
Frank Dorr, Sheldon M. Gallager
Herbert O. Johansen, Alfred W. Lees
Alex Markovich, Herbert R. Pfister
Joan Steen, Ruth Westphal

Editorial Assistants
Ross Lee Beeland (Chief), Anna Dallas
Phyllis Farber, Wanda H. Joseph
Georgette Sparks, Dorothy Zallen

EDITORIAL OFFICES: 355 Lexington Ave., New York 17, N. Y.

Art Director HOWARD C. JENSEN

Art Editors
Herbert Anthony, Reginald A. Hawley
Harry Samuels

Art Associates
Eric A. Karminski Jr.
Henry W. Karminski, Richard J. Meyer

Photography
W. W. Morris (Chief)
Robert D. Borst, Eugene Colangelo



Caning: *Finishing your Kennedy rocker. P. 112*



Painting: *For a slick job, spray it on hot. P. 126*



Shell home: *What makes it such a bargain? P. 143*

Monthly

**America's
NEW-IDEA MAGAZINE
for 89 Years**

FOR HOME AND SHOP

Caning the Kennedy Rocker.....	112
On the Trail of No Raster.....	119
A Model Boat That Flips to Go....	122
Compost Chopper from Mower....	124
For Better Painting, Spray Hot....	126
One Machinist Tells Another.....	128
Boating Hints.....	132
How You Can Track a Hurricane	136
Speed Reducer for Your Lathe.....	137
The Man's Sewing Tool.....	138

SHORT CUTS AND TIPS

Jig for Cutting Box Joints.....	118
Depth Gauges for Drill Bits.....	125
Safety Lock for Metal Tool Box..	131
Auxiliary Bench Saves Stooping..	133
Shaping Brace for Radial Saw....	140
Pull-Down Attic Stairway.....	177

HOME-IMPROVEMENT SUPPLEMENT New Projects for Better Living

Biggest Bargain: A Shell Home....	143
Compact Car—Compact Shop....	152
Using Prefab Iron Railings.....	158
A Planter That Fools the Eye.....	164
Study Desk Hides Hobby Bench..	178
New for Home Improvement.....	182
Prize-Winning Ideas.....	188
Build a Home Theater Wall.....	194

EVERY MONTH

PS Readers Talk Back.....	4
The Month in Science.....	21
PS Puzzlers.....	24
Detroit Report	42
New Ideas from the Inventors.....	79
I'd Like to See Them Make.....	85
Wordless Workshop	134

PUBLISHED MONTHLY by Popular Science Publishing Co., Inc., 355 Lexington Ave., New York 17, N. Y.

E. S. DUFFIELD
President and Publisher

JOHN R. WHITING
Executive Vice President

EUGENE WATSON
Vice President and Circulation Director

LEE P. ADAMS
Vice President and Advertising Director

SUBSCRIPTION SERVICE


New or Renewal Orders: Send to Popular Science Subscription Department, 355 Lexington Ave., New York 17, N. Y. One year \$3.40, 2 years \$6, 3 years \$8 in U.S., its possessions, and Canada. Elsewhere, 1 year \$6, 2 years \$11, 3 years \$16. Single copy 35¢.

All Subscription Adjustments: Write to John Walker, Popular Science, P.O. Box 2059, New York 17, N. Y. For change of address allow four weeks; please give both old and new addresses. Notices of undelivered copies (Form 3579) to Mr. Walker.

ADVERTISING OFFICES

NEW YORK—355 Lexington Ave.
CHICAGO—360 North Michigan Ave.
DETROIT—2810 Book Bldg.
SAN FRANCISCO—114 Sansome St.
CLEVELAND—636 B. F. Keith Bldg.
LOS ANGELES—711 South Vermont
PORTLAND, ORE.—520 S. W. Sixth Ave.

Second class postage paid at New York, N.Y., and at additional mailing offices. Entered as second class matter at the Post Office Department, Canada. Printed in U.S.A. Copyright © 1961 by Popular Science Publishing Co., Inc. All rights reserved.



PS Readers

TALK BACK



Why Can't Johnny Figure?

IN PHOENIX, Ariz., I got two tickets for going through yellow lights. There, lights are set for three-second amber and you must clear before the red. At 35 m.p.h. a car goes 154 feet in three seconds. It takes 110 feet for a safe stop, car length is 18 feet, and the street is 50-60 feet. This makes 178-188 feet to be cleared—including a zone of 24 feet or more in which you can't avoid a violation.

At a public meeting in Phoenix, I had to work the above problem twice on a blackboard before a city engineer admitted that I was right. Why make studies? Simple arithmetic seems adequate.

Later I wrote to the Safety Engineering School at one of the big universities. The director replied that three seconds is ample to cover 150 feet and get through a yellow light at 35 m.p.h. But a manual put out by the Department of Agriculture calls for a *minimum* of five seconds. I pull a 27-foot trailer, and I need all five seconds.

Our education system sure is going downhill. When the director of a traffic school can't figure his way through a traffic light, we've really hit bottom.

RALPH KYLE, Homestead, Fla.

The Case for the Rule

WE READ with astonishment the letter from Dr. A. B. Craig [June] detailing his distrust of rules and—we assume—measuring devices of all kinds.

Would he outlaw airplanes because of an occasional mishap? Would he forego electricity because a fuse blows? One unfortunate soul accidentally cuts off a piece of his rule and the doctor advises a re-

turn to the Middle Ages, measuring with thumb, hand, foot, or nose.

The wood folding rule is always high on the list of basic tools for all handy-men, whether mechanics by trade or professional men seeking relaxation in their basement workshop.

S. A. SCHNEIDER, Vice-Pres.

Durall Tool Corp., Yonkers, N. Y.

I'd Like to See Detroit Make. . .

WHY doesn't somebody come up with a four-speed hand shift to these specs: fourth speed to be direct but free-wheeling teamed with a low-ratio (2.75:1) rear end for open-road, high-speed travel; second and third for driving in traffic; first with a higher ratio for real low-gear loads, higher than now available.

I'd also welcome the return of the easy shifting my '54 Dodge had. You could push it from first to second with one finger, and no hunting.

MARTIN HUIKKO, Litchfield, Minn.

Deprived of His Java

ALAS, that \$1,500 coffee machine ["How a Coffee Machine Works," May] can't dispense coffee the way I, and many other folks, like it. The selector



panel shown gives me a choice of every combination of coffee, cream, and sugar except the one I prefer: cream, no sugar.

H. BUTLER, Des Moines

Don't Blame It on Gus

AFTER reading "Gus Separates the Men from the Boys" [June], I am afraid that he has separated me from some of the basic principles of trouble-shooting. As Aircraft Maintenance Officer of Patrol

5 reasons why ACCOUNTING



offers you

MORE MONEY and SUCCESS



**SEND FOR FREE
SAMPLE LESSON**

REASON #1. If you were an expert accountant right now, chances are you would find yourself in one of the best paid fields of business.

REASON #2. The demand for accountants is great—everywhere. All businesses must have trained accountants to cope with ever-growing requirements. It's a field offering wide opportunity—always—to the man who knows.

REASON #3. You can fit into any business, anywhere in the country—because accounting principles are universal. Think what this means in terms of security and independence!

REASON #4. Accounting is open to all. Any man or woman of good intelligence, who enjoys figure work and is willing to follow LaSalle's systematic "problem method" plan, can rapidly qualify for a highly profitable, enjoyable lifetime career . . . and he doesn't have to finish his training before beginning to "cash in."

REASON #5. Without losing a day from your present work, you can prepare in spare hours at home, at low cost, under LaSalle's step-by-step "Problem Method" of "learning by doing." This famous plan accounts for LaSalle's remarkable record of having trained one out of every 13 of all Certified Public Accountants in the U. S. . . . and of having put many thousands of others into high-paying careers.

Send today for Free Sample Lesson and "Opportunities in Accounting." Learn about the several great fields of opportunity . . . and LaSalle's time-tested plan for helping men and women to rapid advancement, higher income and greater prestige. The coupon below will bring this information to you—without cost or obligation.

Accredited Member, National Home Study Council

SEND FOR FREE BOOK



LaSalle Extension University
— A Correspondence Institution —

Dept. 983H 417 S. Dearborn St., Chicago 5, Ill.
Please send me, free of all cost or obligation, free sample lesson and your latest book, "Opportunities in Accounting."

Name.....Age.....

Address.....

City, Zone, State.....

LASALLE
417 S. Dearborn St.,
CHICAGO 5, ILL.

CRESCENT ADJUSTABLE WRENCHES



Crescent offers unequalled value, performance and selection in Adjustable Wrenches. Choose CRESTOLOY for greatest strength and finest finish in 4" to 24" sizes, single and double end patterns; CRESCENT for toughness and durability at lesser cost in 4" to 18" sizes. Also insulated handles on the 12" CRESTOLOY. See CRESTOLOCK, the new locking adjustable wrench.

Sold by hardware dealers everywhere.

CRESCENT TOOLS

Give Wings to Work



Write for booklet "How to Use Hand Tools." It's FREE. Address Dept. PS-9.

CRESCENT TOOL COMPANY, JAMESTOWN, N. Y.

Squadron Twenty-Four, I must question Gus's "with a faulty exhaust valve, I would have heard it leaking into the crankcase when I removed the breather-cap valve."

DANIEL J. SLIWINSKI,
Lt. Cmdr., U.S. Navy.

... IF GUS WILSON can put pressure in the top of a cylinder and hear a valve leak in the crankcase—boy, has he got something wrong!

ARNOT J. JEFFERS, Radcliff, Ohio.

... A PRINTER's gremlin seems to have swiped a few lines from the Gus Wilson piece. I am sure that experienced mechanics had no trouble supplying the missing text, but some readers might possibly have become confused.

VLADIMIR GIRSS, Oakley, Calif.

You are absolutely right about the error in the June Gus Wilson story. But, as reader Girss guessed, it wasn't Gus



who goofed—it was the printer and the proofreaders who failed to notice that several lines of type were somehow omitted from the text.

Originally, Gus's diagnosis read like this: "With a faulty exhaust valve I would have heard air leaking into the exhaust pipe. With a faulty intake valve I would have heard it leaking into the carburetor manifold. With leaking rings I'd have heard it leaking into the crankcase when I removed the breather-pipe cap."

Thanks for keeping us on the ball.

Hint for Sign Makers

TELL Mr. Corey to use the remains of a broken tempered auto glass for the letters ["Reflective Sign from Glass Chips," May p. 125] and he won't need to break up scrap glass. When tempered glass breaks, it practically explodes—no piece is more than 1/4-inch square.

A. L. MELCHER, Wisner, Nebr.

CONTINUED




*Autolite, the sparkplug that cleans itself
while you drive,
is now standard equipment on the Ford Family of Fine Cars.*

This unique performance and economy feature is one of the reasons why Ford Motor Company, and several other car makers, specify Autolite Spark Plugs as standard equipment on every car they build.


The Autolite Power Tip is longer than the tip of ordinary plugs. It extends much deeper into your engine. Deposits are literally burned off by the exploding gasoline.

If your present plugs are killing the pep and mileage in your car, try Autolite, the spark plug that cleans itself while you drive.

AUTOLITE  SPARK PLUGS

Now standard equipment on the Ford Family of Fine Cars.

LEARN BY PRACTICING! YOU
GET 25 KITS TO BUILD THIS
HEAVY-DUTY CONDENSING UNIT



It's easier to succeed in **Air Conditioning and Refrigeration— the uncrowded top-pay field**

Make no mistake about it: Your opportunities to make big money are best in the uncrowded air conditioning and refrigeration field. Judge for yourself! During a recent 6-month period, the production of commercial compressors increased 40%! Over 3 million refrigerators, freezers and air conditioners are sold yearly. Today more than 150 million units need maintenance. Experts say that 20,000 newly-trained technicians must enter the industry annually to fill top-pay jobs or to open service shops.

Learn at home in spare time by practicing. CTI sends tools and parts to build a 1/4 hp commercial-quality condensing unit. You build a refrigerator, freezer, air conditioner or milk cooler. Many students earn money fixing units while training.

Mail coupon for new catalog and lesson samples. No cost nor obligation. See if air conditioning isn't really best for you—easiest to master—more loaded with big-job opportunities. Act now!—Commercial Trades Institute (a non-profit organization), Chicago 26, Ill.

COMMERCIAL TRADES INSTITUTE

Dept. R-985

1400 GREENLEAF AVE. • CHICAGO 26, ILL.

Send booklets *Success in Air Conditioning & Refrigeration* and Lesson Samples. Both FREE.

Name _____ Age _____

Address _____

City _____ Zone _____ State _____

Accredited by National Home Study Council



Word from the Animal Lovers

FROM the spelling of the names, I'd guess Tico and Tina ["My Two Dogs Never Meet," May] must be male and female. Considering that Tina is only six months old, I think her owner was a little premature in the construction of his elaborate maze—time should take care of the feud between the two.

Or maybe he figures it as a deterrent to batches of unwanted pups? If so, one thing puzzles me: What will happen



when Tina becomes very attractive to Tico and Tico decides to linger in pen A, waiting for his glamorpup, instead of passing on to pen B as he should? Unless I misread the drawing, it seems he has to pass through Tina's pen to get to his own. Somebody had better work fast on this problem unless there are lots of kids in the neighborhood who'd just love to take home a puppy.

L. L. HOWELL, Scranton, Pa.

... IF YOU wish to keep me as a reader, keep articles on murdering our wildlife out of POPULAR SCIENCE. I refer specifically to "ABC's of Crow Hunting" [Apr.]. Leave that stuff for magazines that cater to "sportsmen," another name for sadists.

W. F. HECKMAN, Hillsboro, Ore.

... I SAY Mr. Laycock doesn't know his turtles ["Nature's Most Successful Animal," Apr.]. The turtle captioned "Prehistoric Monster" is either a Troost or Map turtle—a fresh-water turtle—and it cannot pull in all its extremities when mature. Its humped back has nothing to do with it.

LEON HOLUB, Island Park, N.Y.


Gumbo-Loving Trencher

Who says the Bus Brown machine is not successful in hard ground ["The Machine Way to Dig Ditches," Apr.]? I own one of these trenchers and it's sure good. My state has some of the toughest gumbo

CONTINUED

When other
truck tires
are ready
for recaps . . .

this
Firestone
TRANSPORT-100
is still
ready to roll



Both tires unretouched—ran identical mileage. Records provided on request.

BIG CLAIM? Big reason! Because over 109,000,000 test miles (logged by more than 200 independent fleets all over the country) prove you really can get an extra tire mile for every two you now haul! Why? Because the Transport-100's new broad center rib minimizes squirming and scuff wear. A flatter crown gives the Transport-100 a better grip and cuts down on uneven wear. You can get the extra 50% mileage in the Transport-100 at no extra cost. Available in nylon or Tyrex[®] rayon cord, tubed or tubeless at your nearby Firestone Dealer or Store.

Specify Firestone Tires on New Trucks and Trailers
Copyright 1961, The Firestone Tire & Rubber Company

MEMBER  **AMERICAN TRUCKING INDUSTRY**
a T.M. of Tyrex, Inc.

TRANSPORT-100
Transport is a T.M. Firestone

Learn Electronics Radio-Television

by Practicing at Home
in Your Spare Time

WITHOUT EXTRA
CHARGE you get
bits to make
learning easier
faster



Fast Growth Offers Prestige High Pay—Bright Future

Above average jobs with bright futures await men with Electronics training... jobs for which YOU could qualify through NRI. Train right at home in spare time, while you hold your present job. Earn high pay in jobs with TV and Radio Stations, industrial plants, or in a profitable business of your own.


NRI TRAINED THESE MEN



Own Business.
"I was working in a textile factory. Now I own a modern TV Radio service shop." A. TAYLOR, Glasgow, Ky.

Broadcasting.

"I am now chief engineer of Station WARA. NRI was the foundation." R. ARNOLD, Attleboro, Mass.



Industrial.
"Four months after starting your course I went to work at Raytheon."

Now I am an engineering assistant in Microwave Power Tube Research." L. J. BLOOM, Newton Centre, Mass.

Train with the Leader

For 45 years NRI has featured the best Radio-TV Electronics training for beginners—for men without high school diplomas or previous experience. NRI is the oldest and largest home-study Radio-TV Electronics school. NRI "learn-by-doing" training is supplied at low cost. It's the easy way to get into the field of Electronics.

Start Soon to Earn More

Soon after enrolling, NRI shows you how to earn extra money in your spare time repairing sets. Many start a profitable business this way. Others get good paying jobs within a year. Take the first step to a new career NOW. Mail coupon for descriptive catalog. National Radio Institute, Washington 18, D.C.

**64 PAGE
CATALOG
FREE**



MAIL THIS COUPON NOW

NATIONAL RADIO INSTITUTE, Washington 18, D.C. 1/3
Send me full information without cost or obligation. No salesman will call. (Please print)

Name.....Age.....

Address.....

City.....Zone.....State.....

Accredited Member National Home Study Council

I've ever dug into and my trencher digs right along. I've even cut a trench across an oiled street. My machine, a 468R, digs four inches wide and six feet deep.

H. B. McMILLAN, Draper, S. D.

Tips-to-Share Department

To MAKE it impossible to "raise" a check I've written, I stick cellulose tape over the amount. After trying many ways of removing the tape, I'd say it's impossible to do so without damaging the check. I think my protective system is as foolproof as many requiring special equipment.

R. RAMNATH, Bombay, India.

... MY BROTHER and I make up our own goop for cleaning our car engines. Instead of paying for high-priced cleaning fluid, we mix some highly concentrated liquid detergent (purchased for dish washing) and kerosene. When the



mixture is sprayed on the engine from a bug-spray can, it cleans as well as the commercial stuff and at half the price.

JARED SMITH, Neptune Beach, Fla.

... I MADE an interesting discovery while playing around with laundry bleach. When an old felt pen (used for inking in posters) is cleaned with carbon tet and refilled with liquid laundry bleach, it makes a fine ink eradicator. And it's a lot simpler to use than the old two-bottle ink-eradicator routine.

DAVID PIERCE, Detroit.

... WELDING a nut on the shank of a screwdriver so you can get extra leverage with a wrench ["Hints from the Model Garage," June] brings to mind a handy idea thought up by my brother. He had one of those multiple screwdriver deals with a half-dozen shanks and one handle. One day he exerted too much pressure and thereafter had the shanks but no handle. But for extra leverage, and better control while utilizing it, he put a screwdriver shank in a tap wrench. This

What to do about high repair bills...



for about half your driving
**Your engine needs
an overcoat**

All but about 1/10 of your horsepower stays "under wraps", not being used, during most of your driving time. Result: incomplete burning of gas, carbon deposits, sludge build-up and excessive engine wear that lead to repair and replacement expense.

But Pennzoi Z-7 stops that. Gives your engine the *full-time* lubrication protection it needs. Stands up under the grind of low-speed traffic as well

as high speeds. And its power ingredient, Z-7, keeps engine parts *clean*, straight through to the next oil change.

So end unnecessary repairs. Get more miles per gallon and stepped-up all-around performance with Pennzoi. Ask for Pennzoi Z-7 by name at your service station, garage or car dealer. Always be sure that you remember to sound the "Z" that makes PENNSylvania OIL — PENNZOIL.



PENNZOIL Z-7 — WORLD'S RICHEST, MOST COMPLETE MOTOR OIL

Member Penn. Grade Crude Oil Assn., Permit No. 3, Oil City, Pa.

dodge surprised and delighted me. I think it every bit as clever and ingenious as any I've seen published.

A. C. CRAFT, Santa Ana, Calif.

Pity the Poor Mailman

STICKING coins on cellophane tape and hanging it in a mailbox may seem like a clever idea to Mr. Eagan [Short Cuts and Tips, June, p. 175], but not to me, a mailman. It's a time waster and it's par-



ticularly disagreeable in winter. The recommended practice is to put coins in an envelope or a spring clothespin. The Post Office Department furnishes stamp-requisition envelopes on request.

I'd never make it around my route if many people were to follow your cellophane tape hint.

W. H. CLISTER, Markleysburg, Pa.

We Like Our Way Better

THAT hint for starting a flooded outboard [Apr., p. 139], is for the birds. An easier method that can be used with safety anywhere at the dock or on open water is this: First, without disturbing the carburetor settings, put the throttle control at start position and make sure the motor is out of gear. Sit down, shut off fuel valve or disconnect fuel line from motor. Then push the starter button or give five or six good yanks on the starter cord and, if flooding was your trouble, the outboard should start right away.

There is usually enough gas in the carburetor to run your motor until you can connect the fuel line or open the fuel valve. At any rate, you'll be on your way in less time than it would take to find a rope for your method.

ROYDEN WASSON, Lakefield, Ont.

Your method is outlined in most outboard-motor manuals. However, disconnecting the fuel line won't keep the motor from continuing to flood itself with gas drawn from the carburetor, at least until the carb is sucked dry.

Opening the throttle to its widest posi-

CONTINUED

LOOKING FOR LONG WEAR IN SERVICE SHOES?

TRY  MONTGOMERY WARD SHOES

WITH **NEOPRENE SOLES!**



Ask for No. 7363

SATISFACTION GUARANTEED or your money back! 

DUPONT

Ask for neoprene soles the next time you buy service shoes


BETTER THINGS FOR BETTER LIVING...THROUGH CHEMISTRY

12 POPULAR SCIENCE SEPTEMBER 1961

Lay your hammer in the Rocket's shadow and compare them point by point. You'll find out why the True Temper Rocket is a better way to drive a nail. Then go to your hardware store and heft a Rocket. It's the greatest feeling in hammering

No. A16

\$5.49



1. Striking face chamfered and crowned for more durability; drives nail straighter, more completely; won't mar wood.
2. Full-polished, octagon-pattern neck and poll—preferred by professional carpenters.
3. Forged-steel head, heat-treated three ways—for strength at eye section, hardness of face, correct temper in the claws.
4. Patented, locked-on head will not loosen or fly off in use. Withstands 5-ton pull tests.
5. Inside edges of claws precisely tapered. The Rocket will bite and pull out a *headless nail*.
6. Improved tubular-steel handle is the strongest made. It's a result of True Temper's years of experience in making tubular-steel golf-club shafts.
7. Handle's oval shape actually gives each blow more power.
8. Shock-absorbing cushion grip is comfortable and lively—seems to grip back. Bonded to handle by hot vulcanizing process—won't turn or loosen.
9. Grip is made of neoprene to resist oil and grease, and it's impregnated with pulverized fiber to keep grip from slipping, wet or dry, or in gloved hand.
10. Steel end plate on handle keeps end from driving through grip in tapping work. Cushion end will not mark or damage work.


LUFKIN

every home needs all 3

HANDY!

MEZURALL[®] TAPE RULE


is pocket-size for quick, handy measuring. 6-8-10-12-ft. lengths. 10-ft. \$1.69



RIGID!

RED END[®] WOOD RULE

is the carpenter's favorite. 6" brass extension. Markings aren't just painted on, they're embedded in wood. 6-ft. \$2.50



LONG!

BANNER[®] 50' TAPE

lets you do long-distance measuring by yourself. White Clad[®] steel line glides on double rollers. 50- or 100-ft. 50-ft. \$5.49



Look for Lufkin measuring tools wherever you buy hardware or building supplies.

measure for measure,
the finest made

LUFKIN

SAGINAW, MICHIGAN

tion admits air to the cylinders. When flooded, any engine needs air in large quantities to clear itself and encourage combustion. With the throttle wide open, sometimes a single yank on the starter cord will fire up a flooded motor.

As explained, many motors limit the throttle in neutral, and it's necessary to shift into forward in order to open the throttle wide. As for the rope—don't you carry one for anchoring or tying up?

Oh, My Aching Back!

THAT boat your artist drew to show a new flexible boat hitch ["New Ideas from the Inventors," July] has a real novel seating arrangement. Was it planned for



a back-seat driver or has the owner long arms or maybe a bad crook in his back? Personally, I prefer the seat and steering wheel on the same side.

C. J. PRITLOVE, Guelph, Ont.

Just What the Man Ordered

THE man who wants a mud flap for the rear of his station wagon to keep the back window clean ["I'd Like to See Them Make," June] is in luck. We have been making such a flap since July, 1960.

PETER SHOEMAKER, Pres.
Polaris Corp., Dearborn.

Barrel Plane and Thunderchief

I REALLY enjoyed building your ducted-fan flying model [June]. It took about 6½ hours. I modified the landing gear,



using 1/16"-diameter wire and extending it clear through the wings so it wouldn't break as easily on hard landings.

EDDIE GUIGNET, Muncie, Ind.



6 REASONS WHY RCA TRAINING IN ELECTRONICS

can be the smartest investment
you'll make in your *entire lifetime!*

1. You get the finest training-at-home under the supervision of the RCA INSTITUTES, experts in technical training for over 50 years. The very name "RCA" means dependability, integrity, and scientific advance.

2. You get comprehensive training in your choice of many complete up-to-date Courses ... including Radio and Electronic Fundamentals, TV Servicing, Color TV, Transistors, Automation.

3. You get Theory, Experiment, and Service Practice starting with the very first lesson ... a complete training package throughout the course. No special technical background is required.

4. You get prime quality equipment as a regular part of your Course ... equipment that you keep and use on the job. You never have to take apart one piece to build another.

5. Voluntary Tuition Payment Plan. You pay for each lesson only when you order it. If you interrupt your course at any time, for any reason, you owe nothing more unless you resume. You never have to pay for the whole course if you don't complete it.

6. You get top recognition — Graduates of RCA Institutes now work for leaders in the electronics field; many have their own businesses. This record is true tribute to the high quality of RCA Institutes training.

Send for this
64-page Home
Study Catalog
FREE!



RESIDENT SCHOOL Courses in New York City and Los Angeles offer comprehensive training in Television and Electronics. Day and Evening classes start four times each year. Detailed information on request.

RCA INSTITUTES, Inc. Home Study School

A Service of Radio Corporation of America Dept. PS-91
350 West Fourth Street, New York 14, N. Y.

Please rush me your **FREE** Illustrated 64-page book "Your Career in Electronics," describing your home training programs. No obligation. No salesman will call.

Name
please print

Address

City Zone State

Karen Vetsl Enter discharge date.

CANADIANS — Take advantage of these same RCA courses at no additional cost. No postage, no customs, no delay. Send coupon to:

RCA Victor Company, Ltd., 5581 Royalmont Ave., Montreal 9, Quebec

To save time, paste coupon on postcard.

HOLLEY "VENTILATED" IGNITION POINTS OUTLAST ORDINARY POINTS 3 to 1



You can depend upon peak performance and longer life when you replace worn points with *genuine* Holley Ventilated Contact Sets. Their unique design and construction assures fast dissipation of heat and retards the rapid transfer of metal on contact surfaces. Tips are made of highest grade tungsten rod for extra durability. Holley developed and perfected the ventilated principle for original equipment ignition distributors, and every Holley Contact Set for replacement is made to *original equipment* quality specifications. If you are getting poor ignition performance, it will pay you to replace with Holley now.

★ ★ ★

When you make your own carburetor or ignition repairs, be sure to use genuine Holley parts. Your Authorized Holley Distributor or Dealer, listed in the Yellow Pages, has a complete stock of Holley carburetor and ignition repair kits and parts, plus brand-new replacement PEP® Carburetors, priced competitively with rebuilds. All are engineered and built to original equipment standards.



ORIGINAL EQUIPMENT MANUFACTURERS
OF CARBURETION
AND IGNITION PRODUCTS
FOR OVER 55 YEARS

C-7

11955 E. Nine Mile Road, Warren, Michigan

twenty to one dividend . . .

that's the reward you can receive from a college education in engineering or business. Employers like Tri-State graduates . . . interview seniors on campus. Qualify faster Bachelor of Science Degree in 27 months in Electrical (Electronics or Power major), Mechanical, Aeronautical, Chemical, Civil Engineering IN 36 MONTHS a B.S. in Business Administration (General Business Accounting, Motor Transport Management majors) For earnest, capable students. Small classes. More professional class hours. Modernized buildings, well-equipped labs, new dorms. Modest costs. Year-round operation. Enter January, March, June, September. Founded 1884. Write J. F. McCarthy, Director of Admissions for Catalog and "Your Career" Book.



TRI-STATE COLLEGE

591 College Avenue

Angola, Indiana

THE ORIGINAL PACKAGED

KITS

BOAT



BOAT PLANS
PATTERNS FRAME PACS

• World's
Largest
Boat Kits
• Over 400
Plans
• Over 400
Patterns
• Over 400
Frame Packs

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

Send 35¢ for Colored Catalog

CUSTOM • CRAFT Buffalo 7M, N. Y.

Buy and Hold
U. S. Savings Bonds

I'LL FINANCE YOU

...IN YOUR OWN
SCREEN PRINTING
BUSINESS

PRINT WITHOUT A PRINTING PRESS!

requires no expensive Press and can be done in your own home. Start in Kitchen, Spare Room, Garage! Easy, Fascinating!

PRINT BEAUTIFUL SIGNS, POSTERS, BANNERS, FABRICS - anything in hundreds of colors! Use fabulous new glowing fluorescent colors. Can be seen for miles! No Art ability needed - we supply everything.

HELP SUPPLY DEMAND IN YOUR AREA! Just about every kind of business (drug department stores, hardware, liquor stores, gas stations, theaters, jewelry, mortuaries, auto dealers, florists, beauty shops, real estate, etc.) can use Screen Printed things to increase business.

SOME \$100 JOBS USE LESS THAN \$10 WORTH OF MATERIALS - you pocket the difference for your labor and know-how. **\$400.00 A WEEK EARNINGS POSSIBLE!** Yes, some earn less, but Mr. J. T. Anderson reports he earns over \$400.00 a week printing Greeting Cards certain 11 months of year! Get your share Now! Mail Coupon Today!

FREE SAMPLES - MAIL COUPON NOW

Mr. C. J. Hough, Screen Print Co., 5147 S. Broadway
Los Angeles 61, California Dept. 10

Dear Mr. Hough: I am very interested. Please rush me your FREE ALA. SAMPLE PLAN. Enclosing with this FREE PLAN is a 50¢ check for SAMPLES, and NOW TO ORDER! I am under no obligation now or ever!

Name _____
Address _____
City _____ Zone _____ State _____

Build Your Own Bomber

I'D LIKE to pass along to model-plane hobbyists a bit of information I've just picked up. Anybody interested in building the Air Force's supersonic F-105D all-weather fighter-bomber can



get plans from the Republic Aviation Corp., Farmingdale, N.Y. The plans are for solid-model construction

A. J. CONDON, Trenton, N. J.

Anybody Got the Answer?

TIME marches on, but I'm still befuddled and bewildered. That plane forced into a "Tree-point landing" [Picture News, Apr. p. 100]: I've looked at it and looked at it, but never solved the puzzle. How did they get the plane down?

Pvt. T. C. BARBER, Sacramento, Calif.

We'd say the simplest way would be with a big crane.

Can You Clear Up His Trouble?

CAN anyone tell me how to prevent my windshield wipers from producing smears instead of two clear arcs, as they did years ago? What has caused the change—road tars, diesel-exhaust fumes? Sometimes washing the glass and blades with detergent works fine. Sometimes it doesn't. And don't tell me that I've been using a silicone polish on the glass. I haven't.

PHILIP GARAND, Kansas City, Mo.

Solution, anyone?

One for the Road

MAY I add to the driving tips in your mail? This one gives the careful driver a better view of left-hand traffic on parkways and turnpikes: Adjust the inside and outside mirrors so that the fields of vision overlap slightly. That way you eliminate blind spots—a car's image will appear in one mirror before it completely leaves the other.

JAMES P. RUTH, Newark.

ALLIED

MONEY-SAVING 1962 ELECTRONICS CATALOG



SAVE MOST ON EVERYTHING IN ELECTRONICS

Send for this **FREE** catalog—it's the biggest—featuring everything in Electronics for modern living, including products and values available only from ALLIED. Whether you're a kit builder, experimenter, hi-fi fan, Amateur, serviceman or engineer, you'll save most on:

- KNIGHT-KITS®—Best in Build Your Own
- Everything in Stereo Hi-Fidelity
- New Multiplex Stereo FM
- New All-Transistor Stereo Hi-Fi
- KNIGHT® Super-Value Stereo Hi-Fi
- Tape Recorders & Phono Equipment
- Citizens Band 2-Way Radios
- TV Tubes, Antennas, Accessories
- Parts, Tubes, Transistors, Tools, Books
- Amateur Station Equipment
- Public Address & Intercom
- Latest Test & Lab Instruments



SAVE on everything in Electronics at ALLIED—get fastest service, expert personal help, easiest-pay terms, satisfaction guaranteed or your money back. Send coupon today for **FREE** 1962 ALLIED Catalog.

free



ALLIED RADIO

ALLIED RADIO, Dept. 42-J1
100 N. Western Ave., Chicago 80, Ill.

☐ Rush **FREE** 1962 ALLIED Catalog.

Name (please print) _____

Address _____

City _____ Zone _____ State _____

GET READY FOR THE SPACE and SCIENCE ERA! SEE SATELLITES, MOON ROCKETS CLOSE-UP

AMAZING SCIENCE BUYS

for FUN, STUDY or PROFIT



See the Stars, Moon, Planets Close Up!

3" ASTRONOMICAL REFLECTING TELESCOPE


60 to 180 Power—Famous Mt. Palmer Type! An Unusual Buy!



Assembled—Ready to use! You'll see the Rings of Saturn, the fascinating planet Mars, huge craters on the Moon, Star Clusters, Moons of Jupiter in detail. Galaxies! Equatorial mount with lock on both axes. Achromatized and over-coated 7" diameter high-speed f/10 mirror. Telescope tubes equipped with a 6X eyepiece and a mounted Starlow Lens giving you 60 to 180 power. Low cost accessory eyepiece available for higher powers. An Optical Finder Telescope always to essential. It also includes sturdy hardwood, portable tripod, F.I.L.E. with Scope.

—Valuable STAR CHART plus 312 page "HANDBOOK OF HEAVY-WEIGHT" plus "HOW TO USE YOUR TELESCOPE" BOOK.

Stock No. 65,050-N \$29.95 Postpaid



Remove Your Retaining Rings - Disassemble Lenses, Cameras, etc.

ADJUSTABLE SPANNER WRENCH

Made for U.S. Air Force—available at a fraction of Government cost. A top grade versatile tool that every instrument and camera repair man or just plain hobbyist should own. Adjustable for 1 1/2" to 1 3/4" diameter retaining rings. Comes with six different pairs of points to fit all sizes of nuts and bolts. 1/2", 5/8", and 1 1/2" main bar. All steel and finely polished. The finest tool we have ever come across for this type of retaining ring work. A real bargain at our low price.

Stock No. 70,355-N \$12.50 Postpaid

'FISH' WITH A MAGNET

Go Treasure Hunting On The Bottom

Great Ideal Fascinating fun and sometimes the money! Tie a line to our 5 lb. Magnet—drop it overboard in bay, river, lake or ocean. Trawl it along the bottom—your "Treasure" haul can be outboard motors, anchors, fishing tackle, all kinds of metal rubbish. 5 lb. Magnet is war surplus—Alnico V Type—a terrific bargain. Lifts over 125 lbs. on land, much greater weights under water. Order now and try this new sport.

Stock No. 70,182-N, 5-lb. Magnet \$9.95 Postpaid



BLACK LIGHT MAGIC-GLOW KIT

Kit uses long wave blacklight, which is completely harmless to eyes, but causes fluorescence in over 1,000 substances. Includes Magic Glow Lamp, stand, invisible water paints and ink, fluorescent crayon, tracer powder pen, 3 brilliant specimens of fluorescent rocks, wampum from Canada, Quartz from England, whiteite from U.S.

Stock No. 70,255-N \$11.95 Postpaid

DIRECT MEASURING POCKET MICROSCOPE

—50 POWER

Fountain pen size, makes direct reading measurements for checking small parts and structures under powerful magnification. Precision glass optical system. Measures up to 1/10" by .001" divisions.

Stock No. 50,225-N \$7.95 Postpaid



LIFE SIZE VISIBLE HUMAN HEAD

Precise, Full Color, Take-apart Model

Study the most complex organ easily. Inexpensive ideal for study, hobby or professional use. You will be amazed at the detail. Model is an actual human skull. Eyes, ears, nose, teeth, etc. are removed and placed in position for comparison. Easy to break apart and reassemble. Amazingly low price compared to laboratory standards. 16-illustrated picture handbook included.

Stock No. 70,417-N \$9.95 Postpaid



BUILD A SOLAR ENERGY FURNACE

A fascinating new field. Build your own Solar Furnace for experimental and many practical uses. Easy to assemble! Use scrapwood. We furnish instructions. This sun powered furnace will generate terrific heat 2000° to 3000°.

Stock No. 70,130-N \$8.00 Postpaid

ASTRO-COMPASS AND TRANSIT

War surplus! Astro Compass alone cost Govt. \$75. We have added a Sighting Level to improve versatility. Hundreds of uses in carpentry, brick laying, foundation work, grading, irrigation or drainage. Much below cost of ordinary surveying instruments. Ideal for do-it-yourselfers. 10 1/2" high, 8" long, 4" wide. Adjustable leveling plate. Sets—2 spirit levels for aligning—also spirit level in sighting attachment. A tremendous bargain.

Stock No. 70,267-N \$19.95 Postpaid



NEW BINOCULAR-TO-CAMERA HOLDER

For Exciting Telephoto Pictures

With it any camera. Bring distant objects 7 times nearer with a 35 mm camera. 7x55 binocular and our NEW BINOCULAR-TO-CAMERA HOLDER. Ideal for long range shots of wild life, planes, ships, people, etc. Camera and binoculars attach easily. Use any binocular or monocular—any camera, still or movie. Take color or black and white. Full directions for taking telephotos.

Stock No. 70,223-N \$11.50 Postpaid



WOODEN SOLID PUZZLES

13 Different puzzles that will stimulate your ability to think and reason. Here is a fascinating assortment of wood puzzles that will provide hours of pleasure. Twelve different puzzles, animals and geometric forms to take apart and reassemble, give a chance for all the family, young or old, to test skill, patience, and, best of all, to stimulate ability to think and reason while having lots of fun. Order yours now.

Stock No. 70,205-N \$3.00 Postpaid



War Surplus American Made 7x55 Binoculars

Big savings! Brand new! Crystal clear viewing—7 power. Every optical element is coated. An excellent night glass—the same recommended for night viewing. Individual eye focus. Exit pupil 7mm approx. Field at 1000 yds is 176 ft. Carrying case included. American 7x55 a normal cost \$193. Our war surplus price saves you real money.

Stock No. 1833-N Only \$59.00 postpd. (Tax included)




8 x 30 Binoculars—similar to above and a terrific bargain. Stock No. 863-N \$39.00 postpd. (Tax included)

OPAQUE PROJECTOR

Projects illustrations up to 3" x 3 1/2" and enlarges them to 15" x 30" if screen is 6 ft. from projector. Larger pictures if screen is further away. No film or negatives needed. Projects maps, diagrams, pictures, photos, lettering (in all colors of black and white). Operates on 110 volt A.C. current. 6 ft. extension cord and plug included. Operates on 60 watt bulb not included. Size 12" x 8" x 4 1/2" wide. Weight 1 lb., 2 oz. Plastic case with built-in handle.

Stock No. 70,199-N \$7.95 Postpaid



MINIATURE WATER PUMP

Wonderful for experiments, miniature waterfalls, fountains, HO gauge railroad backdrops, etc. Tiny (2 1/4" x 1 1/4") electric motor and pump ideal for hobbyists, labs, schools. The pump pumps flow of water at rate of one pint per minute at a 12" head. With 2 D Batteries in series will pump 2 1/2" high. Runs 48 hrs. on battery. Works in either direction. Seal painting. Stock No. 50,345-N \$2.25 Postpaid



POCKET SIZE SURVIVAL AND FIRST AID KIT

Hardly bigger than a pack of cigarettes, the smallest package of big necessities on the market. Signal mirror, compass, fish hooks, nylon leader, water purifier, ion tablets, knife, candle, signal flag, pencil, matches, safety pins, paper, paper cups, ammonia inhalant for the snafu, gauze bandage, gauze pads, adhesive bandages, burn ointment, complete first aid manual. All this packaged in a tough, clear "snap open" container. Ideal for fishermen, hunters, campers, etc.

Stock No. 40,463-N \$3.00 Postpaid

Order by Stock No.—Send Check or M.O.—Money-Back Guarantee

MAIL COUPON for FREE CATALOG "N"

144 Pages! Over 1000 Bargains!
EDMUND SCIENTIFIC CO., Barrington, N. J.
Please rush Free Giant Catalog N

Name.....
Address.....
City.....Zone.....State.....



The month in science

How to colonize Venus. The planet closest to Earth is Venus (it swings in to 25,000,000 miles). It is also one of the most mysterious. That's because you can't see the planet, only the pale, lemon-yellow clouds that cover it all the time. The mystery may be cleared up fairly soon: The Russians have sent a fly-by rocket probing past Venus (not very close, though), and we're planning to launch a Venus probe of our own next year.



Venus photographed in blue light at Mt. Wilson

Meanwhile, Carl Sagan, researcher at the University of California, has compared bits and pieces of astronomical evidence to deduce the nature of our old Evening Star (most inhospitable, he says), and to propose a weird scheme for making it comfortable for human space settlers ("microbiological planetary engineering," he calls it).

Since no one can see the surface of Venus, scientists have felt free to let their imaginations run, and they sure did. There are four theories, all seriously proposed by recognized experts, and all wildly different:

1. It's dripping wet, covered with swamps. (The clouds were assumed to be water vapor, like our clouds.)

2. It's sunk in a global ocean of Seltzer water. (Much carbon dioxide was detected; this would carbonate the ocean.)

3. It's covered by a huge pool of oil. (If there were originally

a lot of hydrogen-carbon compounds, they would react with water to make all that carbon dioxide—and leave the planet coated with leftover hydrocarbons.)

4. It's an arid, windswept desert blanketed by dust clouds. (Until recently, not a trace of water could be detected.)

Commented Sagan in his report in the journal *Science*, "Those planning manned expeditions to Venus must be exceedingly perplexed over whether to send along a palcobotanist, a mineralogist, a petroleum geologist, or a deep-sea diver."

New evidence, Sagan thinks, blasts all these theories except No. 4, and this is not entirely right. The principal clue is temperature. Venus is apparently heated by a powerful greenhouse effect—incoming sun heat is trapped by the heavy carbon dioxide atmosphere and the cloud layer. The surface runs around 600

The month in science continued

degrees F., more than enough to dry out a swamp, evaporate a Seltzer ocean, or destroy an oil slick.

There can't be any liquid water. The clouds are ice crystals, but they are 30 miles up, where it's cold. It never rains. The surface is a dead, dry wasteland, eroded by the wind. The winds should be mild breezes, since the sun's heat goes mainly into warming up the heavy atmosphere, instead of moving the atmosphere around the way it does on earth.

No living thing we know about could exist under such conditions. Some life might carry on in the cool upper atmosphere, just under the clouds. There's not much chance that it does now, because it is unlikely that life ever got started on Venus—life brews slowly in a warm thin soup, and that Venus never seems to have had.

This dismal geography does not discourage Sagan. To make Venus resemble home sweet home, all you have to do is lower the temperature and set some oxygen free in the atmosphere. That's all. Sagan thinks blue-green algae will turn the trick. (It looks as if well-trained algae are as essential to space explorers as the compass was to Columbus.) Here's how:

The algae—microscopic plants that will float in the air—are squirted into Venus' clouds. There, using carbon dioxide from the atmosphere, water from the clouds' ice crystals, and sunlight, they manufacture carbohydrate and release free oxygen.

This uses up some water, which is scarce on Venus. You have to get it back. Very conveniently, the carbohydrate-fattened algae float down to lower, hotter regions of the atmosphere. The heat there roasts the carbohydrate, releasing carbon and water.

These two reactions build up the oxygen supply at the expense of carbon dioxide. As the carbon dioxide goes, the greenhouse effect becomes less efficient and the temperature drops. As the temperature drops, carbohydrate roasts more slowly, releasing less water. The loss of water vapor cuts the greenhouse effect and the temperature still more.

When the surface cools below the boiling point of water, you have it made. Pools of liquid water form. Then it rains. The rain brings on the "Urey equilibrium"—back-and-forth reactions between carbon dioxide and common types of rocks that stabilize the amount of carbon dioxide gas in the atmosphere. (These reactions won't go without rain, which triggers the chemical processes and stirs things up.) After a while, the Urey equilibrium will establish a carbon dioxide level much like that on Earth, the greenhouse effect will slack off more, and Venus will begin to feel like Florida.

Bait for termites. A new weapon for getting at termites, which—despite effective insecticides—munch through hundreds of millions of dollars worth of house framing every year, has been turned up by researchers of the U.S. Forest Service and the University of Wisconsin, at Madison. It is a clear oil that attracts termites the way cheese attracts mice and could be used the same way. The pure bait was extracted from the voracious bugs' favorite dish: pine wood riddled with brown-rot fungus.



Here are *3 good reasons*

why I'm glad

I became a **DURACLEAN DEALER**

Raising a family takes a dependable, steady income. Too few jobs offer security and chance for advancement. That's why so many men are going into a business of their own. All around us are local merchants making a good living in respectable businesses where they hold a franchise. The big questions are "What is left to go into?—Which business is profitable?—Which requires only a modest investment?" Many have found the answers in DURACLEAN.

EVERY TOWN NEEDS THIS AMAZING BETTER HOME CLEANING SERVICE

Duraclean is a scientific method of cleaning carpeting and upholstery in the home. This better process of cleaning by absorption virtually "lifts" the dirt from fabrics, leaves them bright and lively. Almost every home, hotel and many offices are potential customers who will call you again and again.

Check Experience of Other Dealers

There's no better way to learn of DURACLEAN profit opportunities than by checking with dealers already in business. If there's one near you, call him—or ask DURACLEAN whom to call

M. LYONS: ILLINOIS

"Averaged over \$50,000 my first 3 yrs. Headquarters help makes it possible."

C. RANDALL: OHIO

"My 2nd year and business keeps growing. Have made as much as \$120 in one day."

E. BAILEY: ARKANSAS

"I know of no other business which can offer so much."

L. LAWSON: NEW YORK

"National advertising creates leads. One month, jobs totaled \$1475."

DURACLEAN COMPANY

1-189 DURACLEAN BLDG., DEERFIELD, ILLINOIS

DURACLEAN PROVIDES EVERY BUSINESS BUILDING NEED

DURACLEAN headquarters supplies all equipment and chemicals to put you in business. Regularly held training sessions, cover techniques, methods and means of developing business. Local advertising helps and merchandising ideas are available; and an impressive national advertising program pre-sells customers on the gentle DURACLEAN cleaning process.

Start part time, full time or hire others. **NO SHOP NEEDED.** DURACLEAN service is rendered in the home or customer's place of business. Just 2 average jobs a day can net \$8,750.00 a year.

MORE WAYS TO MAKE MONEY

5 other DURACLEAN services multiply your profits. DURASHIELD soil retarding service, DURAPROOF mothproofing and DURAGUARD flame retarding are among the other services that mean more money for you. It takes less money to establish this prosperous business. No wonder so many men with vision are becoming DURACLEAN DEALERS. Why don't you? Write today for FREE booklets.

MAIL THIS "FUTURE SECURITY" COUPON

DURACLEAN COMPANY

1-189 Duraclean Bldg., Deerfield, Illinois.

Rush me all the facts about DURACLEAN PROCESS and what it takes to become a DURACLEAN DEALER.

NAME _____

ADDRESS _____

CITY _____ STATE _____

PS Puzzlers By Joan Steen

Some September leaves—to burn you up . . . Answers on page 218




Estimating the Gravity of the Situation

FORGIVE the pun, but that's exactly what I want you to do.

The noted physicist George Gamow in a recent article described life on a spaceship far from any large gravitating masses. As long as the ship is in uniform motion, he notes, people and objects aboard will experience weightlessness. But if the rocket motors accelerate, people and objects will be pressed against

the wall opposite to the direction of motion. (That becomes the floor.)

Now suppose under conditions of acceleration a person on board performs Galileo's experiment. He takes two balls, one wood, one iron, and drops them from the same height. What will happen? Can you describe how it would appear to a person inside the ship? To someone outside?



THERE are 2,400 ways of solving this coin puzzle. The trouble is, if you see one way, you'll probably see the rule for all the others. And if you don't—you just kick yourself.

Five coins are placed at the top and bottom of a piece of paper, as shown. You are to remove four of them, leaving the others in place. Now replace the four so that you can form a figure consisting of five straight lines each passing through four coins.

TWO numerical quickies—one's for real, the other's a trick.

First, can you arrange this row of eight 8s to make a 1,000?

8 8 8 8 8 8 8 8

You're allowed to use the ordinary signs of arithmetic plus innumerable parentheses.

Second, can you add five and six in such a way that the sum is nine? (Don't say we didn't warn you.)



WHAT'S the fair fare? Jones rents a car to go from A-town to C-town and back for \$10. At B-town, midway in his journey, he picks up friend Smith who wants to go on to C-town and then be dropped off at B-town on the return trip. How much should Smith pay if they are to share expenses fairly?

FOR INDUSTRY OR HOMECRAFT 8" TILT ARBOR SAW

BUY DIRECT FROM
FACTORY

BLADE TILTS • TABLE
REMAINS LEVEL



NOW
\$995
FACTORY
PRICE

Heavy duty all cast iron
and steel construction.
Precision ground cast
iron table. Precision
massive cast iron motor
gauge and patented mo-
tor drive that fits any

Complete
as shown
less blade

motor. Does everything same as saws costing five times
as much—cross cuts, rips, bevels, mitres, dados, cuts
compound angles. Adjustable depth of cut; 0" to 2 1/4".

SPECIAL BARGAIN—This saw is our 1960 model. Brand
new—sent to you in factory sealed cartons. Sold and
guaranteed direct from factory to you at a fantastic
bargain. This machine has features of machines costing
many times more. 480,000 now out working—winning
praise everywhere.

MONEY-BACK GUARANTEE

Try this famous saw 10 days. If not completely delighted
—FOR ANY REASON—return for immediate refund.

SENT EXPRESS COLLECT Send check or M.O. \$2.00 deposits
on C.O.D. & We reserve right to refund money if stock
is exhausted. Avoid disappointment. Order right now!

AMERICAN MACHINE & TOOL CO.

DEPT. PS-91, ROYERSFORD, PA.

PLAY RIGHT AWAY!

Even If You Don't Know
a Note of Music Now

Now it's EASY to learn to play
instrument. No boring ex-
ercises. Start playing real pieces
by note right away. Amazing
progress at home. No teacher.
No teacher. You learn by reading.
1000-1000 students! Write for
FREE BOOK U.S. School of Music Studio A159, Port Washing-
ton, N.Y. No salesmen. No call. (846.1408.)



**ENGINEERING
SCIENCE
MATH**

**DEGREE IN
27 or 36 MOS.**



B.S. DEGREE—36 MOS. • B.E. DEGREE—27 MOS

Accredited with R.H.D. program prepare for early employment
in field of **MATHS AND ENGINEERING**. Regular 4 year program for
B.S. degree completed in 36 months. Special engineering degree pro-
gram in 27 months. **GRADUATE** employed from coast to coast. Govern-
ment service. For veteran training. Students from 38 states. 40 min-
utes. 20 buildings. dorms. gym. Campus. SAVE TIME AND MONEY
While studying.

Write for catalog and complete information

INDIANA TECHNICAL COLLEGE

691 E. Washington Boulevard, Fort Wayne 2, Indiana
Please send me free information on Bachelor's Degree Pro-
grams in Engineering and Science as checked below

- | | |
|---|--|
| <input type="checkbox"/> Aeronautical Engineering | <input type="checkbox"/> Mechanical Engineering |
| <input type="checkbox"/> Chemical Engineering | <input type="checkbox"/> Metallurgical Engineering |
| <input type="checkbox"/> Civil Engineering | <input type="checkbox"/> Physics |
| <input type="checkbox"/> Electrical Engineering | <input type="checkbox"/> Chemistry |
| <input type="checkbox"/> Electronic Engineering | <input type="checkbox"/> Mathematics |

Name _____

Address _____

YOUR SAVINGS EARN MORE

4 1/2%

INSURED

Wise saving means higher dividends with insured safety.
Prudential Savings gives you both. Watch your account
grow faster under full insurance to \$20,000.00 by Security
Financial Ind. Corp. chartered expressly for the purpose of
guaranteeing insurance and operating under license and super-
vision of the Insurance Department of the State of Maryland.

CONVENIENT!


Whether to save or withdraw we're as near as your mailbox.
We are proud of having honored every withdrawal
request instantly when requested. FREE! Save-by-Airmail
envelopes always pay all postage both ways.

FREE THRIFT GIFTS



PHILCO "SLENDER SEVENTEEN"

Portable television set. 17" screen.
Also does AM, FM, and 100%
perfect reception. 17" screen.
picture FREE with \$5,000
account.



FISHING KIT

Includes 14' fishing reel,
rod, and tackle. 17" screen.
weight 17" screen and tackle
FREE with \$1,000
account.



4 TRANSISTOR RADIO

Amplifier, 4 transistors, 17" screen.
17" screen and 17" screen.
FREE with \$1,000 account.



MADCO AUTOMATIC 200 GOLF CART

17" screen and 17" screen.
17" screen and 17" screen.
FREE with \$5,000 account.



SMITH-CORONA PORTABLE TYPEWRITER

17" screen and 17" screen.
17" screen and 17" screen.
FREE with \$2,500 account.



25 INCH POWER MOWER

17" screen and 17" screen.
17" screen and 17" screen.
FREE with \$2,500 account.

Accounts remain in force for 1 year. If withdrawn in less
than 1 year, you agree to allow the balance of 25% of
the account to be used in any state or local law if restricted
or prohibited by local laws.

PRUDENTIAL SAVINGS & LOAN INCORPORATED

Room 49, Prudential Bldg., Baltimore 1, Md

ROOM 49, Prudential Savings & Loan Inc.

Prudential Bldg., 31 W. North Ave., Baltimore 1, Md.

My choice of FREE GIFT is _____

I enclose \$_____ (or passbook) to open my account

NAME _____

STREET _____

CITY _____

Free Post-Card Brochure #35 Send name and address today

PS Puzzlers continued



A LITTLE algebra—really very little—is all you need to solve this horse-and-buggy puzzle.

A big company decided to stage an old-fashioned Labor Day picnic for its employees, complete with horse-drawn wagons. On the way out to the picnic grounds, 10 of the wagons broke down

so they had to put one extra person on each of the wagons left. Coming back, 15 more wagons developed trouble, so they again had to redistribute the people. By the time they reached town, each wagon carried three more persons than it had held in the morning on the way out. How many went on the picnic?



Puzzle of the month

HERE'S a deceptively simple-looking problem that can be solved in a number of ways—mostly complicated. See if you can find an easy path. I played a hunch that worked.

A ladder 20 feet long extends from the foot of one wall in an alleyway to a certain height on a parallel wall. A second ladder, 30 feet long, extends between the walls in the opposite direction. The two ladders cross at a point eight feet above the ground. How wide is the space between the walls? (Answer next month.)



Answer to last month's P.O.T.M: To free the heart from the wire, first slip the heart around so that it hangs from the bottom of the swing.

Step 1: Hold the bar at the left end (if right-handed) and pick up the heart by its point. Slip the "tongue" through the right-hand loop of the swing.

Step 2: Pull the heart and swing over

to the right end of the bar and, turning the heart so that it's horizontal, slip the tongue around the loop at the end of the bar.

Step 3: Push the heart up and back through the loop at the same time you let the loop drop down. Slight variants of this technique will also work. To replace the heart, just reverse the steps.

BROWNING®

POWER-PACKED .380 AUTOMATIC




\$44.00
with fitted case
U.S. or CANADA

**Accurate
Dependable
Compact**

Excellent for home protection because of its safety features. Hand-finished throughout. 7 cartridges - 20 oz. - 6" Long - 4" High.

Renaissance hand-engraved model with pearl grips and gold plated trigger



Prices subject to change without notice

WRITE
FOR
CATALOG

SEE YOUR BROWNING DEALER
Browning Arms, Dept P3, St. Louis 3, Mo.
— in CANADA, Dept. P3, Box 991, Montreal 9, P. Q.




get into operating or repairing EARTH MOVING EQUIPMENT

Most needed now for good paying jobs in booming road & construction work. Learn operating or repair rebuilding of heavy earth moving equipment by 12 weeks earth moving etc. Actual on the job training \$10.00 per week course. A new start & a new world. Reserve your space now. Complete catalog and reservation form. **FREE** Approved for veterans. Write.

Greer TECHNICAL INSTITUTE
Attn: S.M. Hutch, Box 358, Braidwood, Ill.

FREE TRIAL OFFER

**Proves You Can Make
EASY SPARE TIME MONEY**



**with Only Light Bulb Backed by a
No-Time-Limit Free Replacement Guarantee**

Fill in and mail coupon below and I'll send you a supply of amazing longer-burning Merlite Light Bulbs. These are the incredible bulbs that are making "small fortunes" for men and women everywhere. Just tell friends, neighbors, relatives and others about the amazing No-Time Limit Free Replacement Guarantee which says: "Once You Buy Merlite Bulbs You Never Have to Buy Bulbs Again. Never. Merlite Bulbs burn so much longer than ordinary bulbs we can't make this astounding guarantee. Can anyone resist it?" No one! That's why it's easy to take orders for 12 to 24 bulbs from every home, easily make up to \$100 in a few hours. Some make as much as \$1,000 and more in a month! You need no experience, don't invest a cent to prove you can make easy money spare time or full time. Send no money. Mail coupon and get assortment of Merlite Bulbs (retail value \$5.34) for **FREE TRIAL** on approval.

MERLITE INDUSTRIES, INC., Dept. C-16J
(Light Bulb Div.) 114 E. 32nd St. - New York 16, N. Y.

MERLITE INDUSTRIES, INC., Dept. C-16J
(Light Bulb Div.) 114 E. 32nd St., New York 16, N. Y.

Rush assortment of Merlite Light Bulbs .65.34 retail value for free trial and **FREE** money-making information — without obligation. I'll either send you the wholesale price of \$3.25 or return the bulbs.

NAME _____

ADDRESS _____

CITY _____ ZONE _____ STATE _____

SEND FOR **FREE** BOOK ON YOUR FUTURE IN THESE GROWING INDUSTRIES



ELECTRONICS TELEVISION RADIO

**FREE
BOOK**

More money... security... prestige... all yours in this booming industry. Go into your own TV Service business... into missiles, automation, industrial electronics, and many other fields. Free book tells how thousands have trained at home for a successful, secure future... how you can earn as you learn. Send coupon now!

AUTO MECHANICS

**AND
DIESEL**



**FREE
BOOK**

Fast, Right, Easy... that's how National Technical Schools trains you for top pay jobs in service and maintenance, motor tune-up, diesel mechanics, foreign car service, and many other fields. Training complete... industry recognized, classroom developed, lab and shop tested. Send for Free Book now. Clip coupon.

AIR CONDITIONING

**REFRIGERATION
ELECTRICAL APPLIANCES**




**FREE
BOOK**

Increase Your Earning Power... Master all three phases in one low-cost course at home. Free book describes unlimited opportunities, training methods and equipment you get to keep. Course pays for itself in Spare-Time-Income while training. Mail coupon now.



ACCREDITED
MEMBER



NATIONAL TECHNICAL SCHOOLS

4000 South Figueroa Street, Los Angeles 37, California

Select
one
of the
"Big 3"
now!

NATIONAL TECHNICAL SCHOOLS

Since 1911

National Technical Schools, Dept. C-91
4000 S. Figueroa St. Los Angeles 37, Calif.

Please attach **FREE** Book and Actual Lesson checked
in New York obligation. No salesman will call.

- ☐ I prefer to receive Book
☐ Auto-Mechanics & Diesel Book
☐ Air Conditioning Refrigeration
& Electrical Appliance Book

Name _____ Age _____

Address _____

City _____ Zone _____ State _____

☐ Check here if interested **ONLY** in Resident Training at L.A.
VETERANS Give date of discharge _____

**CHECK
ONE**

16

Not everyone does as well, but T.N. CODY, who started a business of his own, reports...

For 12 months I've averaged

\$800
per month income

— most of it clear profit for me!

Many men have discovered how to be independent, to be free of layoffs and bosses. C. G. Naples grossed more than \$200 his first week. A father-son combination grossed \$44,000 their second year H Lemon says, "I netted \$133 in one 8-hour day."

How much you make depends largely on you. You need no special skill, no large investment. Start part time if you wish.

NO SHOP NECESSARY • Our Electric Deterger shampoo rugs, carpets right on floor—removes dirt and grime and helps to show their natural color and beauty. So efficient and safe it is used by largest railroads and hotels.

This is not a lease proposition. You own the machine, you work when and where you please and all the money you take in is your own. No risk. Machines fully guaranteed.

VON SCHRAEDER MFG. CO.,
911 "K" Pl., Racine, Wis.

Without obligation send me **FREE** booklet about your RUG DETERGER and tell me how I can start my own permanent, profitable business.

Name _____
Address _____
City _____ Zone _____ State _____

SAMURAI SUICIDE WARRIORS

KARATE!

JUDO BOXING! MUSCLEBUILDING! YOGA!
STRONGMAN STUNTS! STRENGTH
ENDURANCE! HANDBALANCING! ETC.

YOU GET ALL THESE! AND Illustrated FOR ONLY 35¢

KARATE moves "MAVATT" foot fighting "KICK".
SERVE (BENTAH) and ANATOMY charts (20)
JUDO throws (20) test for STRONGMAN
STUNTS Complete MUSCLE BUILDING program
"A" in WRESTLING "Ancient YOGA"
secrets "HANDBALANCING" stunts "Complete
BOXING" program "Secrets of ENDURANCE"
WEIGHTLIFTING "schedule" "A" picture
packed, Super wall charts (surplus 1940 print-
ing). No C.O.D.'s. Canadian orders add 25¢.
Satisfaction Guaranteed or Refund.

Order: Studio 44PS Bromfield, Boston, Mass.

BE A CLAIM INVESTIGATOR

INVESTIGATE ACCIDENTS!

Many earning \$750 to \$1000 a month. Thousands of insurance companies, steamship lines and Government Offices need Claim Investigators. Also big opportunities for your own spare time business. We train you at home. National Placement Service **FREE** of extra charge. Bill King writes: "Your course has paid off for me with large earnings. You can quote me—your Adjuster Training Course is worth many times the cost." Write **TODAY** for **FREE** book.

UNIVERSAL SCHOOLS

University Park, Dept. P3-9, Box 8202, Dallas 5, Texas

MAGIC MAIL PLAN

that comes with this Little Machine
CAN MAKE YOU \$5.00 AN HOUR

The machine is turning out a job that will bring operator \$2.50 by mail. Material cost, only 11¢!



Write today for free facts about the newest and most fascinating of all new home-operated businesses. For the first time, a simplified machine brings the fabulous profits of Plastic Sealing and Plastic Lamination within reach of the small operator. Anyone can learn to operate it with a few minutes practice. Then—with our **MAGIC MAIL PLAN**—can get mail orders pouring in daily with cash in every envelope.

No Canvassing or Selling

Fill orders at home in spare time to start. Then expand to full-time business. We even supply circulars to bring back cash and orders. Rush name for all the facts you need to start. A postcard will do. No charge.


WARNER ELECTRIC CO., Dept. L-3-K
1812 Jarvis, Chicago 26, Illinois



PLAY GUITAR IN 7 DAYS

Or Your Money Back Guaranteed

SURPRISE FRIENDS RELATIVES. ENJOY POPULARITY AND FUN GALORE!
In this introductory offer you get **FREE** 15 10 GUITARIST 10 HALL 5 famous 30 page secret system worth \$1.00 which positively teaches you to play a beautiful song the first day and any song by ear or note in seven days. Comes in 33 photos, 21 10 star in big charts, etc. Shows how to keep time, build chords, bass parts, dance chords, swing, etc. 110 popular and waltz songs, words and music. A 31 10 100 popular of the chords used in popular music. A 31 10 100 of knowledge. **TOTAL VALUE \$7.00—ALL THESE for only \$2.95.** **SEND NO MONEY** Just your name and address pay postman 42 10 plus 1 10 10 postage. Or send \$3.00 with order and I will postage. **Send Money-back Guarantee** **ED SALE, Studio 154-C, Avon by the Sea, N. J.**



Locksmithing AND KEY MAKING

Now Made Easy! Practical up-to-date course

Teaches you how to pick locks, de-rude, make master keys, copy & install keys, etc. New & 1 instruction booklet for every handyman, homeowner, carpenter, mechanic, very ne also an operator. 2x1 whip, hardware dealer, locksmith, 60 easy illustrated lessons. Full price only \$5.00, postpaid or C.O.D. plus postage. Satisfaction or refund guaranteed.

Complete course... now only 15.00

Nelson-Hall Co., Dept. JN-1
325 W. Jackson Blvd., Chicago 6, Ill.

FALSE TEETH

New Plate Made From Your Old—Returned **AIR MAIL** Same Day...

SEND FOR FREE INFORMATION on new professional method that gives you light, comfortable, natural looking, perfect-fitting plate—upper or lower—free your old, worn, broken, loose plate without cost for repairs. Work guaranteed. **SEND NO MONEY** Just send name, address we'll rush details without obligation. State if plate is metal, **TRU-ORIENTAL LAB., 127 N. Dearborn, Dept. 66, Chicago 2**

EYE GLASSES by MAIL As low as \$1.95


Write for **FREE** CATALOG with 16 LENS SAMPLE CARD

Thousands of Customers Since 1939



QUALITY LENSING—or **BROKER GLASSES** for **FAIR** and **NEAR** Recommended for folks approximately 40 years or older who do not have astigmatism or disease of the eye, and who have difficulty reading or seeing far.
ADVANCE SPECTACLE CO. Inc., Dept. P5-9
537 So DEARBORN ST. CHICAGO 5, ILLINOIS

DECORATIVE MASONRY CAN EARN BIG PROFITS



Patio stones, screen block, and brick are among the many items of garden masonry which can allow a mark-up of 300% or more on basic costs. And yet sold at prices low enough to build a large volume of sales. No other line of concrete products is so rich in market and income potentials.

You can make these profit-producing quick selling items on the new, compact Versacrete machine. With hydraulic movements and automatic controls it makes manufacturing easy and reduces labor costs. Self-contained can be set up anywhere. Requires only a modest investment—which can be paid on time when preferred. Write for interesting literature.



W. E. DUHM MFG. CO.
402 W. 24th Street
Holland, Mich.

VERSACRETE

IT'S EASY TO ROLL OUT THIN LINES with

Master PAINT STRIPER

You can do professional striping on furniture, high-pile carpet, linens, plywood, etc. Master Striper rolls out uniform lines on wood, glass, plastic, ceramics, almost any surface with paint, tempera, glue, textile paint or underglaze, also used in industry.

DOUBLE STRIPE KIT—5 combinations	\$3.50
SINGLE STRIPE KIT—7 line kits	2.50
TYPE M TOOL with 1/8" roller tip	1.00
OTHER SIZE TOOLS 1/4" x 37" 1/4"	2.00
5/8" x 37" 1/4" each	2.00
Each roller set, with above kit \$1.00, 4" dia. 0.75	
IC O.O. & Postage Collect	

MAKES
CLEAN,
STRAIGHT OR
CURVED LINES;
VARIOUS WIDTHS
AVAILABLE.

Dealers: Write today!

WENDELL MFG. CO., 4334 LINCOLN AVE. DEPT. 34
CHICAGO 36, ILL.

FREE

EICO

CATALOG

Build Your Own
Hi-Fi. Radios.

Ham Gear, Test Inst., Save 50%

Get started in ELECTRONICS the easy EICO way. No technical knowledge needed to build EICO kits. Simple, step-by-step "Beginner-Tasted" pictorial instructions guide you all the way. LIFETIME service & calibration guarantee. Mail coupon now!

EICO, 33-00 Northern Blvd., L.I.C. 1, N.Y.
Please send FREE catalog & name of local dealer

Name

Address

City

Zone State

PS-9

TRAIN AT HOME

in your Spare Time or in
Allied Resident School

1338-42 South Michigan Ave.
Chicago 5, Ill.

DRAFTING—All Branches
• Mech. • Structural • Aeronautical

ENGINEERING
• Industrial Engineering
• Tool Engineering & Design

TOOL & DIE MAKING

MACHINIST TRADE

AIR CONDITIONING
Refrigeration • Heating & Cooling

AUTO MECHANICS

SEND FOR
FREE
BOOKS

Please send me the best
which you are offering at the ALLIED
Institute of Technology, 1338-42 South Michigan Ave., Chicago 5, Ill.
I am interested in the following courses:
MECHANICAL DRAFTING
STRUCTURAL DRAFTING
ELECTRONIC DRAFTING
TOOL ENGINEERING
INDUSTRIAL ENGINEERING
TOOL & DIE DESIGNING
AUTO MECHANICS
MACHINIST TRADE
AIR CONDITIONING
REFRIGERATION
TOOL & DIE MAKING

ALLIED INSTITUTE OF TECHNOLOGY,
1338-42 South Michigan Ave. Dept. PS-93 Chicago 5, Ill.

Send me without obligation information on your curriculum

☐ MECHANICAL DRAFTING ☐ AUTO MECHANICS
☐ STRUCTURAL DRAFTING ☐ MACHINIST TRADE
☐ ELECTRONIC DRAFTING ☐ AIR CONDITIONING
☐ TOOL ENGINEERING ☐ REFRIGERATION
☐ INDUSTRIAL ENGINEERING ☐ TOOL & DIE MAKING
☐ TOOL & DIE DESIGNING

☐ HOME STUDY ☐ RESIDENT

NAME _____ AGE _____

ADDRESS _____

CITY _____ COUNTY _____ STATE _____

MEN PAST 40

**Afflicted With Bladder Trouble,
Pains in Back, Hips, Legs,
Nervousness, Tiredness.**

If you are a victim of these symptoms, your trouble may be due to Glandular Inflammation. A constitutional Disease that requires special types of medical treatment. Neglect of such inflammation causes men to grow old prematurely and before their time.

Most men, if treatment is taken in time, can be successfully NON-SURGICALLY treated for Glandular Inflammation. If the condition is aggravated by lack of treatment, surgery may be the only chance.

NON-SURGICAL TREATMENTS

The NON-SURGICAL New Type treatments used at the Excelsior Medical Clinic are the result of discoveries in recent years of new techniques and drugs, plus over 20 years research by scientific technologists and doctors.

Men from all walks of life and from over 1,000 communities have been successfully treated here at Excelsior Springs. They found soothing and comforting relief and new health in life.

EXAMINATION AT LOW COST

When you arrive, our Doctors, who are experienced specialists, make a complete examination. You then decide if you will take the treatments needed, which are so mild hospitalization is not needed - a considerable saving in expense.

Write For FREE BOOK

The Excelsior Medical Clinic has published a New FREE Book that deals with diseases peculiar to men. It could prove of utmost importance to your future life. Write today. No obligation.



**EXCELSIOR
MEDICAL CLINIC**
Dept. 86251
Excelsior Springs, Mo.

Gentlemen: Kindly send me at once, your New FREE Book. I am interested in full information. (Please Check Box)

- ☐ Glandular Inflammation ☐ Hernia
☐ Rectal-Colon

Name.....

Address.....

City..... State.....


RECTAL-COLON

Are often associated with Glandular Inflammation. These disorders, we can successfully treat for you, at the same time we treat Glandular Inflammation.

REDUCIBLE HERNIA

Is also amenable to a painless Non-Surgical treatment that we have developed. Full details of this treatment given in our Free Book.

HOME IMPORT BUSINESS



**MEN... WOMEN... MAKE
BIG PROFITS...** Buy dazzling bargains abroad. Sell to friends, stores or mail order. New Drop Ship Plan puts you in direct contact with overseas sources—starts you full or spare time, without product investment or previous experience. Complete details FREE. Write today!

MELLINGER CO., Dept. T249
1717 Westwood, Los Angeles 24, Calif.

...Plan shows where you get bargains from abroad for big profit sales. **DO NOT ORDER FROM US!**

PROFIT IN YOUR SPARE TIME

SMALL ENGINE REPAIR PAYS BIG!

Outboard • Powermower • Chain Saw • Tractor
MAKE EXTRA MONEY — or fix your own engines and SAVE! Illustrated, easy-to-learn Home Study Course qualifies you as expert. Free information. Write today!



LINCOLN TECHNICAL INSTITUTE
Suite B-2, 472 Market Street, Newark 5, N. J.

REAL ESTATE BE A BROKER

PAY \$100 SEND FOR FREE, BIG, ILLUSTRATED CATALOG NOW! Graduates report making substantial incomes. Start and run your own business quickly. Men, women of all ages. Learn easily. Course covers Sales, Property Management, Appraising, Loans, Mortgages, and several subjects. **STUDY AT HOME** or in classroom in leading cities. Diploma awarded. Write TODAY for free book! No obligation.

**FREE
BOOK
TELLS
NOW**

Approved for World War II and Korean Veterans
WEAVER SCHOOL OF REAL ESTATE (Est. 1886)
20208 Grand Ave. Kansas City, Mo.



**IS
EASY
NOW**

Famous System of Manual Training brings a complete new conception in Art Instruction at home... Cartooning is a wonderful profession that offers Men and Women a wide field rich in unequalled opportunities to make good money. It is worth while to get the facts. Ask for free information today.

Continental Schools, Inc.
DEPT. E-3 4201 S. BROADWAY, LOS ANGELES 17, CALIF.

GET INTO ELECTRONICS

V T I training leads to success as technicians. Read engineers. Work in electronics communications. Guided in studies. Employs radio automation. Learn advanced courses in theory & laboratory. Your degree in 18 months. B.S. obtainable. E.T.I. approved & adjusted with most colleges. Start Sept. 1. Full-time campus. H.S. graduate or equivalent. Catalog.

VALPARAISO TECHNICAL INSTITUTE
DEPT. 5 VALPARAISO, OHIO

TELEPHONE



HANDSETS

Use as inter-house phone, talk house to garage, as loud speaker system, etc. You receive transmitter, receiver, 8 conductor cord and simplified, illustrated installation diagrams. Handsets are guaranteed to be the same as used in our great National Telephone System. Price delivered \$2.95. Two for \$5.00!

TELEPHONE REPAIR AND SUPPLY CO.
Dept. PS-615 1760 Leapt Ave., Chicago 26

THE 'SLICKEST' QUICKEST AUTO REPAIR GUIDE! YOU'VE EVER TRIED!



Completely new and different!
Easier to use!
Easier to understand!

... BIG TROUBLE SHOOTING SECTION
HELPS YOU FIND EXACTLY WHAT'S WRONG
WITH CARS EASIER, IN LOTS LESS TIME!

- Covers all leading U.S. models for 12 years . . .
- All foreign cars sold in U.S. . . .
- Plus tune-up and front end specs for 125 U.S. trucks

Glenn's giant Auto Repair Manual in the new 1961 Edition weighs over 4 lbs. It has 1100 big pages; over 3000 specially taken "here's how" pictures; and hundreds of thousands of repair facts covering practically every part of every U.S. car, truck or foreign car you might want to tune-up, repair or rebuild. Published by Chilton—world's largest automotive publishers.

Almost 100 pages and 348 pictures—the most comprehensive section of its kind ever published—show how to service and repair modern carburetors and fuel injectors.

A big electrical section includes both chassis and accessory circuit diagrams. Over 100 current foreign cars by 35 mfrs. are covered. There is a big Volkswagen section.

GOODBYE TO GUESSWORK!

You've got to find the trouble before you can fix it! Most manuals neglect this vital subject—but not Glenn's! QUICK-GUIDE TROUBLE SHOOTING CHARTS for every section of a car help you locate troubles in lots less time! Hundreds of users say this feature alone is worth the entire price of the book!

For instance, there are 5 possible reasons why a clutch might slip; 9 reasons for it to drag; 7 reasons for noise; 11 for chattering. Glenn's quickly helps you locate the exact trouble cause—just as it does for other parts or assemblies from transmissions to electrical systems or searching out engine noises, etc.

DOWN-TO-EARTH SERVICE TRAINING

Glenn's shows you how—even if you've never fixed a car before. Includes details on Engines; Air Conditioning; Axles; Bodies; Manual & Power Brakes and Steering; Clutches; Cooling; Power Accessories; Electrical & Fuel Systems; Std. & Automatic Transmissions; Overdrives; Universals; Drives; Tune-ups—and all the rest. It's a comprehensive, easily understood training manual for beginners—a real time-saver for experienced mechanics.

THOUSANDS OF CAR REPAIR FACTS . . . Arranged, explained, illustrated and indexed for your convenience

The largest selection of worn parts pictures ever assembled shows where to look for wear in parts—and exactly what it looks like when you find it.

All pictures are so closely keyed to text that you're seeing what to do while you're reading.

Disassembling and reassembling; cleaning and inspecting are fully explained. You get clearance and tolerance data

right with these instructions—NOT somewhere else.

Shortcuts and cautions are pointed out. Easily understood demonstrations of bench adjustments and on-the-car repair procedures save you loads of time and work. From beginning to end, Glenn's gives you needed information the way you'd like to have it!

PRACTICE 7 DAYS FREE!

Dept. PS-91, THE CHILTON CO.
56th & Chestnut Sts., Philadelphia 39, Pa.

Send GLENN \$ new 1100 page Auto Repair Manual for 7 days FREE EXAMINATION. I will then remit \$3 in 7 days, pay \$3 a month later, and a final payment of \$1.95 (plus 45c postage) a month after that. Otherwise, I will return Manual postpaid.

SAVE 45c shipping charge! Send \$7.95 in full payment of Manual with order and Chilton pays for shipping. Money promptly refunded if you return book postpaid promptly after 7 days.

Name Age
Address
City Zone State

CASH FOR YOU-



Electric APPLIANCES

Learn at Home • \$3 to \$5 an Hour
Spare Time, Full Time • Be Your Own Boss

FREE BOOK tells about profitable business you can run — right at home. Repair Electric Appliances, using simple tools. Pays \$3-\$5 an hour!

CASH IN ON THIS BIG BOOM 400 MILLION Appliances are in American homes right now. People need them fixed. You make good money doing it. In your basement, garage, even your kitchen.

QUICK WAY TO GET STARTED For less than 30¢ a day our

easy, pictured instruction — backed by 45 years of success in home-training — prepares you for top earnings. Earl Reid of Thompson, Ohio says "Made \$510 in one month spare time." At no extra charge you get **Appliance Tester** too. Finds trouble-spots, checks your work. Get your **FREE Book** and **FREE Sample Lesson**. Mail coupon below letter or postcard, now.

NATIONAL RADIO INSTITUTE, Appliance Div.
Dept. E1, Washington 16, D. C.

Send Free Book, Free Appliance Repair Course Lesson. Am interested in:


☐ Spare Time Earnings ☐ My Own Business
☐ Better Job

Name _____

Address _____

City _____ Zone _____ State _____

Accredited Member National Home Study Council



"I Earn \$20-a-Week Extra Now"



Says Samuel J. DeFazio,
Utica, New York

"I should have taken this course 20 years ago, for now I've added an extra \$20 to my weekly earnings. Even while learning I made enough to pay for tuition and tools."

Be a LOCKSMITH

Add 50%-100% to YOUR INCOME with easy spare time earnings. Cash in on nationwide shortage — trained locksmiths in demand! Quickly step into a big-pay opportunity job — high-profit shop of your own.

Earn Extra Money RIGHT AWAY! All Special Tools, Supplies Furnished FREE.

Age, education, minor physical handicaps don't matter in this growing trade. You can quickly qualify as a skilled locksmith. Study at home as little as one hour a week. Gain practical experience through well-illustrated lessons. Do real jobs on car locks, house locks, padlocks and safe locks, under the guidance of experts.

MAIL COUPON FOR FREE BOOK

For a future as your own boss or in a high-pay job, write now for FREE illustrated book! Only school of its kind Lic State of N.J. Accredited NHSC Locksmithing Institute, (Div. Tech. Home Study Schools)

Dept. 209-1, 150 Park Ave., E. Rutherford, N.J.

MAIL COUPON NOW!

LOCKSMITHING INSTITUTE, Dept. 209-1
150 Park Avenue, E. Rutherford, N.J.

Please send Free Illustrated Book without obligation.

Name _____

(Print here)


Address _____

City _____ Zone _____ State _____

☐ Check if Veteran (No Salesmen will call)

PURIFIES AIR

... with NO
outside
ducts!



ELIMINATES COOKING ODORS, removes smoke, grease—even pollen—by time-tested scientific miracle of recirculation through filters of Activated Charcoal—the substance that purifies air in atomic submarines. Self-contained DUCTLESS HOOD permits total freedom in kitchen design.



ORDINARY HOOD, ducts costly to install — use shell space — waste of house heat and conditioned air.

Write for literature: **THE DUCTLESS HOOD CO., INC.**
801 Plandema Rd., Manhasset 8, N. Y.



BARBELLS

140-Pound CHROME DELUXE Barbell (Dumbbell) set only \$19.00.


This is our feature set and is the finest ever manufactured. Training with adjustable weight is the BEST way to keep fit, the ONLY way to develop great strength and a perfect body. As the old, well-known and best maintained barbell company, BULL gives value and prices no one can equal.

SEND FOR FREE CATALOG.

BULL BARBELL CO.

Lyndhurst 5, New Jersey

FREE GERMAN HUNTING KNIFE



We give you handiest hunting and fishing knife you've ever had! Has a 4 IN. H. LONG, highly tempered steel blade—VERY SHARP! Attractive handle. We send knife FREE to anyone who writes our office and sends a 35¢ for handling NO MONEY! But send 25¢ handling for each knife. Order TODAY! HUNTING KNIFE, Dept. K-603, Box 881, St. Louis, Mo.

MEN WANTED

Earn \$125 Per Week and up

AUTO DIESEL MECHANICS

Master a trade with a future — learn Auto-Diesel mechanics in our shops. You learn with tools on real equipment. Earn while you learn. Many of our graduates earn \$125 per week and up. No previous experience necessary. Day and night courses. Approved for veterans.

Write for free bulletin
AUTO-DIESEL COLLEGE
726 1/2 Ave. N. Dept. 4
Minneapolis 5, Minn.

LOANS by mail

\$100-\$600 to responsible borrowers anywhere. Confidential. Easy payments.

Write **UNION FINANCE**

Dept. P50 328 E. Camelback Phoenix, Ariz.

Please Mention Popular Science
When Writing to Advertisers

NEW • BENSON • GYRO-COPTER



Plans and kits for one-man "Spirit of Kitty Hawk" now available. Easy to build and fly. 3-view drawings, specs, photo \$2 or simpler Copter Glider \$1. Order today!

BENSON AIRCRAFT CORP., Dept. P5-91
Raleigh-Durham Airport, Raleigh, N.C.

NAME _____

ADDRESS _____

Learn **PACKAGING!**

MAKE TO 2500% PROFITS AT HOME
YOU PACKAGE WE DO YOUR SELLING!

HERE'S PROOF
that Packaging means
Big Profits for You!

Item	Bulk Cost	Sells For
Per Doz.		
Safety Pins	2 1/2¢	15¢
Balloons	3 1/2¢	18¢
Fish Hooks	2¢	50¢

Make profits like these on over 100,000 other products you can package right in your own home. We show you how!

Package products at home for nationwide sales force. You package bulk items in your own home. We do your selling coast-to-coast. **FREE** 'No Selling Plan' reveals thousands full, spare time big profit opportunities for beginners in self-service packaging, contract packaging, gift wrapping. We guide you step by step. Everything furnished. Write today for **FREE 6-STEP PACKAGING PROFIT PLAN** and full details. No salesman will call.



HOME PACKAGING CO. Dept. H 240
2212 E. Jesse St. Los Angeles 23, Calif.



WANT MORE MONEY? **GET INTO PHOTOGRAPHY**

Coast to coast, high paying jobs in photography are waiting for people with the 'know-how' to fill them. You can quickly easily qualify at home with the world famous NYI learn by Doing Method. Write today for free catalog. Also resident training in N. Y. Our 52nd Year. Approved for Veterans.

NEW YORK INSTITUTE OF PHOTOGRAPHY
Dept. 5 10 West 33 St. New York 1, N. Y.



Another **NEW**
Taft Kit!

"2 SEASON"
AIR BOAT
& Snow Sled
(not shown) **KIT**

with surplus aircraft engine
\$2237.50 **\$3804**
Down Per Mo.

TAFT MARINE WOODCRAFT
Dept. PS 881 638 39th Ave. N.E.
Minneapolis 21, Minnesota



LEARN CRIMINAL INVESTIGATION at home

Prepare for an exciting job, good pay, security! We teach you at home in spare time. Learn Finger Printing, Firearms Identification, Criminal Investigation, Police Photography. Low cost easy terms. Over 200 Bureaus of Identification employ our graduates! Write for famous "Blue Book of Crime"—free! State age please. (A Correspondence School Since 1916).
Institute of Applied Science
1030 BUNNYSIDE AVENUE • DEPT. 1366 • CHICAGO 40, ILLINOIS

POWERFUL NEW INVENTION, ONLY 2" LONG

SHOOTS THRU 100
PAGES-THIS BOOK!
'B-B SHOT'



MAKE THIS TEST... Load your 'BB Shot' and fire against this magazine. Notice that it drives BB's through more than 100 pages. Though only 2" long x 1" in diameter, this pocket-size device has amazing power and accuracy. Use it for targets, pests and hunting. Scientifically designed for high power, operating ease and safety.

FREE! Get the 'BB Shot' now — we'll include an extra Velocity Cone and **FREE** Target, BB's and Automatic BB Dispenser... all for only \$1.98 ppd. Money Back Guarantee. Not sold to N. Y. C. residents or minors.

GRAYSON CO. • Dept. B-45, 210 Fifth Ave., N. Y. C. 10

MONEY-BACK
GUARANTEE

NAME _____
Address _____
City _____ State _____

\$1.98
ppd.

motorists
who
appreciate
quality



ask for...

KENDALL



To protect their investment

The superior quality of Kendall Dual Action or Kendall SuperB Motor Oil will keep your engine operating smoother and quieter. The same quality protection assures less wear, less need of repair — and millions of motorists have proved it.

REFINED FROM THE CREAM OF PENNSYLVANIA
CRUDE OIL

Kendall Refining Company
Bradford, Penna.

EARN \$10,000 A YEAR

- ☐ DIESEL ☐ ELECTRONICS
☐ AUTO ☐ AUTOMATION

The average starting salary of students, completing our FCC License, Electronics Technician Course, and those completing our Diesel Automotive Training, is \$4,300 per year.

After becoming familiar with the industry, their salary usually increases to \$6,000 or \$7,000 per year.

After they become senior technicians, or master mechanics, they can earn \$8,000 to \$10,000 per year.

When they become specialists, or a part of management, or start their own business... they can earn considerably more.

RESIDENT SHOP TRAINING is easier and costs less than you may think! We provide you with housing and part-time jobs while in school, plus free nation-wide placement service for graduates.

Check subject above in which you are interested and mail for

4-year course
in
ELECTRONICS
AND
AUTOMATION

FREE BOOKLET

BAILEY

Technical Schools

Veteran Approved

626 S Grand Rm 50 St Louis 4 Mo

Name _____ Age _____

Street _____

Town _____ Zone _____ State _____

New Table Top Invention Puts You In...

PROFITABLE RUBBER STAMP BUSINESS

Home Operators now make \$9.20 AN HOUR in Business once monopolized by a few big companies

Special rubber stamps bring high prices—cost only a few pennies to make on new, low cost table top machine. Take 2¢ cents worth of material and make perfect stamps. The kind business and offices now buy by the dozen at \$9.20 an hour. Start in spare time in your own home. Run machine on kitchen table using ordinary electrical outlet. Make any kind of stamp. We'll send you free information without obligation about this exciting high profit business. We'll even help finance your start. For free information send name and address today on a postcard to Rubber Stamp Div., 1512 Jarvis Ave. Dept. E-3-K, Chicago 28

Save on Parts, Equipment!

Send for America's most complete, exciting Electronics Catalogs... Radio Shack's bigger, better than ever 336 page Buying Guide plus supplements for 12 months! See Stereo, Hi-Fi, Ham Radio, Tapes, Records, Kits. No money down credit terms. Satisfaction guaranteed. RADIO SHACK Corp. 730 Commonwealth Ave. Boston, Mass.

FREE
ELECTRONICS
CATALOGS
for 1 full year

RADIO SHACK Corp. Dept. 614A
730 Commonwealth Ave., Boston 17, Mass.
Send me Radio Shack's famous electronics catalogs for 1 full year—all FREE and POSTPAID.
Name _____
Address _____
City _____ Zone _____ State _____

MAIL
Coupon
TODAY

Processing of KODACHROME (Licensed by Eastman Kodak)

AT DISCOUNT PRICES

KODACHROME

I & II

8mm ROLL OR

35mm 20 EXP. MTD

8mm MAGAZINE75

35mm 36 EXP. MTD.....1.75

SEND FOR FREE MAILERS and our big FREE CATALOG of Processing, Film and Equipment at DISCOUNT PRICES!



SOLAR KINE 4247 S. Kedzie
PRODUCTS Chicago 32, Ill.

\$10.95
COMPLETE



COLOR DIAL TELEPHONES

Factory rebuilt Western Electric in white, beige, ivory, pink, green or blue. If 4 prong plug is required add \$2.00 Fully guaranteed. Write for free list. All shipments FOB

SURPLUS SAVING CENTER

Waymart

Dept. 8A1

Penna.

SIGN PAINTING

Home-Study Course—Only \$9.95

Teaches you commercial sign painting and sign writing as it is being done TODAY in leading shops all over the country. Complete practice, review for self instruction. Shows latest methods of truck lettering. No guide work. Signs, reflecting signs, plan, line, shaded signs, gold leaf, etc. Includes all the latest techniques. Includes everything you need to get started. Satisfaction GUARANTEED OR REFUND. No money back! Order today. Satisfaction or money back! Order "Sign Painting Course".

NELSON-KALL CO., 325 W. Jackson Blvd., Dept. 2JN-1, Chicago 6, Ill.

FREE GUIDE Reveals 200 Ways to Make Extra Money

YOU can turn your spare hours into cash (\$25 to \$100 a week) by selling products and services to friends and others. Famous Housewife's Opportunity Magazine shows you how. Contains hints, plans, hundreds of offers. No matter what your age, experience or occupation, write TODAY for next 5 issues—absolutely FREE! Send no money just name.

OPPORTUNITY, 650 N. Dearborn, Dept. 381, Chicago 10, Ill.

ANALYZE HANDWRITING

MORE INCOME... MORE PRESTIGE and Greater PERSONAL Success!


YOU CAN learn how to identify character and personality traits from one's handwriting. Learn how to analyze handwriting. Many a job or promotion has been won and money made by those who have learned to analyze handwriting. Full of value, this book will show you how to analyze handwriting. A FREE sample copy and the complete book sent free. No salesman will bother you. (State Dept.)

INTERNATIONAL GRAPHO ANALYSIS SOCIETY, INC.
325 W Jackson Blvd., Dept. JN 1, Chicago 6, Ill.



Please Mention Popular Science When Writing to Advertisers

EXCLUSIVE RUBBER-BEARING HEAVY DUTY PUMPS




INDICATE • DRAIN • CIRCULATE • SPRAY
Use with motor or engine. 1 HP for up to 5,000 GPH; 1.5 HP for up to 7,000 GPH; or 2.0 HP for up to 10,000 GPH. 1" outlet. Stainless steel. TYPE X—2 oil free. \$10.95
TYPE AB—Ball bearing model. \$12.95
Best for belt drives.
Postpaid if cash with order.
Don't delay—send for yours today!
MONEY BACK GUARANTEE
Centrifugal and Gear Pumps in All Sizes
LABAWCO PUMPS, Belle Mead 4, N. J.

This substance is now available in suppository or ointment form under the name Preparation H®. Ask for it at all drug counters.

[illegible]

NEW 4 in one telescopes, 3 variable 2 X
45X 75X magnification 3mm eyepiece
18 power for ultra bright images
43 & 75 power for long range
Guaranteed to bring dis-
tant stars, moons, ob-
jects, sports 75
times closer

**Most powerful
scope sold anywhere**



NOW! ACCORDIONS
UP TO **1/2 OFF** Retail prices of comparable instruments.



**5 DAY
FREE TRIAL**

ACCORDION CORPORATION OF AMERICA
Dept. P-21, 2002 W. Chicago Avenue, Chicago 22, Illinois
Ruehlor Catalogs and 'Importer-to-You' prices on famous-make
accordions. **FREE.**

NAME
ADDRESS
CITY STATE

It's Like Having Factory Experts Right Beside You...



SHOWING YOU
**HOW TO FIX ANY PART
OF ANY CAR**

**Now — Whether You're a Beginner
or an Expert Mechanic — You Can
"Breeze Through" Any Repair Job—
QUICKLY — EASILY — RIGHT!**

THERE'S ONE SURE WAY to "lock" any auto repair job — that's to get the advice of a real auto expert! MOTOR'S Auto Repair Manual brings you this expert guidance from the engineers who make the cars and know them "inside out." Yes, you get the "know-how" from 176 OFFICIAL SHOP MANUALS — boiled down into one giant volume!

No guesswork! MOTOR's Manual "starts from scratch" - leads you through entire job with easy step-by-step directions, clear "how-to" pictures. You CAN'T go wrong!

7,100 B/W PAGES — 2,850 PICTURES

New, Revised Edition covers 2 1/2 car models - 1973 thru 1991, including all the new compact cars 1 1/2. Giant Pages 2 1/2. This is how Pictures 195 Quick-Check Charts 12 1/2 1000 manual for

**Same Free
Offer on
NEW TRUCK
REPAIR
MANUAL**


Covers every job on every popular gasoline powered truck made since 1932 plus GM, Mack and Cummins Diesels.




**TRY BOOK FREE
7 DAYS** — Send no
money. Just mail
coupon (paste on mail-
card for **FAST** ac-
tion). Use Manual for
whole week free. If
not greatest lines and
money saver you've
ever seen — return
book in 7 days and
owe nothing! Mail
coupon **7 DAY** to:
MOTOR BOOK CO.,
Dept. 125, 350 W.
5th St., New York
19, N. Y. (Schools &
Bookstores. Write for
disclosure.)



ALL AUTOMATIC
TRANSMISSIONS 19139



姓名: _____ 学号: _____
 班级: _____ 日期: _____
 教师: _____



τ μ π η α η ε λ ε ν
 τ η ν π ρ ο τ ρ υ γ η ο υ τ ο υ
 ε γ κ λ ο ν ο υ σ α ν τ ο υ

MAIL COUPON NOW FOR 7-DAY FREE TRIAL
Attach to postcard for fast action!

MOTOR LOOK DEPT.

Desk 129, 250 W. 53 St., New York 19, N. Y.

Rush to me at once (check box opposite to book you want):

☐ **MOTOR'S New AUTO REPAIR MANUAL.** If O.K., I will return \$2 in 7 days. \$2 monthly for 7 months and a final payment of \$2.95 plus 4.00 delivery charges and a \$3 tax, one week after that. Otherwise I will return the book postpaid in 7 days.

☐ **MOTOR'S New TRUCK REPAIR MANUAL.** If O.K., I will term \$3 in 7 days. \$3 a month over then \$2 monthly for 3 months, plus 4% delivery charges and sales tax with final payment. Otherwise I will return book postpaid in 7 days.

Print Name.....Age.....

1 2 3 4 5 6 7 8 9 10 11 12 13 14 15 16 17 18 19 20 21 22 23 24 25 26 27 28 29 30 31 32 33 34 35 36 37 38 39 40 41 42 43 44 45 46 47 48 49 50 51 52 53 54 55 56 57 58 59 60 61 62 63 64 65 66 67 68 69 70 71 72 73 74 75 76 77 78 79 80 81 82 83 84 85 86 87 88 89 90 91 92 93 94 95 96 97 98 99 100 101 102 103 104 105 106 107 108 109 110 111 112 113 114 115 116 117 118 119 120 121 122 123 124 125 126 127 128 129 130 131 132 133 134 135 136 137 138 139 140 141 142 143 144 145 146 147 148 149 150 151 152 153 154 155 156 157 158 159 160 161 162 163 164 165 166 167 168 169 170 171 172 173 174 175 176 177 178 179 180 181 182 183 184 185 186 187 188 189 190 191 192 193 194 195 196 197 198 199 200 201 202 203 204 205 206 207 208 209 210 211 212 213 214 215 216 217 218 219 220 221 222 223 224 225 226 227 228 229 230 231 232 233 234 235 236 237 238 239 240 241 242 243 244 245 246 247 248 249 250 251 252 253 254 255 256 257 258 259 260 261 262 263 264 265 266 267 268 269 270 271 272 273 274 275 276 277 278 279 280 281 282 283 284 285 286 287 288 289 290 291 292 293 294 295 296 297 298 299 300 301 302 303 304 305 306 307 308 309 310 311 312 313 314 315 316 317 318 319 320 321 322 323 324 325 326 327 328 329 330 331 332 333 334 335 336 337 338 339 340 341 342 343 344 345 346 347 348 349 350 351 352 353 354 355 356 357 358 359 360 361 362 363 364 365 366 367 368 369 370 371 372 373 374 375 376 377 378 379 380 381 382 383 384 385 386 387 388 389 390 391 392 393 394 395 396 397 398 399 400 401 402 403 404 405 406 407 408 409 410 411 412 413 414 415 416 417 418 419 420 421 422 423 424 425 426 427 428 429 430 431 432 433 434 435 436 437 438 439 440 441 442 443 444 445 446 447 448 449 450 451 452 453 454 455 456 457 458 459 460 461 462 463 464 465 466 467 468 469 470 471 472 473 474 475 476 477 478 479 480 481 482 483 484 485 486 487 488 489 490 491 492 493 494 495 496 497 498 499 500 501 502 503 504 505 506 507 508 509 510 511 512 513 514 515 516 517 518 519 520 521 522 523 524 525 526 527 528 529 530 531 532 533 534 535 536 537 538 539 540 541 542 543 544 545 546 547 548 549 550 551 552 553 554 555 556 557 558 559 560 561 562 563 564 565 566 567 568 569 570 571 572 573 574 575 576 577 578 579 580 581 582 583 584 585 586 587 588 589 590 591 592 593 594 595 596 597 598 599 600 601 602 603 604 605 606 607 608 609 610 611 612 613 614 615 616 617 618 619 620 621 622 623 624 625 626 627 628 629 630 631 632 633 634 635 636 637 638 639 640 641 642 643 644 645 646 647 648 649 650 651 652 653 654 655 656 657 658 659 660 661 662 663 664 665 666 667 668 669 670 671 672 673 674 675 676 677 678 679 680 681 682 683 684 685 686 687 688 689 690 691 692 693 694 695 696 697 698 699 700 701 702 703 704 705 706 707 708 709 710 711 712 713 714 715 716 717 718 719 720 721 722 723 724 725 726 727 728 729 730 731 732 733 734 735 736 737 738 739 740 741 742 743 744 745 746 747 748 749 750 751 752 753 754 755 756 757 758 759 760 761 762 763 764 765 766 767 768 769 770 771 772 773 774 775 776 777 778 779 780 781 782 783 784 785 786 787 788 789 790 791 792 793 794 795 796 797 798 799 800 801 802 803 804 805 806 807 808 809 810 811 812 813 814 815 816 817 818 819 820 821 822 823 824 825 826 827 828 829 830 831 832 833 834 835 836 837 838 839 840 841 842 843 844 845 846 847 848 849 850 851 852 853 854 855 856 857 858 859 860 861 862 863 864 865 866 867 868 869 870 871 872 873 874 875 876 877 878 879 880 881 882 883 884 885 886 887 888 889 890 891 892 893 894 895 896 897 898 899 900 901 902 903 904 905 906 907 908 909 910 911 912 913 914 915 916 917 918 919 920 921 922 923 924 925 926 927 928 929 930 931 932 933 934 935 936 937 938 939 940 941 942 943 944 945 946 947 948 949 950 951 952 953 954 955 956 957 958 959 960 961 962 963 964 965 966 967 968 969 970 971 972 973 974 975 976 977 978 979 980 981 982 983 984 985 986 987 988 989 990 991 992 993 994 995 996 997 998 999 1000 1001 1002 1003 1004 1005 1006 1007 1008 1009 1010 1011 1012 1013 1014 1015 1016 1017 1018 1019 1020 1021 1022 1023 1024 1025 1026 1027 1028 1029 1030 1031 1032 1033 1034 1035 1036 1037 1038 1039 1040 1

Address:

City _____ Zone _____ State _____
 An check box and save it to delivery phone by number

☐ Check box and save 43¢ delivery charge by enclosing WITH coupon in envelope entire payment of \$4.05 for

Auto Repair Manual: or \$1.10 for Truck Repair Manual, plus

Sales tax. Same return-refund privilege.

Free!



**BRAND NEW
LAFAYETTE
ELECTRONICS**

1962

CATALOG 620

**It's Bigger and Better
Every!**

340 giant-sized page catalog from the world's leading supplier of electronics and stereo hi-fi equipment.

340 PAGES

It's a complete shopping center for audiophiles, technicians, engineers, students, hobbyists, servicemen and dealers. Thousands of items at lowest money-saving prices — featuring LAFAYETTE KITS . . . the best value for your money any day.

SPECIAL! NO MONEY DOWN

With Lafayette's NEW EASY-PAY PLAN.

MAIL THE COUPON TODAY FOR YOUR FREE CATALOG

LAFAYETTE ELECTRONICS

**MANHATTAN • BROOKLYN • NEW YORK CITY
NEWARK • PLAINFIELD • PARAMUS • BOSTON**

Lafayette Electronics Dept. KI 1
P.O. Box 190, Jamaica 31, N. Y.
Send me the FREE 340-pg. 1962 catalog 620.

Name _____

Address _____

City _____ Zone _____ State _____

**you can always
BE SURE OF A JOB**



WITH A

FOLEY SAW FILER

Have you been laid off — or afraid you may be? If you want soon to pick a bigger job — or even don't pick it — a job — start your own spare time business. In his first 2 months J. P. Houtchens earned \$100 with his Foley Saw Filer. From his starting day it's made \$100 in 4 months. Frank P. Layne writes: "In our town of 2,800, instead of 200 to 300 saws I did over 1,500 the first year. Average about \$1.50 on it." **FREE booklet "MONEY MAKING FACTS"** shows you how to get business. The new Model 3M Foley saw pens hand, hand and both "hand" and "foot" and comes with saws 1 or 2 in. Payment Plan pay for the machine out of your CASH profits. Retail coupon today — no obligation. Send no salesman will call.

FOLEY MFG. CO., 949-1 Foley Bldg., Minneapolis 12, Minn.
Send Free Booklet and Time Payment Plan on Foley Saw Filer.

Name _____

Address _____

City _____ State _____



NEW— POCKET SIZE INVENTION HELPS



HYPNOTIZE

**YOURSELF or OTHERS
IN MINUTES!**

MUST WORK OR MONEY BACK!

Hold the HYPNO-COIN in front of the person you want to hypnotize. Gently vibrate the plastic lens. This sets a vibrating hypno or path on the spot on that is so fascinating. It captures and holds our subject's gaze. Now give your hypnotic suggestions! Get this amazing hypnotic aid complete with a FREE revealing booklet of secrets and instructions that tell you what to say and do, how to rummage and re-hypnotize with the snap of a finger, how to thrill and amaze them with hypnotic tricks, etc. Get the COIN, Booklet and Stand for Self Hypnosis only \$1.00 and sent in a plain wrapper. Money back if not delighted!

HYPNOTIC-AIDS • Dept. A-75, 1133 Broadway, N.Y.C. 10

\$1.00 Name _____ Address _____

SHORTHAND IN

Famous SPEEDWRITING shorthand. 120 words per minute. No symbols, no machines, uses ABC's. Learn at home or through classroom instruction. Low cost. 300,000 graduates. For business and Civil Service Typing available. 38th Year. Schools in over 100 cities. Write for FREE booklet.

Speedwriting Dept. 2609-1
85 W. 43 St., N.Y. 36, N.Y.

**6
WEEKS**

**"\$7,108.50 FIRST YEAR
SERVICING RADIATORS!"**

— Hank Kester, Newcastle, Wyo.

Make good money servicing auto-truck-tractor radiators. Easy to learn. Inland, world's largest radiator equipment mfr., offers complete package — equipment, merchandising, "pay for itself" financing, free training. Small down payment on equipment starts you. Profitable dept. for garage or service station. Write

INLAND MFG. CO., Dept. PS-9, 1100 Jackson St., Omaha 2, Nebr.

HYDRAULIC JACK REPAIRS



Earn While You Learn at Home

Millions of jacks in gas & auto service stations, truckers, body shops, riggers, factories, farms need servicing. We show you HOW — easy step by step directions — what tools to use. **EARN UP TO \$5 an hour** in spare time in your own basement or garage. Start your own business NOW. Write for folder No. PS 9 & free bonus offer.

Institute of Hydraulic Jack Repair
P.O. Box 30, Bloomfield, N. J.

Broken or Loose FALSE PLATE?




Fix it Yourself EASILY in a Few Minutes

Your plates may become broken or loose just when you need them most. With **FIX IT KIT** you can repair your own broken plates. Also tightens loose fitting plates easily. Get permanent comfort with professional material. Complete instructions. Satisfaction guaranteed or your money refunded. Order Now at a new low price only **\$2.99** postpaid — or sent C.O.D.

DENT FIX DENTAL PRODUCTS, Dept. 149, Box 674, Kansas City 41, Mo.

**Buy and Hold
U.S. Savings Bonds**

UNIVERSAL SAFETY ESCAPE LADDER • A REAL LIFE SAVER
14, 20, 26, 32 rungs to self-rescue. Contains 100' of rope. **\$19.95**



10' \$19.95
25' 26.95
35' 36.95
45' 46.95
Send check or M.O. \$5 deposit on c.o.d. Shipped express collect.
PLANK & SONS ENGINEERING DEVELOPMENT CO.
4201 38th St., S.E., Ark., Michigan

PROTECT YOURSELF

with this Fountain Pen-Type POKET

TEAR GAS

DEVICE...\$15 VALUE 38 Special Col.

\$6.95 Exp. Additiona
Co., shells 50c ea
with 1 shell

For police or civilian
defense against robbers,
mishers, etc. Causes no
permanent injury. Highly
polished heavy nickel
case with spring-steel
pocket clip.

SEND CHECK OR
MONEY ORDER NO COD'S

This Product is not intended for sale in states
or areas which have laws forbidding the sale

Nickel Plated
Pocket Type

HANDCUFFS

\$5.00 value **\$7.95**
SPECIAL or

Deluxe leather
carrying case \$2.50

Registered Cell Distributors
Suppliers for
Official Police Equipment

PUBLIC SPORTS SHOPS, DEPT. P-7 11 S. 16th St., Phila. 2, Pa.

You Can Have a HE-MAN VOICE

STRENGTHEN your voice the tested,
scientific way. You—you may now be
able to improve the POWER of your
speaking and singing voice... in the
privacy of your room! Self-training
lessons, mostly silent. No music re-
quired.

FREE BOOKLET

Write today for Eugene Foughtinger's
great booklet "How to Develop a
Successful Voice." It's absolutely
FREE! You must state your age. Booklet mailed postpaid in
plain sealed envelope. No salesman will bother you. Send your
name and age RIGHT NOW

PERFECT VOICE INSTITUTE

325 W. Jackson Blvd. Studio JN-3, Chicago 6, Ill.



LAW FREE BOOK

THE LAW
TRAINED
MAN

Write today for a FREE copy of illustrated law book "THE LAW-
TRAINED MAN," which shows how you can learn quickly at home
the basic principles of a law topics through the famous Blackstone
Law Course. All necessary books and answers provided. Moderate cost
convenient monthly terms. Write for FREE law training book today.

Blackstone School of Law, 307 N. Michigan Ave.

Founded 1890 Dept. 126, Chicago 1, Illinois



Repair any watch

... SWISS OR AMERICAN

Unique modern Markey System starts from
making repairs right away. This is the only
step by step at home in spare time. Tui-
tion \$5 monthly, diploma awarded. Free
sample lesson. No obligation.

CHICAGO SCHOOL OF WATCHMAKING

2330 Milwaukee, Dept. 491, Chicago 47, Ill.

High School at Home

MANY FINISH IN 2 YEARS

No classes. No time wasted going to and from school.
Progress as fast as your time and abilities permit. Standard
H. S. texts supplied. Thousands enroll each year in this
64-year-old school. Send for FREE descriptive booklet.

AMERICAN SCHOOL, Dept. H646

Drexel at 48th St., Chicago 37, Ill.

Without obligation, please send FREE descriptive booklet.

Name.....

Address.....

Accredited Member National Home Study Council

FREE CAREER BOOKLET



To guide you to a
successful future in

ELECTRONICS RADIO-TV COMPUTERS ELECTRICAL ENGINEERING

This interesting pictorial booklet tells you
how you can prepare for a dynamic career
as an Electrical Engineer or Engineering
Technician in many exciting, growing
fields:

MISSILES • AVIONICS • AUTOMATION
SALES • DEVELOPMENT
ELECTRICAL POWER • ROCKETRY
RADAR • RESEARCH

Get all the facts about job opportunities,
length of study, courses offered, degrees
you can earn, scholarships, part-time work
— as well as pictures of the Milwaukee
School of Engineering's educational and
recreational facilities. No obligation — it's
yours free.

MILWAUKEE SCHOOL OF ENGINEERING

MAIL COUPON TODAY!

Milwaukee School of Engineering

Dept. PS-961, 1025 N. Milwaukee St., Milwaukee, Wis.

Please send FREE "Your Career" booklet

I'm interested in

☐ Electronics ☐ Radio-TV ☐ Computers
☐ Electrical Engineering ☐ Mechanical Engineering

Name..... Age.....

PLEASE PRINT

Address.....


City..... Zone..... State.....

☐ I'm eligible for veterans education benefits.

Discharge date..... MS-117

Superior's New Model 70 UTILITY TESTER® FOR REPAIRING ALL ELECTRICAL APPLIANCES MOTORS • AUTOMOBILES • TV TUNES

As an electrical trouble shooter the Model 70:



- Will test Transformers, Irons, Broilers, Heating Pads, Clocks, Fans, Vacuum Cleaners, Refrigerators, Lamps, Floorboards, Switches, Thermostats, etc.
- Will test all TV tubes for open elements, impedance shorts, burned out tubes, etc.
- Measures A.C. and D.C. Voltages, A.C. and D.C. Current, Resistance, Inductance, etc.
- Will measure current consumption while the appliance under test is in operation.
- Incorporates a sensitive direct-reading resistance range which will measure all resistances commonly used in electrical appliances, motors, etc.
- Leakage detecting circuit will indicate continuity from zero ohms to 5 megohms (5,000,000 ohms).

As an Automotive Tester the Model 70 will test:

- Both 6 Volt and 12 Volt Storage Batteries • Generators • Starters • Distributors • Ignition Coils • Regulators • Relays • Circuit Breakers • Cigarette Lighters • Stop Lights • Condensers • Directional Signal Systems • All Lamps and Bulbs • Fuses • Heating Systems • Motors • Also will locate poor grounds, breaks in wiring, poor connections, etc.

Model 70 comes complete including 64 page book, only

\$15⁴⁵

**SHIPPED ON APPROVAL
NO MONEY WITH ORDER—NO C.O.D.**

Try it for 10 days before you pay. If completely satisfied then send \$5.00 and pay balance at rate of \$4.00 per month for 6 months — No interest or finance charges added! If not completely satisfied, return to us, no explanation necessary.

MOSS ELECTRONIC, INC.

Dept. D-900 2849 Tenth Ave. New York 24, N.Y.
Please send Model 70. If satisfactory, I will pay on terms specified. Otherwise I will return later.

Name _____

Address _____

City _____

Zone _____

State _____

64 pages up, P.O. N.Y.C.

**\$149.50
COMPLETE**

Your Best SCOOTER Buy!



Ready to ride, or put the "Little Gen" together yourself and save money. Price \$149.50 for scooter, new and complete. 100 cc. 2-stroke 20" wheelbase. 20" frame ground clearance. Easy to park in sun or heat as it disassembles. Fast, safe and most economical, up to 100 M.P.H. 3 hrs. of use. No oil burn. In service. Easy to jump over a hump, it's strong enough for big grown ups. Kids can use it too. Before you buy a scooter, get the facts on "Little Gen" from

LITTLE GEN SCOOTER
Box 292 Fort Wayne, Indiana



NEW 12-page Elmer's Wood Gluing handbook gives you details on gluing for heavy construction, home improvements, cabinets and furniture, models and toys, sports equipment. Contains hints, tips, and shortcuts. Includes drawings, as well. Tells you what glue to use indoors and out. Send stamped, self addressed envelope for your free copy. Elmer, The Borden Company, Dept. PS-91, 350 Madison Ave., New York 17, N.Y. (Available in Canada.)

Catalog of 2700 Novelties 10c



Send 10c for amazing catalog of novelties, live animals, scientific supplies, hobbies, funmakers, planes & boats, looms, magic tricks, joke articles, unusual seeds, gadget time-savers, cameras, optical goods, projectors, movies, lucky jewelry, religious novelties, diaphanous, musical instruments, stamps, coins, puzzles, fortune tellers, radios, auto & bike accessories, telescopes, magnifying glasses, banks, smokers' gadgets, artists supplies, printing sets, engines, motors, shockers, knives, billiards, fireworks, guns, rifles, sports, books, games, plants, etc. Send name, address & 10c to:
JOHNSON SMITH & CO., Dept. 508 Detroit 7, Michigan

**Wooded, High-ground
HOMESITE (70 x 130)
on CAROLINA Coast!**

\$500 DOWN \$500 A MONTH

24,000 acres • 50 freshwater lakes
• 80 miles of finished roads
• fishing, hunting, golf.

FREE LITERATURE!
BOILING SPRING LAKES, Seasideport • 30, N. Car.



**Earn HIGH WAGES as a
HEAVY EQUIPMENT OPERATOR**

and years of future security in the multi-billion dollar construction industry. In this country and overseas! Actual field training at National, the original school of heavy equipment operation, teaches you how. For men ages 17 to 56. Amount of previous education no barrier. No correspondence courses, no series of required home-study lessons in advance of training. Train on school owned diesel-engined machines at National's huge proving ground in North Carolina.

VA APPROVED. BUDGET TERMS AVAILABLE
Write TODAY for FREE catalog. No obligation, no salesman will call.

**NATIONAL SCHOOL
OF HEAVY EQUIPMENT OPERATION Dept. A-21
P. O. Drawer 1686, Charlotte, N. C.**

Please send me FREE illustrated school catalog and complete information.

Name _____

Age _____

Address _____

City _____

Zone _____

State _____

Time this high rate of dividend and get one of these valuable free gifts from this modern 53 year old Association. Save by Mail... and we will handle all checks for you.

Current Rate 4%

MONEY IN BY THE 15th EARNS FROM THE 1st



POLAROID CAMERA KIT
Free with \$3,000 Account

GE CLOCK RADIO
Free with \$1,000 Account

GE ALARM CLOCK
Free when opening account for \$100 or more.

63 YEARS - 1900-1963 -
CITY SAVINGS ASSOCIATION
1886 W. Chicago Avenue - Chicago, Ill.
- ASSETS OVER \$20,000,000.00 -

NO JOB WORRIES

AS AN INDUSTRY MANUFACTURER OF PLASTER PRODUCTS, PLASTER INDUSTRIES, INC. HAS A LARGE STOCK OF PLASTER PRODUCTS AVAILABLE FOR SALE AT LOW PRICES. WE CAN DELIVER TO YOU IN ANY QUANTITY. WE CAN ALSO DELIVER TO YOU IN ANY QUANTITY. WE CAN ALSO DELIVER TO YOU IN ANY QUANTITY.

PLASTER INDUSTRIES, INC. Dept. 2, 3421 Third Ave. New York 16, N.Y.



MANUFACTURE this BEAUTIFUL OUTDOOR FIREPLACE in YOUR OWN BACKYARD

\$4.00 worth of sand and cement produces this attractive fireplace. Sells on sight from \$60 to \$80. Easy to start your own profitable business in your backyard. No experience necessary. Big profits. Exclusive manufacturing territories. Write immediately for full details. General machines sold to U.S. Government. Dealer inquiries invited.

GENERAL ENGINES CO., INC. Dept. 5E-91 Rt. 130 Thorofare, N. J.

"TOOK IN \$217 FIRST 10 DAYS"

Some make more, some less...

We help you to start Your Own All-Year Business

Make Big Money! With our easily operated, highly efficient Wall Washer, Charles Stelle took in \$217 in first ten days. E. L. Goss took in more than \$10,000 in one year. G. H. Jones wrote, "I



made a net profit of \$1200 on one job." And no wonder—this machine washes walls 6 times faster and better than by hand and with no mess—no drop cloths needed.

Your Money Making Opportunity • We want more men to go into this profitable business for themselves and enjoy independence—freedom from layoffs and bosses. Customers everywhere—homes, offices, schools, churches, hotels, etc. How much you earn depends largely on you. What you take in is mostly profit. No need to rent shop or office; operate from home. Can start spare time until your full time is justified.

Loss No Time—Send Coupon Today for All the Facts

— FREE BOOK! MAIL COUPON TODAY! —

• **VON SCHRADER MFG. CO.**
• 911 "W" Pl., Racine, Wisconsin
• Send at once (no obligation) your **FREE** booklet containing information about your **WALL WASHING MACHINE** and how I can start my own permanent, profitable business.
• Name _____
• Address _____
• City _____ Zone _____ State _____
•

LEARN MEAT CUTTING AT NATIONAL

Pay After Graduation

The steady dependable trade of Meat Cutting taught easily in 8 short weeks. **YOU LEARN BY DOING** under actual meat market conditions in big modern school at Toledo.

For beginners or men with experience. Get a profitable store of your own. Remember, **PEOPLE MUST EAT!** Big pay jobs. Free employment help. Thousands of successful graduates.

Buying, cutting, percentage, pricing, advertising, selling, etc. A complete retail meat education. National School established 38 years. Get National training **NOW**. Pay your tuition in easy monthly payments after you graduate. Send coupon for **FREE** 40 page school catalog — **TODAY**. G.I. approved.

National School of Meat Cutting, Inc., Dept. 51-W, Toledo 4, Ohio

Send me your **FREE** school catalog on National Training at Toledo in Meat Cutting, Meat Merchandising and Self Service Meats. No obligation. No salesman will call.

Name _____ Age _____

Address _____

City _____ State _____

Approved for Veterans

AUDELS GUIDES

No. 1	AUTOMOBILE MECHANICS GUIDE. 1122 Pages	\$ 4.00
No. 2	HOME APPLIANCE SERVICE GUIDE. 844 Pages	4.00
No. 3	TV & RADIO SERVICE LIBRARY 3 Book Set	8.00
No. 4	HANDY BOOK OF ELECTRICITY 1632 Pages	5.00
No. 5	PLUMBERS & STEAMFITTERS GUIDES. 4 Book Set	9.00
No. 6	CARPENTERS & BUILDERS GUIDES. 4 Book Set	9.00
No. 9	DIESEL ENGINE MANUAL 640 Pages	3.00
No. 10	WELDERS GUIDE. 608 Pages	3.00
No. 11	MATHEMATICS MADE EASY 672 Pages	3.00
No. 12	MACHINISTS & TOOLMAKERS HANDBOOK. 1250 Pgs.	4.00
No. 13	WIRING DIAGRAMS. 304 Pages	2.50
No. 14	REFRIGERATION & AIR CONDITIONING. 1240 Pages	4.00
No. 15	ELECTRIC LIBRARY 10 Volume Set	21.50
No. 25	BLUE PRINT READING. 448 Pages	3.00
No. 26	MASONS & BUILDERS GUIDES. 4 Book Set	8.00
No. 27	ELECTRIC MOTOR GUIDE. 1054 Pages	5.00
No. 28	OIL BURNER GUIDE 416 Pages	2.50
No. 29	SHEET METAL PATTERN LAYOUTS. 1152 Pages	7.50
No. 30	SHEET METAL WORKERS HANDY BOOK. 448 Pages	2.50
No. 43	DO-IT-YOURSELF ENCYCLOPEDIA. 2 Book Set	8.95
No. 44	NEW MECHANICAL DICTIONARY 712 Pages	6.95

7-DAY FREE EXAMINATION

SEND NO MONEY - Pay the postman nothing! We'll send you any of the Audel Guides for FREE examination in your home. If you decide to keep the books you may pay for them under our easy pay plan of only \$2 a month.

IT'S EASY TO ORDER - In the No-First Mail Order Coupon below you need only draw a circle around the number of Audel Guides you want. We will send them to you at once. If you are not completely satisfied, return the books to us.

MAIL THIS COUPON TODAY!

FRSD, AUDEL & CO. - Self Improvement Publishers Since 1879
49 W. 33rd Street, New York 18, N.Y.

Please mail me for 7 days FREE EXAMINATION the books I have circled. I agree to mail \$2 in 7 days on each book or set ordered, and to further mail \$2 a month on each book or set ordered until I have paid the full price plus shipping costs. If I am not completely satisfied with my Audel Guides I may return them.

Name _____

Address _____

Employed by _____

1 2 3 4 5 6 7 8 9 10 11 12 ☐ Check here for Free
13 14 15 16 17 18 19 20 21 22 23 24 25 Complete Catalog

☐ SAVE SHIPPING COSTS! Check here if you prefer complete payment with order. We pay postage charges. You have same return privilege.

FIBERGLASS or PLYWOOD

\$41.95 Up: EASY TERMS
FREE CATALOG

50 Models 8-22 ft.

Cruisers, houseboats, runabouts, convertibles, fishing, sailing. Pre-assembled, pre-formed units anyone easily assembles. Equal factory-built. Save 1/3 to 1/2. Free catalog has all details, color photos, paint, accessories, fiberglass supplies, trailers. WRITE TODAY


LUGER BOAT KITS

Dept. A-9, 9200 Access Road, Minneapolis 20, Minn.

STEP UP to BENJAMIN'S TRADITIONAL EXCELLENCE!

DISCOVER the BIG DIFFERENCE that EXPERT CRAFTSMANSHIP can Make in Your SHOOTING PERFORMANCE and FUN!

25 MODELS SINGLE SHOT and REPEATERS... FIRST CHOICE of SHOOTERS who want SAFETY CONVENIENCE ECONOMY including HIGHEST QUALITY MATERIALS to Assure them OUTSTANDING POWER ACCURACY DEPENDABILITY



No. 2600 BENJAMIN

Super 35 Shot BB

Gas Pistol Safe

No Pumping Uniform Air-Power

For Target & Small Game \$18.95

No. 2620 BENJAMIN 20 Shot Cal

22 Gas Pistol Economical \$20.95

No. 1300 50 Shot BB Air Pistol \$23.50

No. 1370 BENJAMIN 35 Shot Cal 22 Air Pistol \$25.50

FREE Catalog All Models Benjamin Single Shot & Repeaters Cal BB or 177 or 22 Also Special Hunting & Fishing Rifle Offer

BENJAMIN AIR RIFLE CO., 852 MARION ST. ST. LOUIS 4, MO.

You Can Depend on... BENJAMIN

World Famous
AIR GUNS
and
CO₂ GUNS

No. 3800 BENJAMIN

Super 100 Shot BB Gas

Rifle Non-Toxic Safe

Convenient Uniform

Hi-Velocity Power

No. 3520 BENJAMIN

Super 85 Shot Cal 22

Gas Rifle \$21.95

No. 3100 Super 100

Shot BB Air Rifle 43

Shooting Force \$24.95

No. 3120 BENJAMIN

Super 85 Shot Cal 22

Air Rifle \$26.95

No. 3800 \$19.95

No. 3520 \$21.95

No. 3100 \$24.95

No. 3120 \$26.95

RUPTURED

BE FREE FROM TRUSS SLAVERY

Surely you want to THROW AWAY TRUSSES FOREVER, be rid of Rupture Worries. Then Why Do you put up with wearing a gripping, chafing and unsanitary truss the balance of your life? If you do, it will NOT be through necessity but through choice on your part.

Now there is a new modern Non-Surgical treatment that is designed to permanently correct rupture. These Non-Surgical treatments are so certain, that a Lifetime Certificate of Assurance is given. Write today for our New FREE Book that gives facts that may save you painful, expensive surgery. Tells how non-surgically you may again work, live, play, love and enjoy life in the manner you desire. There is no obligation.

Excelsior Medical Clinic, Dept. H8224, Excelsior Springs, Mo.

GOVERNMENT OIL LEASES LOW AS \$1 PER ACRE.

You do no drilling, pay no taxes, may realize a king-size profit without ever leaving home. Write for free map and literature.

AMERICAN OIL SCOUTS, Dept. PS
619 Cascade Building Portland 4, Oregon

For Boys 12 to 16 15 WAYS TO MAKE MONEY

Fifteen proven ways to earn money, detailed in a 34-page illustrated booklet. Money-back guarantee of satisfaction. Send \$1.00 to Waybeth Publications, Dept. 12, P. O. Box 5115, Sacramento 17, California.

FALSE TEETH BREAK?

GOOD NEWS! Now repair them at home in 8 minutes

Amazing PLATE-WELD repairs clear and pink plates and replaces teeth. Simply flow on - put together. Works every time - holds like new or your money back. At Drug Stores or send \$1.98 plus 22c handling to Home Dental Aids Co., Box 1731, Dept. 13A, Bakersfield, Calif.

Your Dollar Will Feed A Refugee

War and political refugees overseas urgently need the direct help, the personal encouragement, of CARE food packages—\$1 for 22 lbs. of farm staples, Delivered In Your Name. Mail your dollars to "Refugee Campaign," CARE... today!



660 First Ave.
New York, N. Y.


Printed as a public service

95% PROFITS YEAR 'ROUND

Be your own boss. Operate a **SIMPLEX** lawn-mower sharpening service in your community. One compact machine grinds all mowers, sharpens cutlery. Low investment, 95% profit. Pays for itself in average month.

SIMPLEX

—4 Machines in One!
Real Grinder—sharpens any mower rec. in or out of mower.
Band Knife Grinder—grinds with either round or cup wheel.



Rotary Blade Grinder—hollow grinds any rotary mower blade.
Cutlery Knife Grinder—sharpens cutlery, tools, scissors.

Send for free, money-making details!

The FAYE-ROOT-HEATH Company • Dept. PS-9, Plymouth, Ohio

ENGINEERING



Heald's Micro-wave and Radar Laboratory Equipment.

AMERICAN INDUSTRY NEEDS
TRAINED ENGINEERS NOW

BACHELOR OF SCIENCE DEGREE, 30 MONTHS

SAVE 2 YEARS' TIME

B.S. Degree Courses:

- | | |
|---|---|
| <input type="checkbox"/> Electronic Engineering | <input type="checkbox"/> Mechanical Engineering |
| <input type="checkbox"/> Electrical Engineering | <input type="checkbox"/> Civil Engineering |
| | <input type="checkbox"/> Architectural |

Diploma Courses:

- | | |
|---|---|
| <input type="checkbox"/> Radio-Television Plus Color Technician | <input type="checkbox"/> Architectural Drafting |
| <input type="checkbox"/> Electronic Technician | <input type="checkbox"/> Mechanical Drafting |
| | <input type="checkbox"/> Structural Drafting |

APPROVED FOR VETERANS

Send for FREE Information

**ENROLL NOW
FOR NEW TERM**

HEALD Engineering College

Van Ness at Post, Dept. PS-951 San Francisco, California

NAME _____

STREET _____

CITY _____

STATE _____

CONVERSATION

... How to be Interesting

Improve your personality, increase your success by learning how to talk well. Simple techniques used in everyday conversation can pay you real dividends in greater popularity, poise, self-confidence, shows you how to make good impression in business, social life.

Complete Course ONLY \$5.95, postpaid

This brand new self-study instruction comes to you in one large 486-page volume, handsomely bound. Full price is only \$5.95 for everything—nothing more to pay. Satisfaction guaranteed or immediate refund. Send check or money order for postpaid shipment—or C.O.D. plus postage if you prefer. Order "Conversation" today. You'll be glad you did!

NELSON-HALL, 325 W. Jackson Blvd., Dept. 334-1, Chicago 4, Ill.

FREE
Catalog
and
Discount
Prices.
Write

CHORD ORGANS—SAVE 1/2 UP TO 1/2

IMPORTER-TO-YOU PRICES

Play at Sight—**FREE** Instruction

Buy Direct—Have It Own the Finest

It's an hand-crafted 5 Day


Free Home Trial. E 2 Term!

Money back guarantee. Free Catalogs

Discount Prices. Write—

Philharmonic Organ Corp.

2002 N. Chicago Ave., Dept. P-91, Chicago 22



LEARN FIBERGLASSING at Home in Spare Time

Interstate's complete home training course in Plastic Fabrication teaches fiberglassing, plastic molding, casting, laminating, internal coring, etc. Shows how to make hundreds of salable articles of plastic. Professionally prepared. Special materials furnished. Send postcard for FREE booklet.

INTERSTATE TRAINING SERVICE

Dept. C-2, Portland 12, Oregon

ELECTRONICS

COYNE ELECTRICAL SCHOOL on a quarter of a million dollars worth of equipment or learn at home in your spare time with Coyne's modern television training.

Use this coupon to get our free book
"GUIDE TO CAREERS"

COYNE ELECTRICAL SCHOOL

1501 W. Congress Pkwy.

Chicago 7, Ill., Dept. of Electronics 51-2

NAME _____

ADDRESS _____

CITY _____ STATE _____

Unlike most other schools, we do not employ salesmen.

☐ training
at Coyne

☐ training
at home

**"I'M MAKING \$1000 a Month
MORE THAN**

Haven't Touched Bottom Yet!"
—reports Charles Rame, Texas, one of many who are "cleaning up" with orders for **PRESTO**. Science's New Miracle Fire Extinguisher. So can YOU! Amazing tiny new extinguisher ends fires fast as 2 seconds. Guaranteed 20 years! So is for only \$4.95. Write for FREE Sales Kit. No obligation. **MERLITE INDUSTRIES, INC.**, Dept. P-163, PRESTO DIV., 114 E. 32nd Street, New York 18, New York

**Bigger than ever...
better than ever**

**FREE
ELECTRONICS
CATALOGS
for 1 full year**

from Radio Shack
Boam-center of Electronics

Mail coupon! See the greatest line of electronics for "pro," amateur, music lover! Receive 1961-62 Buying Guide of 336 pages, 3/4 larger than last year, PLUS exciting supplements for 1 full year! Hundreds of famous brands and our private label Stereo, Hi-Fi, Ham Radio, Tapes, Records, Parts, 30 pgs. of Kits. New No Money Down credit terms. Satisfaction guaranteed.

RADIO SHACK CORP.

730 Commonwealth Ave., Boston, Mass.

MAIL
Coupon
TODAY

RADIO SHACK Corp.

Dept. 6134

730 Commonwealth Ave., Boston 17, Mass.

Send me Radio Shack's famous electronics catalogs for 1 full year—FREE, POSTPAID.

Name _____

Address _____

City _____ Zone _____ State _____

DETROIT REPORT

By Devon Francis

Small Car, Big Plans

THE inside story of Ford Motor Co.'s strategy in bringing out its VW-size Cardinal reveals a more ambitious goal than anybody had imagined.

Officials at GM and Chrysler Corp. privately insist that most Americans don't want cars any smaller than the current compacts. That explains the so-called senior compacts that are coming out this fall.

But Ford has gone confidently ahead with its program. The low-priced, simply engineered Cardinal is being groomed to

challenge Volkswagen as the No. 1 car in the world market, which has much greater potential for growth than the U.S. market.

Sales will be pushed harder in Europe, South America, Africa, Australia, and Canada than in the U.S. The car will be shipped knocked down to some of these areas; in others it will be manufactured almost completely. Cardinals sold in the U.S. will be partially built in Detroit.

There has been considerable foot-dragging at GM and Chrysler about developing Volkswagen-type cars. Some officials at these companies still don't believe Ford will make the move. Nevertheless, both companies have developed prototype cars, and it's generally believed they could begin producing them a few months after the Cardinal goes into production—if demand were strong enough. American Motors, although sticking with its existing cars, is, like Ford, also moving energetically into the world market.

Wankel engine fires up. A trade source reports that Curtiss-Wright will begin marketing its line of rotating combustion engines early next year with a two-rotor, 70-hp. marine engine.

This will be followed shortly by a three-rotor, 105-hp. unit and a four-rotor, 140-hp. engine. These are also for marine

use. Reportedly, they will weigh about 2.4 pounds per horsepower and will be priced somewhat below present marine power plants.

Industrial and tractor engines will follow the marine units. Contrary to reports, the lubricant for these engines will not be added to the fuel.

Off-on fan. One car maker is developing a new type of liquid cooling system for a small car that would eliminate the large fan and radiator in front of the engine. It would be replaced by a small radiator and an electric-motor-driven fan that would operate only part of the time. It could be located in some out-of-the-way spot.

While admitting that all the cooling-system problems have not been solved, an engineer in the program pointed out that this fan would operate only "on need." Most cooling fans, he said, operate more than necessary—reason for the increased popularity of variable-speed fans, which rotate much more slowly at high vehicle speeds.


Bits and pieces. Volkswageners can now buy a factory-rebuilt engine at savings up to 43 percent of a new one. . . . Although Ford deliberately avoided using an aluminum engine, it is showing considerable interest in aluminum body panels. A good possibility for the future is an aluminum roof. However, aluminum is losing favor in the auto industry. Best example is Buick's coming V-6 cast-iron engine. There is a growing belief that aluminum can do a fine job in certain

applications, but that it's been oversold for some jobs that it's not capable of doing

A long-range plan now under study by GM envisions much greater interchangeability of components among its five car divisions for engines, transmissions, drive shafts, and differentials. Buick, which has plenty of manufacturing space, might become the "power-train" division, producing engines and other components for all divisions except Chevrolet.

THE '61 FORD

beautifully built to be more
service-free...inside and out!



■ Bold, imaginative engineering produces many new minimum-service features for the Ford Fine Car Family.

Inside and out, the Ford Family of Fine Cars is designed to require less servicing than ever, with fewer oil changes, less frequent chassis lubrication, self-adjusting brakes and triple-life mufflers.

And inside each engine, too, Ford adheres to traditional high standards of quality by specifying Perfect Circle piston rings for original equipment use. Falcon, Comet, Ford, Mercury, Thunderbird and Lincoln Continental engines utilize the performance advantages of PC ring sets, custom-engineered to each engine's specific requirements.



PERFECT CIRCLE

The Rings the "Pros" Prefer!

PISTON RINGS • PRECISION CASTINGS • SPEEDOSTAT • ELECTRONIC PROGRAMMING EQUIPMENT
Hagerstown, Indiana Don Mills, Ontario, Canada



You can fight either end!

Taste PALL MALL...
**so GOOD!
GOOD!
GOOD!**



Good-looking, Good-tasting, Good-smoking Pall Mall!



Why does Pall Mall taste so good, good, good? Because Pall Mall's famous length of fine, good-tasting tobacco travels and gentles the smoke naturally—makes it mild—but does not filter out that satisfying flavor. That's why Pall Mall tastes so good! good! good! Never too strong. Never too weak. Always just right!




HERE'S WHY SMOKE "TRAVELED" THROUGH FINE TOBACCO TASTES BEST

1 You get Pall Mall's famous length of the finest quality tobaccos money can buy.



2 Pall Mall's famous length travels and gentles the smoke naturally Travels it . . .



3 Over, under, around and through Pall Mall's fine, good-tasting tobaccos — and makes it mild!

Outstanding...and they are Mild!

Enjoy satisfying flavor...so friendly to your taste!

Let's Get Rolling on Car Safety!

It's time to stop fooling around. Cars can be made safer for you and your wife and children to ride in. They are *not* safe now. You know it. Everybody knows it. Now it is time to do something about it.

For years designers have known what to do. Engineers know the specific changes—many of them cheap and simple—that could save thousands of people from death or disfigurement. These changes have been studied, developed—and ignored. The buck has been passed . . . and passed . . . and passed.

The death toll continues to climb. Last year in the U. S., cars killed 38,200 people. (In a decade they have killed an incredible 375,000 men, women, and children.) And nobody really knows how many are seriously injured each year. The best guess: 1,400,000.


Conservatively, this number could be cut a third to a half by simple changes we already know would work.

This month, in the first of a series of articles, Popular Science lays bare the public apathy and special interests that have made needless deaths a national tragedy. The blame is not simple. The remedy is obvious: Federal laws either to permit the auto industry to police itself on safety standards or actually to prescribe those standards.

*Turn the page for the revealing inside story:
"Why They Don't Make Cars Safe"*



Shouldn't we stop
this carnage
in front of us?



This is a 150-m.p.h. collision at Daytona Speedway last spring. Man inside crumpling

Why They Don't Make Cars Safe

Everybody deplores the slaughter on our highways.

Everybody knows how to prevent it. Yet nobody does.

Here is the painful truth about a national disgrace

By Martin Mann

LAST winter, to the sound of trumpets, Detroit issued a big announcement: The '62 models will be equipped—at no extra cost—with anchorages for seat

belts. "Anchorages" means four extra holes in the floor. Front seat only (except on Lark). No belts—these you buy extra.

Can four holes in the floor save one single life? Or is it like fitting out ocean



pile at left, barely recognizable as a car, broke a leg. Driver of No. 73 walked away.

liners with davits, but expecting the passengers to come aboard carrying their own lifeboats?

Maybe you can't blame people for hailing this as a great advance in auto safety. But that so much is made of so little reveals how unreal the situation is.

Modern cars are more convenient and

attractive than ever. They are also safer. But they are not nearly safe enough. Worse, they are not as safe as we know how to make them!

Whose fault is it? Everybody's. The driving public insists on thinking that accidents happen to somebody else. Safety gets no more than lip service. Perhaps most guilt stains the Government, which has known how to cut the death toll but hasn't—so far—chosen to act. After all, those lifeboats don't hang from ocean-liner davits because of shipowners'

CONTINUED

What's Detroit's side of the story?

NEXT MONTH Auto makers answer back. The industry's own experts reveal the inside story of what can and cannot be done to make cars safe.


COMING SOON . . . Popular Science reviews the brand new 1962 models. How safe—or dangerous—are they? You'll get a frank critique from Paul Kearney, nationally known authority on auto safety.

WHY THE RACING DRIVERS CAME THROUGH: Their cars—stock '61s—had been made safe with harness, roll-over cage, locked-shut doors.



Staged crashes point to changes that can save lives

Precisely managed head-on collisions at UCLA's Institute of Transportation and Traffic Engineering convict murderous auto designs. Just a little ash tray "killed" dummy (near photo), even though seat belt held in 45-m.p.h. crash. Steering unit is another killer because it is anchored to car frame, slams back at driver. It broke neck of dummy in center photo and was equally lethal to dummy driver at far right, shearing off nose and tearing chest.



benevolence; Federal law requires that they be there and specifies every detail of their construction down to the screws.

"The only way to solve the traffic-safety problem," concludes Dr. Daniel P. Moynihan of Syracuse University, "is to establish a Federal automotive agency that will develop and then prescribe safe designs for automobiles."

Maybe so. Alternatively, the auto industry might be given an opportunity to set up and police its own safety code under an exemption from the antitrust laws.

The big boondoggle

Uncountable millions of dollars have been spent in the name of automotive safety. Propaganda agencies beg you to go slow and scare you with morbid predictions. Universities pursue the scientific method: Cornell collects statistics, Harvard probes in depth, UCLA and Minnesota smash cars. The auto industry tries all approaches. The cops write

tickets—and radio for ambulances to haul away the bodies.

This vast effort is uncoordinated and timid. Some of it is plain boondoggle. Yet it has proved many useful facts (if anyone will use them):

- Propaganda accomplishes little or nothing. Every year the safety posters get bigger—and more people get hurt, even though accidents-per-mile driven have gone down.

- Safety can be furthered by many different actions—sensible policing, stricter licensing, better roads, more intensive education.

- But the fastest way to get results is to redesign the car.

If you could just keep car doors from flying open in crashes, you would save 5,500 lives every year. That's been known since 1958.

Improvements in the car take effect quickly. A change made in 1962 will be in half the cars on the road within seven years. Remaking the highway system—a

The 10 steps that will make cars safe

These additions immediately (they are options now):

1. Seat belts
2. Padding on dash panel and windshield frame
3. Outside mirror

These additions as soon as designs can be changed:

4. Collapsible steering mechanism
5. Headrests
6. Recessed knobs and handles
7. Stronger roof framing

These improvements as fast as they can be checked out

8. Clear view of the road—standardized windshields that don't reflect dash panel; effective windshield wipers, washers, and defrosters, redesigned mirror system for rear vision
9. Better lighting—brighter, nonglaring headlamps; high-visibility tail lights; unmistakable stop and turn signals
10. Responsive control—more precise handling; quicker, surer braking



favorite safety proposal—would take generations.

Improvements in the car benefit everyone—young and old, driver and passenger, skillful and clumsy, on every road. No other safety strategy does.

But the clinching argument for crash-proofing the car is absolute necessity: Accidents are inevitable. The figures show that at least one-fourth of all cars will be involved in accidents that hurt or kill people.

It can be done—now

POPULAR SCIENCE asked safety experts from government, industry, and the universities these direct questions:

Can reasonable standards of design for crashproofing cars be set?

They said: "Yes."

Would it take long?

They said: "A year or 18 months."

Would safe cars cost more?

They said: "Yes. But \$100 would cover the important items."

Would it be worthwhile? How much could deaths and injuries be reduced this way?

They said: "A great deal—a third or more." Prof. James Ryan of Minnesota said: "Fifty percent."

These men are not spouting opinions off the cuff. They have the facts.

Back in 1954—that's seven years ago—Cornell's Automotive Crash Injury Research proved that an automobile is a strong suit of armor. UCLA's crash tests confirm this. The awesome impact of a 30-mile-an-hour head-on collision—100 Gs, 100 times the force of gravity—is largely absorbed by the crumpling metal of the

car. The driver gets only 30 Gs. But he has to keep his armor around him.

How to do it

Seat belts strap the armor on. Seat belts work. A meticulous comparison of 9,000 people involved in accidents in California showed that belts reduced bad injuries by one-third.

Door locks should hold that armor around you. Better door locks work. The new types introduced in 1956 have reduced accidental openings by a third, and associated injuries by 11 percent. But recent studies reveal that some of the new locks are much better than others. Today's best door lock reduces accidental openings by only half. Surely American engineering talent can do better than this.

And the armor can be beefed up. A roll-over cage—a steel framework surrounding the passengers—would be much safer than flimsy roof supports.

Yet a sad fact remains: The armor itself hurts people in car crashes—unnecessarily. They are smashed by the steering assembly, battered by dash panel and seat backs, impaled by knobs and handles. We know these facts scientifically—and continue to make, license, and buy cars containing known instruments of death and disfigurement.

The steering assembly was convicted years ago as a deadly murderer. It still crushes people, accounting for more "moderate-to-fatal" injuries (eight percent) than any other single cause. The dished steering wheel, introduced with such fanfare six years ago, hasn't solved the problem. It helps only a little. Col-

They knew how to make 'em safe



"SAFETY INTERIOR! Instrument panel controls are recessed . . . Nothing to bump or tear." That was what the ads said about the DeSoto way back in 1937. And the ads were right. Recessing knobs and handles is foolproof, low-cost protection against many injuries. Experts have urged for decades that all cars be made this way.

lapsible or heavily padded units would help a lot. Several designs are available.

The instrument panel is lethal (four percent moderate-to-fatal injuries). But on most cars padding has been optional—at extra cost. Why isn't it standard on all? Can elementary safety be an optional extra? In airliners, coach passengers get the same safety equipment that first-class fares do.

Why are the backs of the front seats so often unpadded? This is the source of five percent of those moderate-to-fatal injuries. Why is it legal to install ash trays at the precise spot where skulls are known to strike?

Headrests can prevent whiplash from snapping your neck. With the rear-end collision on the rise, why are headrests an extra-price option on only a very few cars?

[Continued on page 208]

... but that was 24 years ago. Look what's happened now



SHARP HORN ORNAMENT is criticized as dangerous. When wheel spokes bend down in crash, raised edges on button may cut driver's chest.



UNDERSIDE OF DASH is too low, experts claim. If passenger is hurled forward, knees may rise, hit dash, forcing leg bone back to break hip.



HOOD OVER GLOVE BOX looks pretty, but its thin edge is considered a hazard to passenger. Most dashes are smoothly rounded. Why not all?



CONTROL KNOBS are located where they might stab knee or head of passenger. Most controls—but not all—are now placed behind wheel.



SUSPENDED FAR BELOW GONDOLA, model Navy plane goes through "wind-tunnel" test with help from a big ZPG-2 dirigible. It hangs at end of 33-foot strut that's hydraulically retractable through bomb-bay door.



MOUNTED UPSIDE DOWN by means of slot in bottom of fuselage, 10-foot model of Navy S2F has its vertical stabilizer away from strut's slip stream.

Blimp serves as flying wind tunnel

Although the Navy has scuttled its dirigible program, one airship has been granted a reprieve at Lakehurst, N. J. It will be used as a low-speed flying wind tunnel. Suspended from the 343-foot ZPG-2 on a hydraulically retractable

strut, large models of new planes can be tested for control and stability at speeds from zero to 85 m.p.h., and at altitudes from near sea level to 5,000 feet. It is particularly suited for testing models of planes for short takeoff and landing.



Cart takes weight off shoulder . . . folds for easy carrying.

Collapsible cart for mailbags

Because mail sacks are heavy when loaded, the postwomen in Amsterdam, Holland, have been supplied with collapsible carts. The wheels take the weight when mail is being delivered. The carts can be folded compactly for carrying back to the post office when sacks are empty.

Half-tread tires for big race

Tread on the outside, bald inside. That's how Dunlop made special tires for the Cooper racing car driven by Jack Brabham of Australia in the Indianapolis 500. The tires, designed for maximum speed and traction, were mounted with the treaded half on the right side to provide grip on the all-left-hand curves. The bald section extended tire life when running on the abrasive surface of straightaways. Brabham finished ninth.



Boarding-house reach

Tough but light tubular steel was used for a 170-foot boom to extend the arm of the crawler crane above. With a 40-foot jib on the end, it has a radius of more than 200 feet, can reach nearly 25 stories in the air. It was designed jointly by Bucyrus-Erie Co. and Babcock & Wilcox.



The Atomic Accident That Couldn't Happen



How scientific sleuths solved the baffling mystery of America's first fatal reactor explosion

By Alden P. Armagnac



X marks the spot

... where blast from top of SL-1 reactor killed its crew of three. Men were in circular reactor room at mid-height of tanklike Reactor Building. Entrance to room was from Support Facilities Building, below, by way of short passage and an enclosed stairway, not shown, ascending the outside of the Reactor Building





A BLUE flash lit up the circular room. There was an explosive concussion. From an atomic reactor gone berserk, metal pieces whizzed through the air. Death came to two men, and a third was mortally injured.

That happened last January 3 at the National Reactor Testing Station, a 900-square-mile expanse of sagebrush-covered Idaho desert. The immediate scene was the 350-foot-square test site of Stationary Low-Power Reactor No. 1—a modest-size prototype of military A-power plants to furnish electricity and heat for remote Arctic radar outposts.

It was our first fatal reactor accident—and the more stunning because this reactor was considered accidentproof.

Did an unknown peril threaten the country's ambitious plans to harness nuclear power? Within 24 hours the Atomic Energy Commission launched a full-scale investigation. Now the report is in.

This is the story of what eyewitnesses saw—and how the A-sleuths pieced together the clues to the mystery blast.

At four p.m. on Tuesday, Jan. 3, three young military men came on duty at the "SL-1" plant. They would be alone in it until midnight. All in their twenties, all qualified to operate the reactor, they were John A. Byrnes, Army specialist fifth class; Richard L. McKinley, Army specialist fourth class; and Richard C. Legg, Navy construction electrician first class. Just what they had to do was im-

After the mystery blast came heroic rescue efforts—



EARLY PHOTO following explosion peeks between concrete blocks at wrenched top of reactor. On floor are spewed-out steel turnings and gravel, which served as shielding.



MASKED MAN with meter surveys radiation near Reactor Building, behind him, on day after accident. A small "radioactive plume" that drifted downwind was traced, found harmless.

portant, because it led to the accident.

The reactor had been shut down—for one thing, to insert power-measuring wires through ports in its top. To open the ports, Tuesday's early-morning crew had disassembled the driving gear of the control rods. The daytime, eight-to-four shift had put in the wires. Now Byrnes, McKinley, and Legg were to reassemble the control-rod drives, so that the reactor could start up again next day.

In the reactor-room ceiling above the busy crew was an automatic trouble-detecting device, wired into the NRTS alarm system. A fire, an explosion, or escaping radioactivity would set it off.

At 9:01 p.m., the alarm sounded eerily in NRTS' fire and security headquarters. Six AEC firemen, an assistant fire chief, and a security patrolman raced the eight miles to the scene in a fire truck and two cars. They got there at 9:10. Donning breathing masks, carrying radiation meters, they entered the gate.

Beyond two nearer structures loomed the tanklike Reactor Building, a windowless steel cylinder 48 feet tall—gaunt, still, outwardly unharmed.

Toward it the firemen tramped, through the Administration Building and then

the Support Facilities Building, which housed the reactor's remote-control room. No fire, no smoke, no one there.

From the support building, a short passage led to the foot of an enclosed stairway which ascended the outside of the Reactor Building to its reactor room. In the passage the firemen stopped, as excessive radioactivity kicked over their meter needles.

Reinforcements appeared—health physicists from the Materials Testing Reactor site, 11 miles away, which Phillips Petroleum Company operates for the AEC. Two who arrived at 9:36, already in protective coveralls, reached the top of the stairs and the reactor-room door.

Deadly radiation. There their meter's needle swung to its top reading—500 roentgens an hour, enough r's to kill an average man in an hour's exposure. Inside it would be even "hotter." They peeked in, saw no one, hastily retreated.

Over NRTS' radio network went the grim announcement: "Class I Disaster."

What had happened to the SL-1 crew? A check by radio dashed hope they might be at another site. The three men must be inside the Reactor Building.

More help was on the way—but it had

then sifting of clues

farther to come. No one lives at NRTS; its daytime people were home. Most of them were in Idaho Falls, 41 miles away. So were the AEC's Idaho Operations Office; and the SL-1 headquarters of Combustion Engineering, Inc., which operated the reactor for the AEC and the Army. Raising key men there took 35 minutes. In cars barreling over U. S. Highway 20, they were speeding to the scene.

Time was running out. If anyone was still alive in that hellhole of radioactivity, his exposure to radiation was rapidly nearing a fatal dose. But were there any survivors? Might a rescue attempt only swell the casualties? If the reactor had run away, it might now be hair-triggered—ready, at a slight jar, to lash out again.

The dilemma ended with the arrival of four Combustion Engineering men. Quickly they weighed the appalling risk, the slim chance of saving anyone, and made a heroic decision: They were going in.

At 10:35, CE's supervisor for plant operations and its health physicist entered the reactor room. Within two minutes they returned. They had seen two men. One was moving.

Race against death. All four CE men and an AEC health physicist now braved the room's perils. Working with desperate speed, in three minutes they put the living man on a stretcher, saw the other was dead, and were downstairs with their human burden. An ambulance took the rescued man to Highway 20. Meeting it there, an AEC doctor found the man dead—of a head wound he could not possibly have survived.

At 10:48 another heroic party, of two military men and two from Phillips, went in and saw the lifeless body of the third man—lodged in the ceiling.

The second body was recovered Wednesday evening; the third, the following Monday. Unabated, the radioactivity near the reactor proved as high as 1,000 r's an hour. But advance planning reduced exposures. Timed with a stopwatch, two well-rehearsed servicemen picked up the second body and were out, before their allotted 60 seconds was up.


[Continued on page 212]




RUNAWAY-PROOF when control rods were connected to their motor drives, as pictured here, SL-1 reactor was found by probers to lack a needed safeguard when they were disconnected.



LOOKING DOWN INTO SL-1, preaccident view of core shows the cross-shaped housings in which the wide-finned, close-fitting control rods slid up and down. Sometimes they stuck.



FALLING APART, the SL-1 for months had been shedding pieces of its boron "poison" strips, needed to keep it under control. Seven-inch-long fragment (upper view) and smaller ones (lower view) were among those fished from bottom of water around core before the accident.



Jet-Powered Hydro

A JET engine that powered the old Air Force Shooting Star now hurls a giant hydroplane over the surface of Seattle's Lake Washington. Although designed for speeds of more than 100 knots, Boeing's new Aqua-Jet isn't a marine hot rod—it's a floating test lab. The bow is forked to provide a recess in which

models of experimental hull designs are suspended. While the propellerless hydro pushes the model through the water, a technician, riding alongside, checks design performance by means of instruments and direct observation.

This type of in-action research supplements the conventional tow-tank



LOBSTER-SHAPED HULL is formed of 9- and 11-ply African mahogany. Two externally mounted steel fuel tanks (faired into body behind jaws) hold 165 gallons of 80-octane gasoline.



DRIVER'S COCKPIT is in starboard prow. Snuggly seat has padded flanges that bracket thighs to prevent bounce-out. Observer in port cockpit studies the model's performance.



Tests Model Hulls

method of testing. Together, the two techniques are to hydrodynamics what the wind tunnel is to aerodynamics. The 11,600-pound, \$25,000 Aqua-Jet is intended for straight-line, one-minute runs of $1\frac{3}{4}$ to $2\frac{1}{2}$ miles. The engine, mounted above the water line, operates exactly as it would in an aircraft.



COUPLING ARM, attached to cable-controlled actuator, keeps twin rudders parallel. Aluminum wedges at rudder corners act as skis to dampen fishtailing and provide planing points



MIGHTY THRUST—4,600 pounds—is supplied by Allison J-33 pure-jet engine, silenced by sound suppressors developed for 707 transports. At 100 knots, output equals about 1,400 hp.




ALUMINUM SKIN on underside of twin forward hulls assures sleek, durable surface. The Aqua-Jet, a three-point hydroplane, has an overall length of 38 feet and a 17-foot beam.




IT OPENS WIDE! There's no lack of access to the interior of the new little Renault, as you can see at top of page. Rear seat removes easily, converting car into a cargo carrier.

The Car You Can't Grease

By R. P. Stevenson



FRONT-DRIVE gearbox is just ahead of the front axle, the four-cylinder, 26.5-hp. engine just behind. The R4L model shown here is 143.9 in. long, 58.5 in. wide, and just a shade over 5 feet high. It weighs 1,200 pounds. All wheels are sprung independently, with long torsion bars and shocks. Muffler is under left front fender.



TRAILING ARMS pivoted on chassis suspend the rear wheels. Transverse torsion bars, one behind the other give the car a 94.2 in wheelbase on right side, but only 94.3 on left

Lube points? You won't find any on Renault's new front-drive model. And the sealed radiator contains a year-round coolant

A **SEALED** cooling system is one of two surprises you find in the new Renault. A complete lack of grease points is the second.

The car itself is a rugged but handsome little front-driver that will now replace the 4CV, the famous "Quatre Chevaux" that this French factory has


been turning out to the tune of many thousands each year since 1947.

In designing the car, the engineers had two objectives. First, they wanted a model with good styling and brisk performance that would still be economical to buy and operate. Second,


[Continued on page 216]




GEAR-SHIFT LEVER is placed at middle of dashboard to operate the control rod running forward above engine and down to the gearbox.




ENGINE in both Renault R4 and R4L is modified version of the one used in 4CV and the Dauphine. Electrical system is six-volt.



1. GOLDFISH IN BOWL are set in center of backing sheet. Plastic film, on roll below, runs up into frame shown here raised behind the bowl.



2. FRAME IS PULLED DOWN, covering bowl with plastic film. Heating platen is pulled out on tracks at sides to seal the film around bowl and backing.



3. FINISHED PACKAGE can be tilted without spilling either water or goldfish. Vacuum-seal method is used in packaging many small objects.

How to pack goldfish in their bowl

The next time you move, forget the china barrels, boxes, and newspaper stuffing. There's a machine that will do the work cheaply and efficiently, and leave less mess to be thrown away.

Using polyethylene film on a backing of corrugated cardboard, it vacuum-packs anything from dishes, bric-a-brac, glassware, tools, shoes, condiments, and drugs

to radios, and even goldfish in their bowl. Poly-Tite works on household current, unwinds plastic film from a roll, stretches it over the object to be packed, and heat-seals the film tightly in place.

Mounted on dollies, it can be taken to a home in the moving van and operated by one man. It's made by MfP Co. (Machines for Packaging), San Mateo, Calif.



New interior for Volkswagen "camp on wheels"



A table that can be set up outdoors is one of the new features of the latest Volkswagen camper. The table's stem fits into a detachable adaptor plate in the spare-wheel hub. The camper, a VW station wagon with living facilities, also boasts enlarged closets, a driver's seat

with revolving back that converts to rear-facing bench, an icebox, washbasin, roof luggage rack, hinged roof sun flap, birch-paneled interior walls, and door canopy. Price is about \$3,000. A kerosene stove, chemical toilet, and the tent shown above are extra-cost equipment.

PS FIELD TEST

\$40 Gadget Spots Police Radar—But...

RADAR DETECTOR is completely self-contained. It is just clipped to sun visor. The only requirement is that it have a clear "view" through the windshield, unobstructed by any metal.



By Hubert Lockett

SUDDENLY I heard a burbling sound above the faint noise of static coming from the device clipped to my sun visor. The sound changed to a squeal, rising in intensity as I drove. On the shoulder of the road just ahead, I spotted what I had been searching for all morning—an unobtrusive-looking black box mounted on a tripod.

The squeal faded away as I passed it.


A little farther along, half concealed by roadside bushes, were two uniformed patrolmen. One was squatting in front of a radar speed-meter recorder while the other kept his eye on oncoming cars.

The radar detector worked. Just as the maker of this \$40 gadget claimed, it announced the presence of a radar beam by emitting a squeal from a tiny, self-contained speaker.

The instrument, called Radar Sentry, is a palm-size unit powered by mercury

CONTINUED

At 70 m.p.h. I was repeatedly warned in time to duck under



CHECKING RADAR RECORD of speed after a trial run. This trip, capture zone was 350 feet from radar antenna; warning came at 400 feet.

batteries. It clips to the sun visor or is held on the metal dash by magnets in its base. It "sees" through the windshield. A single knob turns it on and controls volume. The knob and speaker face the driver when it is in operating position. The Radar Sentry is produced and sold by mail order by Radatron, Inc., North Tonawanda, N. Y.

Next question: Do you get a warning in time for it to do you any good?

The double-check. I looped around on back roads and came through the radar surveillance zone once again. This time I noted carefully the exact point I heard the first burble and the beginning of the steady squeal. A soft-drink sign was my marker for the first, a mailbox for the second. I was traveling at exactly the speed limit—30 m.p.h. The two points were about 50 feet apart.

On the next trip I drove at 10 m.p.h. over the limit until I heard the warning, then braked quickly to about 28. I pulled over just past the cops.

"How fast does the meter say I was going?" I asked.

One of them pointed to the last pip on the chart. "This says 25," he replied.

"That was after you got on the brakes," grinned the other. "I had my eye on you and was sure we had a paying customer."

"Do you mean you will only give a ticket if the red line on that paper says the speed was over the limit?" I asked.

"Yep. That's the only evidence we have," he answered.

Needed: quick reflexes. I watched the meter for a while as a number of cars passed. There was some variation in the point down the road at which the speed was recorded. But the telltale pip was drawn for most cars by the time they were a few feet past the mailbox marking the point at which I had noted the beginning of the steady squeal from the radar detector. Obviously, at this particular setup, a speeder would have had to react very fast to the first feeble indications from the detector to slow down in time to avoid a ticket.

With the cooperation of the police, I made a number of trial runs. We tried various speeds, different ways of aiming the radar and different heights for the radar antenna. In some instances, I was able to pick up the warning much farther away. But checking the recorder after these runs, I found it was also recording my speed farther away. The net gain in warning time was very slight.

In this series of tests, I found I could fairly consistently beat the radar when I drove less than 10 m.p.h. over the 30-m.p.h. speed limit. Of course, the cards were stacked in my favor—I knew the location of the radar and was alert to the first warning squeal. Above 10 m.p.h.



HIGH-SPEED TESTS showed that police could outwit the detector (with practice) by proper choice of location for the radar antenna.

the speed limit until . . .

over the limit, my record wasn't so good. My batting average dropped to about .600. At still higher speeds, the device offered small comfort. About the most you can say is that it gives you advance notice that you are going to get a ticket.

I surveyed the radiation pattern from the radar on foot, carrying the detector. Throughout the capture zone and for 50 odd feet beyond, there was a loud, clear warning tone anywhere you held the instrument from about three feet off the ground to about eight feet, and from one shoulder to the other on this two-lane road.

But farther away, there was uncertainty. Eight feet above the road you might get a loud tone and yet get none at, say, four feet. You might hear it over near the center stripe but not close to the shoulder. It seems that an early warning will depend a whole lot on just plain luck. Later experience verified this conclusion.

I'm crossed up. On different days I found several radar installations "cold" and others by prearrangement. Noise level in the car made a big difference. Wind noise with the windows open at high speeds, the radio playing, or a talkative passenger, greatly reduced the chances of hearing the warning in time. As you would suspect, I did much better when I knew where to expect the radar, even though I made every effort to play it straight and keep a heavy foot on the accelerator until I was sure I heard the squeal.

On one setup in particular, everything seemed to be in my favor. I consistently drove along this stretch of road hitting 70 (with police permission) and was able to drop below the 50 m.p.h. limit after the warning and before the radar recorded my speed. I did, that is, until a smart radar cop crossed me up. While I was making my turn-around for another run, he moved the radar antenna to a more favorable location. This time he had me.

Technically the device is an electromagnetic radiation detector, tuned to 2,455 megacycles, which is the frequency assigned to police radar. The back cover of the metal case forms an integral slot antenna. The detector uses eight tran-



MERCURY BATTERIES, claimed to be good for several thousand miles of driving, furnish power for the eight transistors used in the circuit.



INSIDE VIEW OF DETECTOR shows instrument-quality construction. A printed-circuit board is used. Slot antenna is in the back cover.


sistors and two radar-type crystal diodes.

The manufacturer is unwilling to give circuit details and builds it so that the hook-up is hidden. But inspection suggests a relaxation oscillator circuit set up to produce the audible tone. The operating voltages might be adjusted so it would not quite oscillate, but a small change in one would cause it to break into oscillation. Energy from the radar beam, picked up by the slot antenna and rectified by the crystal diodes, could supply the voltage required to start oscillation. There is some corroboration for this guess. If you apply a small DC voltage from a flashlight cell across the diodes, you get the same squeal produced by the radar beam.





Haul low-profile trailer behind your car . . .



. . . take it apart at your camping site . . .

Collapsible trailer converts at camp site to both tent and boat

Tow this British-made fiber-glass trailer to the water, and you're all set for a camping holiday. You can take the lid off and use it as a boat, sturdy enough to hold an outboard motor on its transom.



World's fastest helicopter

A helicopter speed record of 192.9 m.p.h. was set when this Navy twin-turbine Sikorsky HSS-2 flashed past the photo-timer. Cmdr. Patrick L. Sullivan and Lt. Beverly W. Witherspoon set the mark on an official three-kilometer course (1.86 miles) at Bradley Field, Windsor Locks, Conn.

Later they flew the big copter 100 kilometers from Milford to Westbrook, Conn., at 174.9 m.p.h.—a new record for the distance.

Both are pilots at the Naval Air Test Center at Patuxent River, Md. The previous mark was 167.09 m.p.h. made by a Russian Mil-6 in 1959.

Pipe crosses river

Putting on an act reminiscent of Scotland's Loch Ness monster, a section of pipeline is pulled here across the Kootenai River at Bonners Ferry, Idaho. Its bent neck was plugged to keep out water, and the 36-inch-diameter pipe was coated with concrete to overcome buoyancy.

It will connect with the casing in the left foreground to form a link in a line delivering gas from Canada to utilities serving cities on the Pacific Coast.




... use top half upside down as a boat ...



... and flip it back over to roof your tent.

Then, when you call it a day, you can prop it up on three poles, and it becomes a roof over sleeping quarters for two adults and two children. Fabric sides are zippered at the corners so you can

roll up one or more as you would flaps. Collapsed, the trailer is 31 inches high, 62 wide, 132 long, and weighs 224 pounds. Besides the tent poles and flaps, it will carry considerable luggage.



This line is busy


When a bird nested on top of a pay telephone in an outdoor booth, the phone company came to the rescue—of both nature lovers and potential users.

The Chesapeake & Potomac Telephone Co. installed another phone outside the booth at the Naval Ordnance Laboratory in White Oak, Md., and temporarily disconnected the bird's.



Battlefield casualty locator

Wounded soldiers need only flick a toggle on a portable radio-signal beamer to get help. Medics in armored personnel carriers are equipped with receivers that home in on the casualty's position by tone control. The locating system was developed by Ryan Aeronautics. The photo above shows a test by the Army at Camp Roberts, Calif.



NO BIRD IN SIGHT, but seconds later, this turboprop Electra crashed, killing 82 people. Starlings, blanketing runway and nearby marshes, had been sucked into the jet air intakes.



U.S. wildlife

NOT A BAD LOOKER, the English starling has brains as well. The robin-size bird, iridescent in spring, appears mottled in fall. A stranger in 1890, it proved so adaptable that it's now found everywhere in the U.S.

STARLINGS BLACKEN THE SKY in a tornado-like cloud, and, flying in flocks of thousands, they can be just as dangerous. Unfussy about food or climate, they're a menace alike to farmers, cattlemen, and fruit growers.



experts declare war on—

Starlings: Public Nuisance No. 1

By Joan Steen

STARLINGS are darn smart. So smart they've soared from simple nuisances to serious threats in a few years. When a flock got sucked into the air intakes of a turboprop Electra during a takeoff at Boston last fall, the threat proved fatal. The plane stalled and spun in, killing 62 of the 72 aboard. The time had come, officials agreed, to take starlings seriously.

That is what farmers, cattlemen, fruit growers, and incensed citizens have been saying for years. Orchard owners in Oregon tell of complete devastation of their trees; vineyard keepers in the Southwest have lost their choicest grapes; cattlemen have had livestock feed contaminated or ruined.

Now the Government is interested. The aviation and space agencies want ways to handle the problem of birds versus engines. The U. S. Fish and Wildlife Service wants to solve the farmers' plight.

The villain of the piece is a dark-spangled, shapely bird about 8½ inches long, weighing about as much as a robin. From a distance the starling looks like a slightly hump-backed blackbird (al-


though its tail is shorter and droopier). But it's no relative. Starlings do have one famous cousin—the mynah bird.

Oil-slick looks. During spring and summer, they're yellow-billed and their iridescence is at its gleaming best. Like an oil slick on water, their luminous look is caused by reflection and refraction of the sun's rays. But after a season's battering, starlings look shopworn. The birds are freckled with beige spots, their crisp feather edges are blunted, and their bills have darkened.

Until 71 years ago there wasn't a starling in North America. They were freakishly introduced when Eugene Scheiffelin released 100 English starlings in New York's Central Park. His innocent objective: to acquaint Americans with all the birds mentioned by Shakespeare.

And they multiplied. Blessed with an enemyless Eden plus an eerie adaptability, *Sturnus vulgaris* began to live up to its name: It spread with uncommon ease to all compass points. By 1939, starlings had moved out to Kansas, Oklahoma, Texas, and across both borders. By 1942, a few pioneers made it to California. They

Poison, shock, noise, and nets all help thwart starlings, but



CITY STARLINGS take over public buildings. Here it's a courthouse in Frankfort, Ind. U. S. Fish and Wildlife eviction experts are fighting back with shock treatment and poisons.

multiplied astonishingly: In 1947 one starling was seen in British Columbia; by 1953 the estimate was 500; five years later it was 25,000.

The pioneers are the new brood who face a housing shortage if they stick around where they were born. So they begin making tentative sorties into new regions. After advance parties have explored the new territory for upwards of 20 years, a huge wave moves in to nest. California's time is now up.

Things wouldn't be so bad if the birds weren't so prolific (sometimes producing three broods a year), or so omnivorous (if it's edible they like it), or so hardy (any climate is fine). But they're organized. They move in vast flocks, apparently recognize group leaders. One naturalist in North Africa describes the awesome sight of migrant starlings in Tunisia. Each morning just before sunrise, silence descends on the flock—dead silence—where during the night there have been fitful peeps and chirps. Then all at once they take wing. In a few seconds, millions of them blacken the air on their way to the olive groves. There they eat their way through an incredible 165 tons of olives a day.

Wary and wily. They behave shrewdly in small groups, too—if they let you watch them. Starlings are notoriously nervous birds, quick to steer clear of intruders. A biology field worker handled

and marked one egg in a nest while the parents were out hunting food. A week later the marked egg was found four inches away from the others and cold.

But what's more remarkable is their teamwork. Pairs of nesting starlings will settle an area and unite to keep other birds out. This often means destroying existing nests and taking over. Once, when a newly arrived pair of starlings observed a robin getting ready to move into an abandoned woodpecker hole—a favorite starling haunt—the pair immediately enlisted the aid of resident starlings. Pair I squawked and twitted until the robin flew off to chase them. When she returned, Pair II was waiting to carry on the psychological warfare. The robin soon gave up.

Is there any hope? Faced with such talents, it's not easy to come up with sure-fire controls. The Boston disaster led the Federal Aviation Agency to allocate \$100,000 to the U. S. Fish and Wildlife Service to study the problem. In the meantime FAA test engineers are considering redesigning jet air intakes. Some ideas: a ring-shaped intake; an inflatable intake guard; a revolving inertial separator (the heavier-weighted birds would be shaken out); macerating devices.

The fight is not unlike a military operation. Should you build strategic defenses or look for the means to deal a decisive blow? So far the battery of controls runs to deterrents:

- *Shock treatment.* An effective but expensive control is to wire the roosting areas of buildings. The wires themselves and the magnetic field extending four inches on either side of the negative wire

STARLINGS FLUSHED FROM ROOSTS on a pitch-black night will fly straight toward the lights at the back of this large funnel-shaped net. (U. S. Fish and Wildlife Service photos.)

no one yet has found **THE** answer

set up a shock area. One 450-volt DC jolt, and the birds take off. This is what Washington is doing—after years of suffering national mortification from sullied and blackened buildings. There's one trouble—wire one building and you have to wire them all. Otherwise the birds just move across the street.

● *Sticky-foot poison.* A poison in a viscous oil base has been tried experimentally. The poison is spread on parallel pipes a few feet above ground. Cattlefeed laced with it is also spread as bait between the pipes. The birds perch and munch, absorbing the poison through their feet. Its delayed action is timed so that the birds will return to their roosts to die.

This sounds ruthless, and is. And there are dangers. No one knows how harmful the poison may be to plants and trees, or how easily it may be spread.

● *Floodlight traps.* This is an efficient way to trap a lot of starlings in one place. A net—a very large funnel-shaped affair—is spread close to a densely populated roost. On a pitch-dark night (this is essential) spotlights inside the net are turned on at the same time the birds are flushed from their roosts. The birds fly straight toward the light. As many as 100,000 can be bagged this way, and wildlife researchers find it a quick and easy way to band them for study. If it's desirable to do away with them, they can be painlessly gassed.

● *Fog guns.* Another way of administering a lethal dose of gas is to fire it from a gun. At short range this proves very effective. But someone has sensibly asked: How do you get the birds to sit still long enough to sniff a fatal dose?

● *The sound barrage.* Among the "black box" deterrents are a variety of devices, some bogus, some effective. Gordon W. Boudreau's recordings of starling distress screeches are particularly potent bird chasers. But if they're played at a long-held roost, the birds seem to catch on. Apparently they can out-Pavlov Pavlov in associative skills.

The same goes for shotguns, firecrackers, or other noisemaking machines. The birds either realize in short order that the noise is meant to scare them or else

[Continued on page 222]



SCARE-'EM TACTICS: One way to cope with a plague of starlings is to bombard them with noise. The automatic acetylene exploder above does just that.



STICKY POISONS will work, too. The man on the ladder is squirting the goo into favorite starling niches. All of them have to be filled—otherwise the birds just move over a bit.

ULTRASONIC HORN is one of the newer kinds of starling shooers. But the best sound weapons may be records of distress calls.



Why Inventing Is Still a

By Lynn A. Williams



Mr. Williams, president of Anocut Engineering Co., is himself an inventor—his latest invention being a process for electrolytic metal removal. This article is adapted from a speech he made recently before the Society of Automotive Engineers.

ONE of the surprises of modern industrial life is the relatively small contribution of large industrial corporations to the sum total of significant creative and new ideas. Historically, important new ideas have come through individual initiative. They have come less often from the laboratories of our great industrial corporations.

They have not come from committees, they have not come from teamwork, they have not come from organization; but, in very large part, they have come from individuals, often working almost alone and, very frequently, under surprising and often unpromising conditions.

Despite the tremendous size, power, and wealth of our largest industrial firms, and despite the fact that they are totally immersed in technology, their contributions have been far greater in production and in marketing than in creativity.

I am convinced, both by history and by present circumstances, that this is not likely to change. It will not be changed by "brainstorming" or "pyramiding." It will not be changed by plan or organization. A disproportionately large quota of new ideas will continue to come from individuals. The large industrial giants will continue in their roles as developers rather than creators, as producers rather than as innovators.

HISTORY, sociology, and what I term "accident" account for this.

This is not to say that corporations have invented nothing. There have been important inventions by men working within American big business. The transistor resulted from an idea suggested by Dr. Shockley at the Bell Laboratories. Freon refrigerants came from Midgely after he went to work for General Motors. Nylon was originated by a man in the DuPont laboratories. There are others.

The modern corporation has often been superb in development and improvement.


But the creative idea is something else. It is the pregnant suggestion that sets in motion a whole series of new consequences. One consequence is the development, improvement, refinement, manufacture, and marketing of the product that rests on the idea.

For history, let's look at some inventions familiar to us.

The expansion steam engine was invented by Watt, and the steamboat by Fulton. The telegraph was invented by Samuel Morse, the cotton gin by Eli Whitney. And, of course, Edison invented the incandescent lamp, the phonograph, and the moving picture.

The first significant breakthrough in the making of steel was by Bessemer. The steam turbine came from Parson. The process of refining and producing aluminum, still used to-

One-Man Job



day, was invented privately by Hall and Cowles in the United States and, almost simultaneously, by Heroult in France.

A salesman for bottle stoppers invented the safety razor. His name was Gillette. Wireless was invented by Marconi. It was not the telephone company or General Electric or Westinghouse that invented the three-element vacuum tube. This was the work of Lee de Forest. The modern plastics industry began with Dr. Baekeland and Bakelite.

Perhaps these things are too old to be relevant today. Very well, insulin was discovered in the 1920s not by anyone in a great pharmaceutical house but by Dr. Banting of Canada. A private experimenter, Dr. Fleming, found penicillin. Streptomycin was found by Dr. Waksman, polio vaccine by Dr. Salk.

The gyrocompass, so important to our rocketry, was invented by a German named Anschutz-Kaempfe. Frequency modulation was invented not by RCA but by Dr. Armstrong. Kodachrome film was invented not by the Eastman company but by Godowsky and Mannes, who did much of their early work in a kitchen sink.

The Polaroid camera was invented by Dr. Land, whose early work on polarizing films was done when he was 20 years old and still a student at Harvard. Stainless steel was developed not by any of the major steel companies but by two scientific entrepreneurs, Harry Brearley and Elwood Haynes. The cotton picker was invented not by International Harvester but by the Rust brothers. Cellophane was not the invention of the Du Pont company but of a Swiss-born Frenchman, Jacques Brandenberger.

IN THE field of nuclear development, it was Ernest Lawrence, University of California scientist, who invented the cyclotron. The major inventions for the atomic bomb and much of the ensuing nuclear work were by individuals like Niels Bohr, Enrico Fermi, Edward Teller, Harold Urey, and Leo Szilard.

Important new ideas have come, in very large part, from individuals, often working alone and under unpromising conditions.



Critics have observed that the giant corporations have indulged in welfarism to a degree beyond the dream of any Utopian socialist.



The oddball inventor is disturbing. His habits don't fit into a smooth-running organization.



A basic reason why our big corporations will not come to dominate creativity lies in "accident." Invention defies planning.

The automobile? A number of major inventions stem from ideas within the industry. The outstanding one is the automatic transmission, initiated by Thompson while he was at Cadillac and carried by him to Oldsmobile. (The hydraulic torque converter, however, was the work of individuals not associated with any large firm.) Duco body finishing was invented by Du Pont. The sealed beam headlight came from within the industry.

But the four-cycle engine was Otto's, of Germany, and the two-cycle Dr. Diesel's. Vulcanized rubber was the invention of a man named Goodyear and the pneumatic tire of an Englishman, Dr. Dunlop. The self-starter was invented by Vincent Bendix, and by Kettering before he became associated with General Motors.

Four-wheel hydraulic brakes were invented by Loughead, power steering by Davis, and chromium plating by Dr. Fink, a professor at Columbia.

SO MUCH for history. The second reason that the individual inventor will continue to bulk so large in our scientific progress lies in sociology.

Critics (with whom I don't agree) have observed that the giant corporations have indulged in welfarism, particularly for the supervisory classes, to a degree beyond the dream of any Utopian socialist. They say that the brass, including many engineers, of today's big industrial firms is weaned, fed, clothed, schooled, doctored and hospitalized, has his adult being in, and can be buried without leaving, the comfortable company corridor. Let him make the company's first team, and the likelihood of his ever getting fired is remote indeed.

What has such a man to gain by propounding an original idea? Not much. His sure path to success lies in being a good little cooperater and keeping his nose clean.

So say the critics. They may expose a grain of truth in a Sahara of unrestraint. But there are at least four more valid reasons that prevent a factory from being a fertile ground for creative ideas.


The basic purpose of a factory is to produce. To produce efficiently requires planning. Planning requires deadlines, and introducing new ideas along the way disrupts them.

Again, a big factory must avoid mistakes. If I am building a boat in my basement and put a hole in the wrong place, I can plug it and paint it over. But if I am producing 3,000 automobiles a week and put a hole in the wrong place, in a week's time I have a major crisis. It takes a lot of nerve to change things in a factory.

Creativity also involves emotional costs which most managements cannot and will not accept. Every innovator is an iconoclast. His new idea is an attack on an older idea. Through extension, it seems like an attack on the men who are in charge of the old idea—which means the men who are in charge of almost everything.

THE oddball innovator is disturbing. His habits don't fit into a smooth-running organization. I learned this rather poignantly when, as a division manager for a large corpor-

[Continued on page 220]



Space probe to fly past planet Venus

A 1,000-pound spacecraft, Mariner-A, is being built by Caltech's Jet Propulsion Laboratory for detailed investigation of the planet Venus. It's more advanced than Surveyor [PS, June '61], the space probe scheduled for the moon, because of the greater distance it will travel: 26 million miles. The photo above is of a model. The actual space probe will be 8 feet high, 19 feet across from tip to tip of its solar panels. Mariner-B, slated for a later fly-by trip to Mars, will be similar in appearance.

Mariner-A will blast off late next year on an Atlas-Centaur for the three-month

journey. After leaving the rocket, it will be oriented both by the sun and by small jets triggered by radio from the earth. It will pass within 16,700 miles of Venus, and cram data into a memory system for 8 hours—enough to provide 48 hours of telemetering back to earth. Then the craft will go into perpetual orbit around the sun.

Instruments on a planetary platform moving on two axes will record radiation, ultraviolet rays, magnetic fields, and Venus's gravity, temperature, and atmospheric conditions. Infrared scanners will keep them trained on the planet.

School-bus shelter

Steel shelters such as the one at right give protection from weather and traffic to children waiting for school buses. The structures are provided without cost to communities by a Philadelphia subsidiary of a big appliance distributor. Revenue comes from paid advertising carried on the sides.

Each shelter is anchored to a 3,000-pound concrete slab. Up to 14 children can be accommodated in each.



Inside the New and Bigger VW

Germany's stubby beetle goes stylish, with a huskier, sassier engine, in the first radical changes in its history

VW 1500 has top speed at least 10 miles an hour higher than that of standard Volkswagen. Cars above are tooling around VW test track.

FOUR-CYLINDER REAR ENGINE is hidden beneath panel that forms floor for extra luggage compartment. Front compartment, 10½ in. high, measures 27 by 40 in. Rear one is 9¼ in. high and 42 by 35. Leg room is increased



By Devon Francis

THAT spanking-new Volkswagen you've been hearing about was officially unveiled last month.

It looks nothing at all like its beetle-shaped parent. Its lines, in fact, would suggest that Detroit had a hand in styling it. By the performance yardstick that Europe applies to cars in its price class, it's full of beans. A pancake engine is still there in the stern, but gone is the cooling-fan belt.

The car embodies the first radical changes in VW's history.

Designated the 1500 (a nice round figure derived from the 1,493 cubic centimeters in its engine displacement), it compares with the old one:

	Volkswagen	VW 1500
Overall length	160 in.	166.3 in.
Width	60.6 in.	63.2 in.
Height	59 in.	58.1 in.
Curb weight	1,631 lb.	1,896 lb.
Horsepower	40 @ 3,900 r.p.m.	53 @ 4,000 r.p.m.
Piston disp.	72.74 cu. in.	91.09 cu. in.
Comp. ratio	7:1	7.2:1
Bore	3.031 in.	3.3 in.
Stroke	2.52 in.	2.7 in.

The wheelbase for the two cars is the same—94.5 inches.

And now that this bagful of goodies has been dangled before your eyes, you're due for a disappointment: The VW 1500



COMPLETE BREAK WITH TRADITION is emphasized by these comparison views of standard VW and new one. Weight is distributed 60 percent rear, 40 front. Chevy Corvair's is 63-37.


will not be sold in the U. S., at least for the present.

The company, Volkswagenwerk A. G., says it's for distribution solely in Europe and among those citizens of the other 120 countries where Volkswagens are sold. If it were sold over here now, it would cost roughly \$2,000, compared with \$1,595 for the regular VW two-door sedan at the New York port of entry.

Why a new VW? The VW people ad-

CONTINUED

BIG CHANGE in engine, as shown in this cut-away, is in the air-cooling fan. Replacing big, belt-driven, radial-type blower is two-unit fan—one radial, one axial—driven directly off crankshaft. This supplies five parts of cooling air for engine, one part fresh air for warming passengers, plus carburetor air. Axial fan's diameter is 7½ in., radial's 12 in. In standard VW, heating air is ducted to car's interior after cooling cylinders. Newly positioned dipstick is attached to underside of the oil-filler cap.



The VW 1500 looks like a leaf out of Detroit's style

vance some plausible explanations for denying the new car to potential American customers. They say that for what it offers in performance, the 1500 could not compete in price with domestic compacts. They say they haven't the cars to send over here—production of the 1500 this year will amount to only 75,000 out of a total of a million vehicles. They say their dealers would have to stock parts for another car.

This may be a new high in tortured reasoning. As production of the 1500 rises, the price will inevitably drop. U. S. VW dealers would snap at the chance to sell it. Anyone who believes that Volkswagen's new automobile won't appear over here—particularly if the booming sales of the regular VW begin to level off—may go soak his head in a bucket.

This POPULAR SCIENCE reporter saw and drove a handmade prototype of the new VW at the factory in Wolfsburg, Germany, last May.

The car is cannily designed to look economical—as if it *had* been built by especially dollar-conscious elves in the Black Forest. Sieved through the practical German mind, it works out pretty well. The styling is tasty, and even smart, when the old and new cars are put side by side. The front end carries a faint suggestion of Renault's sparkling Caravelle. There is loads of glass area.

Germana aren't used to U. S.-style inquisitive magazine reporting.



HOODED INSTRUMENTS now include a gas gauge as well as an oil temperature and pressure gauge, a speedometer, and clock. A trick lever on left doorjamb locks lid over the rear deck.

"Who styled your car?" you ask a passel of VW dignitaries.

"Nobody. We have no stylists."

"But somebody," you protest, "had to draw a picture of it in advance."

"Well, we employ consultants."

Pursue that dead end if you want to. At the end of 10 minutes you're right where you started.

Frau Nordhoff's handrail. Instruments are hooded in the best Detroit fashion. On the right side of the dash is a handrail like that in a Chevy Corvette. This same handrail appeared some months ago on the regular VW. To carry the Detroit analogy further, even as the wives of reigning vice presidents over here suggest changes in cars in the cocoon stage, so did Frau Charlotte Nordhoff, wife of the Volkswagenwerk director-general, ask her husband why he didn't supply a grab bar for his right front-seat passengers.

There's a gas gauge, even as there is on the regular VWs now beginning to arrive in the U. S. The hardware is elegant, even by Cadillac standards.

Apart from looks, the new VW differs from its forebear in mechanical innards. The engine is Volkswagen only in principle. The manufacturer calls it a "suitcase" engine. It's nine inches lower than that in the regular VW, largely due to a new type of fan for the air-cooled cylinders.

The decapitation makes possible the addition of a station wagon to the line.


Like the standard engine, the new one has no cylinder block as such. VW simply casts four iron cylinders, shrinks them on to steel inserts, and bolts them to a crankcase. The biggest user of magnesium in auto manufacture anywhere, VW makes not only the crankcase of this metal but the transmission and fan housing, as well.

None of the parts of the old and new engines are interchangeable.


All four speeds in the transmission are synchronized—as, indeed, they are now in the standard VW. This box is even more fun to shift than that of the four-speed Corvair. The stick is crisp, the throws short. The ratios in both cars are the same: 3.8, 2.06, 1.32, and .89.

The 1500 keeps its head in the corners. This reporter found it willing to take

book—and even comes in a swank station-wagon version



FRONT SUSPENSION features two-arm ball joints in place of the standard VW's kingpins. Instead of the latter's laminated torsion-bar springs, the new car has solid bars.



HEAT-EXCHANGER SYSTEM for warming passengers is depicted by this cutaway. Fresh air in semiclosed plumbing circuit is routed from blower, around exhaust, and into the car.

hairpin turns on the test track infield at 10 m.p.h. beyond posted speeds.

The ride is splendid. On a deeply ridged washboard road where an American compact car, thoughtfully provided by the VW people, shook off one's spectacles, the 1500 went through as if on skates.

The top speed is in the area of an indicated 133 kilometers (about 83 miles an hour), with the speedometer error three miles an hour on the high side. This compares with an indicated 70-72 in the standard VW.

The 1500 accelerates from a standing start to an indicated 100 kilometers an hour—62.5 m.p.h.—in 20 seconds, compared with 26.8 seconds for the standard VW. Performance, of course, costs money. The standard VW will go 100 kilometers on 7.5 liters of gasoline. The 1500 requires 9.5 liters or, roughly, a gallon for each 25 miles.

Volkswagen officialdom can get pretty


sticky about nomenclature in a discussion of the new car. The standard Volkswagen, for instance, is not "the old car." It's "the Volkswagen." The new car is the "VW 1500," using only the initials, not the spelled-out name.

"They are two different cars," explains a company officer earnestly.

Yes, they are. The VW 1500 was created for the same reason that there are Buicks a cut above Chevrolets and Cadillacs a cut above Buicks. The new Volkswagen—pardon, the VW 1500—is for the man getting up in the world, ready to burnish his status symbol.


For the U. S. market, the 1500's conformance to contemporary styling may be self-defeating. Anyone can spot a Volkswagen a mile away. It has become a mark of distinction. Who wants to drive a car that can't be distinguished from an Opel, Simca, Ford Anglia, Taunus, or Hillman—or indeed, from a Falcon, Comet, Lark, Olds F-85, Tempest, or Valiant? ■ ■

REAR ENGINE in wagon, under floor like Corvair's, permits a cargo space 67 in. long and 48 wide over the wheel wells. One of car's engaging oddments is a cylinder in front compartment that, filled with compressed air, energizes windshield squirters.





◀ **CONTENTED CALF** doesn't miss mother. It gets half a pint of formula from the automatic feeder at left, can come back for more in four minutes.



COMPLEX MECHANISM behind cover includes hopper for powdered formula, thermostat-controlled water tank, and plunger to open and shut valves.

Mechanical mother down on the farm


A new calf feeder can do everything the cow does except moo. It uses four micro-switches worked by a cam to control relays, solenoids, and motors. In sequence, the mechanism dumps a preset amount of dry formula into a bowl, turns on a stir-

rer, fills the bowl with warm water, and triggers a check valve to a nipple. The calf's mother, released from baby tending, goes back on the assembly line to give milk for the dairy's customers. K & K Mfg., Minneapolis, makes Nurs-ette.



Cargo cage for station wagon

The grille in the station wagon above keeps cargo from sliding forward when brakes are applied. It can also confine a dog to the rear compartment. The welded grid stands on two base feet, is secured by wingnuts to the locking lugs for the folding rear seat. It was made by Robert Peters of Walton-on-Thames, England, for his Vauxhall Victor.



Underwater hydroplane

Towed by launch at speeds from 2 to 20 knots, this underwater craft lets a diver survey the sea bed at Port Adelaide, Australia. When the pilot is inside, the cockpit is closed. He gets air from a cylinder, observes through portholes, and can stay down four hours. Hydroplanes fore and aft are controlled from inside to submerge and level off at any depth.

New Ideas from the Inventors

.....




Machine Packs Your Groceries. Supermarket lines might move faster if check-outs were speeded by this recently patented bag packer. A conveyor would move your purchases along to the cashier.


As he rang up each item, he'd place it in a well. The machine would then open and grip a paper bag, slide a load into it, tip it up, and move it forward so that another bag could take its place.

Paper Spoon Peels Off Cup. You wouldn't have to carry spoons or stirrers to a picnic if you used containers like this for tea or coffee. A spoon-shaped cut-out in the stiff outer layer of the paper cup would pull out like the conventional handle tabs, then break free.

Dryer Pipes In TV Sound. A beauty-shop patron could hear music, TV sound, or her attendant's voice while she had her hair dried under a helmet like this. A small speaker would feed into the air space under the shell; each dryer would have its own selector and volume control.



More Inventors' Ideas




Tilt Switch Fights Car Fire. With electrical contact made through mercury in a V-shaped tube, this safety switch would automatically cut off the ignition if a car or other vehicle crashed, overturned, or tilted to an unsafe angle. The cut-off might prevent some fires, and help halt out-of-control cars.



Tool Pockets Zip Onto Apron. You could switch more quickly from one job to another if you didn't have to reload your apron pockets each time. Here, instead of weighing yourself down with nails when you need small tools—or vice versa—you'd just zip off one set of pockets, as shown, and zip on another.

Boat Trailer Carts Anything. You'd get all-year service out of a trailer like this. Y-shaped boat-support pads could be exchanged for side-wall stakes suited to


different kinds of hauling. They'd slip in or out of brackets. A winch in the hitch would let you tilt the trailer bed to provide easier loading, too.





Cop's Billy Lights His Way. With a bulb and battery built into this club, a guard or policeman could use it to shed light or to signal for help while still keeping it handy as a weapon. One version would include a hook to grip a suspect's collar, and a transformer to give him a shock if he tried to get away.

Filter Shows If It's Filtering. You'd know when your car's oil filter needed cleaning or replacement if it were monitored by an indicator like this one. When the relief valve opened to let oil bypass a clogged filter, lowered pressure across the line would allow a switch to close and light—or sound—a signal.



"Air" Spray Chokes Fire. This inventor would suffocate flames with inert gas instead of water. A burner would remove half or more of the oxygen from indrawn air and pump the carbon-dioxide-rich exhaust through hose. The spray would eliminate water damage and drive away smoke so firemen could breathe.

The following patents have been issued on these inventions:
Bag Packer—No. 2,938,890 to W. A. Kerker, Box 513 Hupatung, N. J.; **Spoon**—No. 2,861,365 to H. B. La Tourette, Jr., Clayton, Mo.; **Dryer**—No. 2,906,550 to J. Goldberg and E. Goldstein, Chicago; **Switch**—No. 2,810,589 to G. L. Fohlgren-Crockett, Carl; **Apron**—No. 2,816,685 to W. L. Ehrlich, Chetumse, Ill.; **Trailer**—No. 2,881,138 to Henry Huber, DeLand, Fla.; **Billy**—No. 2,966,621 to S. T. Valt, Great Falls, Mont.; **Filter**—No. 2,843,077 to B. Leefer, Silver Spring, Md.; **Spray**—No. 2,961,010 to C. D. MacCracken, Tenafly, N. J.

Copies of patents may be ordered, by number, from the Commissioner of Patents, Washington 25, D. C., at 25 cents each. To write to an inventor, if the address given above is insufficient, you may address him (by name and patent number) in care of the Commissioner of Patents.



**I drove the Army's new
50-ton killer:**

M60

The World's Toughest Tank

By Erik Miller

LIKE BOATS in a choppy sea, M60
feet bobs across wilderness.

YOUR first glimpse of the squat M60 tank tells you it's hardly designed to take the kids for a Sunday drive. Every big, brutal line, from the dirt-encrusted tracks to the wickedly long high-velocity gun, is strictly business.

You walk around it once, remembering the briefing they gave you—more fire-power, more range, new black boxes,

much better crew protection. It's a fighting machine that is replacing the M48 as our No. 1 battle tank. It can clobber any other tank in the world, they told you.


The tank commander, who has been watching you while the M60's awesome looks sink in, asks you if you're ready to roll it. You hoist yourself onto the brown hull, past the queer ports and grilles,



IN THE MIDST OF AN ARSENAL, the driver's seat is under the cannon and flanked by ammo racks. Controls are surprisingly uncomplicated. Transmission stick follows stepped pattern: far front to start, two forward speeds, and reverse. Above the wheel are tachometer (left) and speedometer (right).



GUNNER'S-EYE VIEW shows open breech of main armament: a British-built, quick-firing 105-mm. cannon. Large plate at right is counterbalance. Tubes below, toward driver's seat, are a few of the M60's 57 shell containers.



COMPARTMENTS FOR CREW OF FOUR—commander, driver, and two gunners—are dovetailed into design for maximum compactness and protection. Unlike gasoline-engine tank it replaces, the M60 needs no "little Joe" auxiliary engine to power radio, lights, and gun-turret rotation. Its supercharged V-12 diesel does it all.

and onto the gun turret. Before swinging down the hatch you glance around at the chewed-up testing ground. This terrain would turn an auto into a bent ruin.

The first footing is the commander's platform below the hatch. You wriggle past and down to the driver's seat. It is a wire-mesh affair that sags comfortably. Somehow you'd always thought that a

tank would have more knobs than a pipe organ, but this is different. You're in a little, white-painted steel room, with only a modest number of levers and gauges to manage. The springy seat is a two-level job, locking upward for heads-out driving and downward for periscope travel if people with ugly dispositions are around. To your right a shift rod sprouts



HUGE DISPLACEMENT (1,790 cu. in.) of diesel helps it put out the 750 hp. needed to hustle 51 tons at a top speed of 30 m.p.h. Although the powerhouse gulps a gallon of fuel for every .85 mile over flat terrain, the 375-gallon tank assures a cruising range of 320 miles. Two top-mounted axial-flow blowers ram 20,000 cubic feet of cooling air per minute into the engine compartment.

from a quadrant to give you two forward gears and reverse. There's no clutch—just an accelerator and brake pedal. You steer with an airplane control wheel. The tank commander needs only moments to brief you on driving.

Work the starter (it's linked with the shift lever). A deep throbbing noise aft tells you that the mammoth 750-hp. diesel has caught. You check the gauges, slip into gear, step lightly on the accelerator.

The big steel beast takes off smoothly, the slapping of the track blending with the chest-punching throb of your supercharged V-12 engine. A whiff of diesel smell drifts into your compartment, and there's a taste of hot metal. Although the ground rolling toward you is rough, the torsion bars on the track wheels translate it into a curiously gentle rocking or pitching motion.


You experiment with the steering wheel, which works by changing the power ratios between the two tracks. If you turn it too far or too fast, there's a hard sideways slam. You get the knack of wheeling the tank where you want it with smaller corrections, getting jerks rather than slams.

Coming around back to the starting place, you tackle some steep little hills. Going up slopes so steep you wonder if you might topple backward, you note that there's power to spare—from a geared-down engine having a whopping 1,710 foot-pounds of torque. Going down, you just touch the pedal and a stack of 18-inch disk brakes, oil-cooled and powerful, haul you down to a smooth stop.

You cut the engine, squirm into the open, and drop to the ground. Then you walk around the awesome M60 again, glad that this killer is on our side. ■ ■




ARMOR-PLATED UNDERBELLY is pierced by water-proof hatches for emergency exit. Tank-width torsion bars, attached to wheels by bell cranks, are sealed where they enter the body. Ground clearance is 1½ feet. The M60 can plow through four feet of water, jump an 8½-foot trench, and squeeze down an alley only 12 feet wide.




IN TRAIL POSITION, cannon rides over stern-mounted engine. Enlarged section of barrel is sleeve covering recoil-suppressing ports and gas evacuator. Heavy grilles over the engine air intakes are flanked by toolboxes. Telephone in the small box at left rear permits foot soldiers to talk with the crew, sealed inside.

"I'd like to see them make..."




DOUBLE-LIFE SHIPPING CARTONS for gas-station supplies. Preprinted with signs in fluorescent


ink, they could be given to customers when empty.—A. J. Preuss, Campbell, Calif.




CHANGEABLE GLUE SPOUTS for squeeze bottles. One wide-spread, one needle-nosed, and one regular would take care of a variety of jobs.—Terry Dawson, Manhattan Beach, Calif.



SOCKET-WRENCH EXTENSIONS with knurled ends to permit easy spin-off of loosened nuts, even though the tool and your hands might be oily.—J. I. Mitchell, Horseheads, N.Y.



BOOK MATCHES with pressure adhesive on the back. Then you could stick the folder to the cigarette package and it would never be mislaid.—Clarence Brady, San Fernando, Calif.



TRANSPARENT FUEL TANKS on power lawn mowers so you could tell at a glance how much gas you had left instead of running dry in the middle of the lawn.—Sam Gainer, Austin, Tex.

Everyone has his own pet idea of a gadget that he would like to see in general use. What's yours? We will pay \$5 for each one published. Please use Government postcards

only. Send to U.S. Editor, Popular Science, 355 Lexington Ave., NYC 17. Write your name and address clearly. Contributions cannot be acknowledged or returned.

Circus daredevils in flimsy gas bags paved the way for a Union reconnaissance fleet that could be launched from land or sea

Text and drawings by Edwin Tunis Author of *Weapons: A Pictorial History*

AS FAR back as 1784 Benjamin Franklin envisioned an aerial invasion by soldiers wafted into enemy territory in 5,000 balloons. French Republican forces used a captive observation balloon to help them defeat the Austrian army at the Battle of Fleurus, June 26, 1794. In this first effort, the observer dropped weighted notes to convey information to the French commanders. After that, military aeronautics was little more than talk until the American Civil War.

On July 31, 1861, less than four months after the fall of Fort Sumter, John La Mountain made the first effective war use of an observation balloon in this country near Fortress Monroe, at the mouth of the James River. At that time James Allen and John Wise also had balloons in the field from which they subsequently made useful observations. All three were professional showmen using their own balloons. But these, too lightly constructed to stand much military use, were soon destroyed by accident or by the inexperienced handling of soldier ground crews.

Professor Thaddeus Sobieski Constantine Lowe was also a civilian with his own balloon, the *Enterprise*, well named to match its owner's character. Lowe was determined to head an organized army balloon corps. He landed the job after a demonstration in Washington, during which he dispatched a telegram (the first ever sent from aloft) to President Lincoln over a thin wire hanging from the "car" to the ground. Still in the air, the Professor was then towed to the south lawn of the White House, where he descended.

The title "Professor" wasn't the result of any college degree, nor was there anything derisive about it. Lowe was a highly respected man of intelligence, energy, and executive ability, as well as a man of


great courage. He knew that a showman's balloon wouldn't do for army work and he so persuaded the generals, who authorized him to build one, to be named the *Union*, of the best India silk, with linen rigging and cordage. With the help of 50 seamstresses, Lowe turned 1,200 yards of pongee into a balloon in 16 days.

In the intervals between active work as balloonist and observer, Professor Lowe designed and supervised the building of seven military balloons. They varied in size from the *Union* and *Intrepid*, each holding 32,000 cubic feet of gas, and able to lift five men, to the *Eagle* and *Excelsior* of 15,000 cubic feet, which could carry only one. Although the larger ones had more than twice the cubage of the smaller ones, the difference in size was curiously slight. The diameter of the *Intrepid* was 38 feet, that of the *Eagle* only eight feet less. The small balloons were spherical; the larger ones were top-shaped. The outside of the envelope was "doped" with four coats of boiled linseed oil, to make it gastight, and the whole thing was then turned inside-out (what a job!) for a coat of neat's-foot oil to keep it pliable.


A large wooden valve for discharging gas at need was fitted into a reinforced circular hole in the top of the gas bag. The valve-control rope passed down through the center of the envelope and emerged from the dangling snout through which the balloon was filled with gas. The bottom of this snout remained open so condensed moisture could run out and pressure from absorbed heat could be relieved; except under such pressure, the light gas would not escape downward.

A net of strong linen cords enclosed the envelope and transferred its lift to the gondola. The cord ends reached down to a strong wooden "concentration ring"

PROFESSOR LOWE'S "BALLOON BOAT," the U.S.S. G. W. Parke Custis, began life as a coal barge. Although she had no means of moving under her own power, she must be counted as the world's first regularly commissioned aircraft carrier. The Professor built an overhanging flight deck on her, big enough to permit handling a balloon and with room to spare for two hydrogen-gas generators. A ring of sandbags restrained the balloon when it was not in use. Pulleys bolted to the deck helped to hold its guy ropes when it was aloft. The Custis was 122 feet long. She saw active service on the upper and lower Potomac River in the fall of 1861, and in the Peninsula campaign in the spring of 1862.



MAHOGANY VALVE from the top of Lowe's balloon Enterprise is shown open at left. This device was normally used for descent at the end of a free flight; in captive flight it was seldom touched. The control cord passed through the middle of the balloon and its lower end was within reach of the aeronaut. With it he pulled the central disk down, making an opening to release gas and so reduce buoyancy. Releasing the cord allowed the "India-rubber springs" to close the valve again. The crevice between valve and seat was calked with a thick "goop" of soap and wax. (These and other details have been provided by F. Stanbury Haydon's *Aeronautics in the Union and Confederate Armies*, Johns Hopkins Press, 1941.)



Civil War aeronauts 1,000 feet up could see the enemy

placed well below the envelope. The basket in which balloonist and passengers rode hung from this ring by stout lines spread by a ring placed at about head height from the floor of the basket. The basket itself was woven of willow withes, or of rattan on a willow frame. It was rectangular and flat-bottomed, with sides only two feet high. These "cars" were either painted blue and decorated with white stars, or had red and white stripes painted below a star-spangled blue band. The envelope was decorated, too. If all this seems unmilitary, it was at least stylish at the time.

Handling and observation

In addition to the aeronaut, the telegraphers with their five miles of wire, and the transport men to handle seven or eight four-horse wagons, 33 soldiers were assigned to handle the balloon itself. This made quite an encampment, usually in a hollow, or behind a screen of trees, that would hide their big ball and protect it from strong winds. When inflated but not in use, the balloon was held down by 30 or 40 100-pound sandbags attached to its cordage, as well as by its guy ropes secured to trees or to iron grappling hooks. During inflation it rested on straw or a ground cloth.

Ascensions were not made from the camp area but from a cleared space a little distance off to which the soldiers towed the balloon by hand. This was to save the camp from the Rebel artillery fire that an ascension always drew. At observation height the aeronaut was beyond range, but he had to pass through lower levels where the Confederates threw everything they had at him. Though Southern newspapers reported imaginary hits, and though there were dozens of hair-raising near misses, including shells that passed through the rigging, no balloon was ever hit by a shell, or indeed anything bigger than a musket ball.

The largest craft were restrained by as many as four Manila cables, hanging from the spreader ring, with the ground end of each run through a pulley and handled by a six- or eight-man team. When the observer reached working height, grappling hooks on the line ends could be anchored in the ground to hold him there. Balloons were sometimes towed considerable distances while at observation altitude; Professor Lowe was once moved 20 miles in this way. Most ascensions went up from solid earth, but quite a few took off from boats—either ordinary gunboats, or the G. W. Parke

BALLOONS CAN RISE when inflated with ordinary illuminating gas; the Confederates used it in the one rather touching patchwork envelope they made from silk dresses contributed by Southern women. But hydrogen has the greatest known lifting power. Thaddeus Lowe designed a portable hydrogen generator that completely freed Union Army balloons from city gas mains. The generator itself was a wooden box 11 feet long, 5 feet high, and about 3 feet wide, narrow enough to ride on an army transport wagon. A second wagon carried the necessary auxiliary parts.

The generator box was strongly built, braced to stand gas pressure, and acidproofed inside. Access to the interior was through a manhole in the top and a clean-out door in the rear wall, both tightly bolted down when gas was being made. Shelves on the inner walls held 3,300 pounds of iron filings, submerged in three feet of water. Sixteen hundred pounds of sulfuric acid was slowly added to the water through a copper funnel. As the acid attacked the iron, hydrogen gas formed and was drawn off in a six-inch hose to the cooler. This was a box some five feet long with a smaller, though higher, box inverted in it. Enough water was

put in to fill the inner box about half full. Incoming gas entered the inner box under water and bubbled upward around baffles to leave through a second hose attached flush with the box top. Through this the gas passed to the purifier, a duplicate of the cooler, but filled



for 20 miles—and stay out of range of artillery fire

Custis, which was planned for the operation.

One balloon made an accidental free flight over Rebel territory and got away with it, but normally a stationary position 500 to 1,000 feet up was best for military observation. At 1,000 feet an observer could see up to 20 miles with field glasses, and he remained in constant communication with the ground. In the larger balloons a telegrapher was standard equipment, and engineer officers often went up as passengers to map the country below.

The aeronaut wasn't a trained soldier (not even Lowe held any military rank); still he and his half-dozen subordinate balloonists became expert at discovering and interpreting enemy activity—though they could also be misled. They could spot artillery; but the Rebels could fool them with wooden "Quaker" guns. They could count campfires at night; but they couldn't distinguish them from dummy fires lighted to deceive them. Still, the dust of moving columns was unmistakable, as was the blue-and-white smoke of gunfire.


Just as airplanes have been used in later wars to observe the effect of artillery fire and correct the aim, balloons were used for this purpose at times in the

Civil War. The balloon had one point of superiority over the plane: Its observer could hear the blowing of bugles, the shouting of men, and the rattle of gunfire. There was talk in Civil War times of the military advantages of photography from balloons, but no example seems to have survived and there is no evidence it was ever tried. ■ ■

.....

with a lime-and-water solution to absorb unwanted gases that were byproducts of the chemical action. Here, though, the gas, which entered by a six-inch hose, left by a twelve-inch one to go into the balloon.

The generator took three hours to fill a large balloon. Lowe had no way of storing gas, though he once met an emergency by transferring some from a small balloon to hasten the inflation of a large one.





TWO-PIECE METAL TOP for formal use has polished black rear section, brushed finish at

front. Exterior and interior are navy blue that looks black at night. The trim is light blue.

The President gets a new car

The new Lincoln Continental delivered to President Kennedy this summer has so many pushbuttons that it takes a special panel on the dash for them all. The car took four years to design and build

by Ford in cooperation with the Secret Service. It will be used for parades and other official purposes.

The car has three interchangeable tops: all metal, transparent plastic, and con-



ELEVATOR REAR SEAT rises 10½ inches on push-button power so President can see and be seen when crowds line streets. Footrest goes up with it. Jump seat is at normal height.




VIEW OF INTERIOR shows rear seat wide enough for three adults. Control panel at left contains reading lamp, radio, and seat-elevator switches. Lap robes fold into recessed doors.



Floating two-story hotel

A 100-foot houseboat that once did duty as a dormitory for construction crews on a TVA project is being converted into a "boatel" on Lake Chickamauga near Chattanooga, Tenn. It will contain a grocery store and restaurant for boaters and campers, a top-deck dance floor and sun porch, and 14 bedrooms for guests.

The 280-ton boat was moved from Florence, Ala., by two 80-hp. outboards, making the 216-mile trip on the Tennessee in five days. Workmen completed renovations during transit.



PLASTIC TOP is transparent so President can be seen in parades but keep dry in rain. Third

interchangeable roof is convertible fabric. They are stored in trunk when not in use.


vertible. The latter two can be stored in the trunk when not in use.

An elevator back seat can be raised 10½ inches by pushbutton so the President can be seen by crowds. The compartment can be closed off from the front seat by a pushbutton sliding panel and has a handrail the President can grasp


while standing. It has two two-way radio telephones, one fitted with a scrambler. There are separate air conditioners and heaters in front and back. The car is an elongated 1961 Continental, 253.7 inches in length (41.3 inches longer than the standard) and has a 156-inch wheelbase (33 inches longer). It weighs 7,822 pounds.



RETRACTABLE FOOT-STANDS and recessed handholds in body (two on each side) are for Secret Service men. Two more built into rear bumper have grips that can be mounted on trunk.



TWO RADIO TELEPHONES keep President in touch with country's business. One has a scrambler for confidential calls. Above, Secret Service chief U. E. Baughman checks phone.



Big flying boat scoops 7,000 gallons from lake . . .


Huge aerial fire fighter

Three giant Martin Mars flying boats are being converted by a group of Canadian lumber companies to combat seasonal fires in the immense forests of British Columbia. Each is equipped with two 3,500-gallon tanks into which it can scoop water from a lake. Speeding to flaming woods, it can dump a third of an inch on an acre of ground every 15 minutes.



. . . dumps it on blazing forest.


WHAT'S NEW IN PHOTOGRAPHY




Ultrasonic Projector

No cord to trip over is the latest refinement in remote-control projectors. This one does all an earlier model did with wires [PS, Mar. '61]. It threads the film, turns off the room light, starts the projector, reverses, arrests action, varies speed, stops the show, and turns the room light back on. You push buttons on a transmitter to send ultrasonic waves to a receiver in the projector and trigger operation.

Two models: a Tele-Sonic movie projector sells for \$299.95; a Tele-Sonic slide projector for \$269.95. Bell & Howell, 7100 McCormick Rd., Chicago.




GAS CAMERA is powered by a CO₂ cartridge of the kind used in siphon bottles. Carbon dioxide operates a motor that advances the film and cocks the shutter. One charge is enough for six to eight 20-exposure rolls. The lens is fixed; you focus by moving the film. The 35-mm. Graphic Jet costs about \$120. Graflex, Inc., Rochester, N. Y.



BARNDOOR LIGHT fits around an R40 reflector bulb in a clamp-on fixture to help you put light where you want it.


Pressed-in "eyes" in four sides are shaped to the contour of the bulb and slip on without taking it from the socket. Big 5-by-10-inch flaps swing back 270 degrees or come off so you can fold the device flat. \$5.75. Lowel-Light Photo Engineering, 421 W. 54 St., NYC.



PROJECTION SCREEN is made of embossed material resembling beaded plastic to give bright, glare-free reflection. The 40-by-40-inch screen weighs only 14 ounces with its container, is so light you can hang it on a picture hook. Sparklescope screen costs \$3.98. Central States Paper & Bag Co., 5221 Natural Bridge, St. Louis, Mo.



THROUGH-LENS CONTROL lets you focus and see the exact picture this 8-mm. movie camera is taking. It also sets the exposure, sensing only light that falls on the film. The system works



through a prism behind the lens, mirror, and photocell. The camera has two-speed electric zoom. Roll-film model, \$349.95; magazine-load, \$369.95. Bell & Howell, 7100 McCormick Rd., Chicago.




MOVIE FLOOD with a sealed beam is rated at 650 watts, but it gives as much light as four 300-watt R30 lamps and lasts twice as long: eight hours instead of four. It contains its own reflective coating, needs no separate reflector. With holder and cord, it sells for \$19.95; lamp replacements, \$5.45 each. Westinghouse, Bloomfield, N. J.




LIGHT FILTER in a pocket holder lets you view light-and-shadow contrast as they will actually appear in the finished photo. You can then shift indoor lighting or wait for better outdoor conditions. Contrast Viewer costs \$2.95. Bausch & Lomb, Rochester, N. Y.




CAMERA ADAPTOR enables you to project slides through the lens of a Rollei having a detachable hood. You simply remove the focusing hood, invert the camera, and insert it in a frame on top of the projector. The adaptor with a double 2 $\frac{1}{4}$ -by-2 $\frac{1}{4}$ -inch carrier is \$49.50; 2-by-2 carriers, \$2.50 each. Burleigh Brooks, Inc., 420 Grand Ave., Englewood, N. J.



PUMPING PEDALS CREATES A VACUUM




THE POWER SYSTEM of a player piano resembles that of a vacuum windshield wiper. Two foot-powered bellows maintain a partial vacuum (about $1\frac{1}{4}$ p.s.i. less than atmospheric pressure) in a spring-loaded, bellowslike reservoir. Pipes from this run where power is needed—to turn the music roll and hit the strings, for example. As a foot pedal opens one of the power bellows (left), outside air pressure shuts an outward-opening flap valve so that air cannot enter. But an inward-opening valve admits air from the reservoir. As air is exhausted from it, the reservoir is partially collapsed against its spring by the pressure of the outside air.



AS YOUR FOOT COMES UP, pedal linkage lets exterior springs collapse the power bellows, now full of air from the reservoir. Squeezed by the bellows, this air closes the interior flap valve to the reservoir but blows open the exterior one. The closing bellows thus forces air out into the atmosphere. Meanwhile the bellows worked by the other pedal (not shown) takes over the job of exhausting air from the reservoir. Should pumping stop, the spring in the reservoir bellows tends to open it, making it a power bellows temporarily to maintain "low air" for a short time. Units that use power admit outside air, which must continuously be pumped out.

How a Player Piano Works



AFTER years of obsolescence, the player piano is making a comeback camouflaged as a spinet. Music rolls of both new and old favorites are pouring from revived factories. Fans find treading such fun (you can express yourself in the music by rhythmic pumping, varying foot pressure while working the controls) that the makers aren't electrifying it. And, in this era of runaway prices, the player piano seems an astonishing holdout. In its heyday a good one cost over \$1,000. Though still largely hand-


made, the new spinet player above costs slightly less.

Early mechanical players were set in front of a piano and pressed the keys with mechanical fingers. One of this kind hit the American market about 1896. But buyers preferred to have the works inside, and that became universal.

The paper rolls were produced mechanically until a German manufacturer named Edwin Welte designed a piano with electric key contacts. On this, the pianist himself created the master roll,

A FIVE-BELLOWS MOTOR DRIVES THE MUSIC ROLL

ROTARY POWER IS GENERATED by five smaller bellows connected to a crankshaft. Linked to each connecting rod is a hollow-faced slide valve. The low-air line runs to a port under each valve. Another port to bellows is nearby. As a valve cavity bridges both ports (at bottom below), low-air suction draws air from bellows, making atmospheric pressure collapse it. This turns the crankshaft, moving the slide valve. When it uncovers the bellows port (see middle one below) air enters, and bellows open again. Overlapping impulses give smooth action which, through chains and gears, turns the takeup spool for playing the piano, or the music roll for rewind.



recording not only every note and its precise length, but even his tempo, phrasing, and dynamics—the key-striking force.


The player piano is an air-powered instrument, in which pumping the foot bellows creates a partial vacuum. Other bellows are connected by piping. Higher outside air pressure putting the squeeze

on them provides the mechanical power.



Today's player piano has a governor to maintain set tempo no matter how furiously you pump, and a device that centers the paper roll pneumatically on the perforated tracker bar. Once again called the Pianola, the spinet player is the product of Pianola, Inc., NYC. ■ ■

HOW AIR PRESSES THE KEYS

EACH KEY IS LINKED to its own tiny bellows channeled to upper chamber of a valve unit (shown at right). Low-air line exhausts lower chamber above a diaphragm and, through a bleed vent, the space below it, which is connected to a hole in the tracker bar over which the roll runs. With low air on both sides, diaphragm lies flat. Atmospheric pressure holds down a two-faced transfer valve, sealing lower chamber but opening bellows to atmosphere (below, right). As a hole in a music roll uncovers one in the tracker bar, air rushes in under diaphragm. The diaphragm lifts and the transfer valve is raised (below, left). This shuts the top port, channels low air to bellows. Collapsing bellows depresses key, and hammer strikes string. As roll moves and paper covers hole in tracker



bar, air in tubing and under diaphragm is exhausted through the vent. The diaphragm flattens and lets the valve drop. This opens the bellows to atmosphere again and draws the hammer back to its previous position.






Dockside telephone

Some cities have curbside pay phones you can use from your car.

The Eisenhower State Park Marina on Lake Texoma, near Denison, Tex., went them one better. It had one installed on a dock for float-in phoning.



FAIRED-IN HEADLIGHTS and rectangular grille are new. The 136-inch-long roadster has an 80-inch wheelbase.


LOCKING TRUNK LID is offered on Sprite for first time. Tail lights are also restyled.



More bite for the Sprite

The diminutive Austin Healey Sprite, one of the lowest-priced sports cars, has grown slicker.


Gone are its familiar bug-eyed headlights and grinning grille. Changes under the hood include a higher compression ratio (now 9:1), larger valves, and improved carburetion. Result is a 25-percent power increase; the 57 9-cu.-in. four now generates 50 hp. Top speed is over 85 m.p.h. Price, still around \$2,000.



Solar golf cart

Energy from the sun drives this car around the golf course. It is powered by batteries, shown here drawing a new charge from a panel of solar cells.

The demonstration was put on by Hoffman Electronics Corp. of Los Angeles, makers of solar cells.



Space test for liquid hydrogen

A flying laboratory enables Convair engineers to find out how liquid hydrogen reacts to weightlessness. A container of hydrogen (center) is put in a balloon which is inflated inside the fuselage of an Air Force KC-135 tanker. At 35,000 feet, the plane is put into a shallow dive and maneuvered to achieve zero gravity. Since leaking hydrogen could explode in air, the nylon bag is filled with nitrogen, making it necessary for the "floating" engineers to wear oxygen masks. Liquid hydrogen will propel the Centaur space booster.

Remember the B-36?

A dozen years ago, this incredible "flying apartment house" was our first line of defense. Now it's an epic museum piece

By Wesley S. Griswold



In March '49, four jets were



First B-36 dwarfs a B-29. Mark I's two huge landing wheels gave way to a more balanced set.

THE B-36 was the biggest bomber the world ever knew, and it lived and died without having to fly through anything worse than a war of words.

That was darn lucky for the United States, said many top Navy officers, who could never speak of the huge plane without getting mad.

Leading British aeronautical engineers, and even some prominent American ones, openly snickered at the B-36. Yet the U. S. Air Force claimed, in the late 1940s, that it was invincible. Maybe it was. At least, there was never anything else like it.

People with a fondness for spilling statistics found a mouthful here. The B-36 could tote a 10,000-pound bomb load 5,000 miles, drop it, and fly home again without refueling. On shorter hops it could lug along as much as 84,000 pounds of high explosives. Its bomb bay had the capacity of three railroad box-cars.

The giant craft could climb until it

could no longer be seen or heard. Its 230-foot wingspan was considerably greater than the length of the Wright Brothers' first flight. Its wing was 7½ feet thick at its fattest part, and contained a crawlway, providing access to the engines.

The 163-foot-long plane had 10 engines, developing a total of 44,000 hp., as much as nine locomotives or 400 automobiles. It could generate 160,000 watts of electricity, and contained 30 miles of wiring. Its de-icing system could have heated a 600-room hotel. The 30,000-plus gallons of fuel it took off with would have sent a car around the world 18 times.

The big bomber's crew of 16 could take turns napping in eight bunks on long flights. Out in the tail, there were an electric stove and refrigerator, folding chairs and retractable tables.

What did all these men do? Well, in a sample B-36 lineup toward the end of the bomber's career in the Strategic Air Command, there were a plane commander, a pilot, two flight engineers, a radar-bombardier, a navigator, a nose



added to the B-36's power plant, a pair under each wingtip. Final horsepower: 44,000.

gunner, two radio operators, a forward gunner (who was also a copilot), a forward gunner-observer, two lower-aft gunners, a tail gunner, and two upper-aft gunners.

Connecting the pressurized cabin and tail was a tunnel that ran through the unpressurized middle. To go from one end of the plane to the other, the traveler rode through the tunnel on a flatcar, pulling himself along by an overhead cable.

The B-36 mounted 16 guns, which was why it was often called the Flying Battleship. It was also given less flattering nicknames: Magnesium Monster, Flying Apartment House, Sitting Duck, and, most distasteful of all, Billion-Dollar Blunder.

The controversy. It was Admiral Arthur W. Radford who gave the B-36 this last, surly label. Radford earnestly believed that super aircraft carriers were a much better investment for the taxpayer. He was blunt in asking if the B-36 was really as good as it was cracked up to be. Could it fly fast and high enough to do its job?


The Navy said no. The British said no. The U. S. Air Force said yes.

This elephantine bomber was conceived in mid-1941. Western Europe then was largely in Nazi hands. England was enduring the worst of its blitz. The outlook in the Pacific was bleak. Air Force planners realized they might have to deal

with Germany and Japan from home bases entirely.

There were no jet interceptors or guided missiles to worry about. Anti-aircraft fire was still fairly low and inaccurate. Fighter planes were all propeller-driven and not very fast.

The Air Force asked for a bomber with a 10,000-mile range, 10,000-pound payload, 35,000-foot ceiling, and a cruising speed of 240-300 m.p.h. Moreover, it would have to be able to use 5,000-foot



"GREENHOUSE" was the crew's name for the front. Besides the pilot's plastic bubble, the navigator and bombardier had wide glass area below. Guns stuck out from under canopy.

Faster planes and new tactics made the big B-36 obsolete



BOX FORMATION was standard for B-36s in group flight. With sixteen 20-mm. cannon on

each plane, they could cover every quadrant of the sky with heavy fire in case of attack.

runways—quite a feat for a monster of that size.

All these requirements were considered fantastic. But Consolidated Aircraft came up with a design, to be powered by six 3,000-hp., pusher-type, propellered engines. Development dawdled, however, as the favorable progress of World War II made it seem less essential.

Then came the atomic bomb and, with the end of the war, the almost immediate evidence that Russia was going to become the new world threat. The U. S. was the only nation with the A-bomb. It had to have a means of delivering it to any target in Russia, if necessary. The B-36 seemed the obvious bird to bank on.

The improvements. Consolidated had meanwhile merged with Vultee and become Convair; and on Aug. 8, 1946, it launched its first B-36. That experimental model had two enormous main landing wheels, more than nine feet in diameter. But these concentrated too much weight on too small an area of runway. So, when the first production model of the B-36 rolled out, a year later, it had


eight landing wheels, about half the size of the originals. It also had a bubble on its nose, so the pilot could get a better view.

These changes were the first of many. Between August, 1947, and August, 1954, it ran through 10 model changes. The horsepower of its propeller engines rose from 3,000 to 3,800 apiece. Beginning with the D model, which first flew in late March, 1949, four jet engines were added, a pair under each wingtip.

Meanwhile, the world's biggest bomber strained toward greater heights and higher speeds, until in midsummer, 1949, the Air Force revealed that a B-36D had topped 435 m.p.h. and climbed above 50,000 feet.

The Air Force had no sooner released these performance figures than the Navy shouted that they weren't good enough. Their own Cutlass, Banshee, and Panther jet fighters could all climb to the B-36's ceiling in a few minutes and knock it out of the sky.

A few Congressmen were all for giving the Navy a chance to put up or shut up.



A BODYGUARD for B-36 was needed, it was thought, as fast jets developed. So this modified RB-36 was fitted out to take aboard or launch a light fighter plane. But the experiment got nowhere. One trouble: The little plane, even in retracted position, slowed momma down too much.

and it landed on the scrap heap

But that wasn't in the interest of national security, rumbled the Defense Dept.

Even U. S. airmen themselves disagreed about the B-36. Gen. George Kenney, first commander of SAC, said it would be dandy for night bombing, but he wouldn't use it in the daytime. Gen. Curtis LeMay, who succeeded him, said the plane was great day or night. Gen. Hoyt Vandenberg said B-36s could fly far enough, fast enough, and high enough to drop A-bombs on any target in Russia. That fact, he said, was the best insurance against war.

Question from Britain. While the fight raged on in Washington, some British aeronautical engineers couldn't help raising their voices, too. Britain's Vampire jet interceptors, one expert declared, could climb to the B-36's best level in eight minutes, and fight right on up to 56,000 feet. And, he added, the Russians probably had something just as good.

"We fancy that our American friends are prone to underestimate the height of the Iron Curtain," wrote the editor of Britain's *Flight and Aircraft Engineer*.

But the B-36 calmly rode out the controversy and remained, for a time, the mainstay of SAC. The Navy got its super-carriers anyway, and the storm blew out to sea.

The B-36 finally retired to make way for waves of much faster B-47s and B-52s.

Altogether, there were 385 B-36s built, at a cost of around \$3,000,000 each. Most of them have now been cut up for scrap. The last to come off the production line, in mid-August, 1954, is now a public monument at Amon Carter Field, Fort Worth.

Like almost all super-big objects, the B-36 was often a figure of fun. For one thing, despite all the brave words about its mounting speed, the B-36 *sounded* slow. The acoustical mix of its piston and jet engines resembled nothing so much as the noise of a distant race among sedate motorboats.

Before each landing, some rear-crew member had to come forward through the tunnel, crawl out into the wing, and gaze through the wheel wells to make sure the main gear was down and locked. Another peered out through a hatch in the floor of the forward radio compart-



PILOT PERCHED in a position 30 feet above and 80 feet ahead of his landing wheels. Here he indicates the jet controls—usually handled by the copilot, whose seat is at right.

ment to be certain the nosewheel was ready for touchdown.


There was something ludicrous, too, about the fact that the pilot sat 30 feet higher than the landing wheels and about 80 feet ahead of them. And he never moved the bomber's controls directly: All he did was manipulate spring-loaded tabs, which caught in the slipstream and tugged the huge control surfaces in the direction the pilot wanted them to go.

B-36 pilots had to take lightplanes aloft between missions in order to keep fresh the vital "dimension awareness" of flying. For, as one of them said, piloting a B-36 was "like sitting in a bay window and flying an apartment house."

Still, no matter how much one joked about the B-36, it had two qualities every crewman was grateful for. It was immensely stable and rugged.

A B-36 once lost three engines on the same side and still made a perfect landing. Another dropped its rudder on a low-level flight, but kept right on going for 250 miles before it set down—safely.

Because the B-36 carried the A-bomb, it was called the Big Stick. But because it merely held the Bomb and didn't drop it, the mammoth ended its career with the proud name—Peacemaker. ■ ■



ALL FOUR FRONT WHEELS turn at once. Tiny 4.50-by-12 tires cost less than half as much as


standard tires. Large lights, Klaxon horns, straight windshield pack plenty of nostalgia.

Eight-wheeled car

If railroad coaches have eight wheels, thought Enoch Johnson, Red Wing, Minn., machinist, why shouldn't automobiles? So he built this one.

Every component, except for a few he made himself, stems from Dodges up to 46 years old. Trimmed with mahogany and painted a dazzling yellow, the 2,200-pound machine makes an arresting sight. "It rides great," says Johnson. "The eight wheels glide over bumps and dips like a snake crawling over the ground."

PROPANE-GAS TANK by Johnson's side is used in place of choke when starting the car. Huge exhaust collectors (over running boards) lead from a 250-hp. Dodge V-8. Rear-mounted radiator has two electric fans; water circulates through the car's frame, made of 2½-inch pipe.



Respiration dummy

A new manikin teaches British first-aid students the art of mouth-to-mouth artificial respiration. It consists of a head, windpipe, and transparent lungs so a learner sees the effect of his breathing.

The head must be held back at the correct angle to keep from blocking the air passage, and the nose pinched and released rhythmically like a valve. A plastic face mask may be sterilized. The model folds up compactly to carry or store.



Royal southpaw: Queen Mother Elizabeth. Charlemagne, da Vinci were lefties, too.

It's a Clumsy World for Lefty

... But getting better. Now he can get left-handed rifles, saxophones, penknives—even checkbooks

ABOUT 10 percent of all newspaper readers who saw a recent photo of Britain's Queen Mother Elizabeth shooting pool got a special kick out of it.

Why? Because, with the confident stance of an old pro, the royal lady was wielding the cue with her *left* hand. She has the same problem they have.

She and 300,000,000 other people live a more or less frustrated existence in a right-handed world. They deal as best they can with doorknobs, zippers, buttons, gearshifts, tools, scissors, musical instruments, telephone dials, corkscrews, can openers, and a whole catalogue of other objects not designed for their convenience.

But Lefty leads a far happier life than he used to. There was a time when parents shouted: "You'll learn to use your right hand or else!" As a result, a few high-strung kids were left stuttering in protest, and clumsy with both hands.

Today, warned by psychologists, par-

ents are inclined to let a left-handed youngster be himself. The theory now is: If you're a lefty, be a good one.

Nobody cared. There was only a feeble effort to take pity on the left-hander a century ago. It produced a spate of left-handed shaving mugs with a side mirror to the right of the handle. There was a somewhat larger production of left-handed mustache cups.

Nowadays, manufacturers cater to the 18,000,000 left-handed Americans by making scissors, shears, baseball gloves, sickles, refrigerators, pocketknives, golf clubs, dental equipment, fishing reels, bowling balls, one-armed writing chairs, rifles, and saxophones for them alone.

As long ago as 1945, the Trade Bank & Trust Co., New York City, started providing left-handed checkbooks—stubs printed at the right of the check. Since any well-trained checkbook user fills out the stub first, a left handed client thus will avoid the risk of smudging the ink



WITHOUT STOPPING, a lefty can rapid-fire the new Savage, working bolt with his best hand.

Now the Bolt's on the Left—Where Southpaws Want It

DESPITE the fact that millions of hunters are left-handed, not until two years ago was there a rifle or shotgun designed especially for them.

Early gunsmiths coped half-heartedly with the problem by providing duplicate cheek pieces on both sides of their stocks—the rest was up to the user. Since then, lefties have put up with rifles they had to turn upside down to load, shotguns with precisely built-in castoff slant precisely on the wrong side, and ejection mechanisms designed to spew a stream of used shells right across their startled eyeballs.

When World War I introduced the bolt-action rifle on a really big scale, southpaw shooters had had it. Slide- and lever-action guns were barely manageable; bolts were impossible. The Army had one answer: force all recruits to shoot right-handed—usually with less than spectacular success. Sportsmen either paid for expensive alterations on their shooting pieces or simply didn't buy bolt actions at all.

But recently, one noted firearm maker—Savage Arms—took pity on the suffering southpaws. First came a left-handed version of its famous Model 110 bolt-action rifle.

with his knuckles when he starts writing the check.

Taking pen in hand. The big trouble with writing left-handed is that the penman drags his hand over what he has just written. It's also harder work, for he pushes the pen, whereas the right-hander pulls his along. Furthermore, the lefty can't see what he has written last, for his scribbling hand is in the way—unless he has been taught to grasp the pen higher up than the right-hander does.

An important aid to the left-hander is to arrange the paper with the top left corner uppermost—just the opposite of what suits right-handers. This gives relief from the cramped writing position so often the mark of the lefty.

One way to lead the lefty's customarily cramped writing hand to greater legibility is to guide it in scribbling from left to right (which doesn't come naturally to it), and in making big, flowing, clockwise loops across the page.

It's possible to turn the ostensible handicap of left-handedness into a very tidy asset. Edward R. Murrow, for instance, has been called "the best left-handed putter in Christendom." And no baseball fan is likely to forget the shining

examples of Babe Ruth, Lefty Grove, Stan Musial, Johnny Podres, and Warren Spahn.

And while we're still on the diamond, consider the pitcher-spooking versatility of Mickey Mantle. In a game against the Detroit Tigers last May, he hit a left-handed homer in the eighth inning and a right-handed homer in the tenth.

Is it inherited? Scientists haven't yet decided whether left-handedness is the result of heredity or environment. Most think it comes from a blend of the two.

There is evidence that when both parents are left-handed, half their children will be. If only one parent is a lefty, one child in six is likely to be in the same boat. If neither parent is left-handed, there is still a one out of 16 chance of it showing up in a child.

However, a baffling fact weakens the heredity theory: 20 percent of all identical twins are opposite-handed, one preferring the right, the other the left. Since identical twins result from the split of a single embryo, they have identical genes. Therefore, a difference in handedness between them cannot be hereditary.

Another mystery is why twice as many boys as girls are left-handed.



SHELLS EJECT TO THE LEFT of this special 12-gauge Savage shotgun, out of shooter's line of vision. On standard models, shells flit uncomfortably across a southpaw's eyes.



ONLY HOPE FOR SOUTHPAWS before new left-handed guns was custom conversion. Here you see a left-bolted .30-40-cal. Steyr. Such alterations often cost \$200 for machining alone.

made in several calibers for about \$125. For the first time now a lefty could rapid fire a bolt action without stopping after each shot to switch hands and throw the bolt with his right. Sales zoomed.

Savage soon added a 12-gauge shotgun in which the shells were ejected to the left instead of to the right across the user's line of vision. Known as the Model 30L and ACL,

it sells in standard and deluxe versions for about \$85 to \$90. Except for their left-handed orientation, shotgun and rifle have the same working parts as their right-handed cousins.

While telephones and doorknobs are still for righties, southpaws are at last getting a break where accuracy and safety are an absolute must —Ken Warner.

Doctors have long known that people often prefer the use of one eye, or foot, or even one side of the jaw to the other. The command comes from the side of the brain opposite to that of the body member. For instance, the right side of the brain controls the left hand. Also, the center of speech and expression is on the same side of the brain as the center of motion, and close to it. This has led to the theory that when a child is forced to change handedness, the resulting confusion spreads to his speech center and garbles his tongue.

There is no proof, however, that forcing a nervous youngster to change hands is more likely to make him stutter than obliging him to give up teasing the cat. The point, say psychologists, is that no emotionally unstable individual should be forced to do anything. Encouraged, yes, but not shamed or whipped into it.

Can you prevent it? One confusing fact is that young babies use either hand equally well. They simply reach with the hand that's closest. The best way to encourage them in the direction of a more agreeable later life is to put everything they're expected to touch within easier reach of the right hand.

Between the ages of six months and a year, a child's natural preference begins to assert itself. Most children decide the matter once and for all between the ages of three and seven.

If someone's kid is sprouting fast and still hasn't made up his mind which hand he prefers, it's advisable to take him to a clinical psychologist. Tests will help determine the degree of left-handedness.

If the youngster's preference is simply not very strong, it should be easy to encourage him to switch hands. If nature really intended him to be a lefty—well, let him learn to be a ballplayer.

There are shreds of comfort. Researchers at the University of Wisconsin have found that left-handed students are notably quicker with the left than right-handers with the right. Other researchers report that the majority of cats are left-pawed, and that parrots are predominantly left-clawed. In between are rats, rhesus monkeys, and chimpanzees, which seem to be able to do equally well with either front foot or paw.

The sinister left. There's no telling when things to the left first got a bad name, but it was in the dim reaches of

[Continued on page 223]



RADIO RECEIVER in can (circle) mounted near top of pole picks up signal and starts timing device that controls system. Warning light and bell are between the traffic light and pole.



Double-decked fishing boats

Most of them loaded in tiers above deck, 99 fishing boats were put aboard the freighter *Talkeetna* at Seattle bound for Alaska. The 32-foot gill-netters are valued at \$10,000 each and can hold 4,000 fish. The largest fleet sent to the 50th state at one time, the boats were part of a shipment of 223 by the Alaska Steamship Co.



\$10,000 horse blanket

Some lucky horse will soon be wearing the pure-vicuna blanket shown on display above. H. Kauffman & Sons, New York City saddlery firm, made the eight-by-eight-foot covering for presentation to "the horse of the year," to be selected by leading horse-breeding and riding groups in November. Its value: \$10,000.



TOUCHING BUTTON on transmitter turns traffic light red four ways, lights warning signal, and rings bell at intersection for 30 seconds.

INSIDE CONTROL CAN: Chrysler adjusts receiver, which gets signal through antenna at bottom and triggers pneumatic timing relay at top.



Fire trucks control traffic lights

Fire trucks, police cars, and other emergency vehicles can turn traffic lights red in all directions as they approach dangerous intersections in Lorain, Ohio. The driver simply presses a button on a radio transmitter mounted on the windshield. Its signal, with a range of 100 feet, is picked up by a receiver mounted on a power-line pole at the nearest intersection. This triggers a timing device that turns the traffic light red in four di-

rections for 30 seconds, puts on a warning light, and rings a bell. The driver of a following emergency car can gain 30 seconds more to pass by pressing his transmitter button.

The system was designed by Lorain Fire Chief Alfred G. Nickley and Thomas Chrysler, superintendent of police- and fire-alarm telegraph. Chrysler built it mostly from parts of confiscated pinball machines, illegal in Lorain.

Aircraft flies on flexible wings

The kitelike machine at right may look like something out of a museum, but it's no antique. Ryan Aeronautical Co. built it for testing in flight for the National Aeronautics and Space Administration and the Army.

Its V-shaped wing of flexible nylon is attached to poles at center and edges. Slung under it is a platform with pilot in front, pusher-prop engine at rear, cargo space between. Tilting the 555-square-foot wing steers the plane. The wing folds compactly for storage.

The Army is interested in the plane,



both as a glider and with engine, for cargo and troop carrying; NASA sees it as a parachute to recover for re-use the costly Saturn-rocket first-stage engine.

The Mystery of the Forgotten Briefcase



By Walter S. Bowen and Harry Edward Neal

IN 1914 a war flared in Europe, a struggle that was to embroil many nations in what history now calls the First World War. The United States, not yet involved, sought to mind its own business, and President Woodrow Wilson issued a proclamation of neutrality.

As a neutral, America had every right to sell goods—including munitions and other war materiel—to any and all purchasers on a cash-and-carry basis.

Since Great Britain and France controlled the seas, and Germany herself could not obtain war goods in the United States and get them past the fleets of her enemies, the Germans sought desperately to prevent her opponents from replenishing their stockpiles from America. There were two ways—sabotage and propaganda in the United States.

Both methods were being used soon after President Wilson's proclamation was made. Stories in certain magazines and newspapers sought to gain American sympathy for the German cause. Strikes were called in factories producing the goods of war.

Wilson ordered Secretary of the Treasury William Gibbs McAdoo to send Secret Service agents into action against the plotters.

William J. Flynn, then Chief of the Service, promptly established a counter-espionage unit in New York, headed by Agent Frank Burke and staffed by 10 picked investigators. Burke was short and stocky, with light brown hair parted in the middle; spectacles rimmed Irish eyes that could twinkle or drill. He was shrewd, bold, and dedicated to his job.

One prominent German put under surveillance in New York City was George Sylvester Viereck, editor of a periodical called *The Fatherland*. Although no direct suspicions centered on Viereck, he was shadowed in the belief that persons active in espionage and propaganda might visit him.

Adventures of the U.S. Secret Service: 2

Other agents were assigned to shadow certain German Embassy officials.

ON SATURDAY, July 24, 1915, Burke sat writing a report at his desk on the top floor of the Custom House at the Battery. From the windows he could look across the shimmering harbor at the Statue of Liberty. Burke was not, however, destined to enjoy the slight breeze that wafted in from the harbor, for a telephone call sent him out on an assignment that was to make history.

The call came from another Secret Service agent, William H. Houghton, whose job it was to keep Viereck under surveillance. Houghton reported that he had followed Viereck to the building at 45 Broadway, owned and occupied by the Hamburg-American Steamship Line, and suggested that Burke join him there in case Viereck emerged with other persons.

Burke joined Houghton immediately, and the pair kept watch on the entrance. Since it was Saturday afternoon, lower Broadway was virtually deserted and the sun-roasted streets were quiet. At three o'clock Viereck came out with another man, who carried a bulging brown-leather briefcase.

Viereck's companion was about 50 years old, tall and slender, with close-cropped graying hair. His cheeks were branded with old dueling scars, and he walked stiffly and ramrod straight in the haughty manner of the Prussian aristocracy.

It would make a better story to say that this stranger had earlier been identified as an important cog in the German propaganda machine and that the Secret Service had been on his trail for weeks. The truth is that neither Burke nor Houghton had ever seen him before, did not know who he was, and had no knowledge of his importance. Only afterwards did they discover that he was Dr. Heinrich Friedrich Albert, Privy Councilor of the German Government, who had entered the United States officially as a commercial attache of the German Embassy.

DR. ALBERT and Viereck walked to the Rector Street elevated station and boarded a northbound Sixth Avenue train. Burke and Houghton boarded the same train. The Germans sat together, and Burke sat down behind them. Albert held his brown bag in his lap. Burke tried to listen to their conversation above the rumble of the train, but they spoke in German.

When the train halted at the 23rd Street station, Viereck said goodbye to Dr. Albert and left the car, followed by Agent Houghton. Burke remained to keep an eye on Albert.

Just before the train gates closed at the 23rd Street station a young lady stepped aboard and sat down in the seat vacated by Viereck, next to Dr. Albert, who was closest to the window.



At three o'clock, Viereck came out with another man who carried a bulging briefcase.

BOOK DIGEST : U. S. Secret Service

Apparently Albert was en route to his living quarters at the German Club at 59th Street and Central Park. To get there it was necessary for him to leave the train at 50th Street and take a shuttle train that ran between 50th and 59th Streets. As they rode, Burke noticed that Albert removed the briefcase from his lap and placed it on the seat by the window. The German then took a paper from his coat pocket and began to read.

As the train pulled into the 50th Street station Albert was still reading, and he seemed oblivious to the fact that the train had stopped. Just as it was about ready to move, he glanced out the window, saw the station sign, and realized that this was where he wanted to get off.

He sprang out of the seat and shouted at the train guard, "Wait! Wait! I get off here! I get off!"

As he dashed toward the door, the girl who had sat beside him called out, "Hey, wait! You forgot your briefcase."

Evidently Albert did not hear her, for he ran out of the door and was on the station platform before he suddenly halted and turned, an expression of anxiety on his face. In that instant Burke made a fateful decision. He reached over the back of the seat and seized the briefcase.

"That's mine!" he said to the startled girl. With the case, Burke, noting that Albert was trying to re-enter the car through the rear door, headed for the door at the front end of the car. Albert was having some difficulty, his path barred by a very fat woman who stood in the doorway asking a question of the train guard. When finally the German pushed past her and rushed to his former seat, the girl pointed at the seat in back and said, "The man who was sitting there took the briefcase. He went out the other door."



Burke stuck a cigar in his mouth and pretended to light it.

OTHER passengers had alighted from the train, and Burke made himself as inconspicuous as possible by mingling with them. He saw Albert "come tearing out in a hurry, greatly disturbed." The doctor was between Burke and the exit stairway, and Burke knew it would be folly to make a break for the street at that moment. Instead, he walked calmly to the station wall, stuck a cigar in his mouth and pretended to light it, blow-

ing out one match after another as though the wind were the culprit. With his body he held the precious briefcase tight against the wall, partly covered by his jacket. The train rumbled out of the station.

Albert glanced hurriedly at all the people on the platform, then whirled and rushed down the stairs to the street. There was no other train in sight and Burke figured that it would be disastrous to wait on the platform any longer, so he walked rapidly to the stairway and descended to the sidewalk below.

On the street Burke saw Dr. Albert "with panic on his face," looking at pedestrians in all directions. Suddenly the German saw Burke and the briefcase. He let out a wild yell and dashed in Burke's direction.

Again Burke made a split-second decision. A Sixth Avenue trolley car was approaching, headed uptown. It was one of the open cars then popular, a car with running boards on each side and open seats extending the entire width of the vehicle. Burke jumped on the running board of the moving car, near the conductor. Albert was racing to catch up, shaking a clenched fist and screaming at the top of his lungs.

"See that man?" Burke said to the conductor. "He's crazy—stark, raving mad! He's just stirred up a lot of trouble on the elevated station. If he gets aboard this car you're going to have more headaches than you can handle."

The conductor took one good look at the wild-eyed, fist-shaking, shouting Dr. Albert and decided that Burke was telling the truth. He called loudly to the motorman, "Hey, Joe, step on it! Don't stop, Joe—don't stop!"

The motorman looked back, saw the frantic Albert, and speeded up the car, which soon outdistanced the doctor and turned west on 53rd Street.


At Eighth Avenue and 53rd Street Burke hopped off and boarded a downtown trolley. A few blocks down he alighted and went to a nearby drug-store, where he telephoned Chief Flynn, then in New York.

Flynn drove to the store in his car, picked up Burke and the briefcase, and went to the Secret Service office in the Custom House. Together they opened the bag. Virtually all the documents it contained were in German, which they could not read. Flynn promptly telephoned Secretary McAdoo, then on vacation at North Haven, Me. McAdoo requested that the case and its contents be brought to him immediately.

Meanwhile, agents reported consternation in the German Embassy in Washington and at 45 Broadway in New York. The Germans suspected that a British spy had seized the briefcase. But apparently they had a weak hope that it had been stolen by an ordinary sneak thief, because on the following Monday a pathetic little advertisement appeared in the *New York Evening Telegraph*. "Lost: On Saturday, on 3:30 Harlem Elevated train, at 50th Street station, brown leather bag, containing documents. Deliver to G. W. Hoffman, 5 East 47th Street, against \$20 reward."

When Flynn and Burke delivered the briefcase to Secretary McAdoo, a translation of the German documents provided incredible revelations of the vast and bold operations of the German propaganda and sabotage machine.

There was indisputable evidence that Albert was the top financial agent of the Imperial German Empire in the United States; a total of \$27 million had been deposited in American banks for his use. The doctor, it appeared,




He jumped on the running board of the moving car . . . Albert was racing to catch up.

[Continued on page 224]

Mechanics and Handicraft SECTION

AN EXPERT WEAVER, Mrs. Sadie Robbins, tacks first strand of cane to underside of seat frame to begin warp—the parallel strands of cane into which other strands are woven. One bunch of water-softened cane is stretched out on floor, while another soaks in tub. Cleat nailed to chair keeps frame from sliding while warping and weaving




1. TO START THE SEAT, the cane is wrapped around the frame from front to back. Frame is turned end over end (arrows) in photo above, as cane is wrapped around it and pulled taut. Every fifth turn is wrapped around the front

3. FIRST STEP IN WEAVING is the starting of seven strands of cane through the top warp. First strand (arrow) is tucked under nine warp strands, second under eight, and so on



4. USING FOUR-OVER, FOUR-UNDER PATTERN, weave strands to left. Ends of No. 1, 2, and 3 are staggered along rear edge of warp as below. Ends of strands 4 to 7 lie together under warp.



Weaving Cane for the Kennedy Rocker

...or any favorite antique chair

By Herbert R. Pfister


PHOTOGRAPH BY MICHAEL WOODRIDGE

WEAIVING cane by hand is an art that has nearly vanished. Only a few skilled weavers now practice their trade in factories similar to the P & P Chair Co. that makes the Ken-

nedy rocker. Some antique restorers also know how, but they get high prices.



So, whether you're building a JFK rocker as described last month, or just want to recane an old chair, knowledge of this almost-forgotten handicraft can be worth real money.

Mrs. Sadie Robbins is one of the ex-
CONTINUED




rail to space out the warp along the wider front edge of the frame. These extra turns would not be needed on a square seat, since warp would be uniform along front and rear.



5. STARTING STRANDS ARE PUSHED TOGETHER so that they lie snugly side by side to begin herringbone pattern. Strands 1 to 7 now dangle from left of frame, and frame is turned over.



2. CANE IS TIED TOGETHER to make a single continuous strand around frame. Some knots will be hidden under crossweave. Those that aren't will be untied later and ends tucked in.


6. WITH FRAME TURNED BOTTOM UP, six new strands—No. 8 to 13—are started into right side of bottom warp, pushed together and pulled to left. Strands now hang from both sides.





7. STRANDS NO. 1 TO 7 at right side are woven into bottom warp after starting strands 8 to 13. This is a simple "over 'n under" pattern found on seats of many antique chairs. In pho-

to above at right, the last strand (No. 7) of the group is being pulled through to the left side. At this point, there will be thirteen strands, numbered in starting orders, at the left side.




10. AT END OF WEAVING STRAND, a new strand (B in insert drawing) is tucked under the end (A) of the strand that has run out, to continue the weave. The old strand end (A) is then trimmed and tucked under the next four warp strands as at (C) to conceal the splice.




11. AS WEAVING NEARS COMPLETION, warp tightens, and a table knife must be used to separate strands. Arrow points to warp knot that has been untied. Ends will be tucked into pattern.






8. FLIPPING FRAME TOP UP swings thirteen dangling strands to right side. Strands shown in preceding drawing have been renumbered 1 to 13; weaving will now be done in that order.



9. STARTING WITH NO. 1, dangling strands are woven in from right and pulled through to left. Above, No. 13 is being pulled through, and herringbone pattern is fully developed.




12. AT FINISH OF BOTTOM WEAVE, strands 1 to 6 are pulled through to dangle at left. No. 7 to 10 are cut and ends tucked in at left edge; 11 to 13 are staggered across front edge.



13. THE END: Strands 1 to 6 are woven into front edge of seat top. Ends are cut and staggered along front edge, just as they were staggered along the rear edge at the start.


How to weave the backrest

1. WARP IS WRAPPED AROUND FRAME as it was in the seat, except that pattern is different. Two strands of cane are tacked to bottom stretcher (arrow in photo at left) and wrapped first around entire frame, then around dowels at each side. Completed warp is shown in drawing below. Pairs of warp strands are separated by pairs of strands wrapped around dowels. The strand ends hang free at top.





One
Place
You Can
Buy
Cane . . .

. . . is from Su-Ann, Inc., Box 545, Asheboro, North Carolina. The price is \$2 a bunch, and two bunches are needed to cover the seat and backrest of a JFK rocker.



2. WITH BACKREST ACROSS LAP, and front facing up, six strands of cane are woven in from the right and pulled to the left to stagger their ends as shown in the drawing above at right. Then

the two free ends of the warp are wrapped around the top stretcher and woven in beside the starting strands. Eight strands now hang from the bottom of the frame.



3. FRAME IS TURNED AGAIN, and twelve strands from rear are brought around top stretcher and woven into front. Note: Numbers are changed, and weaving continues in order shown.

4. SAME TWELVE STRANDS are woven into front and rear progressively, until frame is covered. As with seat, new lengths are tucked under ends that run out, to continue strands.

My Most Embarrassing Shop Moment

I HAD just gotten out of high school and was working at my first job in a machine shop. My supervisor was teetering on the brink of insanity trying to teach me the simplest rudiments of shop work.


One day he handed me a 150' coil of red rubber air hose and explained he wanted it cut into foot lengths on a saw. To save the time of measuring each piece, he showed me how to saw off one length, then use this as a guide for cutting the others. That was where he made his mistake.

Feeling proud over the new trick I had learned, I raced through the job in only a few minutes. As I neared the end, however, it began to dawn on me that a piece of hose as wide as my fist couldn't be 12" long. I checked the others—I was standing knee-deep in a pile of hose pieces only one of

which was the required 12" in length.

My supervisor wandered over and suddenly turned the color of the red hose. Where, he thundered, was the original piece I was supposed to measure with? I explained that I had used that only for the first cut. I then had used the newly cut second piece to measure the third, the third to measure the fourth, and so on—just as he had said, I hadn't realized that the curvature of the hose had made the inside piece slightly shorter than the outside guide piece laid beside it. Each length thus came out shorter than the preceding one.

I got another chance, though. My supervisor handed me a second coil of hose and a ruler and growled: "This time, measure each piece if it takes you all day."—Steve Haas, Charlotte, N.C.



3. FRAME IS TURNED OVER from left to right, so rear is up and bottom is at right hand. Four new strands are started and staggered along edge, and eight strands from front are woven in.



4. PAIRS OF SHORT, LOOSE STRANDS are tucked into weave and laid across the rear and front face of both stretchers to fill in the blank areas not covered by the warp wrapping.



7. STRANDS ARE CUT AND STAGGERED along edge of frame to end weave. Strands 1 to 6 are ended along edge at rear; No. 7 to 12 are brought around and ended along edge at front.



perts employed by P & P for this job. She's been weaving cane since she was six. Her mother taught her. In the accompanying photos, Mrs. Robbins shows how you can weave cane into the *three different patterns* used in the JFK rocker. Drawings explain in detail how the patterns are formed. You'll very likely find that one of these patterns is precisely the same as the original caning on many old chairs, or so similar that the difference will hardly be noticed.

Cane has a surface like bamboo, but it lacks the joints that make bamboo so easy to recognize. It grows wild in China as a tubular reed, often as tall as 20 feet. The reed is slit lengthwise into strips about $\frac{1}{4}$ " wide and tied into bunches. Each bunch contains enough for an average chair seat. Soaking the cane in water makes it pliable and easy to pull taut.

Starting the pattern is the most difficult part of weaving cane. Once you get the strands started properly, you simply repeat the weaving pattern over and over until the job is done.

Simple tools are used: a tack hammer, a sharp knife for cutting the cane, and a dull one to open the warp and push the woven strands together.



Even with one eye on these pages as you work, you should be able to cover a seat in less than an hour. If the frame is an integral part of the chair, it might take a bit longer—you'll have to turn the chair over repeatedly as you advance the weave across the top and bottom of the seat.

Short Cuts and Tips

FROM THE READERS

Jig for Cutting Fingerlap Box Joints

MULTIPLE slip joints (so common in wooden boxes) are seldom attempted by the amateur cabinetmaker. Yet they can be cut easily and accurately on a bench saw with this homemade jig. The piece to be cut is set on end and held flat against the hardwood fence that's screwed to the face of the miter gauge. Move the piece against the left side of the projecting tongue and make the first pass. Fit the resulting saw kerf over the tongue and make the second pass, repeating this for the width of the joint. The saw blade or assembly must, of course, make a kerf as wide as the brass tongue. In my jig, the tongue is $\frac{1}{4}$ "-by- $\frac{1}{4}$ ".—A. E. Harrold, Willoughby, Ohio.



Rim Peg for Garbage-Can Lid

Do you wish for a third hand when it comes to juggling a sack of garbage and the can lid? Bolt a large spool to the underside of the lid, at the center, and you'll be able to hook it over the rim.—G. E. Hendrickson, Argyle, Wis.



Note Tabs on a Yardstick

I'm THE type that has to take a measurement five times unless I jot it down. So I stick paper adhesive tabs on my yardstick. They can be erased or covered with fresh tabs when I'm through with them.—Ken Patterson, Moose Jaw, Sask.




The cat blew another note on his trumpet; the TV screen went blank. He intoned, "Night has just fallen."

On the Trail of No Raster

By Art Margolis

NOTHING seems to trigger more anxiety about the repair bill than a picture tube that remains dark. You turn on the TV, the sound comes in loud and clear, but there is no sign of

light on the screen even when you turn the brightness control all the way up. Unless you know something about TV circuits, your most logical deduction is that the picture tube must be dead. Fortunately for your pocketbook when there's no raster—pattern on the screen—



AN ORDINARY NEON TEST LAMP will indicate the presence of high voltage in your TV. No connection is necessary. Just hold the bulb near the cap of the horizontal-output tube.



ION TRAP is a small permanent magnet clipped around the neck of the picture tube. Improper positioning can cut off brightness. It should be adjusted for maximum brightness.



HIGH-VOLTAGE FUSE may be found either in the high-voltage cage, on the chassis, or under the chassis. If you are getting sound but no brightness, this fuse may be blown.



TROUBLES THAT COME AND GO are often due to tubes with loose elements, intermittent shorts, or intermittent opens. Gently tapping the tubes will usually pinpoint the offender.

the picture tube itself is rarely the trouble.

TV Repair Blues

"SALUTATIONS, man, it's like Big Brother has nodded out—like dead, man."

The bearded young man grabbed my tube caddy in one hand and waved me in the door with a trumpet he held in the other. Sound blared from a battered TV perched on orange crates in one corner. The screen was dark. I turned up the brightness control. Still no raster.

He said, "Told you, Dad. Luminescence quiescent."

I started checking. High voltage and CRT were okay. I rotated the ion trap—not a glimmer. Suddenly there was a loud blast behind me. I spun around. The cat took the trumpet from his lips and announced, "Then there was light."

I looked back at the set and saw the raster shining brightly. The cat blew another note; the screen went blank. He intoned, "Night has just fallen."

I had to laugh, but now I had a pretty good idea of what was wrong. I started tapping tubes with my tube tapper. When I hit the video-output tube, the raster came on.

He blew a note; the raster went off.

I hit the tube and it came back on.

He blew another note and off it went.

The video-output tube feeds the TV signal into the picture tube. With no signal, the bias voltage in some sets will be far enough off to cut off the electron stream in the cathode-ray tube. This was one of those sets.


The 6AC7 video-output tube had developed an intermittent short. Any vibration would make or break the short. I replaced the 6AC7. I tapped. The raster stayed on. He blew a couple of notes. It still stayed on.

"You blow a powerful trumpet," I said, starting to repack my tube caddy.

He handed me my tube tapper. "You beat crazy yourself, Daddy-oh."

Mystery of Avery's Aviary

"OUR birds are worried, Art. We've already lost a cockatoo." There was a frantic note in John Avery's greeting. His wife, Mildred, nodded her con-



NO RASTER, BUT SOUND OKAY? The troubleshooting road has two branches. A neon-light test will indicate which to follow. Loss of high voltage is most often the cause of no bright-

ness, and about 75 percent of the time the trouble will be among the first six items shown on right-hand branch. Make substitutions in the sequence shown until raster is restored.

cern as she nervously tucked wisps of hair into a small bun on top of her head.

"I'm sorry, John," I said, "but you must have called me by mistake."

"No mistake," he said. "It's the TV that's upsetting the birds."

One wall of this elderly couple's living room was screened. In a lighted recess behind the screen were about 50 beautiful small birds chattering away.

I turned on the TV. Sound blasted out but no light came on the screen. The birds went into a wild frenzy. I turned down the sound, but the birds still kept up the racket.

John pleaded, "They can't stand it; please turn the set off."

I turned it off, and the birds quieted.

Taking out my neon tester, I held it near the 6BQ6 horizontal-output tube and switched the set on. The neon didn't excite but the birds did. There was no high voltage. Suddenly, I was aware of a chirping from the set. I quickly looked inside. Could a bird have crawled under

the chassis? Then I laughed at myself. There were no feathers on the source of that sound—it was purely electronic.

The horizontal oscillator runs at a frequency of 15,750 cycles per second. In addition to providing the horizontal sweep voltages, it also figures in the manufacture of the high voltage. If you lose it, you lose the high voltage. A circuit called the horizontal phase detector is responsible for keeping the horizontal sweep precisely in step with the transmitted signal. In this set the tube used for the job was a 6AL5. It should have two little filament lights. I looked closely. There were two lights all right, but one was dull and the other overly bright. I pulled the tube.

The chirping stopped. High voltage came on and the birds settled down. Of course the picture was flopping sideways without the control tube. The tube had shorted and caused interruptions in the running of the oscillator at such a rate

[Continued on page 226]



The Model Boat That Flips to Go

By Roy L. Clough Jr.

THIS boat model is guaranteed to drive kibitzers crazy as it sits there in the water. It has no propeller, no paddle wheels, no hidden jet pump, not even a rudder. Yet, when you close a switch mounted on the deck, away it goes, kicking up a wake.

There's no mystery about the basic power source—an electric motor and a dry cell. But how is the thrust applied?

After everybody has had a guess, let them in on the secret. It swims like a whale or porpoise. But its horizontal flipper is transparent plastic, invisible in the water. The flipper is quite efficient, too, and drives the boat about as fast as a conventional propeller.

The boat goes together easily. Cut the sides, transom, and spreader bulkhead from $\frac{1}{16}$ " sheet balsa. Cement the sides together at the stern, bend them over the bulkhead, and secure to the transom with pins and rubber bands. Even up the symmetry and cement on 3"-wide planks for bottom and deck. Cut these pieces a trifle oversize and sand them flush after the glue sets.

Cut the four cabin parts from $\frac{1}{8}$ " sheet. After assembly, hinge the front to the decking with cloth tape. Dope the entire job inside and out with at least two coats.

The driving mechanism is tin-can

stock and $\frac{1}{16}$ " music wire. It consists of a flipper clip pivoting in a mount, and (soldered to the clip) a rocker arm, driven by a connecting rod from a crank disk on the motor. Exact dimensions are not critical as long as the mechanism works freely. Keep the slot in the back of the boat as small as is consistent with smooth operation of the flipper. The rocker holder has teeth that are pushed through the boat bottom and clinched.

Make the connecting rod a bit long. Solder the crank disk to the motor shaft, taking care not to overheat the motor. After cementing the motor to the floor, rotate the shaft so the crank throw is in the maximum forward position, and tilt the rocker arm to its limit of forward travel. Bend the connecting rod at the proper spot to hold this position and slide it into the hole in the rocker arm. Cut the rear bulkhead to size from $\frac{1}{16}$ " balsa and make the vertical slot just large enough to let the connecting rod play without binding.

Solder a couple of pigtails to a D cell; one wire goes directly to the motor, the other has a slide or knife switch inserted. Polarity and direction of rotation are unimportant. A rubber band fastened between two hooks bent from music wire keeps the cell in its cradle.

The boat can be made to circle in either direction by twisting the tip of the flipper to produce a side thrust.

GLUE THIN CARDBOARD
AROUND TWO IDENTICAL
TEARDROP SHAPED BLOCKS
TO FORM STACK

CABIN TOP
 $2\frac{1}{2} \times 6\frac{5}{16}$

$1\frac{3}{8} \times 2\frac{1}{2}$

USE $\frac{1}{8}$ " DIA. DRILL
FOR PORTHOLES

TRANSOM
 $1\frac{1}{4} \times 2\frac{1}{4}$

SPREADER
 $1\frac{3}{8} \times 2\frac{5}{8}$

DECKING
 $\frac{1}{16}$ " SHEET

SPREADER
5"

$\frac{1}{8}$ " STEM PIECE -
CEMENT ON AND TRIM
AFTER ASSEMBLY

SIDE

12"

FLIPPER - 009
CLEAR SHEET
ACETATE

ROCKER
ARM

FLAPPER CLIP
 $\frac{3}{16} \times 1\frac{1}{8}$ BEND AND
PINCH OVER AXLE

FLAPPER
MOUNT

CABIN SIDE - $\frac{1}{8}$ " SQUARES

MOUNT FOR OR
EQUIVALENT -
EITHER IN
ROTATION
OR IN PLACE

CRANK DISK
 $\frac{1}{2}$ " DIA.

$\frac{1}{8}$ " THROW

$\frac{1}{4} \times \frac{1}{2}$ BLOCKS

LWL



FOR SAFETY, use weed stalks—not your hands—to push material into the revolving blades.



FIRST STEP in conversion is to discard the handle, roller, and pinion gears that drive reel. Wheels will serve as mounting plates.



PIERCE ONE WHEEL with a hole large enough to permit the reel shaft extension to turn freely. A pulley on this shaft is belted to the motor.

Compost Chopper from Old Mower


THERE'S no need to do without a compost chopper because the cost is beyond your gardening budget. You can make one from a reel-type lawn mower. If you've bought a power rotary recently, you may still have your old back-buster. If not, pick up a used one.

Chopping up grass, leaves, and vegetation from the garden and flowerbeds shortens the time required to turn this waste material into valuable fertilizer.

Since the power is to be hitched directly to the reel shaft, this shaft must be extended through one wheel (and a pillow-block bearing) so a pulley can be attached at the end. The extension is a steel sleeve, fitted to the shaft by drilling through both and inserting a steel pin. A short piece of rod, the same diameter as the reel shaft, is pinned in the opposite end. Fasten the mower upside down within the frame, bolting the wheels to the legs.

The bottom opening of the wooden hopper should be a little less than the diameter of the reel. Mount the motor on a platform bolted to the frame, aligning the drive pulley with the shaft pulley.

—D. C. Marshall, Manhattan, Kans.



CHOPPER FRAME is made of two-by-fours assembled with screws and bolts. Cross-brace is used at one end only, to support pillow block.

Short Cuts and Tips

FROM PS READERS




Raincoat for a Radio


WANT to tote a transistor into the wilds? To keep it dry, slip it into a plio-film bag (used for frozen foods), twist the neck, double it back, and snap on a rubber band. The film is pliable enough to permit tuning, but won't muffle the sound.—D. D. Myers, Marion, Ohio.

▶▶▶To DRY a casting line, draw it through a cellulose sponge as you reel it in. First wet the sponge, squeeze it dry, and fold it in half lengthwise. The line will dry in a third of the usual time.—Ken Murray, Colon, Mich.

Anchor Standing Cabinets



MANY reasonably tall cabinets or bookcases tend to wobble when the baseboard prevents them from being backed up flat against the wall. Where they're against a hollow wall, you can anchor them with a toggle bolt through the back panel. Turn on two nuts, as shown.—Harry Sallee, Cleveland, Ohio.



Depth Gauges for Drill Bits

BORE to preset depths by adjusting these homemade bit stops. For spade-type bits, slot a spool and slip it down over the blade. Turn a screw-eye in at right angles to the shank to position the spool. For twist drills, bore through a short piece of dowel.—Jerry Buebe, Peru, Ind.

▶▶▶Do you keep a barrel of rain water standing by at your country place for use in case of fire? Then you've probably had a summer serenade of mosquitoes. A cake of soap dropped into the barrel will keep them from breeding there


Getting Oil into Tight Spots

WHY is it that the thirstiest spots are those that are hardest to reach with the spout of your oil-can? You'll have no trouble getting oil to them if you buy a box of flexible drinking straws at the grocery or five-and-ten. They'll bend to any angle and can be discarded later.—F. C. Gardner, San Angelo, Tex.





HEAT THE PAINT in the kitchen oven with the thermostat set at 150 degrees. Shake the can from time to time as it heats. Or you can heat it in a water-filled skillet (below), checking heat with a candy-making thermometer.



For Better

Here's how to adapt a successful factory painting technique to standard home shop equipment

By John Burroughs

THERE'S nothing tricky about hot-paint spraying. It's just a matter of heating ordinary paint before you use it in an ordinary shop spray gun.

When you spray paint hot, you can build up a heavier, smoother, glossier finish with fewer coats. Hot-spraying virtually eliminates runs, sags, pinholes, thin spots, blushing, or orange-peel. That's why hot-sprayed finishes are now so widely used in industry—for finishing products ranging from Lincoln Continentals to toilet seats.

More paint per pint. Production-line hot-spray guns are expensive. But they are based on a simple idea—heating the paint to lower its viscosity. When the paint is heated, it's not necessary to dilute it with volatile solvent. Hot-sprayed paint, therefore, has a higher solids content.

Try a quick experiment: Heat a can of heavy-bodied enamel in an electric frying pan. As it heats, stir it with an inexpensive candy-making thermometer to check temperature.

Heated to around 125 degrees, the sirupy enamel will thin to approximately the viscosity of No. 20 SAE motor oil, ordinarily proper spraying consistency.

TESTING SAMPLES at different temperatures, as below, is a good idea before you try to hot-spray a brand of paint with which you aren't familiar.



Finishes, Spray 'Em Hot

Further heating, to roughly 150 degrees, thins it even more. Yet the important properties of the paint—its drying time, coverage, gloss, and color retention—aren't adversely affected.

Watch the heat. Don't let ordinary resin-based paints get much hotter than 150 degrees. According to textbooks, it's possible to heat most paints to around 180 without ruining them. But in using improvised heating equipment, 150 allows a margin of safety. Nearly all oil-based, alkyd-based, and synthetic-resin-based paints and varnishes when heated to 150 can be sprayed without added thinner in shop spray guns that pump up perhaps 30 p.s.i. air pressure.

You're not limited to "ordinary" paint, of course. Heating the material, you can also spray cellulose-based industrial lacquers—the same lacquers used in commercial finishing operations. But there'd be little point in heating water-mixed paints. And don't try to hot-spray epoxy-based paints or others that come with a separate catalyst.

The paint can be heated satisfactorily with nearly any electric kitchen utensil that has a built-in heating element. You can even use an open-element hotplate if you set the can of paint in water.

Or you can use your kitchen oven; its accurate temperature control will do a first-rate job. Set the thermostat at 150

degrees and allow adequate time for the paint to heat through. Open the can and mix pigment and vehicle thoroughly before heating it. Replace the lid tightly.

Heating tightly closed cans of paint to 150 in an oven is perfectly safe. Using a hotplate with an exposed electric element in an area in which you're spraying, however, can be dangerous. Even though hot-spraying produces less flammable vapor than does cold-spraying paint diluted with thinner, remember to observe safety precautions.



Keeping the paint hot. On small jobs, this isn't the problem it might seem. A nearly full quart cup of 150-degree paint will hold heat long enough to allow you to spray a good-size object. If you're using an aluminum spray gun, warm it before pouring hot paint into the cup.

To delay cooling of the paint between passes at the work, rest the gun on an electric trivet or in hot water; or wrap the cup with sheet-asbestos insulation.


If you want to keep the paint in the gun hot for extended periods—as you would if you were hot-spraying a car—wrap the paint cup with lead or plastic-covered heat cable, the sort used to protect pipes from freezing. A cable with a thermostat is preferable, but one without a thermostat that heats to about 150 degrees will serve. Bind the cable to the paint cup with fiber-glass tape.

KEEPING THE PAINT HOT while you spray is easily solved by setting the can in container of hot water. Two coats of refrigerator enamel made the washing machine below look like new.

VIBRATOR SPRAYER will handle a heavy-bodied varnish without any thinning if you heat the varnish first. Thus you can avoid runs and sags



One MACHINIST tells another...



PARTS OF THE TURRET are shown here left to right: locator pin, tool shank, turret head, and pivot bolt.

...MiniTurret Head for Your

WITH this miniature lathe turret head you can avoid the bother of frequent tool changes when turning out small, odd-shaped parts. Though simply made, it is accurate enough for use in my regular work as a toolmaker.

Cut the tool shank from $\frac{3}{8}$ "-by- $\frac{3}{4}$ " cold-rolled steel. Using a #19 drill, drill and tap the two holes for 10-32 screws as shown in the drawing. Drill a $\frac{1}{8}$ " hole first for the locator pin; then finish to size with a $\frac{1}{4}$ " drill. Use light feed and cutting oil for a good finish.

Mill or saw the turret head from $\frac{3}{8}$ " flat cold-rolled steel. Square this piece carefully. Mill the tool-holding slots,

keeping them all parallel to the edges.

Carefully mark and prick-punch the pivot-hole location. Drill $\frac{5}{16}$ " and finish-drill $\frac{3}{16}$ ". Counterbore $\frac{1}{4}$ " with a flat-bottomed $\frac{1}{8}$ " drill. Drill and tap the eight setscrew holes.

Cut off a 10-32-by-1" socket-head cap screw to make the pivot bolt. Turn the locator pin from $\frac{3}{8}$ " steel rod. File a flat as shown.

Assemble the tool, align the top edge of the turret head exactly parallel to the top of the shank, and clamp in place by tightening the pivot bolt. Using the $\frac{1}{4}$ " hole in the shank as a drill guide, spot-drill (don't drill through) the turret for



Mandrel Holds Washers

HERE'S an easy way to tool up for holding washers when you want to turn down the outside diameter. With a taper mandrel, a loose bushing of proper length, and a ball-bearing pipe center, work can be held tightly and yet be unloaded quickly. The bushing should be long enough so that the center contacts it rather than the mandrel. The work is held by pressure from the tailstock exerted through the bushing against the washer.—H. J. Gerber, Stillwater, Okla.

MACHINE TURRET and tool shank from flat rolled steel. Dimensions are for $\frac{1}{4}$ " tool bits.



ANY ONE OF FOUR CUTTERS can be quickly brought into use simply by rotating the turret.

Lathe Saves Time

the locator hole. Repeat for the remaining three locator holes. Disassemble and drill through the holes with a ± 10 drill.

Degrease and case-harden turret head, shank, and locator pin. (Leave the pivot bolt unhardened.) After hardening, clean all threads and polish the locator pin.

Reassemble the tool. Screw the detent setscrew into the shank deep enough to engage the flat on the locator pin and act as a withdrawal stop without hindering free sliding action. Any of the tool bits can be brought into position by withdrawing the locator pin, turning the turret head, and sliding the pin to lock position.—*Norm Fried, Los Angeles.*




TOOL BITS are ground to keep cutting edges identical in height when turret is rotated.

Rack Keeps Oil Handy

CUTTING oil is always in reach with the oilcan on this holder. It can be slid along the lathe right behind the tailstock.

A clean paint-can lid, turned upside down, is riveted to a bracket shaped to fit the lathe ways and hooked under the rear of the front one. Aluminum is the best material as it will not scratch the ways. Rivet guides at right angles as shown and cement felt pads where the bracket touches the ways.—*Harry Walton, White Plains, N. Y.*



One MACHINIST tells another... (cont.)




Collet Holds Square Stock in Three-Jaw Chuck

INSTEAD of switching chucks, save time with a simple collet that holds square stock in a three-jaw chuck.

Chuck a scrap of round stock three to five times as long as the size of the square stock across flats. Make a centerpunch mark at the No. 1 jaw. Drill through undersize for the square stock. Remove

and mark for three cuts 120 degrees apart. Hacksaw one through and the other two about halfway, as shown.

Rechuck with the mark at the No. 1 jaw, tighten chuck moderately, and bore to a close fit for the square stock. Insert stock with one flat bridging the through cut and tighten the chuck firmly.



Dowel Pins Increase Vise Capacity

You can enlarge the capacity of any machine vise by this simple alteration; it often saves clamping over-size jobs directly to the machine table. However, I recommend it only for light-duty milling jobs, or easily cut materials such as aluminum or brass.


Drill and ream the vise body and sliding jaw for four hardened-steel dowel pins. Drill air-escape holes into the sides to meet dowel holes. Lap dowel holes slightly after reaming to provide a snug, slip fit on the pins.—H. J. Gerber, Stillwater, Okla.


Easy Way to Turn Small Rods

TURNING down long, thin rods is no longer a problem since I started using this system. Turn a section of the rod about $\frac{1}{2}$ " long to the desired diameter by working close to the chuck and taking light cuts. Reverse the tool holder and chuck a drill of a size for a running fit on the finished diameter of the rod. Run the carriage up and drill through the tool holder (a piece of bar stock can be used instead).

Clamp a tool bit to the holder as shown at right so that the cutting edge is in line with the edge of the hole. Rechuck the workpiece and insert the turned-down part in the hole. Use plenty

of lubricant and start the feed. You'll find that about the only limitation on this system is the ability of the rod to withstand cutting torque without twisting.—W. B. Rasmussen, Prosser, Wash.





Short Cuts and Tips

FROM PS READERS


Safety Lock for Metal Toolbox

As a machinist, I leave hundreds of dollars worth of tools in the shop. Though they're in a regular machinist's toolbox, the cheap lock can easily be forced. To avoid thefts, I made this double-hinged guard of stainless-steel strap. It fits over the protruding lock and under the handle, so it can't be slipped off. A good padlock makes the toolbox jummyproof.—*Joseph Skis-cim, Harvey, Ill.*

Installing a Grinder in Cramped Space


SINCE my workshop is my garage, I have a real space problem. I needed a grinder, but there was no room for another tool stand. So I mounted it on a platform fastened between the wall studs at a convenient work height. I bolted a 1/4-hp. motor to a board secured above the platform—spaced to suit a V belt I had on hand. Mounting slots in the motor base permit adjustment for belt tension. There's still plenty of room for the car.—*Boris Starr, Sun Valley, Calif.*

▶▶▶ A CLOTHES brush is more likely to be used if it's kept within sight and reach. Put a screw-eye at the tip of its handle and hang it from a cup hook at the middle of the closet pole. You can't miss it.—*Ken Murray, Colon, Mich.*




Use Car to Anchor a Fence Stretcher

WHEN stretching wire fence around your yard, you don't have to go to the trouble of setting a heavy post in order to anchor the fence stretcher. Just back your car within a few feet of the wire span and attach the stretcher securely to the frame of the automobile.—*John N. Shockley Jr., Nashville, Tenn.*



Boating Hints

Slow Down: Man Fishing




TAKE along a "Do Not Disturb" sign from a hotel. Hang it on the boat and others will know you're more interested

in fishing than in aquabatics or boat racing. The trick is always effective because it brings a smile




A Cushion for the Fuel Can

THE usual out-board gas can tends to mar the bottom of a boat. One way to prevent it: Slit a piece of garden hose and slip it over the can's bottom edge.



Lock the Oars to the Boat

HERE's a way to lock oars. Hinge the rowing seat and place a hasp at the free end. Mount a narrow board across the boat below the seat, and drill holes for the oarlock pins. Insert pins and oars, padlock the hasp, and your oars will be there when you return to the boat.



Rod Socket for Faster Baiting


FLATTEN the end of a piece of aluminum tubing and screw it, open end up, to the inside of the boat. Set the butt of your rod into it while attaching bait.

A Cushion for the Bow

ONE boater found his bow was being scratched and gouged by sand and gravel as waves rocked the boat while on the beach. He now carries a piece of auto casing and slips it on while beached.

Short Cuts and Tips

FROM READER





Auxiliary Bench Saves Stooping

THIS miniature workbench eliminates the discomfort of crouching over the work surface when you're building tiny models or repairing delicate mechanisms. It raises the work 3" higher if placed on the bench or table top, and 9½" higher if held in a machinist's vise.

The top is a piece of ½" plywood, 14" by 18", with a ¾" rail around three sides. Both cleats on the underside are 2½" high. One cleat is ¾" thick and is fastened 2" in from the left side. The other cleat, 2" thick, is set 4½" in from the right side to minimize overhang when in a vise.

A small vise clamps to the edge as shown.—J. P. Goodenough, Milwaukee.



Oilcan Brush Applies Coolant

HERE'S a neat way to apply coolant on a long drilling or machining job. Crimp some bristles in the tip of an oilcan and brush them over the work or tool bit. The bristles clear away chips and flow on some coolant, but not enough to splash around and make a mess.—Daniel Bousha, Jackson, Mich.








Can Rim Holds Straining Cloth

WHEN straining paint, I've found that the inner coffee-can rim can be used to stretch cheesecloth over the can in half the time it takes to tie the cloth in place with string. Pry off the rim, crimp it slightly, and press it, with the cheesecloth, into the mouth of the can.—Joseph J. Maffei, San Francisco.

Wordless Workshop

By Roy Doty
and Herbert R. Pfister





TRACKING CHART

How You Can Track a Hurricane

REMEMBER the Great New England Hurricane of 1938, Diane in 1955, Donna last year? Their routes are mapped here on a Weather Bureau tracking chart. Using a blank copy of the map, you can track any hurricane that develops during the storm season beginning this month. Plot its location, speed, direction, and wind velocity data obtainable from regular TV and radio bulletins. Send a dime to Supt. of Documents, Gov't Printing Office Washington 25, D. C. for Hurricane Tracking Chart No. C30.22:H94

Great New England
Hurricane of 1938

DIANE 1955

DONNA 1960

GRACIE 1959

HURRICANE WARN

The slower the better for some jobs

Speed Reducer Runs Lathe in Slow Motion


TRICKY lathe operations—such as coil and spring winding, and turning or threading large-diameter parts from cast iron or stainless steel—require very slow spindle speeds. Often, the slowest speed on the machine isn't slow enough.

A simple jackshaft—just two pulleys and a steel rod, mounted on pillow-block bearings—can reduce the speed of the typical small lathe to 12 r.p.m. That's *five seconds* for each revolution.

Mount the jackshaft behind, and in line with, the lathe countershaft. Since this spot is usually occupied by the motor, the addition of the jackshaft involves remounting the motor. Depending on the setup of your lathe, you can move it farther back on the bench, place it on a shelf under the bench, or hang it on a pivoting mount fastened to the underside of the bench top. I cut a hole in the bench top for the V belt and mounted the motor beneath it.

Shim blocks under the pillow-block bearings raise the jackshaft so the original V belt and two-step pulley that were on the motor can be used to link the jackshaft with the lathe countershaft. I installed a 2½"-to-4½" cone pulley plus a 7" pulley on the jackshaft. Since my motor mount permits the motor to slide as well as pivot, I mounted only two pulleys—1½" and 2½"—on the motor. By shifting the motor, these can be aligned with any diameter pulley on the jackshaft. When the 2½" motor pulley is belted to the 2½" cone pulley, the normal range of machine speeds is restored.

The slowest speed available on my lathe before the changeover was 54 r.p.m. Using the 1½" motor pulley with the 7" jackshaft pulley cut this down to 12 r.p.m.—*Manly Banister, Portland, Ore.*



CUTTING COARSE THREADS in large-diameter work (such as 1½" pipe, above) is easier at reduced speed. Here, the 1½" motor pulley is used with a 4½" jackshaft pulley to run a lathe at 30 r.p.m. In rear view (below), setup is for slowest speed—about 12 r.p.m.





Moneysaving jobs you can do with—

The Man's Sewing Tool

By Herbert R. Pfister

UNTIL the stitches in my car's convertible top began to pop at the seams, I had never given sewing awls more than a glance—though I'd passed them many times in hardware stores.


Hoping to save the car top, I bought

an awl and received a surprise; it's a man's sewing tool that will put neat, strong stitches in canvas or leather. It is most impressive when used to sew something that has come apart; you simply follow the holes left by the original stitches, and the finished repair looks factory sewn. The tool does a job that surpasses the overlapping, and often misaligned, sutur-

How to make a lock stitch with the sewing awl

PUSH THE AWL THROUGH THE MATERIAL, holding a finger on the reel as shown below in (1) so that the short end of the thread won't slip through the eye. Release the reel and pull the

thread through the groove in the needle until its length is about twice the distance to be sewn (2). Pull out the awl (3) and move ahead a distance equal to the width of stitch





CONVERTIBLE TOP can be saved if it pops at the seams; today's fabrics often outlast the stitching. Work can be speeded if you have someone inside the car to pass the thread through the loop and pull it tight after each stitch.



GOOD LEATHER seldom wears out; it comes apart at the seams. New stitching can restore luggage and camera cases to like-new condition. Soften the leather in water before you start sewing it, so the thread can be pulled down snug.

ing for which your shoemaker charges you 50 cents or a dollar.

The stitch is identical to that made on a bobbin-type sewing machine—a thread on the face side locking with a thread on the underside.


The sewing awl was first manufactured in 1910. There were many more horses then, and it filled a need for folks who

liked to repair their own saddles and harnesses. Stockmen also used it to sew cuts in the hides of cattle that had wandered into barbed-wire fences.

Either of the awls illustrated sells for \$1.98 at hardware and marine-supply dealers, or by mail order. Any thread can be used, but most dealers stock waxed cotton thread for leather work.

desired. Push the awl through the material with reel released (4) to begin the second stitch, and immediately pull it part way out (5). This forms a loop on the side of the needle opposite the groove. Insert the lower thread in the loop (6) and pull it through (7). Hold the reel

while you withdraw the awl and pull it and the thread in opposite directions (8) to tighten the stitch. All stitches after the first one are made the same way, releasing the reel each time you push the awl through the material. After the last stitch, cut the thread and tie it securely.




Short Cuts and Tips

FROM PS READERS


Shaping Brace for a Radial Saw

A RADIAL saw can be set up as an efficient shaper, but in making a heavy cut in hardwood the cutter may chatter, resulting in a rough cut. To reduce this, make a bracket of right triangles and two-by-fours. After adjusting depth of cut, clamp one side to the table and the other to the motor.—*Ben Quann, Ottawa, Ont.*



▶▶▶STEEL table-saw blades dull rapidly when they're used to cut tempered hard-board. I get smooth cuts without chatter or twist by substituting an abrasive blade intended for brick cutting.—*Elmer E. H. Jorgensen, Springfield, Ill.*

▶▶▶WHEN pouring liquid into bottles, you won't have to steady the funnel if you seat it in a bedspring slipped over the bottleneck. This leaves both hands free to hold the container you're emptying.—*Steven R. Scadding, Toronto, Ont.*



C Clamp Turns Sink-Trap Nut

THE only available wrench large enough to grip the nut on my sink trap was one with toothed jaws that would mar the chrome. So I tightened a small C clamp on opposite flats to turn the nut.—*T. G. Thompson Jr., Anacortes, Wash.*



Push-Stick Empties Hog Trough

DON'T strain your back lifting one end of an outdoor hog trough to tip out rain water or slush. Cut a scrap block to conform to the angle of the trough sides and insert a long handle. One push clears the trough.—*G. E. Hendrickson, Argyle, Wis.*



Make Sandpaper Last Longer

THE thin paper backing of fine sandpaper usually wears out before the grit. It won't if you reinforce it with a piece of cloth the same size. Dry-mounting tissue for photos makes a good bond, but slip paper between the cloth and hot iron, so the tissue doesn't gum up the iron.—*Ken Patterson, Moose Jaw, Sask.*

Raising the Roof Takes Big Prize

"We owned a three-bedroom home. We had three children, all boys. Then our fourth child arrived—a girl! We needed more room. With the help of two carpenters and a crane, we raised the roof and added three 10-by-11 bedrooms and space for a future bath. Pictures enclosed."

William W. Buckwalter of Phoenixville, Pa., made the above entry a year ago in the Popular Science Home Improvement Contest. It won him first prize, a Studebaker Lark. See pictures of his home below.

Hereafter, twice a year—in April and September—POPULAR SCIENCE will make a special award of \$50 for what the editors consider to be the best home improvement idea they have seen in the previous six months. Other ideas considered worth publishing in "Home Improvement Ideas" will be paid for at regular rates. Send entries to Home Improvement Editor, Popular Science, 355 Lexington Ave., New York 17, N. Y.



Home Improvement Ideas

FALL 1961

A Shell Home: Your Biggest Home Improvement Bargain.....	3
How to Have a Compact Shop	12
Using Prefab Iron Railings.....	18
A Planter That Fools the Eye.....	21
Pull-Down Attic Stairway.....	25
Study Desk Hides Hobby Bench.....	26
What's New for Improving Your Home	30
Prize-Winning Home Improvement Ideas	36
Build a Home Theater Wall.....	42

• • •

"Home Improvement Ideas," published as a supplement to a regular issue of POPULAR SCIENCE, is devoted exclusively to the physical betterment of the average man's greatest investment—his home.

• • •



"Just tell us how you like it!"

(a **DURO-PLASTIC** quality fix-it product, that is!)

WIN ONE OF 1001 Valuable Prizes

**1,001 Chances to Win
ENTER TODAY!**

- FIRST PRIZE** RCA 21" Color Television Set
- SECOND PRIZE** Westinghouse Stereo Hi-Fi Set
- THIRD PRIZE** Eastman Kodak Complete Home Movie Set



IT'S EASY! JUST TELL US HOW YOU LIKE ANY ONE OF OUR FAMOUS FIX-IT PRODUCTS

OFFICIAL RULES!

"Just tell us how you like it!" • Enter as many times as you wish!
• Just follow these simple rules:

PLUS 998 ADDITIONAL PRIZES!

- 7 ROADMASTER BICYCLES
- 5 WESTINGHOUSE TRANSISTOR SETS
- 6 SPORTSMASTER FISHING RODS
- 6 DAINTY MAID 4-SLICE TOASTERS
- 25 AIRPLANE 2-PC. LUGGAGE SETS
- 25 DETECTO SCALES
- 50 REGENT-SHEFFIELD 9-PC. CUTLERY SETS
- 50 CASCO ELECTRIC HEATING PADS
- 50 ITALIAN ICE BUCKETS
- 375 EMERGENCY FLASHER LANTERNS
- 399 DURO-PLASTIC HANDY FIX-IT KITS

- Print the name of the DURO-PLASTIC fix-it product you've used, and why you like it in as many words as you choose, on the back of the entry blank or on a plain sheet of paper. You must use a separate entry blank or sheet of paper for each entry. Be sure to fill in your name and address and the name, city and state of the store where you purchased our product. There will be a duplicate prize awarded to the dealers named by the first 25 winners.
- Clip off the WOODHILL Name and Address from the corresponding DURO-PLASTIC fix-it package and mail with your entry to DURO-PLASTIC CONTEST JUDGES, 3113 Prospect Avenue, Cleveland 15, Ohio.
- Entries will be judged on the basis of originality, uniqueness and openness of thought. Judges' decisions will be final. No entries returned. All become the property of The Woodhill Chemical Corporation.
- All entries must be postmarked no later than midnight, Thursday, November 30, 1961.
- Any resident of the continental United States and Canada may compete except employees of The Woodhill Chemical Corporation, its representatives, its advertising agency, the Judges and the sponsors. Contest subject to all Federal and state regulations.
- Winners will be notified by mail approximately four weeks after close of contest. List of winners available to those requesting same who enclose a stamped, self-addressed envelope.

GET YOUR ENTRY BLANK TODAY AT YOUR FAVORITE HARDWARE, DEPARTMENT, AUTO ACCESSORY, PAINT OR VARIETY STORE!

THE WOODHILL CHEMICAL CORPORATION
"Originators and World's Largest Manufacturers of Plastic Metals"



Home Improvement Ideas

A Shell Home:

Your Biggest Home Improvement Bargain

YOUR biggest buy in home improvement today is a shell house. A builder puts up the outside for you—the foundation, floors, walls, and roof—then you take over and finish the interior yourself.

The result: You get a home at a fraction of the cost of a conventional custom-built job. Full-size two- and three-bedroom shell houses are now selling for \$2,000 to \$5,000.

The shell idea has been around for years, but there are three big reasons for its recent whirlwind rise in popularity.

- Shell homes are now mass-produced by the thousands in the same way that early devel-

CONTINUED



FOR ABOUT \$66 A MONTH, you can own a 25 by 36' three-bedroom shell like this Crumpton model in Tampa, Fla.



THIS THREE-BEDROOM SHELL comes complete with materials to finish it from the Robert R. Layton Co. in Delaware.



NO MONEY DOWN, seven years to pay, brings this three-bedroom Jim Walter shell to a \$3,595 time payment price.

YOU GET TWO BEDROOMS, porch, and car port for less than \$3,000 in this Institute For Essential Housing model.



What is a shell home?



FRAME IS PUT UP by professional carpenters, often using prefabbed parts to speed the job.



FINISHED SHELL is complete on the outside, including doors, windows, trim, even paint.



WHAT YOU GET looks like this on the inside. Beams are bare, ready for you to take over

opment builders took over whole neighborhoods. The difference is that you can have a shell built on your own lot, anywhere you want it, and in any of a wide choice of sizes and styles.

- You can now finance up to the full cost of a shell home, no money down, and still do the finishing work yourself. In the past, shell homes were not eligible for regular mortgage loans.

- Unlike other forms of do-it-yourself houses, a shell home comes to you completely finished on the outside, including siding, shingles, windows, even two coats of paint. The heavy structural work has all been done for you—you can't even tell from the outside that it isn't finished.


Inside, a shell home looks much like an unfinished attic or basement; in fact, the finishing jobs are similar. In most cases, the floors are down, but wall studs and ceiling joists are exposed. You add insulation, paneling, doors, trim, and the heating, plumbing, and wiring.

The shell is a natural for custom-tailoring your own home improvements because you aren't tied down to a fixed plan. Built-in furniture, cabinets, storage walls, and special shop and hobby areas are easily designed to suit your own needs. Most builders will allow you to choose any room plan you want.

Modern materials make it easier. The many prefinished materials and packaged kits now on the market are another big reason for the boom in shell homes. They make it practical to tackle finishing jobs yourself that would have been difficult or impossible a few years ago. By the same token, many of the tricks used in finishing a shell can be borrowed for improving an existing home.

Peter Leschuck, who recently finished a two-bedroom shell on Long Island, N. Y., says: "I found that prefinished plasterboard is only a few cents more a square foot than the regular stuff. It looks terrific and saves patching joints and painting. I also used prefinished ceiling tiles, which go up fast and require no extra work."

Leschuck spent \$3,500 for his original shell and another \$2,500 to complete it for a total of \$6,000. This, he figures, is equivalent to a \$10,000 custom-built home. "I got a good wiring book and did all the electrical work myself," he adds. "Even put in my own 220-volt line



ALL YOUR BUILDING NEEDS FROM A TO Z

One stop shopping . . . from A to Z . . . that's the kind of shopping and service you get when your local Lumber and Building Materials Dealer is your headquarters for building, improving and remodeling your home. ☐ Want to do the job yourself? How about tools? Need a contractor? How about estimating and financing? Do you need free, experienced advice on doing an easier and better job. ☐ Your hometown Lumber and Building Materials Dealer stands ready to help you all the way. He has ample parking facilities, too . . . and you can fill all your needs in just one store. ☐ As a member of the National Retail Lumber Dealers Association, he is pledged to serve you honestly, courteously, efficiently and economically. NRLDA keeps your dealer aware of up-to-the-minute news on products and methods to assure you of the best for the least cost. ☐ It will pay you to make your local NRLDA Lumber and Building Materials Dealer part of your team when you build or remodel . . . during these FALL BUILDING AND HOME IMPROVEMENT VALUE DAYS.

NATIONAL RETAIL LUMBER DEALERS ASSOCIATION/18TH & M STREETS, N.W., WASHINGTON 6, D. C.



PUTTING WALLS TO WORK is easy in a shell. Owners of this Paddock Lake, Wis., home hid the laundry area behind two ceiling-high doors that close (left) for entertaining. Doors are wood-framed hardboard with shallow cabinets on the front and X braces in back for strength.

for an electric range." Another owner used prefinished hardboard on his walls and ceilings and says: "Those big sheets really made the job easy."

Many owners are also discovering the convenience of packaged kitchens, bathrooms, plumbing kits, and simple fit-in-a-closet furnace units that are now available. Some building-supply houses and mail-order outfits like Sears, Roebuck will sell you a complete heating system of any type for \$275 to \$700. You get all the parts—including pipes and ducts cut to exact length—plus instructions for putting them together yourself.

How swank can a shell get?



SPACIOUS SPLIT-LEVEL DESIGN in Cold Spring, N. Y., is one of many luxury models available at low cost. It includes three bedrooms, garage, even a playroom. Empire Swift Homes sells it for \$5,375 as precut package or \$7,075 as fully erected shell on your lot.

Everything you need for a bathroom can be had for \$150 to \$300. Flexible plastic pipe is now used extensively for cold-water lines and may soon be available for hot lines. Pre-wired electrical fixtures and surface raceway wiring also speed the work.

How about building codes? These are usually no problem on the shell itself since manufacturers make sure that their houses meet local code requirements before moving into an area. On the finishing work, you will be expected to meet the same codes set up for professional plumbers and electricians. As long as you follow the requirements carefully, you'll have no trouble getting your work inspected and approved.

There are ways around this, too. Some builders will sell you all the finishing materials along with the shell, including the basic code-approved wiring, plumbing, and heating supplies. Many owners have this basic work roughed in by a professional, then do the final hook-up of fixtures themselves. Another way to get skilled help is to join forces with other nearby shell finishers—you help them and they help you, combining each other's abilities. Or you can hire out all the plumbing and electrical work and still save a considerable amount by doing the other finishing jobs yourself.

You should know, in any case, just what the local requirements are. Some shells are designed with 24" spacing of studs and joists. Where this isn't per-

NEW STORAGE PANEL!!!

WITH THE WAINSCOT RIGHT ON IT,
SUITS ROOMS ALL OVER THE HOUSE

In children's rooms, utility rooms,
workshops, G-P's new Garage Liner
looks handsome, works hard, wears
well. A heavy-duty hardboard, it pro-
vides storage for tools, toys, para-
phernalia... makes a perfect set-up for
shelves. With the wainscot right on the
panel, you just add a molding and the
job's done. Factory-finished, it needs
no paint... costs about 22¢ a sq. ft.
at your lumber dealer's. 1/4" V-groove
4 x 8 panels, perforated to wainscot.



GEORGIA-PACIFIC

Plywood • Lumber • Redwood • Hardboard • Pulp • Paper • Chemicals

Free "how to" booklet! Ways to work with
hardboard. Write: Georgia-Pacific, Dept
PS961H, Equitable Bldg., Portland 4, Ore


name _____

address _____

city _____

county _____

state _____



mitted, there will be an extra charge for setting the beams on 16" centers. Some codes also require that a home be completely finished before you move in—a hardship if you're planning on a live-while-you-work arrangement.

How much do you really save? Some shell builders advertise savings of up to 50 percent over a custom-built house of comparable size. This is probably optimistic. According to actual experiences of shell owners, savings range from about 25 to 40 percent.

Some companies are not strictly shell manufacturers, but offer houses in various stages of completion—a good tip-off on how prices compare. The Institute For Essential Housing in Princeton, N.J., for instance, will sell you a three-bedroom house for \$3,188 in shell form, \$4,380 for the shell plus materials to finish it, and the same home completely finished for \$5,780. By buying the shell plus the materials and doing your own work, you can save \$1,400—or about 25 percent.

Arthur Tickner in Tampa, Fla., bought a two-bedroom shell for \$4,200 and added another \$4,300 to finish it. He didn't need a full heating plant, but otherwise this included everything, plus several extras—an added utility room, double-size car port, screened porch, and larger windows. He did most of his own work except for the wiring and plumbing. Time: about three months, working evenings and weekends with a helper.

As a rule of thumb, you can figure that finishing costs will run from about half up to as much as the shell itself. Many shells, especially those in the South, come with an inexpensive pier-type foundation; if you want a full foundation, you'll pay several hundred dollars more. Basements are also extra, as are sewer and water hookup charges, and a septic tank if you need one.

How you can buy a shell. Most shell builders make it easy for you: They'll either lend you the money themselves or arrange a loan for you. The only requirement is that you own your own lot.

Mortgages run five to seven years, usually at six-percent interest. Typical monthly payments range from \$32.87 for a \$2,250 shell up to \$65.74 for a \$4,495 model. Builders who also sell finishing materials will include the entire cost in

one mortgage so you have nothing else to buy.

Is a shell a risk? This is a point of some controversy. The Institute For Essential Housing will sell you a shell if you insist, but frankly doesn't recommend it. Too many shells go uncompleted, they maintain, because owners suddenly find themselves short of cash to buy the finishing materials.

A safer bet, says the Institute, is a shell-plus-materials deal where there's nothing extra to pay for. Monthly payments may actually be lower, they point out, even though the total cost is higher. The reason: The shell-plus-materials plan is financed over a much longer period—up to 12 years—so the monthly payments are spread thinner.

Of the Institute's own sales, only one percent of owners bought the bare shell. The majority elected either the shell-plus-materials package or the same home in semi-finished stage. "So we're definitely not in the shell-only business," says the Institute.

Those who sell only shells argue back that the greatly increased value of a finished home is strong enough inducement to force owners to get the work done. Records show, they claim, that most shell homes are completed within two to four months. They also cite the fact that only about one percent of shell homes are lost through nonpayment of their mortgages. This figure does not include cases, however, where mortgage payments are kept up but the house still goes unfinished for years. A bank would never permit this; a shell builder can afford not to care.

Responsible builders, like the Institute, also warn against some operators who "load up" an owner with a high mortgage just to sell him a house. "This makes it look easy," they point out—"sometimes too easy."

In any case, the finish-it-yourself home is fast becoming the answer for those who want to trade their own time and muscle for a substantial saving in cash. An estimated 60,000 owner-completed shells went up last year alone, with more than 100,000 predicted for this year. One happy Florida owner built a \$2,780 shell on a \$1,000 lot, adding only about \$600 worth of finishing materials. He's been offered \$8,000 for it. ■ ■

Seal up for Winter with

DAP



seal up cracks, holes and leaks that lead to costly heat loss, water damage or repair work with these quality **DAP** products

Do-it-yourself with DAP. Make your house snug and comfortable—keep out drafts, dirt and insects—prevent heat loss, water damage, rusting and rotting of building materials. Get ready for winter now. Get nationally advertised DAP caulking-glazing-sealing compounds at leading hardware, paint or building supply dealers.



Use **DAP CAULKING** to seal cracks and joints in wood, metal and masonry . . . around window and door frames, porches and steps, in wood or metal siding along flashings. Buy DAP Caulk in cartridges, cans or tubes. Apply with gun, knife or from tube.



Use **DAP "33" GLAZING COMPOUND** to replace broken glass, dried-out putties that leak air, water at windows. DAP "33" outlasts ordinary putties. Get **DAP "1012" Aluminum Gray Glazing Compound** for aluminum sash—needs no painting



Use **DAP KWIK-SEAL** to seal cracks in joints around tubs, sinks and lavatories. For pointing or resetting tiles, too. Squeeze Kwik Seal from the tube—use finger to smooth and finish—works quickly, easily. Waterproof—dries white, stays "rubbery"



Use **DAP ROPE CAULK** for scores of do-it-yourself jobs—a fine easy-to-use weatherstrip around windows or window air conditioners, seals joints or cracks in most materials. Apply with fingers—no tools! Stops air, water leaks; takes paint.



Use **DAP vinyl paste SPACKLING** for easy patching of cracks, holes and breaks in plaster. Seals dry wall panel joints. Good for wood too! Use right from can. Creamy smooth—sticks tight, sands to a feather-edge. Easy to paint. No priming needed

DAP

DAP Inc.

General Offices Dayton 31 Ohio

Manufacturers of nationally advertised DAP Glazing, Caulking, Sealing and Spackling Products; Duratite Wood and Metal Fillers, Glues and Adhesives.



**1961
WINNER
OF PRODUCT ENGINEERING'S
MASTER DESIGN
AWARD**

POWER POWER POWER

DISSTON'S NEW 1/4" DIRK DRILL. breezes through concrete block, too!

The new Disston 1/4" Dirk gives you exceptional power for the toughest jobs because it has a full 3-amp, 1800-rpm motor with Spiroid® gearing. With the new Disston Dirk you can drill closer to corners than with any other drill in its class. Dirk's offset motor and recessed Jacobs chuck give it the slimmest profile available. You are able to work between joists, in corners, closer to floors and ceilings than ever before.

Here's what a popular handy-man's magazine says about the new Disston Dirk, "The unusual design makes sense (winner of Product Engineering's 1961 Master Design Award). With your hand directly behind the bit, you can drill straighter, apply more muscle on tough boring jobs and eliminate the wobble that breaks bits and gives you oval holes."

The new Disston Dirk is the only drill with a "stand-up base." It's easier for you to change drill bits and they won't snap or bend when you set the unit aside.

See the Disston Dirk 1/4" drill now on display in your local hardware store for \$30.00 (only a nickel more than the next best drill). Once you try it, you'll want to buy it. The Dirk, made in Danville, Virginia, is another fine product from Disston, master toolmaker since 1840.



The Disston Dirk

Other Disston Products you'll want to try and buy!

D600 Circular Saw

D20 Sabre Saw

Electric Hedge Trimmers

PORTER

DISSTON DIVISION
H. K. PORTER COMPANY, INC.

Compact Shop

Shares Garage with

A wonderful way to use that extra space a compact car opens up

THE new compact cars—short, narrow, and low—give you extra space in your garage. Nudge one of them into a corner of even a one-car garage, and you'll have enough room left over for a king-size workbench and a huge cabinet; plenty of wall space for hand tools; and enough floor area for some power tools.

Building such a shop is a simple job, especially since the bench and cabinet also double as the partition between the


shop and garage. The idea for it popped up when a **POPULAR SCIENCE** writer traded his road-scarred, standard-size automobile for a compact.

The old car—some 17' long and 80"

CONTINUED



Compact Car



No tricky joints; just plywood over a frame of two-by-fours



TWO-BY-FOURS frame entrance doorway and bench. Where possible, frame is nailed to studs in garage wall to anchor unit in place. Top of door frame is nailed to ceiling joists.



BUILD AROUND THE HOOD when laying out the framing. With the car in the garage, you'll be certain it will fit when the job is done. Note clearance between hood and cross member.

NOSE OF CAR snuggles into this space under the bench. Two-by-fours in lower foreground are fastened to the floor with cut nails to stop the car just before it bumps the bench.



wide—had only a couple of feet behind and in front of it when parked in the garage. That's about par for the course; a single-car garage averages 21' in length, and is about 11' wide. A compact car—a mere 15' long and 67" wide—leaves 6' of parking space unused in front of it, and more than 4' of wall-to-wall space at its sides.

Like stalling a horse. The lowness of the hood—it's only 35½" off the floor—made the shop idea still more practical. Between the hood and the garage ceiling there was a big 5' of usable space—making it possible for the workbench and cabinet to be built *over the hood*. Since the 2½' depth of the bench is actually in the garage area, the effective length of the shop adds up to 8½' (6' of floor space plus the 2½' bench top). In a garage 11' wide, you'd get more than 93 square feet of shop space.

That was the idea. It worked out fine. The plans show how you, too, can squeeze a shop into the extra footage your compact—or small foreign sedan, for that matter—adds to your garage.

After erecting the framework, start building the cabinet. It's easier to work on it without the workbench in the way. The two ends, partition, shelf, and bottom of the cabinet are cut from ¾" plywood and assembled on the cantilevered frame members fastened to the wall and door frame. The partition, fastened between the shelf and bottom of the cabinet, creates an I-beam effect that keeps the cabinet from sagging in the center.

Do-it-yourself aluminum track guides the ¼"-hardboard sliding doors on both sides of the cabinet. Note that the track on the shop side must be installed on beveled shim strips to match the slope of the cabinet face.

Fit the ¾"-plywood bench top in place, screw it to the frame, and cover it with ¼" tempered hardboard to provide a smooth, durable work surface.

Cover the front and right end of the bench with panels of ¾" plywood. Close in the toe space along the front with plywood strips. All joints are butted and fastened with 1½"-10 wood screws. Cut three openings in the top edge of the front panel: two for the drawers, and one to clear the guide rods of your woodworking vise.

CONTINUED


Remarkable new PPG LATEX House Paint guards against ugly blistering and peeling!



Left: Moisture escaping from inside the house causes some house paints used on wood siding to blister and peel.



Right: New PPG LATEX protects siding against such damage. Its trapped moisture turns out without harm to paint film.



Lasts years longer . . . goes on faster, smoother . . . can be applied even over damp surfaces . . . dries in just 30 minutes . . . brush or roller wash clean in soapy water!

• Thorough testing . . . in various climates . . . has proved sensational new Pittsburgh LATEX House Paint superior in many ways.

• Far easier to apply, it "wraps" your home in an amazingly tough, flexible film that prevents unsightly blistering and peeling years longer.

• Thanks to new miracle resins, white stays whiter, and colors stay brighter—on any type of construction!

• PPG LATEX goes on right over damp surfaces . . . dries dust- and bug-free in $\frac{1}{4}$ hour. Wash up with soapy water!

• For the best paint job ever, just use new PPG LATEX and follow directions.



• Saves time and work, because PPG LATEX goes on faster, smoother without brush drag, or lap marks.



• No rain worries, no wasted week ends! Soon as the rain stops, you can start right in painting again!



• Dries bug-free and dust-free in $\frac{1}{4}$ hour. You can apply second coat without even moving your ladder!



• Easy cleanup! Just wash brush, roller or spray in soapy water—wipe up spatters with damp cloth.



PITTSBURGH[®] PAINTS

PAINTS • GLASS • CHEMICALS • BRUSHES • PLASTICS • FIBER GLASS



• For America's finest oil-base house paint, ask your Pittsburgh Paint dealer for Sun-Proof—famous for quality since 1892.

PITTSBURGH PLATE GLASS COMPANY

IN CANADA: CANADIAN PITTSBURGH INDUSTRIES LIMITED

Doorways extend the shop even farther into the garage



TOOL-LADEN DOORS open up a pass-through more than 4' wide at the rear of the bench. Doors swing out into garage, putting tools within reach when you're working on the car.

ENTRANCE DOORWAY permits long boards to extend out into the walkway beside the car while being cut to size. Extra-long lumber can be supported at outboard end with a sawhorse.



BIG JOBS can overhang bench at front and rear with pass-through doors open. With all this room inside the shop, take care not to build something so big that you can't get it out.



BIG PANELS SLIDE THROUGH the wide opening. By elevating the saw on blocks until it is flush with the bench top, you can use the bench as a support for cutting the panels.

The drawer sides, front, and rear are $\frac{3}{4}$ " plywood framed around a $\frac{1}{4}$ "-hardboard bottom. The drawers are hung on metal slides fastened to the bench frame.

A pass-through for the coffee break. The doors at the rear of the bench are built up over two pieces of $\frac{3}{4}$ " plywood cut to fit the opening. Nail a one-by-one frame around the edges of the plywood on both sides, and fasten perforated hardboard over the frame. This provides space behind the perf-board to take the ends of the wire tool hangers.

The plywood floor is laid over two-by-fours, supported by one-by-two blocking fastened to the concrete with cut nails. Besides adding to your comfort

in the winter, the combined thickness of the blocking, the two-by-fours, and the plywood will raise you an extra 5". Without this lift, the surface of the bench, 46" above the concrete floor, would be too high for comfortable working. Floor tiles, cemented over the plywood, make sweeping up easier. You can pass up the luxury of the floor, but then you'll have to lower the bench top to about 40". This means omitting the drawers, or making them very shallow to clear the car.

A 30" flush door is hung in the main doorway so that it swings outward into the garage. Locks can be installed on the door and pass-through to safeguard your tools. ■ ■



BEAUTIFUL MARLITE PANELING

wash-and-wear walls you can install yourself

You can finish a room with Marlite this weekend—and eliminate redecorating for good! Marlite's melamine plastic finish is *baked* on, so it's smooth and durable as the surface of a refrigerator. It takes abuse that would spoil other finishes, then wipes clean with a damp cloth. And Marlite's simple to install in new rooms or old. Choose from a handsome array of Trendwood® reproductions, beautiful patterns and decorator colors—in large sheets or easy-to-handle Plank and Block. See your building materials dealer.



Tongued-and-grooved Marlite Random Plank (16" x 8" x 1/4") goes up fast over furring strips or solid backing with no waste, mess or fuss.

Marlite®
plastic-finished paneling

Marlite Division of Masonite Corporation
Dept. 926, Dover, Ohio

Please send full-color building and remodeling folder on Marlite Paneling.


Name

Address

City Zone State

ANOTHER QUALITY PRODUCT OF MASONITE® RESEARCH





**...MOST
OF
ALL**

GRAB WITH LOCK

Ask any skilled electrician or auto mechanic about CHANNELLOCK Pliers. He'll tell you they're the handiest pliers of them all . . . basic tools he wouldn't be without. And this same all 'round usefulness will help you do hundreds of jobs . . . faster, easier. Be sure your basic tools include genuine CHANNELLOCK Pliers. Get them at your tool supplier's. If he's out of them, ask him to order for you. Available in three jaw capacities: $\frac{3}{8}$ " , $1\frac{1}{2}$ " and 2".

Use it as a plier

Use it as a wrench



Write for Catalog of Complete Line of Pliers

CHAMPION DEPARTMENT TOOL COMPANY

MEADVILLE 2, PENNSYLVANIA

You can add beauty to your home, indoors and out, by—

Using Prefab Iron Railings

WANT to dress up your porch or patio, the front steps, or even a living-room alcove, with iron railings? Good idea. Today's improved prefabs offer good looks, utility, lower costs, and easy installation.

How do you do it? Use pre-welded railing sections and special posts and fittings. You set the posts (surface mount them if you wish) and then bolt on the railing sections. To top it off, you can choose from a slew of prefab iron ornaments and columns.


Railings, plain and fancy. Prefab iron railings come in 4', 6', and 10' lengths. Basically, a section consists of U-shaped top and bottom channels (1" wide, $\frac{1}{2}$ " deep, $\frac{1}{8}$ " thick) with pickets welded on at 5" or 6" centers. The railing sections vary in height. Some are 27", some 29". They are all around 31"-32", however, when installed.

Some manufacturers offer just a basic, low-cost, lightweight railing with flat pickets— $\frac{1}{2}$ " wide, $\frac{1}{8}$ " thick—twisted and welded on 6" centers. Others make prefab railings with traditional $\frac{1}{2}$ "-square solid pickets, usually on 5" centers. One variation on the square picket design is the alternate-twist pattern—with every other picket twisted.

A unique virtue of prefab railings is adjustability. Each railing unit may be slanted to fit any slope or set of steps. It takes a little heave-ho, but not much. Railings of this type are available from several manufacturers and from mail-order houses such as Sears, Roebuck.

One maker offers nonadjustable railing for entrances. This ranges from 2' 8" to 4' 2" in length and has an end post

Here's how wrought iron dresses up a stairway



welded to the railing section. The hand-rail curves up at the back where it attaches to the wall. Another curve at the front makes a lamb's-tongue ornament.

One type of prefab railing distributed by a mail-order house (Ward's) is a real do-it-yourself item. You make up your own railing sections by bolting individual flat, twisted pickets on 6" centers to pre-drilled T-bar top and bottom rails 3' or 5' long. The railings are then bolted to posts.

These railings are not adjustable, but they don't have to be—you build them right in place and they conform to any angle from the beginning.

A useful accessory in the prefab-railing line is


a kit for making a gate. It includes a hinge section, latch section, and latch plate. The hinge and latch sections are bolted to a railing section of desired length, and the entire unit is mounted on a railing post.

Posts to hold it all. Posts are heavy-gauge steel tubing 1" square and 35"-36" long. This permits them to be anchored in concrete. If they are surface-mounted, about 3" is cut off.

Posts in the higher-priced lines have molded, welded-on fittings for attaching the railings. Such posts are made in end, intermediate, and left- and right-corner types for both steps and porches. Posts in the lower-priced types

Home  Improvement Ideas

Use wrought iron at the entranceway





of railings are simply lengths of tubing.

Surface installation of posts is possible with base plates or flanges. One type of plate has a socket into which the post fits, held by setscrews. Another type has a stub that fits into the hollow end of the post. Usually the post is then welded to the base plate.

For bolting railing sections to posts that do not have welded-on fittings, the manufacturers furnish $1\frac{1}{2}$ " right-angle iron brackets. The posts are usually pre-drilled, but holes have to be drilled in the railing channels. The brackets are bent to adjust for railings on steps.

The designer's touch. Various orna-

Use columns and railings for room dividers



MAKE YOUR HOME WINTER-TIGHT DRAFT-FREE!

IT'S TIME TO TACK UP

Warps **CRYSTAL CLEAR**

FLEX-O-GLASS

Cover Your Screen Porches, Breezeways, Windows and Doors with Genuine, Shatterproof

FLEX-O-GLASS

HOOD AND COLD - WIND AND HEAT

Keep up to 40% less heat loss

Don't let cold weather catch you unprepared. Have a warm, cozy home all winter long. Get Flex-O-Glass NOW!

So Easy - Anyone Can Do It. Costs So Little—Anyone Can Afford It. \$18.00 is all that it takes to cover a 9 x 12 screen porch with Flex-O-Glass. Makes a dry, protected room for play or storage.



CUT WITH SHEARS




TACK ON SECURELY


AT YOUR LOCAL HARDWARE, LUMBER & BUILDING SUPPLY STORE

HERCULES HOOKS

FIT OVER 1"x4" BOARD




HEAVY DUTY WALL STORAGE



LOOK TWICE! These aren't wall board hooks. They are Hercules Hooks that fit over the common 1" x 4" board—NO perforated wall board is used.

Hercules Hooks hold the heaviest tools, lawn equipment, boxes, cans, industrial equipment, etc. It's easy to get your garage, basement or shop ship-shape with Hercules Hooks. At your dealer.



Write for free booklet to:



KERR WIRE PRODUCTS COMPANY

Dept. P-81, 833 North Cicero Avenue - Chicago 51, Illinois



CLIK-STOP

Adjustable Wrench

AUTOMATICALLY LOCKS AT EVERY SETTING



No levers . . . no gadgets . . . It won't slip or work loose . . . ever! You can yank it, bang it, even on the toughest jobs the jaws will never work loose. Available in both chrome or industrial-black finish in sizes from 4" to 20".

Send 10c for descriptive P&C Tool Catalog.





Look for the colorful P&C Merchandise in over 2,000 stores.

P&C TOOL COMPANY

Portland 22, Oregon • subsidiary of Pendleton Tool Industries, Inc.

NOW!

no spindle deflection



South Bend's design eliminates the major cause of inaccuracies common to all drill presses—spindle deflection resulting from depth gage pressure. There is no depth gage collar on the quill. Travel of the quill is controlled by an exclusive Rack Type Depth Gage that limits the rotation of the quill feed shaft. Write for more details about South Bend's exclusive features.

Prices of South Bend 14" Precision Drill Presses start at \$134 f.o.b. factory

Use railings for patios and porches



ments of cast iron or flat steel may be bolted, screwed, or welded to the posts or railing pickets.

For the posts, there are ball and urn ornaments that screw to the top, and the traditional lamb's tongue. At the foot of steps, a scroll or S-shaped ornament may be added to the posts.

Ornaments for pickets come in a broad range of designs. Among them are shield, heart, diamond, scroll, and fleur-de-lis patterns, as well as leaf and floral shapes.

One prefab-iron producer also makes a rail capping intended to give the do-it-yourself installation a custom look. The capping, made in 6' and 10' lengths, snaps on the top railing and gives it a molded, convex surface.

Columns, Southern-style. Columns capable of supporting several tons are also basic items in the prefab-iron inventory and are often used with railings. Outdoors, they support roofs for porches, terraces, and car ports. Indoors, they're

SOUTH BEND

LATHE

South Bend Lathe, Inc., South Bend 22, Indiana

Builders of Lathes, Milling Machines, Shapers, Drill Presses, Pedestal Grinders

Up to 36 months to pay




adaptable as room dividers, fastened between floor and ceiling.

Columns usually are 8' tall, but allow an average height adjustment of some 14". There are both flat and corner (right-angle) types. Columns are made of 1"-square steel tubing (like that used for posts), with welded, decorative steel or cast-iron inserts. Columns range in width from 9" to 20".

What about tools? For the installation job, you'll need a hammer, screwdriver, hacksaw, level, an adjustable wrench, and electric drill. Depending on what you'll be drilling, you'll need masonry-, wood-, or metal-boring bits.

Before you plan your job, check with your building-supplies dealer to see what he stocks. Prefab-iron producers put out parts sketches and work sheets that will help you. These tell what lengths of railing you'll have to work with.



HOW YOU ADJUST RAILINGS: Prefab railings are adjustable, as you see here, to fit any incline or flight of steps. To slant the section, you simply press down and to one side.

Surface mounting of posts is quickest and easiest. You simply drill two holes for screws to hold each base plate. Use lead expansion shields when sinking the screws in masonry.

For the utmost strength and rigidity in a masonry installation, you may still wish to sink the posts in their base. Each will need a hole about 1½" square and 2" or 3" deep.

Perhaps the easiest way to make such a hole is to chuck a masonry bit in your drill, drill out the corners of the square, and remove the center with a cold chisel.

When installing railings, you brace the posts temporarily while you measure, cut, and attach the railings. Both posts and railings are cut with a hacksaw. To simplify finishing, most prefab railings and other ironwork come already prime-painted in black or gray. ■ ■



... as any other sander at its price


NEW *Weller* HI-POWERED SANDER

Powerful performance at low price is made possible by Weller's new *heavy duty* reciprocating motor. Full ½" stroke—14,400 strokes a minute—and big 26 sq. in. sanding surface. Maintenance-free, too. No brushes, commutators or metal bearings to wear. Lubricated for life. And it's the *safest* sander on the market. Plastic handle, housing and plate, no exposed metal parts that can be energized, and 3-wire grounded power cord eliminate electric shock hazard. *Sands with the grain* for smooth finish unobtainable with circular or orbital sanders. *Guaranteed 1 year.*

Model 77 **\$19⁹⁵**

At your Hardware Dealer

WELLER ELECTRIC CORP., EASTON, PA.



GRECIAN WHITE Z-BRICK gives a stylish face to the rough concrete-block planter shown under construction at left. The smartly angled planter doubles as a patio retaining wall at the California home of Mr. and Mrs. Darrell Hoff.

A Planter That Fools the Eye

Behind the delicate brick facing is a rugged retaining wall of reinforced concrete block

HERE'S an interesting new way to build a combination retaining wall and planter for a terrace. It starts with a crude but husky double wall of inexpensive concrete block. It finishes with a new kind of bricklike facing called Z-Brick.

The brick facing is made of vermiculite, cement, and coloring. It is so light in weight that it goes on with adhesive, needs neither foundation nor mortar. Units are $\frac{7}{8}$ " thick by $1\frac{1}{2}$ " by 12" and come in green, red, tan, and off-white.

Z-Brick, a product of Vermiculite Manufacturing Co., 2107 N. 34th St.,



SPECIAL ADHESIVE attaches the facing brick. A skim coat of the adhesive was first scraped on the block with a finishing trowel. Three gobs were then used on the back of each brick.



ANY WOOD SAW, or a hacksaw, will cut the brick where special lengths are needed. A $\frac{3}{8}$ " round wood rasp is fine for duplicating the curved joint recess after a cut is made.

Seattle, was made originally for interiors. Since there is no need for a foundation, it can be stuck to an ordinary wall in remodeling a fireplace or kitchen. Recent tests, however, open up a whole new field of uses. They show that the bricks will stand up outdoors if placed on a permanent surface—concrete or other masonry, or asbestos-cement board, not wood.

This combination method allows you to build strong concrete-block walls without worrying about their crude appearance. And you can use the cheapest of blocks. The builder of the planter wall shown here gives the following account of how he went about the job:


"I put down a 4" slab of concrete with $\frac{3}{8}$ " reinforcing rods stuck into it. On this I built up my walls, using the thin type of 4" blocks. I ran the walls 9' out from the corner of my house, then added a 4' spur section at a 30-degree angle. For strength, I poured concrete into hollows containing the steel rods.

"Z-Brick can be laid from the top or bottom, but from the bottom up is easier. I placed a board at the base of the wall to give a straight edge. Because a planter gets pretty wet, I took the precaution of covering the blocks with a thin skim coat of the Z-Brick adhesive before applying the bricks.

"Z-brick goes on much like tile—it's the fastest part of the whole job. You just put three dabs of adhesive about the size of a quarter on the back of each piece. Then you slide the piece firmly into place sideways. At corners, I just butted the bricks together for a joint that I considered most bricklike. For an even slicker appearance, it would be easy to miter the corners.

"The bricks cut like wood with any hand or power saw. Shaping can be done with a rasp. I found they can even be ground to an exact fit by rubbing them on the rough surface of a concrete block. What could be simpler?

"I topped off the planter with two-by-six trim boards of redwood. These were cemented in place with the Z-Brick adhesive to avoid using bolts that would show. I then turned the job over to the gardening authority of the family. She planted hydrangea and pittosporum in a mixture of soil, sand, and peat moss. Of course, I take *all* the credit when visitors drop in and admire the fine results."




Stairway Folds Into Attic

THIS folding attic stairway will operate in tight quarters where you can't install a commercial swing-down stairway. As the lower section is pulled up by a rope, the hinged top section slides up into the attic on U-shaped tracks made by nailing one-by-twos to the sides of two one-by-threes. A self-locking rope hoist (Sears, Roebuck No. 9H78365) holds the stairs in the up position, and the rope is coiled around four hooks on the inner side of the hinged trap door. The stair sections, joined on the back with large strap hinges, become rigid when they are in the down position.



Home Improvement Ideas

Here's just the thing for a teen-age boy's room—to save space and banish clutter



The Study Desk That Hides a Hobby Bench

IT'S hard to believe that such a handsome desk is also a practical workbench. But POPULAR SCIENCE planned this piece for double duty. When the lid's down, there's a 26"-by-48" study surface at the proper desk height of 30". Once the homework's done, the books are whisked into a drawer, and the desk is transformed into a hobby bench by just swinging up the lid.

Underneath, there's plenty of space to work on a boat model or hi-fi kit. A perforated board panel at the back (spaced

out with $\frac{3}{8}$ "-thick rubber washers to take hangers) keeps tools handy. And there's no rush to clear away before bedtime. The clutter can be left as is. With the lid dropped—and locked—the project-in-progress is safe from the kid brother's curiosity or Mom's urge to straighten up.

No fuss, no finishing. The desk's sleek good looks are achieved without hardware or fussy finishing procedures. And you can build it of inexpensive plywood. The secret: All visible surfaces are faced with a plastic-surfaced hardboard called



Marlite. Since it's impervious to dirt, grease, or ink, it's a cinch to keep clean. We used two types: $\frac{1}{8}$ " white for the top and drawer fronts, and $\frac{1}{4}$ " Swiss Walnut random plank for the sides and drawer pulls. The plank is actually a grooved wall panel like the American walnut pattern shown in the background above.


When applying the prefinished hardboard to large areas, use Marlite adhesive C-350. Small pieces can be bonded with white glue or contact cement. Cut all pieces a little oversize and plane them flush after they're attached.

Plans are simple, for quick construction. You can use $\frac{1}{2}$ " plywood throughout, but for greater stability we used $\frac{3}{4}$ " for the two-piece top, the four-piece workbench, and the notched right side. The recessed back of the drawer case is $\frac{1}{4}$ " plywood.

Build this case first, then make the drawers to fit. They're simple butt-joint boxes with $\frac{1}{4}$ " plywood bottoms. They don't need guides since they rest on dividers. Attached $\frac{1}{2}$ "-thick fronts hide all joints and overlap the case edges. Where they meet on a divider, each front overlaps halfway. The facing for the deep drawer can be center-scored or applied in two $5\frac{3}{4}$ " pieces, spaced a bit apart to simulate two drawer fronts.

Join the bench section to the drawer case and attach the screw-on legs and both top panels. The underside of the

CONTINUED



THE WELLSAW 400 ELECTRIC HAND SAW

Yes, a Wellsaw 400 with a 16" blade* actually cut a house in two in 30 minutes (see page 82, July, 1961, POPULAR SCIENCE). While we don't think many people will want to do this, it is a dramatic demonstration of the practical utility of this unique saw.

You just can't match the Wellsaw 400 for versatility. You can do just about anything with it that you can do with a hand saw—saw flush with support... cut big posts or beams... trim trees.

Try a Wellsaw 400 at your dealer's or use the coupon below for further information.

*Also available with 8" blade.



Wells Manufacturing Corp.
266 Service Road, Three Rivers, Mich.

☐ Send descriptive bulletin on Wellsaw 400


☐ Send name of nearest dealer

Name _____

Street _____

City _____ Zone _____ State _____

PSM 981



FRUSTRATED MISCHIEF-MAKER can't lift lid to reach inside. Chest lock (inset) is Corbin's No. 34 from American Hardware Corp., New Britain, Conn. Note how facing extends past notch in side to hide edge of false drawer's frame.

MARSH & ALL PRODUCTS, INC., has separate working plans for this versatile piece of furniture. If you like the convenience of working with such plans, address a postcard to Marsh & All Products, Dept. PR-5, Dover, Ohio, asking for the desk-hobby bench plans.


lid and the interior surfaces can be painted or stained—but leave the hardboard work surface unfinished. The top is propped open with a big hook and eye.

The plank facing for the sides of the drawer case should extend $\frac{5}{8}$ " at the front to conceal the edges of the drawers. The edge of the facing is covered with a metal molding, available where you buy the Marlite.

**Simple plywood is faced
with prefinished hardboard**



ATTACH DESK TOPS to complete assembly. The large, lipped panel is hinged; smaller one is screwed on top of drawer pedestal. Metal moldings are added at the front of pedestal and workbench to conceal edges of the hardboard facings.



FACING GOES ON LAST. Though scored for random-plank effect, side is single panel. Apply with special adhesive and slide block across surface, tapping with mallet to assure firm bond. Attach hardboard work surface the same way.



WHITE FACINGS are bonded to drawer fronts with contact cement. Before attaching spacer blocks, paint edges black, bore lead holes and countersinks. Wood-grain Marlite pulls are centered on blocks, cemented, and clamped.



New from Reynolds! **Aluminum Corner Posts**

Reynolds Aluminum Corner Posts are the easy way out of any cornering problems.

- No butting of joints
- No exacting angle measurements
- No elaborate corner finishing

And they're easy to use! Just slip the material into the open slots on either side and screw or glue into place. That's all there is to it. Corner posts may also be extended to form legs or supports on chests, cabinets or desks. Storage chests, paneled walls, furniture . . . all take on a real professional look. Available in 8 ft. sections to match any cuts, without waste, made from standard 4 x 8 ft. panels; for $\frac{1}{4}$ ", $\frac{1}{2}$ " or $\frac{3}{4}$ " thick materials. Reynolds Aluminum Corner Posts are now available at your hardware or building supply dealer; see them soon!

Watch Reynolds TV show, "Harrigan & Son," Fridays, ABC-TV




REYNOLDS METALS COMPANY
Richmond 18, Virginia

Home

Improvement Ideas





What's New



A slim new dishwasher fits into almost any kitchen layout. Patterned after the flexible-design concept used in cooking-range units, the dishwasher will go just about anywhere—tucked into an existing cabinet, hung below it, placed on top of a



counter, built into a wall, or used as a portable on a wheeled stand. The smallest of three models is only 13" deep, 15" high, and 30" wide. A new operating principle is said to save water and cut washing time in half. After dishes have

	
Has the face of our house changed!	We used to have this old basement door.
	
Till we heard about all-steel Bilco.	And replaced our old door.

Spring balanced Bilco Doors open at a touch... lock securely... are weathertight, cost so little! The door used on thousands of new homes!

The Bilco Co., Dept. R-109
New Haven 5, Conn.

Please send me your fully illustrated folder and name of local dealer

Name _____
Address _____
City _____
Zone _____ State _____

Bilco
AMERICA'S FINEST
BASEMENT DOOR


Today's "MAGIC" name
in wood finishing



America's #1
Quality
Finish

Fast dry, trouble-free. Nothing else to use from raw wood to final coat. Wherever paints are sold, or write for FREE Finishing Chart Folder.
P.O. Box 2216, Dept. PS-9, Torrance, Calif.

for Home Improvement



been washed, they are steam-treated for 12½ minutes. The steam comes from a built-in generator that creates its own distilled water to eliminate mineral spotting of dishes.

Complete cleaning takes only 25 min-

utes, after which the steam-hot dishes are air-dried. Because the water is recirculated, only nine gallons are used in all. Ling-Temco Electronics, Inc., P.O. Box 6191, Dallas, Tex., sells the dishwashers for about \$200 up.

CONTINUED

ARROW'S T-50 All-Purpose Heavy Duty STAPLE GUN


Get the gun that gets the job done *faster, easier and better!* It's a breeze! One *squeeze* and it's tiled — with Arrow's *one-hand operated* T-50 Automatic Staple Gun! And you always have *other hand free* to position work or balance self! This rugged, all-steel, jam-proof professional tool built for a long life of smooth, trouble-free operation!

Uses 6 staple sizes:
1/4", 5/16", 3/8", 1/2", 9/16"
and ARROW'S CEILTILE STAPLE
Specially Designed for Ceiling Tile

Shoots A Staple Wherever You'd Drive a Nail




CEILING TILE



INSULATING



UPHOLSTERING



SCREENING



WIRE FENCING

Pioneers and Pacesetters
For Over a
Quarter Century

ARROW FASTENER COMPANY, INC.

Our main office is located in...

AVAILABLE
at your local
Hardware, Lumber,
Building Supply or
Stationery Dealer.

THE EASIEST WAY IN THE WORLD TO DRIVE AND REMOVE SCREWS



1. After drilling pilot holes simply attach Versamatic to electric drill. Fits any make.



2. Place screw in hole, drive it easily with slight forward pressure . . . hold housing in fingertips.

3. Your fingers act as a clutch . . . starting, stopping action instantly. Simple and safe . . . no blisters.

Versamatic puts your power drill into low gear...



4. Versamatic runs in reverse for removing screws. You won't believe how easy it is until you try it.

by means of 7 to 1 speed reduction. Gives your drill 7 times more power.

Supreme Versamatic

MADE BY THE MAKERS OF
SUPREME BRAND CHUCKS

SUPREME PRODUCTS
CORPORATION

2222 S. CALUMET, CHICAGO

Sold by leading tool dealers...\$14.95 list

PRECISION  PRODUCTS

Home Improvement

News



Gutters won't clog with leaves if they're capped with these strips of galvanized screening. The strips slip under the shingles, and the outer edges clip to the gutter. They're sold in 3' lengths for 59 cents each by Reynolds Div., National-Standard Co., Dixon, Ill.



You can spray insect-killing fog over your whole yard quickly with this electric "gun." Oil-base insecticide is first atomized by a nozzle, then vaporized by heat into a thick cloud that kills both flying and ground insects. With the heat tip removed, the gun can be used as a conventional sprayer for weed-killer and other garden chemicals. It sells for about \$40 from Burgess Vibrocrafters, Inc., Grayslake, Ill.



New life for an old roof can be painted on with a rubber coating said to add 15 years of use at about a third the cost of reroofing. Designed for asphalt roofing, the coating seals leaks and cements down loose shingles and surface granules. It can be brushed, rolled, or sprayed on. A gallon covers 80 to 100 square feet, sells for about \$6. Superior Paint and Varnish Corp., 3065 N. Rockwell St., Chicago, makes the coating in four colors, including white for high heat reflectance.



You can build this three-view mirror yourself from plans offered free by the Masonite Home Planning Service, 111 W. Washington St., Chicago. Ideal for a dressing or sewing room, it folds flat, taking up no floor space. Cost is about \$35, including the three 4'-tall mirror panels. Pictures, shelves, or sewing supplies can be hung on the perforated-hard-board back panels.

CONTINUED

**There's a
DIAMOND
PLIER
for every job**


*"There is
nothing finer
than a
DIAMOND"*

DIAMALLOY

All shapes, styles and sizes to the user's choice—all incorporating outstanding Diamond quality. Ask your favorite dealer for famous Diamond Tools.

Only manufactured by

**DIAMOND TOOL
and Horseshoe Co.**

DULUTH, MINNESOTA  TORONTO, ONTARIO

For free tool booklet, write your name and address on margin below, clip ad and mail to manufacturer.

1

2

3

3 easy ways to bore holes faster

1. Irwin Speedbor "SB" for all electric drills. Bore up to 5 times faster in any wood, at any angle. Sizes $\frac{1}{8}$ " to 1", \$.75 each. Sizes $1\frac{1}{8}$ " to $1\frac{1}{2}$ ", \$1.25 each.

2. Irwin No. 22 Micro-Dial expansive bit. Fits all hand braces. Just dial your size. Bore 35 standard holes, $\frac{1}{8}$ " to 3". Only \$4.00. No. 21 small size bores 19 standard holes, $\frac{1}{16}$ " to $1\frac{1}{4}$ ". Only \$3.60.

3. Irwin 42T Solid Center hand brace type. Only 16 turns to bore 1" holes through 1" wood. Double-center boring action. Sizes $\frac{1}{8}$ " to $1\frac{1}{2}$ ". As low as \$1.05 each.

EVERY IRWIN BIT made of high analysis tool steel, heat tempered, machine sharpened and highly polished, too. Buy from your independent hardware, building supply or lumber dealer.

Strait-Line Chalk Line Reel Box

only \$1.25 for 50 ft. size

New and improved Irwin self-chalking design. Durable aluminum alloy box. Practically damage-proof. Fits pocket or hand. 50 ft. and 100 ft. sizes.

IRWIN every bit as good as the name

at Wilmington, Ohio, since 1885



WOOD FOLDING DOORS

ASH • BIRCH • OAK • PINE • PHILIPPINE MAHOGANY • AMERICAN WALNUT

HERE'S AN IDEA—Use PELLA WOOD FOLDING DOORS with their natural beauty of wood as room dividers, closures for closets, utilities, storage areas. Save floor and wall space. Easily installed. Order unfinished and save. Distributors in U. S. and Canada.

CLIP AND MAIL TODAY!

ROLSCREEN COMPANY, Dept. MC-51, Pella, Iowa
Please send free 6-page Folder on PELLA WOOD FOLDING DOORS.

NAME _____

ADDRESS _____

CITY & ZONE _____

STATE _____



Prefab walls go up so fast that an entire house can be enclosed in one day with these stressed-skin wall panels. Developed by Johns-Manville, they consist of insulated load-bearing sections for exterior walls, complete with door and window headers, plus panels for partition walls. Outside walls may be finished in board-and-batten style or with shingles or masonry. Interior walls are ready for paint or paper.




Walls that look like wood are actually grain-patterned plasterboard, giving a rich appearance at moderate cost. The 4'-by-8' panels come in two finishes, pine and teak, and are coated with clear plastic to prevent staining and scuffing. They're $\frac{3}{8}$ " thick and are easily scored with a knife and snapped to desired size. The panels, called Vinyl-Guard, can be nailed to framing or used to cover an existing wall. National Gypsum Co., Buffalo, N.Y., makes them.



A real masonry fireplace can be added to your home in a new, easy way for as little as \$275. The secret is a metal form that gives you the basic shape—you simply add a masonry facing, hearth, and mantel around it. The form, guaranteed smokefree, includes firebox, smoke chamber, downdraft shelf, and built-in damper. You also get tubular flue sections that go up through the house and a simulated masonry chimney for the roof. Complete units, including 12' 9"-high flue, sell for \$208 for 24" logs, \$221 for 28" logs. The Heatilator fireplaces are made by Vega Industries, 714 E. Brighton Ave., Syracuse, N. Y.

▶▶▶How to protect your home against lightning is told in a free booklet, *Lightning Facts and Figures*, offered by the Lightning Protection Institute, 53 West Jackson Blvd., Chicago. It gives tips on avoiding lightning damage. ■ ■

New from Weldwood® DEEP FINISH FIRZITE Penetrating Sealer-Finish



Oil finish without rubbing. New Deep Finish Firzite® produces a beautiful Danish-type "hand-rubbed" effect. Just brush on, wipe off!



Almost indestructible floors. Deep Finish Firzite penetrates the wood fibers—producing a beautiful low-luster finish that wears with the wood.



Seals as well as its famous predecessor, Clear Firzite! Deep Finish Firzite helps prevent grain raising or checking when used before paint or varnish, and "wild grain" when staining softwoods.

FREE—8-PAGE BOOKLET: "Professional Gluing And Wood Finishing Guide," for free copy, write: United States Plywood, Dept. PS 9-61, 55 W. 44th St., New York, New York.

Professional
Gluing and
Wood Finishing
Guide
1961-62

Weldwood

WELDWOOD WOOD FINISHES


Products of United States Plywood




Prize-Winning Home Improvement Ideas

Here, and on the following pages, is a selection of ideas that won prizes or special awards in the recent PS contest

To cool his home on hot summer days, A. E. Brochon, Old Lyme, Conn., ran a copper-tubing water line up to a soil-soaker hose stretched along the peak of the roof. Dripping water evaporates from the roof, cooling the house below. Any runoff just waters the flowers and shrubs at the sides of the house.



This study corner was designed and built by Drayton Deen, Stillwater, Okla., for his teenage daughter's small bedroom. The drop-leaf desk is lighted by a fluorescent fixture attached beneath the drawer section. Open shelves and a cupboard provide lots of needed storage space.



To save steps in answering the telephone, E. C. Toman, Allentown, Pa., has made it accessible from adjoining rooms. The instrument revolves on a turntable in an opening in the wall. Half of the turntable is enclosed with aluminum, blocking the opening. The telephone line is in the wall and passes through the center hole of the turntable. A stop keeps the line from twisting.



A Northern barn in small size was built in the back yard by F. W. Smith Sr., Miami, Fla., to solve the problem of no storage space in the house. "The barn's loft gave us the needed space and the kids love to use the lower part as a playhouse, rain or shine," he says. The miniature building is 8' by 12'.

A WILHOLD GLUE FOR EVERY HOME IMPROVEMENT JOB!



WILHOLD Glu-Bird WHITE GLUE

- GRABS FAST
- SPREADS FURTHER
- SANDS CLEAN
- DRIES CLEAR



WILHOLD BUILDERS ADHESIVE BONDS WOOD TO MASONRY

Sets Base, Trim, Furring Strips,
WITHOUT shims,
anchors or plugs



Los Angeles 31 WILHOLD GLUES, INC. - Chicago 12

Wonderful way to strip paint

This remover penetrates coat-after-coat of the toughest finishes. Can be used indoors or out.

Paint, enamel, varnish, etc. come off clean in one easy scraping - not coat by coat.

WONDER-PASTE REMOVER

At paint and hardware stores. Write for Wonder-Paste folder.

● Send 25¢ for helpful, illustrated Refinishing Manual
WILSON-IMPERIAL CO., 121 Chestnut St., Newark 5, N. J.



CLEAN as new!

PAINT-HARD BRUSHES are ready to use in minutes when you use Imperial Brush Cleaner. Acts instantly. Leaves bristles glossy and springy. Economical - used liquid can be saved for future cleaning.

At paint and hardware stores.

Send 25¢ for illustrated Refinishing Manual
Write for free folder "Care of Paint Brushes"

Wilson-Imperial Co., 121 Chestnut St., Newark 5, N. J.

IMPERIAL Brush Cleaner

Home Improvement Ideas




To get more counter and storage space, Irwin A. DeGraff, Winthrop Harbor, Ill., combined this kitchen snack bar with a swing-out rack for cans. The hinged rack has vegetable bins at the left end and rolls on a caster at the outer end.



To hide garbage cans, Thomas L. Robey, Larchmont, N. Y., built this slide-out carrier. Roller-skate wheels mounted under a plywood platform roll out on rails of 2" pipe. The carrier holds two cans, fits under a roof overhang.

screens, upholstery, carpets...
hundreds of other uses.



Swingline 101 Staple Gun

Staples practically anything. Exclusive push-button loading and built-in staple extractor. At your stationery, department or hardware store.

only **4⁹⁵**

FREE: New 8-page
"TIPS FOR TACKING" Booklet

shows you how to save time, money and effort—with a Swingline Automatic Staple gun. Send for yours today!



Swingline INC.

32-00 Skillman Ave., Long Island City 1, New York

OLD DOOR CLOSER ROUND-UP



Here's the all hydraulic closer that solves your storm and screen door closing problems. No more heel bumping, failure to latch or constant adjustments — when you have a Glidraulic.

- 15 Year Guarantee
- No Bounce
- Smooth, Even Closing
- Extra Latching Power
- More Power Against Wind
- Fluid Action, Needs no Adjusting


WRITE TODAY
See your Hardware Dealer

FREE
\$1

CERTIFICATE

If you don't have a closer to trade in. Just write and we'll send a certificate good for \$1.00 off at your dealer.

THE ILLINOIS LOCK CO.
307-13 W. Hints Rd. • Wheeling, Ill.



A built-in planter solved a decorating problem for J. R. Tucke, Pittsford, N. Y. It's located in a corner of the vestibule between the front entrance and a closet door. Potted plants and vines are kept in the enclosure sketched here.



Space under a cellar stairway, closed off by adjoining walls, was made accessible for storage in the home of D. W. Vandeven, Syracuse, N. Y., by hinging the lower stair treads. A screen-door hook holds up each tread.

FREE!

CERTIFIED

LIFETIME SHARPENING



WHEN YOU BUY YOUR COMET QUICK-SET DADO

—during this special offer, you will receive free sharpening by factory experts for the lifetime of the blades! You will receive a Certificate with your purchase of any Comet 6" or 9" Quick-Set Dado. This Certificate (plus \$1 for insurance, postage and handling) is all you need to save an average of \$4-5 each time the blades need sharpening. Only Comet can make this offer—because only Comet Dados stay sharp 5 times longer, are perfectly balanced to cut clean every time.

SPECIAL LIMITED OFFER EXP RES MIDNIGHT OCT .5—SEE YOUR LOCAL COMET DEALER NOW, OR WRITE FOR ONE NEAREST YOU

Offer good in U.S. only
Hurry! Send me the name of my nearest Comet Dealer:

Name:

Address:

City:..... State:.....



COMET MANUFACTURING COMPANY
875 Arroyo Parkway Pasadena, California

© Comet—1961



Short Cuts and Tips

FROM PS READER



Adding Holders to a Fire Set

Few stands for fireplace tools are equipped with an individual holder for each implement. Jumbling three or four together in one loose bracket makes it hard to pick out the tool you need. Make separate hangers by hacksawing $\frac{1}{2}$ " sections from $\frac{3}{4}$ " pipe and then cutting

slots in the sides of the rings wide enough to take the tools' shafts. File the rings smooth and drill a hole in each one for a small machine screw. The rings can be fastened to the arms of the stand with nuts; or, for a neater appearance, turn the screws into threaded holes tapped in the stand.—Herbert G. Eidson Jr., Winston Salem, N. C.



Brighten and protect your home with

SUPERPLY

the high gloss enamel that's so easy to apply!

This alkyd enamel is ideal for kitchens, bathrooms, woodwork and furniture. Keeps its brilliant porcelain-like finish after repeated scrubbing. So durable, people even paint boats with it!

ONLY
\$1.79
qt.

SUPERPLY SATIN, 100% Latex Paint

for walls, ceilings, woodwork. Just brush or roll it on... no laps or brushmarks, no trace of touch-ups. Dries in 20 minutes... no unpleasant odor.



ON SALE AT

WOOLWORTH'S and NEISNER'S
A. WILHELM CO. • READING, PA.

THE POCKET SIZE MACHINE SHOP

Dremel MOTO-TOOL


In your workshop, on your job — it's the handiest tool you'll ever own! Moto-Tool is ideal for precision grinding, polishing, carving, drilling, engraving, deburring, sharpening — does fine detail work with pin-point accuracy. It eliminates time-consuming hand work, gives the finished job a professional look. Moto-Tool weighs only 13 oz. — fits your hand like it belongs there. Fastest, most powerful tool of its kind — develops 27,000 rpm! Widely used by tool and die makers, model builders, craftsmen, lab technicians, repairmen, gunsmiths, schools.



Moto-Tool Kit No. 2
with steel case \$27.50
No. 2 Moto-Tool
only \$19.95

See your dealer or write
for free catalog.

DREMEL MFG. CO., Dept. 121-I, Racine, Wis.
Quality Power Tools Since 1934



Is the top of your chimney the warmest place around your house?

*Stack temperatures are cut as much as
200 degrees by this new Iron Fireman
CUSTOM Mark II oil firing with
VoluMetric Combustion*

*Saves fuel? Of course! When you stop that much
heat from blowing into the sky you've got to save
fuel . . . lots of it.*


Saves fuel, eliminates smoke and soot, substantially cuts service costs

Mr. Francis Woodworth, Center Junction, Iowa, tells us: "This is the furnace that cut my fuel bill in half. It operates without smoke, soot or odor. The service expense so far is nil." Hundreds of such letters report fuel savings of 18 to 50 per cent. How is this accomplished? First, VoluMetric Combustion not only reduces stack temperatures, but it practically stops standby loss (furnace heat lost through the chimney during "off" periods when the burner is stopped), which is the most serious waste of all. Second, the moment the burner starts, it transfers

heat into the system at the full maximum rate. No "warm-up" period; no delay while refractory heats. CUSTOM Mark II heating systems respond more quickly and shut off more quickly. Third, it burns fuel completely—no residue of smoke or soot, even when starting in a cold firebox. You prevent this waste, and also cut service troubles to almost nothing, because soot causes about 90 per cent of service calls due to coated heating surfaces, fouled electrodes, carboned oil nozzles.

Mail coupon for further information, sent free.

HERE'S THE SECRET OF VOLUMETRIC COMBUSTION



Natural chimney draft is erratic, undependable. The Combustion Flow fan (left) creates its own draft. No chimney draft is needed—simply a vent pipe through the roof (local codes permitting)

At the start of the firing cycle the fuel and air injector (right) supplies excess air to insure complete combustion. As the furnace warms up the air supply is diminished. A natural draft burner cannot make this critical adjustment and therefore starts with an air-starved, smoky flame. (Fifty or more starts a day)



CUSTOM Mark II fuel economy is due partly to its smokeless, sootless flame (smoke and soot are unburned fuel), and partly to its sealed combustion chamber which prevents the loss of furnace heat through the chimney or vent after the burner turns

off. No other firing system has ever eliminated this serious standby loss. Iron Fireman CUSTOM Mark II oil firing is available in a wide range of sizes for warm air, steam or hot water heating in homes or small commercial installations.

CUSTOM Mark II heating — white glove clean



IRON FIREMAN

HEATING AND AIR CONDITIONING

ELECTRONIC EQUIPMENT

CONTROL INSTRUMENTS

AIRCRAFT COMPONENTS AND EQUIPMENT

MISSILE AND AIRPLANE GYROSCOPES

Iron Fireman Manufacturing Company
3116 W. 106th St., Cleveland 11, Ohio
(In Canada, 80 Ward St., Toronto, Ontario)

I would like more information as checked


☐ CUSTOM Mark II furnace, ☐ CUSTOM Mark II boiler.

☐ CUSTOM Mark II horizontal furnace for
commercial or home heating.

Name

Address

City State or Prov



How to build a rear-projection cabinet for—

A Home Theater Wall


YOU can have your own home theater for viewing movies or slides with this rear-projection cabinet that can be built right into a wall or room divider. Placed alongside a TV set or hi-fi, it gives you a complete entertainment center for putting on shows. The projector remains permanently set up—you just start it going and sit back and relax.

The design comes from a new booklet entitled "Rear-Projection Cabinets," available free from Eastman Kodak Co., Rochester 4, N. Y. It's a trick done literally with mirrors. The projector is aimed through the side of the cabinet, and an angled mirror at the back reflects the beam onto a viewing screen.

The image is reversed by the mirror, but is then re-reversed correctly when you view it from the front. Projectors with long-focal-length lenses must be moved a few feet away to gain a full-size image. A low projector should be blocked up level with the mirror's center.

What kind of screen? The cabinet's back panel is automatically at the correct angle—you merely cement the mirror to it. Several types of rear-projection screens are available from photo dealers. Even white beaded-plastic shower curtain will work. Your best bet, however, is a special black screen made for the purpose. It produces brilliant images and can be viewed in full room light.

A plastic version, called 3-D Black, comes 20" square for \$6.75 from Trans-Lux Corp., 625 Madison Ave., NYC. A black-glass screen, also 20" square, is sold for \$16.50 by Edmund Scientific Co., 101 E. Gloucester Pike, Barrington, N. J. (order number 85,131). To avoid cutting the glass, the cabinet's opening can be enlarged slightly. The plastic can be cut with scissors.



**Join the Brand-New
POPULAR SCIENCE
BOOK CLUB!**

Get TWO GREAT SCIENCE BOOKS FREE with First Selection ^{AT} ONLY \$1.95

total value
\$9.00

**Become a Joining Member of the Brand-New
POPULAR SCIENCE LIVING LIBRARY PROGRAM!**

Here is a completely new kind of book club, created especially for POPULAR SCIENCE readers! This exciting book program makes it simple for you to build an ever-growing library of fact-filled, easy-to-understand science books at tremendous savings. In these exciting books you'll explore every aspect of modern science—from the invisible atom to the complex human machine to the vast solar system.

By joining the POPULAR SCIENCE LIVING LIBRARY PROGRAM *now*, you immediately get two free selections: **ELECTRONS GO TO WORK** and **VIRUS IN THE CELL**. With these two free books comes your first regular selection, **OUR ASTONISHING ATMOSPHERE**. Your bill for *all three* books (\$9.00 in bookstores!) will be a mere \$1.95! After this first shipment you receive a new, exciting LIVING LIBRARY selection every three months—at a *guaranteed* low price of only \$1.95. That comes to barely 2¢ a day!

You never pay in advance for POPULAR SCIENCE LIVING LIBRARY PROGRAM books and all selections are fully returnable within 10 days. You may quit the PROGRAM at any time by simply dropping us a line. So, mail coupon below **TODAY!**

YOUR FUTURE BOOKS WILL COVER OTHER THRILLING SCIENCE SUBJECTS!

New books in the POPULAR SCIENCE LIVING LIBRARY PROGRAM will cover such fascinating subjects as the living drama of medicine . . . the amazing world of animals and nature . . . the development of power from windmill to nuclear reactor . . . the conquest of space . . . the fantastic workings of the human body and much, much more! Drawing upon the riches of chemistry, biology, botany, archeology, atomic science, zoology, physics, meteorology, etc., the LIVING LIBRARY PROGRAM will bring you matched volumes to regularly enrich your growing, comprehensive home science library.

**You Get \$9.00 Worth
of Books in Your First
Shipment for ONLY \$1.95!**

MAIL COUPON TODAY!

**BUILD A VALUABLE SCIENCE LIBRARY
FOR ONLY 2¢ A DAY!**



ELECTRONS GO TO WORK. Here are the mysteries of matter from the heretofore guarded secrets of ancient Egypt to the unfolding of today's atomic theory. Learn of the fascinating role of the electron in radio, TV, radar, see how modern electronics can cook foods, harden plastics, count crowds, even sort oranges! Plunge into the amazing world of the future!

VIRUS IN THE CELL. This exciting book raises the curtain on one of today's great laboratory dramas of science against disease! Discover what happens when viruses attack humans, animals, insects, plants, learn the difference between germs and viruses; follow the thrilling victories over smallpox, yellow fever, polio; watch the exciting advances against the common cold, see actual photos of viruses taken through the electron microscope.

OUR ASTONISHING ATMOSPHERE (Your first selection, only \$1.95). Science on a spectacular scale! Here is a book charged with excitement and little-known facts on the vast bag of gases that envelope the earth like a filmy sea. Watch the seething turmoil inside a thundercloud, learn all about clouds and cosmic rays. See how people's breath actually can and does affect the world's climate. Read about the enormous forces that make our weather, the menace of poisoned air, much more.


POPULAR SCIENCE LIVING LIBRARY PROGRAM
355 Lexington Avenue, New York 17, New York

PS-961

YES. I wish to join the brand-new Popular Science Living Library Program! Rush my first big shipment of **Electrons Go to Work** (free), **Virus in the Cell** (free), and my first selection, **Our Astonishing Atmosphere**. For this \$9.00 book shipment you will bill me only \$1.95 cost of the first selection alone, plus postage. Hereafter you will send me a new selection every three months and bill me for only \$1.95 plus postage. I may examine each book free and return it without obligation if I do not want it.

NAME _____
ADDRESS _____
CITY _____ ZONE _____ STATE _____

New Ideas in Photography



ZOOM LENS is controlled by the same button and the same motor that operate the camera. Push up for wide-angle, down for telephoto—or stop anywhere between or zoom manually for special effects.

Dramatic movie zoom close-ups made easy by new Reflex Camera

Dramatic ultra-close zoom shots are easy with a Kodak Zoom 8 Reflex Camera—because you do your viewing right through the taking lens! There's no framing error—even at close range!


With this movie camera, you can show a face—then safely zoom in for expressive eyes . . . or for a youngster's missing front tooth . . . or for an identifying badge on a cap. You know the framing will be

exactly right! You can picture a flower bed—then zoom in confidently for the center beauty. Or show a single bloom, then zoom in for the butterfly on it!

The camera's motor-driven lens lets you zoom in and out with professional smoothness. Electric eye adjusts exposure automatically. A meter lock lets you switch from automatic to manual exposure control whenever you choose.

Kodak Zoom 8 Reflex Camera is less than \$200. Other Kodak movie cameras from less than \$27.

EXTREME CLOSE-UP MOVIE ZOOM is simple with Kodak Zoom 8 Reflex Camera. Through-the-lens viewing lets you compose your picture precisely. Low-cost Kodak Portra Lenses, attached to camera lens, let you come as close as 16 inches to your subject.



BEAM-SPLITTER lets you see in viewfinder the exact picture going to the film. It is an angled glass disc with a small translucent mirror spot in the center. Part of the light hitting the spot is reflected to the eyepiece—to produce a sharp, clear image.

from Kodak

New automatic cameras solve old problems of outdoor action

Two Kodak automatic 35mm cameras are bringing new freedom to outdoor picture-taking—where action is fast and conditions change quickly.

The Kodak Motormatic 35 Camera and Kodak Retina Automatic III Camera not only set the exposure for you automatically—they also let you select fast shutter speeds to handle fast action. And the Motormatic 35 Camera even advances the film for you—keeps you always ready for the next shot!

Fast action is only one outdoor problem—when picturing sports or frolicking kids, for example. Variable light is another—as when clouds are passing across the sun. And going from sun into shade is a third.

Fast shutters . . . electric eyes

The Kodak Motormatic 35 and Retina Automatic III Cameras handle all these situations easily. On the Kodak Motormatic 35 Camera, you can set the shutter up to 1/250—on the Kodak Retina Automatic III Camera, all the way to 1/500 second.

And each camera has an electric eye which reads the light continuously. When you press the shutter release, your lens instantly sets to the right opening.

Manual setting, too

If you wish, you can set either camera manually. The Kodak Retina Automatic III Camera also has a precision lens-coupled rangefinder for measuring distance. And the Kodak Motormatic 35 Camera has a special linkage for flash shots—as you change focus, the lens opening automatically adjusts for correct flash exposure.

Examine these remarkable ultra-modern cameras. One is just right for your kind of outdoor picture-taking.

See your dealer for exact retail prices. Many dealers offer terms as low as 10% down.



Electric eye sets lens for you

Flash link makes indoor shots easy

Motor drive winds film automatically

KODAK MOTORMATIC 35 CAMERA can take 10 shots in 10 seconds! After each shot, a tiny spring motor swiftly advances the film, cocks the shutter. Fast f/2.8 lens. Fully automatic lens setting. Full manual control. With this camera, you can keep your eye glued on the action, ready for the best shots, no matter how fast they come. For flash pictures 5 to 25 feet from subject, setting focus automatically sets correct lens opening. Less than \$110.



Electric eye sets lens for you

Rangefinder for precise focusing

Manual control for special uses

KODAK RETINA AUTOMATIC III CAMERA has superb Retina Xenar f/2.8 Lens. Fully automatic exposure setting, with override for manual control. Fast single-stroke film wind. Coupled rangefinder. Depth-of-field scale. ASA film settings from 10 to 1250. Shutter release locks if light is too dim or too bright. Less than \$130.

Now—snap fast action in color!


This weekend, start exploring the new picture possibilities opened by Kodak's ultra-fast 35 mm color film, *Kodak High-Speed Ektachrome*. With a sizzling daylight index of 160, it lets you take action shots in color that once were out of the question. Lets you get greater depth of field. Permits many indoor available-light shots with the camera handheld. Try it!

Prices subject to change without notice.


EASTMAN KODAK COMPANY, Rochester 4, N.Y.




Hints from the Model Garage



If a gasket sticks in the recess when you're removing spark plugs, fish it out safely and quickly with the hooked end of a wire-type gap gauge. Probing with the thin wire won't damage the threads or push dirt into the cylinder



When making a hole in the dash or fire-wall, avoid the danger of drilling through into wiring or equipment by slipping a dowel over the drill bit to limit its penetration. Applying masking tape will keep the dowel end from chafing the finish.



A thief will take off fast the moment he opens the door of a car equipped with this burglar alarm. The horn is the alarm, and it blows loudly and steadily when an intruder actuates the dome-light switch by opening the door. Slamming

the door shut *won't silence the alarm*; there is a second horn relay, wired into the existing circuit as shown above, that keeps the horn blowing until you return and flip a shut-off switch concealed in a spot known only to you.



Jaguar's new XK-E convertible


Jaguar engineers specify
Champion spark plugs
because they demand the utmost
in quality and performance.

Why settle for less in your car?



CHAMPION



More Hints from the Model Garage




Interior of your car shabby? You can renew the appearance with little effort by painting the trim molding around the windows and windshield. These parts are easily removed. Sand them smooth and hang them on a wire for spray-painting.




Air leaks at the rim seal of tubeless tires can be detected without immersing the wheel in a tank of water. Just lay the wheel flat, pour water around the rim, and watch for bubbles. Repeat the test on the other side of the wheel.



Tips on draining oil: (1) Slit an eight-quart can near the top and press the side in. Oil will run down the trough and into the can, where it is retained when the can is picked up. (2) Use the lid from a garbage can to catch scattered



drips when removing the oil filter. (3) Solder a quart juice can to the cap of an eight-quart can and join them. The tall juice can will catch oil as it runs out of the crankcase. The oil will flow through the cap's hole to the large can.



This car needs Load-Levelers. Does yours?

Does your car sway dangerously around curves? Does it "bottom" on the frame when you hit a bump or rut? Does "tail drag" cause your rear bumper or tailpipe to scrape on driveways? Your car needs Super Load-Leveler® stabilizing units to compensate for the added weight of passengers and luggage, to keep your car riding its level best under all road and load conditions. And, in keeping your car level, they hold your headlight beams on the road, out of the eyes of oncoming motorists. Have a set of Super Load-Levelers installed today wherever you have your car serviced. *Monroe's 60-day free ride plan guarantees you complete satisfaction.*



LOOK FOR THE YELLOW AND BLUE SAFETY BARREL WITH THE SHOCKS ON TOP!

MONROE

MONROE AUTO EQUIPMENT COMPANY • MONROE, MICHIGAN • In Canada, MONROE-ACME LTD. Toronto, Ontario
In Mexico, MEX-PAR, Box 26154, Mexico City • World's Largest Maker of Ride Control Products, Including MONRO-MATIC® Shock Absorbers





Gus Makes a Fast Getaway

By Martin Bunn

OPEN to late-summer warmth, the doorway of Gus Wilson's Model Garage suddenly darkened with the bulk of an entering car.

"Come on out, Gus!" bellowed the driver "No use sneaking under a car."

Gus came out of the office, grinning "Our big-mouthed fire chief! Haven't been eating much smoke lately, have you Mal?"

Chief Maloney's seamed face puckered into a frown. "It has been kind of quiet. How'd you know?"

"Couldn't yell like that if you'd been earning your pay," cracked Gus.

"At least I don't diagnose auto jobs wrong and make people pay for my bum guesses!" roared Maloney.

"So what can I soak you for?"

"Got a noise. Boys at the firehouse say it's a bad water pump. Listen!"

Gus cocked an ear over Maloney's five-year-old sedan. It idled with a regular, metallic twang.

Stan, Gus's young helper ambled over. "Pump bearing's shot," he said.

Maloney cut the engine "Good thing you've got a real mechanic, Gus," he roared. "Or you'd be charging me for something else. Have it tomorrow, huh?" He started out, but swung back. "Give my best to Nora Blythe, Gus."

Gus started. "Nora Bly—you mean Mrs. Simpson?"

"She's a rich widow now, back from Florida to settle her husband's estate," said Maloney with a wolfish grin. "I've sort of fixed it for her to see you."

"Now hold on—" began Gus.

"Didn't take much fixing," was the Chief's parting shot. "She's willing."

AN HOUR later, Gus got his hat. "I'm going upstate to see Tom Powers about overhauling his truck."

"But he said there's no rush," protested Stan. "I've got that brake job, and you promised to put that new radiator in Bronson's car today."

"You handle 'em," said Gus with uncharacteristic brusqueness. "I'll be—"

A horn blast interrupted him. From a shiny convertible, a mature, youthfully dressed woman with red hair called, "Gus! Gus Wilson!"

Hastily Gus walked over to the car.

"It's wonderful to see you again," said Nora Simpson warmly. "I've thought of you so often. I really have."

"Been a long time," said Gus.

"And you've never married! Naughty you," she cooed. "Look what Chief Maloney left on my car yesterday."

A slip headed "Fire Department" stated that the car had been found leaking gasoline in the street, and that excess gas had been drained from the tank as a safety measure. A suggestion that any necessary gas-tank repairs be made immediately was underlined. The slip was signed by Malcolm Maloney.

Equally annoyed and amused, Gus told Stan to put the car on a lift.

"Mal's very conscientious," Gus said to Mrs. Simpson. "But I think we can have you out of here very quickly."

The handsome red-haired woman pursed her lips prettily. "Are you in a hurry to get rid of little me?"

"No, no, of course not," fumbled Gus. "But I thought you might be—"

"I have oodles of time until I have to sign things at my lawyer's."

"Yes, ma'am," said Gus miserably, and took refuge under the raised car. "There's not a thing wrong with your gas tank," he reported presently.

"But it was leaking gas!"

"Somebody overfilled it with cool gasoline from an underground tank. It was a hot day. With the car in the sun, that tankful expanded. Some had to get out, so it spilled over."

"That's all that was wrong?" asked Nora Simpson.

"That's all," said Gus firmly. Motioning Stan away, he escaped further talk

by lowering and turning the car around to get Mrs. Simpson on her way.

SURPRISING Stan, Gus now forgot all about going to the Powers farm. Instead, he tackled the radiator job. And the convertible rolled back in.

"I forgot," said Nora Simpson triumphantly. "My no-charge light is on."

Silently Gus peered at the dash. The charging indicator stayed lit even when she revved up the engine.

"Tiresome," she pouted. "I had a new generator put in on the way up here because that light stayed on."

"Could be your voltage regulator," said Gus. "Or something even simpler."

"Well, do put in a new voltage thing, Gus."

"Could be just a loose wire."

"No, the other man said it might be that voltage thing, too. I want a new one. Then it's sure to be all right."


"Yes, ma'am," said Gus dubiously as, with a flirt of a braceleted wrist, Nora Simpson tripped out of the shop. With some misgivings, Gus ordered Stan to install a new voltage regulator.

"That car has a printed instrument circuit," Stan reported later. "With a fuse in it. I checked that, too. Everything works, so she shouldn't be coming back again."

Gus looked at him narrowly. "Okay. You finish the radiator job, because now I am going up to Tom Powers' place."

RELIEVED to see the convertible gone when he entered the Model Garage next morning, Gus set to work on the Maloney sedan. He removed the belt that drove the water pump. Then, just to

Where'd it come from?



The equal sign

Good mathematicians as they were, the Hindus by the 11th century had a sophisticated symbol for equality, three dashes

But the Arabs, responsible for spreading much Indian learning through Europe, in this case went back to more literal expressions. As late as the beginning of the 16th century, if you wanted to say two things were equal, you spelled it out: "fera egale." But by mid-century an Englishman, Recorde, had come along to father the modern sign. In his *Whetstone of Wit* issued in 1557, he selected the double dash = because "no 2 thyngs can be moare equalle."

check the diagnosis, he started the engine.

The tinny clank was still there.

"Sure sounded like a pump bearing," remarked Stan, a bit crestfallen.

"Sure did," agreed Gus, leaning close to the left-hand cylinder bank. "It also sounds like a broken valve spring in number one cylinder. Let's—"

A familiar horn interrupted him.

"I hate to bother you," called a smiling Nora, "but it's lighting up again."

The charge indicator was mockingly alight. In grim silence, Gus put a meter on the generator. It was charging. The regulator, too, worked perfectly. Along-

Gus explained hastily. "Salt-water corrosion caused a bad contact. You didn't need a new generator or regulator."

"Oh, well," she said mollified. "But I do wish you'd visit Florida."

"My sinuses can't stand sea air," lied Gus. "Now Mal, he just loves it. Always wanted to fish for tarpon, too."

Almost absently-mindedly Nora Simpson started the engine. The indicator winked out. Thoughtfully she drove away.

"WHERE'S the ham-handed boss?" "Over here," retorted Gus. "Trying to figure how to get even with you."

Maloney guffawed. "It wasn't all a gag. Her car was spilling gas, Gus."

Gus grunted. "Keep laughing—I've got bad news. We put a new pump in your car, but the noise stayed. Thought it was a busted valve spring then. But after we pulled the head, we found them all okay—"

"Ho-o-ld it!" bellowed Maloney. "You did two jobs I didn't need?"

"Tough break," said Gus, starting the engine. Under its smooth idle was the metallic twang. Maloney turned brick red.

"Notice how awkward it is to pull the dipstick out? It's under the generator. The double pulley makes it harder."

Grasping the dipstick, Gus yanked. It came out—and the noise stopped.

"You almost have to bend the stick to put it back," explained Gus. "And some serviceman did. See how shiny the bent part is? It's been hitting the first crank throw. Easy enough to straighten. I won't even charge you—for that."

"But you'll soak me for a new pump and for pulling the head!" sputtered Mal. "Why didn't you find this first?"

"Relax. I did," admitted Gus with a wicked grin. "The dipstick's in front of number-one cylinder, where the noise came from. So I checked. Are we even?"

"Cagey, aren't you?" rumbled the chief. "That how you stayed single with a gal like Nora Blythe chasing you?"

"No," said Gus. "It was by running a bit faster than Ed Simpson." ■ ■



side him, Nora chattered on amiably.

"You look so well, despite the awful winters you have here. You should move to Florida—such good fishing and—"

Gus ducked under the instrument panel. If the fuse were blown, the indicator would "fail safe" by lighting. He shorted the fuse clips with the engine running. The light went out.

He removed the fuse. It wasn't blown, but the light he turned on the clips showed green corrosion. By handling the fuse, Stan had restored contact until, overnight, creeping corrosion had again interrupted it. Gus stopped the engine, cleaned the clips, put back the fuse.

"Do you keep this car near the shore much?" Gus asked as he got out.

"A great deal. We have a seashore cottage. I'd just love to show you."

"That's your trouble, Nora."

The curved lips set angrily.

"I mean that sea air at the shore,"

Why a good tune-up includes Spark Plugs

Some people do engine "tune-ups" and never look at the spark plugs; others service or replace spark plugs, and that's all. Either of these operations can give a temporary lift to engine performance—but it's only temporary, you can be sure. A good tune-up *starts* with spark plugs, then checks all the things that affect their operation—compression, battery, coil,

distributor, timing and carburetor. In a good tune-up, the prime concern is the proper functioning of the spark plugs, for only when spark plugs are right and everything that works with them is right, is your engine conditioned for long-lasting top performance. So, for the very best results, make sure your spark plugs are checked when your engine is tuned.

Why the best tune-up includes AC Fire-Ring Spark Plugs

Your engine will perform better—longer—if the tune-up it gets includes new AC Fire-Ring Spark Plugs. AC Fire-Rings have a host of superior performance and reliability features. ACs give you the exclusive Hot Tip that provides self-cleaning action as you drive. ACs are built with heat-bonded internal seals and pressure-

formed external seals for positive prevention of gas leakage, overheating and pre-ignition. ACs have exclusive Buttress Top insulator for greater strength and better wet-weather firing. In every area, ACs offer the most advanced design. For the best tune-up, make sure your spark plugs are ACs.

AC SPARK PLUG  THE ELECTRONICS DIVISION OF GENERAL MOTORS



BUILT BEST FOR EVERYTHING YOU OWN THAT RUNS ON GASOLINE

Why They Don't Make Cars Safe

[Continued from page 20]

Most of all, why do we continue to tolerate those chromium-plated stilettos so malevolently aimed at heart, brain, and legs? There are trim screws and ash-tray knobs that pierce skulls, ignition keys and parking brakes that shatter kneecaps, dash panels that hit knees to break hips. Deadliest, perhaps, is what safety experts refer to among themselves as the "cookie-cutter horn button." This is a sharp ring of chrome that for several years has been fitted to the center of some dished wheels. In a moderate collision the wheel spokes bend down and the cookie cutter punches right through the breastbone to the heart. A driver who could have come out with broken ribs ends up dead.

The needless tragedy caused by such designs was vividly illustrated by Dr. William Haddon of the New York State Department of Health. He told the Society of Automotive Engineers:

"I chanced to be first to arrive at a head-on collision at low speed between late-model cars. A practical nurse who had been driving was thrown across on a small screw projecting only an eighth of an inch from the sun-visor bracket. She left a piece of her scalp and her gray hair on it as it ripped her scalp in the fashion of an Indian almost from her hairline to the back of her head."

Then Dr. Haddon quietly added: "I think it is reasonable to say that someone placed that screw there by design."

The known hazards

Much can also be done to *prevent* accidents.

You can't always see the road clearly. Not all cars have windshield washers. Some wipers are sloppy.

Multiple mirrors or periscopes are essential. Today's inside rear-view mirror helps your wife get her lipstick on straight, but not much else. And the outside mirror—without which no savvy trucker or bus driver would even start his engine—is an optional extra on most passenger cars.

These things are simple and fairly cheap. The need for them is obvious. A smart 15-year-old boy could look around a modern car and tell you how to make it safer. But if common sense isn't

enough, the research reports overflow the files.

A deadpan statement from the staid Liberty Mutual Insurance Co. is illuminating. In a pamphlet describing the company's modification of a '60 stock sedan into "Survival Car II" appears this offhand remark: "The immediate problem was to redesign the known hazards out of the car."

Why don't they make cars safe?

The answer is disturbing: Nobody forces anybody to do it. Worse, all kinds of pressures from many sources work against it.

Detroit bears the brunt of the blame, more than is warranted. Its view was put by L. H. Nagler, staff safety engineer for American Motors, who said recently:

"The automobile industry has promptly adopted safety equipment and designs proved to have definite safety values, where economics and public acceptance have not been seriously adverse . . ."

It's that last clause that kills you. Economics are almost *always* adverse. Safety devices cost money; they raise the price of cars at least a little—and in an intensely competitive business that endangers sales. Detroit is also convinced that "public acceptance" is usually adverse, that a safety pitch scares customers away. Ford still bears scars from 1956, when it sold much safety and fewer cars.



Yet the industry cannot shuck all responsibility. Those lethal skull-crackers and eye-gougers sprinkled over doors and dash panels could be eliminated at no cost in money or public acceptance. They have not been.

You can't expect Detroit to move on safety without sharp prodding. The case of the seat-belt anchorages—those four holes in the floor—is an example.

Detroit nurtures the impression that these four free holes are being provided voluntarily out of the goodness of the industry's heart, an agreeable marriage of commerce and public interest. Actually, it was a shotgun wedding.

The man with the shotgun was a tough and savvy lawyer-politician from Mineola, Long Island: New York State Senator Edward J. Speno, chairman of


use these new **PANELING IDEAS**



*This booklet of design and color ideas
free at your lumber dealer's*

Get this free booklet on wonderful new ideas in solid lumber paneling. See how *only* solid lumber paneling lets you obtain striking uses of color on wood . . . offers dozens of variations in pattern, design and texture. And how easy and economical it is to install. There are ten different Western Pine Region woods and numerous interesting interior textures and finishes to give your home the beauty and warmth that only genuine lumber can provide.

Your local lumber dealer will help you select the right materials and methods. See him for your free paneling booklet. If he is unable to supply you, write to Western Pine Association, Dept. S-4, Yeon Bldg., Portland, Oregon, giving us the name of your dealer. Please enclose 10c for handling and mailing.



WESTERN PINE ASSOCIATION Quality Graded Lumber

IDAHO WHITE PINE • PONDEROSA PINE • SUGAR PINE
WHITE FIR • LODGEPOLE PINE • DOUGLAS FIR • LARCH
ENGELMANN SPRUCE • INCENSE CEDAR • RED CEDAR



Why They Don't Make Cars Safe

the legislature's committee on motor vehicles. Speno proposed a law requiring anchorages on all new cars licensed in New York. That was nothing. Similar bills pop up and wither all the time.

What rocked Detroit was the discovery that Speno had the determination *and* the votes to pass his law. Faced with the inevitable, Detroit agreed "voluntarily."

It took the power of a state legislature to force a change for safety—and a very minor change at that.

And the power of the public?

Couldn't ordinary car buyers force manufacturers to offer safe cars? They could, but they don't. Seat belts have been available since 1956, but fewer than two cars in 100 have them. Only about one in three car buyers coughs up \$20 for dash padding, although radios costing three times as much are bought by 90 percent.

It is unrealistic to expect the entire public to act like paragons of virtue—especially when it means facing facts and spending money.

Can't insurance companies put the squeeze on car buyers by offering cut rates for properly fitted cars? They do exactly this with factory owners. If the factory installs safer machines, the workmen's compensation insurance gets cheaper. If the factory tries to get away with an obvious hazard—like leaving shields off grinding wheels to speed production—the insurance may be canceled completely. The shop is shut down.

This simple economic pressure has made American factories into just about the safest places in the world. But such a squeeze play works only because the insurance companies take in premiums and pay out claims to the same group: the factory owner and his employees. A safer factory means fewer claims *from that factory*, and therefore cheaper rates *for that same factory*.

Car insurance is different. The company collects premiums from you, but usually pays damages to somebody else—somebody it doesn't know, driving a car it doesn't know. You could be driving the safest car possible. If you hit another guy, your safe car might protect you completely. Your insurance company might be happy for you, but it wouldn't save

much money; it has to pay the other guy. So how can it give you a cut rate for your safe car?

Then there ought to be a law

State laws have regulated automotive equipment for more than 60 years. But with rare exceptions (like Speno's seat-belt holes), the states never prod Detroit. They meekly follow Detroit's lead.

When auto makers wanted dual headlamps—a safety improvement that also carried styling advantages—the state administrators were brought in and sold the new idea. The laws regulating headlamps were then amended.

The state agencies do not have the money, the people, or even the clear authority to specify improved auto design. This may be a blessing. Chaos is in sight if headline-hungry politicians in 50 states, their appetites whetted by Speno's success, legislate their own pet safety gimmicks.

That leaves the Federal Government. It already regulates the design of every other vehicle—ship, train, and airplane. Why not cars, which are just as vital to interstate commerce? Only the Federal Government has the power and the facilities to do the job right.

It needs doing right, desperately. ■ ■

Fill 'er up!



An incongruous mixture of the old and the new took place when this mule-drawn wagon rolled into a Memphis service station to get some air in its pneumatic tires. Adjust the blinders, sir?

CHOOSE YOUR JOB TRAINING - THEN LEARN BY DOING

Challenging work—if you can get it. To land a job as a Bulldozer Operator, you need training. The kind of training you get through the Army Choose-It-Yourself System.

If you qualify (by passing aptitude and physical exams), this system lets you choose your job training before you enlist.

On-the-job or in school, Army training is practical. You learn by doing. The skills you absorb can pay off for the rest of your life.

You can choose from many different kinds of job training. Construction Machinery Operation is one possibility.

There's also Telephone Maintenance, Missile Operations, Administration, Military Police, Radio Relay & Carrier Operation—to name a few. Ask your local Army recruiter to show you a complete list.

Can you qualify for the job training you want? It's easy enough to find out. Before enlistment. Without obligation.

CHOOSE-IT-YOURSELF



VOCATIONAL TRAINING SYSTEM

US ARMY





**THE
NEW**

Dyna-Glas SOUND
MAKES YOUR CAR

stand out



Sing the song of the sixties with Dyna-Glas whispering power. Rocket-age fiber glass packing — and exclusive "Whisper Chamber" — release built-in factory power — but lullaby low.

The Dyna-Glas flat oval shape snugs into place and installs in minutes. You're back to the original equipment look with *more* road clearance — *more* power — *more* zip — and the "mellow without bellow" sound of the sixties.

For mufflers of original equipment type — see the Goerlich Standard or Master models. Each is a top value!



GOERLICH'S, Inc.
MUFFLERS AND PIPES
Dept. A-2, 619 Smith St., Toledo 1, Ohio

Atomic Accident That Couldn't Happen

(Continued from page 55)

Army men from Dugway Proving Grounds, Utah, got the last body down from the ceiling. A crane boom, poked through a cargo door, swung a net over the reactor lest any falling object jar it. Five teams of two men each, working in relays, lowered the body into the net and the crane backed out with it.

Concussion had killed these two crewmen instantly, medical examination showed.

All three, besides, were fatally exposed to radiation. As if from a shotgun, radioactive particles were driven into their bodies by the blast; the victims were so "hot" that it was 20 days before funerals could be held. They were buried in lead-lined vaults.

The investigation. A team of five investigators headed by Curtis A. Nelson, director of AEC's Division of Inspection, arrived shortly after the blast and began sifting clues. Photos of the scarred reactor room were soon in their hands. A cameraman in mask and coveralls, given 30 seconds for his task, took the first on January 5.

Clearly the reactor had exploded. Its metal cover was wrenched upward. Heavy fittings called shield plugs, closing the reactor ports, had been sent flying. Two were embedded in the ceiling.

But only over the reactor was a light bulb broken; others were still burning. A steam blast would hardly be so localized — straight up. Apparently water had been explosively hurled from the reactor.

Proof that the reactor ran away was announced on January 19. A brass screw of a crewman's cigarette lighter, AEC analysts found, contained copper 64. So did a brass watch-band buckle worn by another victim. In the third man's gold ring was gold 198. Only in one way could those telltale radioactive substances have been formed — by flying neutrons from a runaway chain reaction.

Would the reactor explode again? On Feb. 22, a camera on a crane boom got the first pictures of the reactor's wrecked interior. Observers with telescopes, atop a wooden tower 200 feet away, directed the crane man. But even a Navy photo interpreter could not tell from the pictures whether the reactor was safe.

Thus, entering the reactor room was

Atomic Accident That Couldn't Happen forbidden, after recovery of the crewmen's bodies (which the first photos had helped to plan). For three months—until probes found the reactor empty of water and safe—new clues were hard to get.

So, for more light, the probers turned to delving into the two-year-old SL-1's past history. What they found was enough to make their hair stand on end.

The search into SL-1's past. Designer and builder of SL-1 was the famed Argonne National Laboratory, Tiffany of reactor makers. Much of its design was admirable. Some out-of-the-ordinary features proved otherwise.

Immersed in water, the core's fuel elements were shaped like square organ pipes, and contained uranium 235. The heat of its chain reaction boiled the water. The steam ran a 200-kw. turbo-generator, and warmed air for heating.

Five motor-driven cadmium control rods regulated this atomic boiler. Lowering them into the core stopped the heat-producing chain reaction; raising them started and accelerated it.

Since water had to surround the fuel for the chain reaction to occur, such a "water-boiler" reactor was supposed to be runaway-proof. Steam bubbles would push the water away from overheating fuel elements—and halt an out-of-control chain reaction. True, that could eject a geyser of hot water and steam, if the control rods were pulled out far and fast. But if SL-1's fuel elements went "pfft," safety valves could handle anything that happened—because its control rods' motor drives enforced safe limits on the rods' travel and speed.

But what would happen when the rods were not connected to their drives? Overlooking this eventuality was the flaw in the reasoning—because of a decidedly unusual feature of the SL-1's design:

An important clue. One control rod, the center one, was "strong" enough to start up the reactor all by itself. When this rod was disconnected and moved by hand, one man could undo all the runaway-proofing.

On Jan. 3, using a T-shaped handle, a crewman had to lift this 80-pound rod just high enough to reconnect it to its driving pinion. "Not more than 4 inches," said his instruction manual.

Raise it 16 inches, and the sleeping

CONTINUED



CITY STREET, OPEN ROAD OR MOUNTAIN TRAIL

HONDA'S FABULOUS "50"

THE NEW LOOK IN LOW-COST, HIGH-FUN
PERSONAL TRANSPORTATION!

No other motor vehicles—two-wheeled or four—have created a greater sensation throughout America and other parts of the world than the amazing new HONDA "50"s. They're converting thousands of men, women and youngsters every month to two-wheel travel—to work, market, school and outdoor fun. This year, over one million people will buy HONDA "50"s!

You have 4 light, lively and unbelievably economical models to choose from... precision-built beauties that cost only \$275 (there's even one for \$245), get up to 225 m.p.g., take you places at a whisper-quiet 40 m.p.h.

Easier and safer to ride than a bike, the HONDA "50" has an automatic clutch and 3-speed transmission that shifts with a simple touch of the foot. The revolutionary 50 cc 4-stroke OHV engine delivers 5 lively horsepower, is practically maintenance-free and uses pump gasoline (no messy oil & gas mixture!).

For hunters and fishermen, nothing on the market equals the performance of HONDA'S Trail "50". It'll take you over desert and mountain country where not even a Jeep will go. The rugged gearing (low gear 82 to 1) climbs 45° grades with full load, takes you over rocks, logs, through underbrush. Quick-change rear sprocket for speeds up to 45 m.p.h. Knobby-traction tires, dual-cam type brakes and hydraulic shocks both front and rear for easy handling over roughest terrain.

See HONDA'S four fabulous "50"s at your sporting goods, bicycle or motorcycle dealer.



For nearest dealer, call Western Union by number and ask for OPERATOR 25. Or visit nearest dealer for full facts.

AMERICAN HONDA MOTOR CO., INC. Dept. PSR-9
4077 West Pico Boulevard Los Angeles 19, Calif.
Please send me literature on the HONDA "50" line to:

NAME _____
STREET _____
CITY _____ ZONE _____ STATE _____

☐ I am especially interested in Honda Trail "50"
☐ I include information on Honda mopeds and other 10 models available from 125 cc to 350 cc
☐ I am interested in dealer franchise information

EASY DOES IT!

Remove snow
faster, easier
with Monarch
Power
Hydraulic
Controls!



The heart of the job is Monarch!

Now's the time to install a Monarch unit for fast snow removal this winter. Lift, lower your snow plow with a flick of the wrist right from the cab with Monarch Controls! Instant up-and-down action.


Can be installed quickly. See your dealer or write for illustrated folder.

MONARCH



MONARCH ROAD MACHINERY COMPANY
1331 Michigan St. N.E. Grand Rapids 3, Michigan, U.S.A.

SAVE MONEY ON POWER TOOLS & WORKSHOP SUPPLIES WOOD



World's Largest Selection, Rare, Fancy and Imported Woods, Mosaic Tile, Lamp and Upholstery Supplies, Tools and Hardware! All at Money Saving Prices!

Send for this complete new wood buying guide and project book. Craftsman is your best most complete source of finest kiln dried domestic and rare imported woods, beautiful wood inlays, colorful bandings, matched plywoods, furniture edge embossed moldings, carved ornaments, newest wood-working tools, hardware, cabinet hardware and fittings—more than 500 items! Packed with new patterns, project ideas and money-saving plans. Enclose \$2 to help pay mailing and handling cost. Write:

CRAFTSMAN WOOD SERVICE CO.
2729 S. Mary St., Dept. B-3, Chicago 8, Ill.

NEW 140 PAGE CATALOG Send Today!

Save on Parts, Equipment!

Send for America's most complete, exciting Electronics Catalogs. Radio Shack's bigger, better than ever 336 page Buying Guide plus supplements for 12 months! See Stereo, Hi Fi, Ham Radio, Tapes, Records, Kits. No money down credit terms. Satisfaction guaranteed.

FREE ELECTRONICS CATALOGS for 1 full year

RADIO SHACK Corp.
736 Commonwealth Ave. Boston, Mass.

RADIO SHACK Corp. Dept. 6148
736 Commonwealth Ave., Boston 17, Mass.

Send me Radio Shack's famous electronics catalogs for 1 full year—all FREE and POSTPAID.

Name _____
Address _____
City _____ Zone _____ State _____

MAIL Coupon TODAY

Atomic Accident That Couldn't Happen
reactor would come to life; 22 inches, and the awakening could be violent. A simple safety stop could have guarded against that. The SL-1 had none.

A mock-up of the center rod was built. Trials proved a strong man could have yanked it high and fast enough to cause the runaway. The most likely scene at the moment of the accident, the A-detectives concluded, was this:

A crewman was lifting the center rod. Possibly another was helping him.

But pulling so hard could have been no careless slip. Why do it? The SL-1's Operating Log revealed a likely answer:

Sticking control rods had plagued the SL-1's crews—40 times in the last two months. Sometimes the binding of the rods in their close-fitting housings was so severe that a crewman with a pipe wrench had had to help the motor pull one out.

So this, said the sleuths, was their "suggested hypothesis" of what happened:

When the crewman tugged at the center rod, it balked. To free it, he gave a mighty heave. Like a stuck window coming unstuck, the rod suddenly shot upward—and the explosion followed.

Other things wrong. But control rods were not all that was out of order.

Another unusual SL-1 feature was this: To prolong the life of the core, it was crammed with a three-year supply (30 pounds) of enriched uranium. That was altogether too much for the control rods, unaided, to hold in check. So "poison" strips—so-called because they weakened the chain reaction—of aluminum-coated boron were tack-welded to the outside of the aluminum-clad fuel elements. As the uranium burned up, so would the boron. The idea was fine; the material, faulty.

The brittle strips warped, cracked, shed fragments. Bowing out, they jammed fuel elements—and must have squeezed the control rods' housings, too, which may have caused the sticking. In pulling out fuel elements forcibly for inspection, their poison strips were shattered, some ripped off.

Ominously sinking control-rod settings warned that SL-1's margin of safety was dwindling. To replace the decrepit core, a new one of different design and make was ordered, for spring of 1961—just a

Atomic Accident That Couldn't Happen few months too late, as it turned out.

The "distance to death." No one knows how much boron the SL-1 shed during its last shutdown, from Dec. 23 to Jan. 3. The estimate that the center control rod had to be lifted 22 inches to cause a runaway was based on control-rod settings when the reactor was last running. If much boron fell off after that, the "distance to death" could have been even less—somewhere between 4 and 22 inches.

That would have made it easier for the accident to happen—with or without the complication of a sticking control rod.

Which of SL-1's faults contributed most to the accident may never be known—but the mystery of what could have caused it was solved. What probably happened was vividly pictured.

Who were to blame? Many, said the report of the Nelson board of probers:

The designer: For failing to provide a safety stop, or test the boron strips adequately ("probably not defensible").

The operator: A "prudent" one would have shut down the SL-1 as unsafe. (It should have, CE agreed.) That was the major one of a number of misjudgments.

The AEC, too (said its own probers): Why did it let the SL-1 go on running? Astonishingly, its Washington headquarters was unaware of how serious the SL-1's defects were; even its Idaho office was poorly informed. Liaison had been faulty among the groups at NRTS, and between Idaho and Washington.

Horried by the SL-1's blot on its outstanding safety record, the AEC set in motion a huge-scale safety survey of all reactors. Just one other was found, a military one in Greenland, that could be started with a single control rod; at once a safety stop was installed. While all was well with the rest, safety and reporting procedures got tightened up.

Lastly, the AEC will disassemble the wrecked SL-1 for any further clues. That may take well into 1962. Radioactivity, though down to 100 r's an hour by last June, will be too high for months to work there. Probably remote-control mechanical arms must do the job. Experts doubt much more will be learned—but the accident's victims will not have died in vain, for lack of any possible effort to profit by its lessons. ■ ■

get more

GE UP AND G

from every engine

cars...




A can of GUMOUT in your gas tank cleans the carburetor while you drive . . . gives you easier starts, more power, better gas mileage



boats...




MARINE GUMOUT cleans in-board and outboard carburetors fast . . . for instant starts, full power, extra speed.



mowers...



A dirty carburetor robs your mower of power and makes it hard to start. POWER MOWER GUMOUT makes it run like new again



For easier starts, better engine performance, increased gas mileage, clean all carburetors with GUMOUT.

On sale at most service stations, auto supply, marine and hardware stores.

GUMOUT

Cleveland 4, Ohio

The Car You Can't Grease

were introduced for a sound reason. With an eye on world markets, Renault's objective is a vehicle that will keep running, even under conditions of neglect, in areas where roads are poor or there are none at all.

There's no place at all for a grease gun. You are advised to change the engine oil every 3,000 miles and the transmission oil every 6,000. But beyond that you have either rubber bushings for moving parts or permanently greased and sealed joints.

On my test trip, as I neared my luncheon rendezvous with some Renault men, I saw ahead what appeared to be a road block. And it was—a group of Renault officials who waved me off the road.

"Just follow the arrows," they said. I looked where they pointed—to a twisted landscape of ravines and hills, strewn with rocks. It wasn't a place where I'd choose to drive my own car. But a sentence I'd read in the Renault announcement came back to me:

"The exceptional ground clearance of 7.9 inches and the perfectly flat underside allow the R4 and R4L to travel over the worst possible terrain, even over rough ground that only specially designed vehicles would normally tackle."

Tire trouble. Ahead of me was the chance to prove out this claim on the devil's very own torture course. "A jeep would have real trouble on that one," another American visitor remarked as I successfully completed the circuit. I was inclined to agree. Later in the day, several tires went flat (presumably from rock bruises) on other cars that went over the route. A decision was made to fit heavier tires on later models.

This experience convinced me that in the far reaches of our own West you could use this car nicely as a camper. Leave the rear seat at home (both bench seats are readily removable) and you have plenty of space for hauling your outdoor equipment. In fact, if you installed a leveling framework of plywood in the depression where the rear seat rests, you'd have a level area for two sleeping bags.

With a setup like this, you could go just about anywhere. No need to think about roads. For this new Renault is a car that doesn't need a road. ■ ■



For safe handling
and smooth riding
even under tough going...

BRIGGS

IMPERIAL ADJUSTABLE SHOCK ABSORBERS

For sure control in driving and greater comfort in riding, replace your present shock absorbers with Briggs Imperial Adjustables. The adjustable feature means they can be adjusted to the needs of your car. Ask for Briggs Imperial Adjustable Shock Absorbers by name.

BRIGGS


The Briggs Shock Absorber Co.
Cleveland, Ohio



space
age
hobby

BUILD-YOUR-OWN ELECTRONICS FOR MODERN LIVING

IT'S FUN...IT'S EASY WITH MONEY-SAVING

knight-kits 

A PRODUCT OF ALLIED RADIO



featured in the 444 page

1962 **ALLIED**
ELECTRONICS
CATALOG

free

send
for it!



Dozens of new hobbyist kits including amazing Electronic Science Lab—over 100 projects!



Everything in Stereo hi-fi components new Multiplex Stereo FM tuners



New tachometer kit and outstanding test instruments



New all-transistor intercom many other kits for modern living

SAVE ON EVERYTHING
IN ELECTRONICS



Get the most for your money in: Stereo hi-fi systems and components • Recorders and tape • Citizens Band radios • Amateur station equipment • TV tubes, antennas, accessories • Electronic parts, tubes, transistors, tools, test instruments, books. Send today for your FREE 444-page 1962 ALLIED catalog!

NO MONEY DOWN
Easiest Terms

FREE
CATALOG



ALLIED RADIO

ALLIED RADIO, Dept. 27-J1
100 N. Western Ave., Chicago 80, Ill.

☐ Rush FREE 1962 ALLIED Catalog

Name

PLEASE PRINT

Address

City Zone State

WORLD'S
BIGGEST

Answers to PS Puzzlers on 24 and 26

Gravity. As long as they are held in the hand, the balls experience the same accelerated motion as the person holding them and the ship itself. But when they are released, they are no longer so driven, but start to move with a velocity equal to the ship's at the moment of release.

They are then, à la Galileo's experiment, moving side by side. The ship itself, however, is continuing to gain speed, and the "floor" (the part opposite to the direction of motion) will quickly overtake the balls and hit them simultaneously. The person on board the spaceship will see the balls "drop" and hit the floor; the person outside will see the floor rise and meet them.

Ten coins. The general solution to the 10-coin puzzle—when restricted to the rule that the rows of five were at top and bottom of the paper—boils down to the form at right:



But this form is capable of many distortions—all of which involve selecting three coins from one row and one coin from the other. The possible combinations for choosing the four coins in this way total 100, and if we consider each permutation of the four selected as a particular solution, there would be 24 such permutations for each selection, or 2,400 solutions all together.

Number quickies:

$$[(8 + 8) \times 8 - (8 + 8 + 8)/8] \times 8 = 1,000$$

Make six strokes at equal distances apart:



Now add five more strokes in appropriate places and behold.

NINE

Fare. Smith should pay \$2.50. He traveled half the total distance with Jones and so owes half of that cost.

Picnic. Let n = the number of wagons, p = the number of persons per wagon at the start. Then the total, np , can be figured in two ways:

$$\begin{aligned} np &= (n - 10)(p + 1) \text{ and also} \\ np &= (n - 25)(p + 3), \text{ yielding:} \\ n - 10p &= 10 \\ 3n - 25p &= 75 \end{aligned}$$

Multiplying the top equation by 3 and then subtracting, you get

$$\begin{aligned} -5p &= -45 \\ p &= 9 \end{aligned}$$

which, on substituting, makes $n = 100$.

It was a big company—900 people went on the picnic.

An all-new engine... all-new ride!

CUSHMAN.

SILVER EAGLE!




Power-Packed... vibration-free

Ride the Silver Eagle motor scooter. Enjoy the "instant go" of its great new aluminum 4-cycle engine. Relax to the easy new ride. Test the many other new features, including electric starter. Your Cushman dealer wants you to try it. Take him up on it right away.

FREE Silver Eagle Medallion Key Chain

Take this ad to your dealer for your FREE gift

Send coupon for FREE scooter booklet



CUSHMAN MOTORS

912 No. 21st, Lincoln, Nebraska

A subsidiary of Outboard Marine Corporation

Please send Silver Eagle folder.

NAME _____ AGE _____

ADDRESS _____

CITY _____ STATE _____



GENUINE ALNICO MAGNETS

AMAZING, PERMANENT, NON-ELECTRIC, HIGHLY PRACTICAL. For fuel interest or experiments. Hundreds of uses. Retrive 100% of steel items such as pins, tacks, nails, fresh or salt water tools from tanks & drains. **GUARANTEED**. Try any magnet one week. Money back if you are not well pleased.

No. 8-110	Wt. 53 oz.	Has pull of 225 lbs. on steel block	\$18.00
No. 8-524	Wt. 71 oz.	Has pull of 125 lbs. on steel block	\$10.00
No. 8-875	Wt. 18 oz.	Has pull of 75 lbs. on steel block	\$6.00
No. 8-500	Wt. 10 oz.	Has pull of 50 lbs. on steel block	\$3.50
No. 8-90	Wt. 8 oz.	Has pull of 15 lbs. on steel block	\$2.00
No. 8-47	Hot Pad Magnets, 10 for \$1.00		\$0.10
No. 8-55	Hobbyist assortment of 8 magnets		\$2.00

Send M.O. or check. We pay postage. Hurry as S.O.B.'s. **MIAMI MAGNET COMPANY, 3240 N.W. 27th Ave., Miami 42, Fla.**



make your own Gems 36.50

The Gem Maker comes complete with all necessary equipment, including a super-charged diamond blade for sawing and all the wheels for grinding, shaping and polishing, also complete instructions. The complete equipment as shown, less motor and belt for only \$36.50, f.o.b., Burlington, Wisconsin. Write today for information and literature.

B&I MANUFACTURING CO.
Dept. 2, Burlington, Wis.



It's Sharp... keep it that way with the right sharpening stone by



CARBORUNDUM



CASH FILING SAWS

Here is a steady repeat CASH business you can start at home. No experience needed—no canvassing—every saw you sharpen will bring new customers. You can make up to \$5 or \$6 an hour—\$20 to \$30 a week in your spare time as a starter. "My spare time saw filing business has made me \$952 these first ten months," says R. T. Chapman.

The new model 200 Foley Saw Filer automatically sharpens combination (rip and crosscut) circular saws, hand saws, band saws and crosscut circular saws.

Free Book—"MONEY MAKING FACTS" shows you how to get into this CASH business. Time Payments if desired. Mail coupon now. No salesman will call.

FOLEY MFG. CO.


919-1 Foley Bldg., Minneapolis 18, Minn.

Send me free book "MONEY MAKING FACTS" and Time Payment Plan.

Name _____

Address _____

City _____ State _____





- * DRY SOFT
- * STAY SOFT
- * WEAR LONGER
- * LEATHER

... where better
work gloves
are sold

WOLVERINE GLOVES

YOU NEED MOTION

Protects by displacing moisture, sealing surfaces with complete molecular film that lubricates, stops rust, frees "frozen" parts. Stops squeaks in hinges, locks, all moving parts. Protects electrical gear and motors, instruments, tools. FREE extension spray tip. 2 oz. Aerosol can at dealers or postpaid.

(Jobbers, Dealers, WANTED!)

\$1

PRODUCT RESEARCH
& DEVELOPMENT CORP.
DEPT. PS, BLUE BELL, PENNA.



Constantine's Catalog & Manual for WOODWORKERS

ALL-NEW! 3000 pages. More than a catalog—a manual. Tool 100 pages of the new 1961-62. World's most complete source for new, imported & domestic woods at rock bottom prices. Also, hand new services, hard-to-find hardware, (inlaid wood, pearl inlaid, new brass hardware, etc.) (also tools, plans, etc.) or a. Karlson 20¢ refunded on order. Get FREE "Chips & Chisel" too. Write NOW!

ALBERT CONSTANTINE AND SON, INC.
8000 Eastchester Rd., Dept. M-4, New York 21, N. Y.



DRAINS clogs, clogs, wash tubs; IRRIGATES - CIRCULATES - SPRAYS



1001 uses. 24" hose. 1/2" hose. 1/4" hose. 1/8" hose. 1/16" hose. 1/32" hose. 1/64" hose. 1/128" hose. 1/256" hose. 1/512" hose. 1/1024" hose. 1/2048" hose. 1/4096" hose. 1/8192" hose. 1/16384" hose. 1/32768" hose. 1/65536" hose. 1/131072" hose. 1/262144" hose. 1/524288" hose. 1/1048576" hose. 1/2097152" hose. 1/4194304" hose. 1/8388608" hose. 1/16777216" hose. 1/33554432" hose. 1/67108864" hose. 1/134217728" hose. 1/268435456" hose. 1/536870912" hose. 1/1073741824" hose. 1/2147483648" hose. 1/4294967296" hose. 1/8589934592" hose. 1/17179869184" hose. 1/34359738368" hose. 1/68719476736" hose. 1/137438953472" hose. 1/274877906944" hose. 1/549755813888" hose. 1/1099511627776" hose. 1/2199023255552" hose. 1/4398046511104" hose. 1/8796093022208" hose. 1/17592186044416" hose. 1/35184372088832" hose. 1/70368744177664" hose. 1/140737488355328" hose. 1/281474976710656" hose. 1/562949953421312" hose. 1/1125899906842624" hose. 1/2251799813685248" hose. 1/4503599627370496" hose. 1/9007199254740992" hose. 1/18014398509481984" hose. 1/36028797018963968" hose. 1/72057594037927936" hose. 1/144115188075855872" hose. 1/288230376151711744" hose. 1/576460752303423488" hose. 1/1152921504606846976" hose. 1/2305843009213693952" hose. 1/4611686018427387904" hose. 1/9223372036854775808" hose. 1/18446744073709551616" hose. 1/36893488147419103232" hose. 1/73786976294838206464" hose. 1/147573952589676412928" hose. 1/295147905179352825856" hose. 1/590295810358705651712" hose. 1/1180591620717411303424" hose. 1/2361183241434822606848" hose. 1/4722366482869645213696" hose. 1/9444732965739290427392" hose. 1/18889465931478580854784" hose. 1/37778931862957161709568" hose. 1/75557863725914323419136" hose. 1/151115727451828646838272" hose. 1/302231454903657293676544" hose. 1/604462909807314587353088" hose. 1/1208925819614629174706176" hose. 1/2417851639229258349412352" hose. 1/4835703278458516698824704" hose. 1/9671406556917033397649408" hose. 1/19342813113834066795298816" hose. 1/38685626227668133590597632" hose. 1/77371252455336267181195264" hose. 1/154742504910672534362390528" hose. 1/309485009821345068724781056" hose. 1/618970019642690137449562112" hose. 1/1237940039285380274899124224" hose. 1/2475880078570760549798248448" hose. 1/4951760157141521099596496896" hose. 1/9903520314283042199192993792" hose. 1/19807040628566084398385987584" hose. 1/39614081257132168796771975168" hose. 1/79228162514264337593543950336" hose. 1/158456325028528675187087900672" hose. 1/316912650057057350374175801344" hose. 1/633825300114114700748351602688" hose. 1/1267650600228229401496703205376" hose. 1/2535301200456458802993406410752" hose. 1/5070602400912917605986812821504" hose. 1/10141204801825835211973625643008" hose. 1/20282409603651670423947251286016" hose. 1/40564819207303340847894502572032" hose. 1/81129638414606681695789005144064" hose. 1/162259276829213363391578010288128" hose. 1/324518553658426726783156020576256" hose. 1/649037107316853453566312041152512" hose. 1/1298074214633706907132624082305024" hose. 1/2596148429267413814265248164610048" hose. 1/5192296858534827628530496329220096" hose. 1/10384593717069655257060992658440192" hose. 1/20769187434139310514121985316880384" hose. 1/41538374868278621028243970633760768" hose. 1/83076749736557242056487941267521536" hose. 1/166153499473114484112975882535043072" hose. 1/332306998946228968225951765070086144" hose. 1/664613997892457936451903530140172288" hose. 1/1329227995784915872903807060280344576" hose. 1/2658455991569831745807614120560689152" hose. 1/5316911983139663491615228241121378304" hose. 1/10633823966279326983230456482242756608" hose. 1/21267647932558653966460912964485513216" hose. 1/42535295865117307932921825928971026432" hose. 1/85070591730234615865843651857942052864" hose. 1/170141183460469231731687303715884105728" hose. 1/340282366920938463463374607431768211456" hose. 1/680564733841876926926749214863536422912" hose. 1/1361129467683753853853498429727072845824" hose. 1/272225893536750770770699685945414569152" hose. 1/544451787073501541541399371890829138304" hose. 1/1088903574147003083082798743781658276608" hose. 1/2177807148294006166165597487563316553216" hose. 1/4355614296588012332331194975126633106432" hose. 1/8711228593176024664662389950253266212864" hose. 1/17422457186352049329324779900506524425728" hose. 1/34844914372704098658649559801013048851456" hose. 1/69689828745408197317299119602026097702912" hose. 1/139379657490816394634598239204052195405824" hose. 1/278759314981632789269196478408104390811648" hose. 1/557518629963265578538392956816208781623296" hose. 1/1115037259926531157076785913632417563246592" hose. 1/2230074519853062314153571827264835126493184" hose. 1/446014903970612462830714365452967025298656" hose. 1/892029807941224925661428730905934050597312" hose. 1/1784059615882449851322857461811868101194624" hose. 1/3568119231764899702645714923623736202389248" hose. 1/7136238463529799405291429847247472404778496" hose. 1/14272476927059598810582859694494944809556992" hose. 1/28544953854119197621165719388989889619113984" hose. 1/57089907708238395242331438777979779238227968" hose. 1/114179815416476790484662877555959558476455936" hose. 1/228359630832953580969325755111919116952911872" hose. 1/456719261665907161938651510223838233905823744" hose. 1/913438523331814323877303020447676467811647488" hose. 1/1826877046663628647754606040895352935623294976" hose. 1/3653754093327257295509212081790705871246589952" hose. 1/7307508186654514591018424163581411742493179904" hose. 1/14615016373309029182036848327162823484986399808" hose. 1/29230032746618058364073696654325646969972799616" hose. 1/58460065493236116728147393308651293939945599232" hose. 1/116920130986472233456294786617302587879891198464" hose. 1/233840261972944466912589573234605175759782396928" hose. 1/467680523945888933825179146469210351519564793856" hose. 1/935361047891777867650358292938420703039129587712" hose. 1/1870722095783555735300716585876841406078259175424" hose. 1/3741444191567111470601433171753682812156518350848" hose. 1/7482888383134222941202866343507365624313036701696" hose. 1/14965776766268445882405732687014731248626073403392" hose. 1/29931553532536891764811465374029462497252146806784" hose. 1/59863107065073783529622930748058924994504293613568" hose. 1/119726214130147567059245861496117849989008587227136" hose. 1/239452428260295134118491722992235699978017174454272" hose. 1/478904856520590268236983445984471399956034348908544" hose. 1/957809713041180536473966891968942799912068697817088" hose. 1/1915619426082361072947933783937885599824137395634176" hose. 1/3831238852164722145895867567875771199648274791268352" hose. 1/7662477704329444291791735135751542399296549582536704" hose. 1/15324955408658888583583470271503084798593099165073408" hose. 1/30649910817317777167166940543006169597186198330146816" hose. 1/61299821634635554334333881086012339194372396660293632" hose. 1/122599643269271108668667762172024678388744793320587264" hose. 1/245199286538542217337335524344049356777489586641174528" hose. 1/490398573077084434674671048688098713554979173282349056" hose. 1/980797146154168869349342097376197427109958346564698112" hose. 1/1961594292308337738698684194752394854219916693129396224" hose. 1/3923188584616675477397368389504789708439833386258792448" hose. 1/7846377169233350954794736779009579416879666772517584896" hose. 1/15692754338466701909589473558019158833759333545035169792" hose. 1/31385508676933403819178947116038317667518667090070339584" hose. 1/62771017353866807638357894232076635335037334180140679168" hose. 1/125542034707733615276715788464153270670074668360281358336" hose. 1/251084069415467230553431576928306541340149336720562716672" hose. 1/502168138830934461106863153856613082680298673441125433344" hose. 1/1004336277661868922213726307713226165360597346882250866688" hose. 1/2008672555323737844427452615426452330721194693764501733376" hose. 1/4017345110647475688854905230852904661442389387529003466752" hose. 1/8034690221294951377709810461705809322884778775058006933504" hose. 1/16069380442589902755419620923411618645769557550116013867008" hose. 1/32138760885179805510839241846823237291539115100232027734016" hose. 1/64277521770359611021678483693646474583078230200464055468032" hose. 1/128555043540719222043356967387292949166156460400928110936064" hose. 1/257110087081438444086713934774585898332312920801856221872128" hose. 1/514220174162876888173427869549171796664625841603712443744256" hose. 1/102844034832575377634685573909834359332925168320742488748512" hose. 1/205688069665150755269371147819668718665850336641484977497024" hose. 1/411376139330301510538742295639337437331700673282969954994048" hose. 1/822752278660603021077484591278674874663401346565939909988096" hose. 1/1645504557321206042154969182557349749326802693131879819976192" hose. 1/3291009114642412084309938365114699498653605386263759639952384" hose. 1/6582018229284824168619876730229398997307210772527519279904768" hose. 1/13164036458569648337239753460458797994614421545055038559809536" hose. 1/26328072917139296674479506920917595989228843090110077119619072" hose. 1/52656145834278593348959013841835191978457686180220154392238144" hose. 1/105312291668557186697918027683670383956915372360440308784476288" hose. 1/210624583337114373395836055367340767913830744720880617568952576" hose. 1/421249166674228746791672110734681535827661489441761235137905152" hose. 1/842498333348457493583344221469363071655322978883522470275810304" hose. 1/1684996666896914987166688442938726143310645957767044940551620608" hose. 1/3369993333793829974333376885877452286621291915534089881103241216" hose. 1/6739986667587659948666753771754904573242583831068179762206482432" hose. 1/13479973335175319897333507543509809146485167662136359524412964864" hose. 1/26959946670350639794667015087019618292970335324272719048825929728" hose. 1/53919893340701279589334030174039236585940670648545438097651859456" hose. 1/107839786681402559178668060348078473171881341297090876195303718912" hose. 1/215679573362805118357336120696156946343762682594181752390607437824" hose. 1/431359146725610236714672241392313892687525365188363504781214875648" hose. 1/862718293451220473429344482784627785375050730376727009562429751296" hose. 1/1725436586902440946858688965569255570750101460753454019124859502592" hose. 1/3450873173804881893717377931138511141500202921506908038249719005184" hose. 1/6901746347609763787434755862277022283000405843013816076499438010368" hose. 1/13803492695219527574869511724554044566000811686027632152998876020736" hose. 1/27606985390439055149739023449108089132001623372055264305997752041472" hose. 1/55213970780878110299478046898216178264003246744110528611995504082944" hose. 1/110427941561756220598956093796432356528006493488221057223991008165888" hose. 1/220855883123512441197912187592864713056012986976442114447982016331776" hose. 1/441711766247024882395824375185729426112025973952884228895964032663552" hose. 1/883423532494049764791648750371458852224051947905768457791928065327104" hose. 1/1766847064988099529583297500742917704448103895811536915583856130654208" hose. 1/3533694129976199059166595001485835408896207791623073831167712261308416" hose. 1/7067388259952398118333190002971670817792415583246147662335424522616832" hose. 1/14134776519904796236666380005943341635584831166492295324670849045233664" hose. 1/28269553039809592473332760011886683271169662332984590649341698090467328" hose. 1/56539106079619184946665520023773366542339324665969181298683396180934656" hose. 1/113078212159238369893331040047546733084678649331938362597366792361869312" hose. 1/226156424318476739786662080095093466169357298663876725194733584723738624" hose. 1/452312848636953479573324160190186932338714597327753450389467169447477248" hose. 1/904625697273906959146648320380373864677429194655506900778934338894954496" hose. 1/1809251394547813918293296640760747729354858389311013801557868677789908992" hose. 1/3618502789095627836586593281521495458709716778622027603115737355579817984" hose. 1/7237005578191255673173186563042990917419433557244055206231474711159635968" hose. 1/14474011156382511346346373126085981834838867114488110412462949422319271936" hose. 1/28948022312765022692692746252171963669677734228976220824925898844638543872" hose. 1/57896044625530045385385492504343927339355468457952441649851797689277087744" hose. 1/115792089251060090770770985008687854678710936915904883299703595378554175488" hose. 1/2315841785021201815415419700173757093574218738318097665994071907571

As observed by Jewkes, Sawers, and Stillerman in *The Sources of Invention*. George Eastman of Kodak was trained as a bookkeeper, not as a technician; Midgely was a mechanical engineer, not a chemist; the men who invented color film were not chemists but musicians; the inventor of the ball-point pen had been at various times a painter, sculptor, and journalist; Dunlop was a veterinarian; and the inventor of the dial telephone was an undertaker.

IT IS important that our big businesses welcome new ideas. I find much of American business far less receptive to new ideas than the businesses of Europe. So long as our conservatism is confined to our business organizations, I do not fear any desiccation of the wellspring of creativity from individuals. The danger lies in this: that the organizers, who in business keep the innovators in their place, may extend their dominion to society at large. This could lead to economic stagnation and, more important, to the atrophy of the creative spirit.

If big business comes to want new ideas, it can help itself by improving the climate for their growth within business. It can help itself much more by opening its doors to creative individuals outside the walls.

As a lawyer, I have written some of the documents that inventors are required to sign before their inventions will be considered. I know something about the kind of reception that inventors usually receive.

I think that our corporations are lawyer-ridden. There is far more concern to avoid a possible lawsuit than there is to get hold of a new idea. This, I think, has to change.

Beyond this, I would urge the manager of any business who is really interested in new ideas to get a new crew of people to interview inventors. He should also set aside an amount of money that he fully expects to lose. If a man is never explaining his failures because he has only successes, it means simply that he is not taking enough risk. ■ ■

221



TAKE IT OFF!


WITH

KLEAN-STRIP

PAINT REMOVER

- fast • clean
- non-inflammable
- peels off paint and all other finishes

THE KLEAN-STRIP CO., INC.
Memphis 6, Tenn., Winston-Salem, N.C.



Works
in
seconds!



Loosens Rusted Bolts

nuts, screws, "frozen" parts

LIQUID WRENCH.

SUPER-PENETRANT

The super-penetrating rust solvent that quickly loosens rust and corrosion

AT ALL HARDWARE
AND AUTO STORES

LIQUID WRENCH SPECIALTY COMPANY
CHICAGO 16, ILL.



AUTOMATIC

MAKES HIGH
PROFITS

RETOOTHER

for HAND SAWS

Cuts new teeth in 30
seconds—any size 4 to
18 points. Old teeth
fall off as chips. Easy
to operate. A
perfect job.



Free
Literature

BURR MFG. CO.

8842-S VENICE BLVD.

LOS ANGELES 34, CALIFORNIA

FREE CATALOG!

TREMENDOUS SAVINGS ON
HUNDREDS OF SURPLUS AND
NEWLY MANUFACTURED ITEMS!

New 1961 edition contains over 30 pages of
shop, farm, and hydraulic equipment, pumps, motors,
refrigerators and more. Free! Write for your FREE CATALOG Today.

GROBAN SUPPLY COMPANY

1137 South Wabash Ave., Dept. 99 Chicago 5, Ill., WEster 9-3790



4-WAY WELDER \$14.95

WELD-BRAZE-SOLDER-CUT Complete

NO OTHER WELDER AT THIS PRICE
Complete with SAFETY FOOT SWITCH,
FULL FACE SHIELD, twin carbon arc
torch, welding rod holder, clamp, carbons,
welding & brazing rods, flux, fuses, in-
struction book. FULL YEAR GUARANTEE.
More than a quarter million in use in homes.

garages, farms, shops, factories. NOW anyone can weld, braze,
solder cut heat without experience. Does 1001 jobs on all metals.
Save & earn money. Make & repair auto bodies, parts, fenders,
trailers, boats, metal furniture, fixtures, ornamental iron, farm
equipment, garden tools, bicycles, toys, etc. Operate on any prop-
erly wired 110 V AC line. SEND ONLY \$2. Pay postman \$12.95
plus C.O.D. charges. Ideal lifetime gift for hobbyist, mechanic,
hot rodder, homeowner. Order on 10 day money back guarantee.
FOUR WAY WELDER CO. DEPT. F3-J, 18106 FEDERAL ST.
CHICAGO 16, ILL.

Starlings: Public Nuisance No. 1

[Continued from page 69]

they have such short memories that a continual barrage is necessary. This is hard on human residents.

Radar and ultrasonic methods are being tried, but so far not very effectively. The dose has to be severe, causing deep irritation or pain or—literally—frying the birds. No ultrasonic whistle like that used on dogs will work: The birds' hearing limits are much like ours.

Bird lovers' fears? Some starling supporters may be alarmed at the dire measures aimed at innocent creatures. After all, the birds do eat many harmful insects. But they needn't worry. You might be able to kill half a million birds in one blow—but the starling problem is many times bigger. Most conservationists agree that the species will survive any mass attacks.

Enlisting Nature. Instead ornithologists are turning their attention to the birds themselves. What about drafting kestrels—their natural predators in Europe? Here, only the common house cat, a species of hawk called "Coopers hawk," and man himself, attempt to fight the birds. (This may be why decoys of owls or sparrow hawks don't seem to scare starlings.)

Are there specific diseases starling flesh is heir to? Some dead birds have shown evidence of disease, possibly carried by parasites that are associated with starlings. Birth mortality is another question. Why, out of a nest of six or seven eggs, are one or two often infertile?

These questions are being considered at wildlife research centers in Laurel, Md., and Amherst, Mass. There, scientists hope to come up with methods as effective as the radiation that turned the tide against the screwworm plague in the South.

This acts as a gametocide—i.e., it interferes with the production of sex cells. Feed the birds the right chemical just before nesting time and enough could be sterilized so that offspring would be limited. A bird birth control, in other words. This would salve the consciences of bird lovers and not unduly upset the already confused balance of nature. It also would leave enough of the iridescent bright ones around for the man with the binoculars to contemplate.

It's a Clumsy World for Lefty

[Continued from page 105]

history. The Greeks thought it most unlucky to hear thunder on the left. Before Columbus sailed, Guatemalans were paying serious attention to the antics of a soothsayer's left leg. The seer would rub both his legs vigorously to prophesy. If the right leg muscles twitched, the future looked rosy; if the left leg muscles quivered, watch out!

Even today, primitive African tribes insist that their women prepare food with the right hand. The practice of wearing a wedding ring on the left hand reputedly began as an effort to ward off evil spirits. Even language contains built-in sneers at left-handers. The Latin word for "left" has become our ominous "sinister"; the French word for "left" is now our snooty "gauche."


Social scientists generally believe that because about 90 percent of all people are natural right-handers, the majority early made a virtue of it and decided there was something queer about anybody who was different.

Fancy company. Civilized opinion began shifting slightly in favor of the ill-used left-handers when Alexander the Great came along. Being a lefty seemed to be no handicap at all to him in conquering the world. Then Charlemagne, another ruler who cut a wide swath, found it handier to grip a mace or a sword with his left than his right. This gave left-handedness a substantial boost toward respectability.

Since Charlemagne's time, quite an array of notables have been left-handers. Four great artists are among them: Michelangelo, Leonardo da Vinci, Raphael, and Picasso. Da Vinci, with his usual flair for outdoing everybody else at anything, could write, draw, or paint equally well with either hand.

President Truman always threw out the first baseball of the season with his left hand, but he writes with his right. President Garfield, on the other hand, was a lefty all the way.

In addition to a large and immensely valuable collection of ballplayers who are left-handed, the fraternity includes Betty Grable, Danny Kaye, the cartoonist Milton Caniff, and, now that her secret is out, that elegant snooker player, George VI's widow.—Wesley S. Griswold.



New Continental shapes—strikingly handsome—excitingly different—perfectly balanced—moderately priced! Like all Dr. Grabows they're mechanically pre-smoked with fine tobacco. Never need breaking in—sweet, cool, satisfying from first puff...Write for FREE BOOKLET.

Dr. Grabow Pre-Smoked Pipes—Greensboro, N. C.

BUILD YOUR WORKSHOP LIBRARY

Seven handsome hard cover books, 120 pages each, tell and show you with photos and drawings how to get the most out of your CIRCULAR SAW & JOINTER, DRILL PRESS, LATHE, ABRASIVE TOOLS, BAND SAW AND SCROLL SAW, SHAPER and RADIAL SAW. Your choice—\$1.00 each. Mail check or money order to Delacraft Books, Rockwell Manufacturing Company, 5041 N. Lexington Ave., Pittsburgh 6, Pa.

Fill Cracks And Holes Better

Handles like putty. Hardens like wood.

PLASTIC WOOD®

The *Genuine*—Accept No Substitute.

had been spending about \$2 million a week to buy sabotage and propaganda.

Plans and correspondence showed that Albert and his spies had incited strikes of longshoremen, of munitions workers, and of employees of other plants manufacturing goods of strategic importance to the Allies. The strikes were engineered by Capt. Franz von Papen, the German military attache, with the cooperation of certain labor leaders.

In one case Albert, through dummy purchasers, had actually bought a Bridgeport, Conn., munitions plant that made artillery shells for the British and Russians. The company proposed to accept orders for the ammunition, but never to make shipment, or to furnish defective shells that would be useless against the Germans.

Albert's plans called for purchase of American newspapers and magazines, through which he proposed to influence public opinion in favor of his government. He financed motion pictures with a pro-German slant. Through Albert and Von Papen, the Germans would corner the supply of liquid chlorine, used for poison-gas warfare. Another aim was to deprive England of her supply of cotton from the United States.

ALBERT had personally prepared a gigantic plan for the military occupation of the United States. Some 85,000 German soldiers were to be landed suddenly on the New Jersey coast, out of reach of U. S. coast protective facilities.

The plan included detailed statistics showing that it was necessary for New York City to replenish its food supplies about every five days. The invading Germans were to cut off New York from the rest of the country within 24 hours, to starve the metropolis into submission. With 75 percent of the financial resources of the nation concentrated in New York and captured by the Germans, this occupation would cripple all effective resistance. The first invasion wave would be reinforced by a second, and the United States could be brought to its knees within a short time.

Accurate and abundant information regarding U. S. coastal defenses was among

Albert's papers, including maps of defense stations and strategic military positions along the entire east coast.

WITHIN 24 hours after reviewing the contents of the briefcase, Secretary McAdoo sent both case and papers to President Wilson at the White House. The President agreed that the American public must be made aware of the extent and seriousness of the German plots.

To expose the Germans and to disclose their machinations to as many people as possible, McAdoo talked with Frank I. Cobb, editor of the *New York World*. Cobb was told the entire story and was informed that he would be permitted to publish all of the Albert documents, provided he would keep secret the manner in which they were obtained. Cobb promptly began to make front-page history with banner headlines and illustrations of many of the incriminating papers. Americans who had been fooled by Albert's underlings learned about their mistakes by reading the red-hot stories in the *World*—and promptly moved to sever all connections with those who had beguiled them.

True to his word, Cobb never revealed how the papers were obtained. In later years more than one individual "admitted" that he was the genius who had acquired the Albert briefcase.

In December, 1915, only a few months after the Albert episode, President Wilson demanded that the German Ambassador send Capt. Franz von Papen back to Germany, because Von Papen was responsible for the intrigues aimed at violating the neutrality of the United States. Von Papen returned to Germany, later to become Chancellor under President Paul von Hindenburg and Vice Chancellor under Adolf Hitler.

On April 6, 1917, after the Germans deliberately sank many American ships, the United States entered the war against Germany. German Ambassador Johann Heinrich von Bernstorff was recalled to Berlin, and with him went Dr. Heinrich Albert, whose usefulness as a propaganda director in the United States had virtually ended when Secret Service Agent Frank Burke grabbed his briefcase and got away on a trolley car. ■ ■

SURPLUS SALE

GOVT. SURPLUS
EXCESS INVENTORY
BANKRUPT STOCK

AC-DC ELECTRIC GENERATOR

Item #675. New hi power
Govt. bearing unit. Generates
115-v 1800 cycle AC. 200-w and
30 v up to 200 amps DC.
Very versatile. Use for 115-v
AC lights or power or for DC
40-amp welder. Use with tractor
or engine etc. Size 11" x 16" x 6".
Wt 15 lbs. Govt. cost over \$250.

SALE \$15.85 FOR

SELF PRIMING WATER PUMP

Item #204. New Govt.
unit. Fine for boat pump, air
pump, pump, etc. 1/2" intake and 1/4"
charge ports. 3/4" shaft. Size
12" x 10" x 18". Wt. 30 lbs. Cost
\$47.50.

SALE \$19.49 FOR

STORAGE BATTERY WINCH

Item #311. Powerful fully
reversible unit. 1000 lbs. or
more. Use on 6 or 12 v battery.
11" x 10" x 18". Wt. 30 lbs. Govt.
cost \$80.

SALE \$49.95 FOR

DIAL PHONE

Item #716. WE
phone home. Used in
to a home office.
Use as extension or
main line phone. Set
up your own private
system. Wt. 8 lbs.



\$7.95


Color (aper for) Coral, Yellow,
Lt. Green, Buff \$11.95 FOR

GOVT. BEARED BATTERY MOTOR

Item #588. Power
to gear-down motor
115-v 1800 cycle AC.
11" x 10" x 18". Wt. 30 lbs. Govt.
cost \$200.

SALE \$21.79 FOR

POWER PLANTS



Item #607. Super Sae
c-a. Fine. 115-v 1800 cycle
AC. 200-w and 30 v up to 200
amps DC. Water cooled. 4" x 10"
x 18". Wt. 1400 lbs. Govt. cost
\$2100.

SALE \$649 FOR

Hydraulic Speed Reducer

Item #1304. 1 hp variable
speed hydraulic transmission.
Variable speed 0 to 35 rpm.
Instantly reversible. Ideal for
drives, motor, etc. etc. R.
1/2" bore. 1/2" shaft. Complete
with 1 phase 230 v AC ball
bearing motor. Size 11" x 10" x 18".
Wt. 200 lbs. Shaft fitted with pulley
(specify diameter desired). Govt. cost
\$100.

SALE \$89.50 FOR

BATTERY REMOTE CONTROL WINCH

Item #322. Powerful 1000
lb. winch. Up to 1000 ft. cable.
Battery remote control. 20' cable.
1/2" bore. 1/2" shaft. Complete
with 1 phase 230 v AC ball
bearing motor. Size 11" x 10" x 18".
Wt. 200 lbs. Shaft fitted with pulley
(specify diameter desired). Govt. cost
\$100.

SALE \$58.25 FOR

FLEXIBLE POWER CABLE

Item #1105. Finest
War surplus. 1 conductor
for power. 115-v 1800 cycle
AC. 200-w and 30 v up to 200
amps DC. 1/2" bore. 1/2" shaft.
Complete with 1 phase 230 v AC
ball bearing motor. Size 11" x 10" x 18".
Wt. 200 lbs. Shaft fitted with pulley
(specify diameter desired). Govt. cost
\$100.

SALE \$44.50 FOR

SPECIAL OF THE MONTH!

ARMY AC GENERATOR



Item #626. Brand new
original. 115-v 1800 cycle
AC. 200-w and 30 v up to 200
amps DC. 1/2" bore. 1/2" shaft.
Complete with 1 phase 230 v AC
ball bearing motor. Size 11" x 10" x 18".
Wt. 200 lbs. Shaft fitted with pulley
(specify diameter desired). Govt. cost
\$100.

SALE \$139.50 FOR

SALE \$139.50 FOR

SALE \$139.50 FOR

SALE \$139.50 FOR

SALE \$139.50 FOR

SALE \$139.50 FOR

SALE \$139.50 FOR

SALE \$139.50 FOR

SALE \$139.50 FOR

SALE \$139.50 FOR

SALE \$139.50 FOR

SALE \$139.50 FOR

SALE \$139.50 FOR

SALE \$139.50 FOR

SALE \$139.50 FOR

SALE \$139.50 FOR

SALE \$139.50 FOR

SALE \$139.50 FOR

SALE \$139.50 FOR

SALE \$139.50 FOR

SALE \$139.50 FOR

SALE \$139.50 FOR

SALE \$139.50 FOR

SALE \$139.50 FOR

SALE \$139.50 FOR

SALE \$139.50 FOR

SALE \$139.50 FOR

SALE \$139.50 FOR

SALE \$139.50 FOR

SALE \$139.50 FOR

SALE \$139.50 FOR

SALE \$139.50 FOR

SALE \$139.50 FOR

SALE \$139.50 FOR

SALE \$139.50 FOR

SALE \$139.50 FOR

SALE \$139.50 FOR

SALE \$139.50 FOR

SALE \$139.50 FOR

SALE \$139.50 FOR

SALE \$139.50 FOR

SALE \$139.50 FOR

SALE \$139.50 FOR

SALE \$139.50 FOR

SALE \$139.50 FOR

SALE \$139.50 FOR

SALE \$139.50 FOR

SALE \$139.50 FOR

SALE \$139.50 FOR

SALE \$139.50 FOR

SALE \$139.50 FOR

SALE \$139.50 FOR

SALE \$139.50 FOR

SALE \$139.50 FOR

SALE \$139.50 FOR

SALE \$139.50 FOR

SALE \$139.50 FOR

SALE \$139.50 FOR

SALE \$139.50 FOR

SALE \$139.50 FOR

SALE \$139.50 FOR

SALE \$139.50 FOR

SALE \$139.50 FOR

SALE \$139.50 FOR

SALE \$139.50 FOR

SALE \$139.50 FOR

SALE \$139.50 FOR

SALE \$139.50 FOR

SALE \$139.50 FOR

SALE \$139.50 FOR

SALE \$139.50 FOR

SALE \$139.50 FOR

SALE \$139.50 FOR

SALE \$139.50 FOR

SALE \$139.50 FOR

SALE \$139.50 FOR

SALE \$139.50 FOR

PAINT SPRAY UNIT

Including
Spray Gun

APPROX.
COST \$225.00

OUR LOW
PRICE... \$44.50

Diagram with
parts list.

U.S. GOV
SURPLUS
AIR
COMPRESSOR

115-v 1800 cycle AC.
200-w and 30 v up to 200
amps DC. 1/2" bore. 1/2" shaft.
Complete with 1 phase 230 v AC
ball bearing motor. Size 11" x 10" x 18".
Wt. 200 lbs. Shaft fitted with pulley
(specify diameter desired). Govt. cost
\$100.

SALE \$44.50 FOR

SALE \$44.50 FOR

SALE \$44.50 FOR

SALE \$44.50 FOR

SALE \$44.50 FOR

SALE \$44.50 FOR

SALE \$44.50 FOR

SALE \$44.50 FOR

SALE \$44.50 FOR

SALE \$44.50 FOR

SALE \$44.50 FOR

SALE \$44.50 FOR

SALE \$44.50 FOR

SALE \$44.50 FOR

SALE \$44.50 FOR

SALE \$44.50 FOR

SALE \$44.50 FOR

SALE \$44.50 FOR

EMERSON ELECTRIC

PORTABLE WELDER

High Capacity... Low Price

Ideal for farm, home workshop. Cuts,
brases, solders, welds. One man can
carry... only 68 lbs. & welding
heats up to 180 amps... 1/8" to 3/8"
rod sizes. Write today for prices and
receive FREE WELDING SELECTOR
GUIDE... gives working data you
need in seconds! Dept. W-5

EMERSON ELECTRIC St. Louis
2100 Florissant St. St. Louis 8, Mo.



HOW TO TURN Concrete INTO Gold



A MUST FOR EVERYONE CONCERNED!

This MANUAL Tells You
How To Make
Randome Profits
From Concrete Items
YOU CAN MAKE

All you need is a mold or two and a little knowl-
edge. This Manual contains large, clear pictures,
gives prices and description of more than 300 differ-
ent molds you can buy direct from the manufacturer
AND... priceless trade secrets that make production
easy. Take the first step. Today!!!

SEND ONLY \$7.95 FOR YOUR COPY
(Or \$12.95 for 3 copies)

CONCRETE MACHINERY COMPANY, INC.
Dept. 74
Mishawaka, Ind.

FREE from RADIO SHACK

America's most complete, exciting
ELECTRONICS CATALOG
PLUS all other issues for a full year!
Latest giant book is 1/2 bigger! 316
pages! Stereo, Hi-Fi, Ham Radio,
Tapes, Records, Parts. 30 pgs. of
Kits! No Money Down credit terms.
Satisfaction guaranteed.

RADIO SHACK Corp. Dept. 614C
730 Commonwealth Ave., Boston 17, Mass.
Send me Radio Shack's famous electronics catalogs
for 1 full year—FREE, POSTPAID.
Name _____
Address _____
City _____ Zone _____ State _____

MAIL
Coupons
TODAY

AConomize on Gasoline

Get more miles per dollar—install an AC ACon-O-Mizer between your fuel pump and carburetor. Reduces flooding and stalling... tailors fuel pressure—precisely and instantly—to every driving condition from idle to full throttle. The best answer yet to real gasoline economy!

suggested retail price


\$7.95



At Your Nearby Service Station, garage or General Motors Dealer

ACon-O-Mizer

AC SPARK PLUG THE ELECTRONICS DIVISION OF GENERAL MOTORS



Attachable Cutter Blades



Miller Sewer Rod, Dept. PR-1, 4640 N. Central Ave., Chicago 30, IL

CLOGGED SEWERS REMEMBER THE COSTLY PLUMBING BILL

Chicago—September 1. Just introduced is a Free Booklet on machines which enable the Home Owner, Janitor or Factory Maintenance Man to find it himself. Yet anyone can operate this new Red-Clay Tool which is whirled down the drain in a few seconds. KITCHENS, BATH-TUBS, TOILETS, URINALS, PLUMBING DRAINS, HOUSE TO STREET SEWER-PIN can be cleared of Grease, Paper, Sand while Cutter blades can be added for removing roots. A new discovery in Swedish Music Wire gives the rod 100% more flexibility. A newer new unit is the Miller Electric Rodder which has patented cutters that expand automatically to the size of the pipe. It will clean out heavy obstructions in pipe diameters 3" to 12". Smaller Sizes available. But now, what are these Tools worth in COSTLY PLUMBING BILLS SAVED. Test this Ad out—and write your name and address beside it for FREE BOOKLET on Hand and Electric Units. Obey that urge. No Agent will call. A post-card will do. Chicago Phone Kildare 6-17021

TOOLS WHOLESALE

\$100 PUTS YOU IN BUSINESS

Start your own business, sell tools to your friends and neighbors, or buy tools for your own use and **SAVE MONEY \$\$\$**

A MILLION DOLLAR INVENTORY AT YOUR FINGERTIPS. NO STOCK TO CARRY. ORDER AS YOU NEED IT.

BUY AT WHOLESALE PRICES. Extra 12% off profit on your accumulated purchases. \$1.00 refund on first purchase or refunded if you are not 100% satisfied.

SILVO HARDWARE CO., Dept. PS-9, 107 Walnut St., Phila. 6, Pa.

JOINT AND SHARPEN ALL SAWS

SUPER FILER No. 11
Joint and sharpens hand and circular saws 8" to 10" with all tooth correct in height, depth, pitch, bevel. When file is set, water, teeth are finished. Saw runs true with no side pull. The only 8" file.

\$2.95 PPD.

SUPER DRILL GRINDER
Sharpens round, flat, and drill bits. Like new. Use hand or power drill.

\$2.95 PPD.

"TRU-CIRCLE"

Saw set automatically sets teeth at 10° or more.

\$2.95 PPD.

PAINT BRUSH HOLDER
and Wiping Bar. It holds brush securely. Fits any bucket or roller pan.

2 for \$1.00 PPD.

Send for free catalog. Calif. Residents add 4% Sales Tax. A. D. McBurney, 5908 Hollywood Blvd., Hollywood 28, Cal., Dept. 5-91

On the Trail of No Raster

[Continued from page 121]

that it sounded like the chirping of a strange bird.

I replaced the 6AL5. The picture stopped flopping and came on sharp and bright.

I've had customers give me the bird before, but this was different. The Averys insisted on my taking a token of their appreciation. Parakeet, anyone?

The Do-It-Yourself Doctor

OUR family physician, Doc Strouse, is an avid do-it-yourselfer. When he gets stuck, he turns the tables on his patients and seeks free advice over the telephone.

He wastes no words. The other day I immediately recognized the clipped tones on the phone when the voice said, "No raster."

Falling in with the routine, I asked, "Neon test?"

"Negative."

I ran through six ordinary troubles and got six negatives. I pulled the schematic diagram of his set from my files and checked over the high-voltage circuit of Doc's set.

In addition to the high voltage for the picture tube, this circuit produces a by-product—about 400 volts called "B-plus boost." In this set, the boost voltage is fed to the audio-output tube and the vertical-output tube.

I said, "Pull the audio-output tube."

"Can't be that," he came back. "Sound is okay. If the audio tube was bad, the sound would be affected."

"Good thinking, Doc. Pull the vertical-output tube."

He answered, "You're reaching into left field now. It's high-voltage trouble, not vertical sweep."

I insisted. There was a pause, then an excited, "Positive. High voltage snapped on when I removed the 12BH7. How could that be?"

I said, "The tube shorted and loaded down the B-plus boost. The load killed the high voltage. Now, instead of a full raster you have only a bright horizontal line. Right?"

"Right," he snapped.

I sent over a new 12BH7. Word came back that the patient had recovered. ■ ■

WAR SURPLUS THE SHIP SAVE UP TO 90%



FRESH WATER SYSTEM PUMP—For boats, campers & trailers. Output 10 to 200 gal. an hr. Variable rheostat controls output. 1/2" pipe thread. Air-brake impeller housing. 12 V D.C. Radio noise filter. 5/2 amp. draw. Explosion-proof cone. Shpg. wt. 11 lbs. Complete with mounting instructions & wiring diagram. Approx. GOVT COST, \$200 NEW \$10.95


"SUPER 9" 200 AMP WELDING KIT With Deluxe accessories consisting of one 200 AMP Gen. adjustable helmet, electrode holder, ammeter & shunt, rheostat, giant toggle switch, voltmeter, voltage reg. 1 pr. heavy-duty welder's gloves and 30' cable. All on a guaranteed pre-tested. Approx. GOVT COST \$300. Most items new—all perfect. \$27.50.



AIRBORNE ELECTROMATIC WINCH For automatic control. Fully beargested with a reduction of 225 to 1 operates at 12 & 24 V. D.C. 1 lb. tremendous loads. Safety clutch set at 100 lbs. Automatically reverses on locking brake. Handles over 500' of 1/2" steel cable or rope. Tensile strength unit for use on jeeps, trucks, docks, etc. 30" x 14" x 10" H. Shpg. Wt. 100 lbs. Approx. GOVT COST \$450 NEW \$99.95. Limited offer! Same unit w/ 250' cable capacity 24" L. x 8" W. x 12 1/2" H. NEW \$99.95.



ELECTRIC STORAGE BATTERY WINCH Fully reversible with heavy-duty 2-way drum switch. Heavy-duty motor. 15:1 to 1 reduction. Drum will handle 90 ft. of 1/2" cable. Can be operated manually by hand crank. Use on 11, 24, 32 V. battery. 115 cal. 2-mi. on plus. Complete with mounting flange, safety locking brake and leads. Ready to install & operate. Dimensions 17" x 11" x 11" x 7" high. For jeeps, trailers, boats, trucks, etc. Approx. GOVT COST \$400 NEW \$49.90



HYDRAULIC KIT consisting of 2 heavy-duty 7/8" double-acting cylinders and 1 hydraulic hand pump. 1500 PSI. Great for a wide variety of work, car jacks. Approximate GOVT COST \$200 NEW. Only \$10.95

NEW 1961 CATALOG

Tremendous catalog, our biggest ever—fully illustrated. Lists of hundreds of war surplus & other items. Send 25c in coin for a free copy today or free copy with order. Where paid, indicated applies to U.S. only. Other prices FOB Culver City, Calif. Need cash, check, money order, 50% deposit for C.O.D.



AIRBORNE SALES CO., INC. DEPT. PS061
8501 Stellar Drive, Culver City, Calif.

GUNK® removes grease like no detergent can!



Cleans power mowers, engines, garage floors, kitchen walls, ovens, exhaust ducts, paint brushes, furnace filters, bar-b-q grills, machinery! At auto supply, farm or hardware stores!

GUNK CHICAGO CO., Silver Forest, Ill., serving the Midwest and Southwest
DAWSON SPECIALTY CO., Charlotte, N.C., serving the East, Southeast and far West



MAGNETS

- TSX-15 Magnet Assembly (150 lb. pull) Each....\$9.50
- TS-1 Magnet Assembly (50 lb. pull) Each..... 2.95
- TSX-18 TS-2 Alnico 5 Pol Holder Magnets 50 for \$3.50, 20 for 1.50
- TS-4 Pencil Magnet with clip, 29c each, 4 for..... 1.00
- TS-3A Rectangular U's (4 lb. pull) 10 Magnets .. 3.25
- TS-6 Sample Magnets & Catalog (over 200 sizes listed) 25c

Money Back Guarantee—Send check or money order, sorry no C.O.D.'s
TERRY SALES CORP., 1045 Silver Beach Rd., Riviera Beach, Fla.

KROIL® LOOSENS RUSTY FROZEN PARTS



Frozen bolts, pipe threads, bearings, etc., yield to Kroil, the chemical lubricant that creeps into millionth inch spaces, dissolves rust and dried grease. Harmless to metal or skin—used by 25,000 shops for 20 years. Now available in half-pint spout cans, 65c at your dealer.

KAND LABORATORIES, Nashville 11, Tennessee

JEEP OWNERS

Re-Power NOW with a V-8 or 6 Cyl engine—Use Ford - Chev - Mercury - GMC - Pont - Stude - Dodge or Plymouth in Jeeps, Jeepsers, Six-Wgn, Trucks, Kaiser & H.J. cars. Conversion kits \$45.35 to \$56.90. Want fast action? Give us full information, send \$15.00 Dep. and we will ship correct kit. Bal. C.O.D. Send full amount for prepaid shipment. Wire, phone or write today. Details FREE

HOOSIER MACHINE PRODUCTS CO.
214 S.E. 6th St. Phone CR8-3442 Pendleton, Oregon

If it's worth painting
it's worth sanding
with sandpaper by



CARBORUNDUM®

KING MIDGET FOR 1961

WORLD'S MOST EXCITING LOWEST PRICED CAR



Drive it for 75c a week. Rider Agents Wanted. Send 25c for 32 page book, full details, dealer price. Or send \$1 (refunded first order) for this plus Service and Repair Manual and 16 5x7 photos of car and factory

MIDGET MOTORS CORPORATION, Athens 2, Ohio

6-IN-1 ONLY MACHINE OF ITS KIND! UNIMAT



Compact workshop for all metal, plastic, wood. Precision lathe, milling machine, drill press, surface grinder, polishing/grinding machine, portable drill. Complete basic unit \$129.50. WRITE FOR FREE CATALOG
AMERICAN EDELSTAAL INC., DEPT. M, 350 BROADWAY, N. Y. 13, N. Y.

Fill Flaws In Plywood

Handles like putty. Hardens like wood.

PLASTIC WOOD®

The *Genuine*—Accept No Substitute.

World's greatest classified

opportunities

POPULAR SCIENCE MONTHLY
355 LEXINGTON AVE.
NEW YORK 17, N. Y.

Classified Ads only \$1.15 per word insertion, payable in advance. Minimum ad 10 words. To be included in November issue, copy should be in our office by September 20. No cancellations accepted after September 15. Address orders to O. K. Kelly, Classified Adv. Mgr.

1 AUTOMOBILES & MIDGET CARS

CROSLEY or Foreign car parts catalog. Parts discount club. Box 7, Elmont, New York

USED Cars & Goldmine. Big List Of Wholesale Auto Auctions. Latest Wholesale Prices. Send \$1 Today. Pruitt, Box 4036, Charleston Heights, Pa. Car

AUTOMOBILE Literature: Antique thru modern; photos, manuals, models. Hobby Club. monthly bulletin. Information free. Auto Enthusiasts, Box 451J, Mount Clemens, Mich.

2 AUTO SUPPLIES & EQUIPMENT

JUST Out! New 736-page, illustrated Catalog offering savings up to 80% on over 100,000 auto parts and accessories. Everything to renew, rebuild, renovate '28-'31 Model 'A' Fords. All makes (1920-1941) model trucks, foreign and sports cars. Hollywood accessories, custom styling. Hi-Speed Equipment. Send 25c for postage packing refundable on first order. Whitney, 1919-P88 Archer, Chicago 16, Illinois.

JEEP Parts! For Military and Civilian. At great savings. Largest inventory Catalog for owners and dealers. Inquiries invited. American Auto Parts Co., 1830-P8 Locust, Kansas City, Mo.

AUTO shop welding repair training in world's largest non-profit welding school. Low tuition. Free booklet. Hobart Welders, Box F-81, Troy Ohio.

CONVERT column shift transmission to lightning-fast straight line floor shift with top quality easy-to-install Conversion Kit Complete, only \$25.70. Includes bent, straight lever (specify) knob, boot, instructions. Specify make year model type of transmission. Enclose 25c for C.O.D. orders. Whitney, 1919-P88 Archer, Chicago 16

HYDRAULIC Jack repair kits—free catalog—free "Silent-Salesmen" with each kit. Hydraulic Jack Packing & Tool Co. P. O. Box 60 Bloomfield, N. J.

DETECT police radar traps before they detect you. Buy Radar King. Plaza 31 Wardell Smith, Electronic Designs, 45 Glenwood Road, Upper Montclair, New Jersey

COPPER Tubing For all purposes. 60 foot coils. 3/4" \$4.85, 5/16" \$5.99, 3/8" \$7.49. All other sizes in stock. Freight prepaid. B and H Metal Company, P.O. Box 615, Boston 2, Massachusetts

PARTS Model "A", List 25c (Refundable) Matco, Box 135, San Pedro, Calif

1909-1914 FORD Parts. Illustrated catalogs 75c. Mark Auto, Edison, New Jersey.

AMAZING New Kit Stops Automobile Voltage Regulator Troubles Before They Start—Saves Money. Write For Free Literature. Electro-Mechano Co., 161 E. Erie Street, Milwaukee 2, Wisc

USE THIS HANDY INDEX TO FIND WHAT YOU WANT

Advertiser Agencies for Advertisers	33
Adm's Wanted	47
Antiques, Books & Indian Goods	29
Art Instruction, Cartooning, Signs	54
Painting	33
Authors Service	3
Auto Supplies & Equipment	3
Auto Trainers	3
Automobiles & Midget Cars	3
Aviation	2
Batteries, Generators Etc.	4
Boats, Outboard Motors	11
Body Building Courses, Jiu Jitsu Etc.	13
Books & Magazines	23
Business Opportunities	37
Buy It Wholesale	38A
Camera Photo Supplies	34
Camping Equipment & Tents	14
Cartooning, Sign Painting, Chalk Talk	34
Coin & Currency	26
Contests	48
Detectives	47
Do It Yourself	60
Dolls, Birds, Nameters & Pets	17
Earthworms, Crickets, Frogs	18
Education & Instruction	45
Electrical Supplies & Equipment	7
Employment Information	47
Engines, Motors, Air	10
Farms, Other Real Estate	19
Feld Glasses, Telescopes	14
For Inventors	60
For Sale Miscellaneous	71
Formulas, Plans, Etc.	39
Gifts	49
Government Supplies	11A
High grade Beermen	44
Hobbies, Collections	31
Home Craftsmen	95
Hydroponics	24
Import Export	18D
Inventions Wanted	61
Jokes, Games, Novelties, Etc.	24A
Language, Grammar	48
Leases, By Mail	81D
Machinery, Tool Supplies, Etc.	9
Magic Tricks, Puzzles, Etc.	25
Manufacturing	61
Minerals & Precious Stones	31
Miscellaneous	70
Models, Model Supplies	84
Motorizing, Conventions	74
Motion Pictures & Color Slides	33
Motorcycles, Bicycles & Supplies	4
Musical Instruments and Song Writers	35
Of Interest To Women	70
Old Gold, Jewelry, Watches	67
Patents For Sale	82
Personal	80
Photograph Records	35A
Photo Enslaving, Photocons, Etc.	32
Plans	40
Printing, Multigraphing, Etc.	37
Printing Quizzes, Supplies	38
Profitable Occupations	22
Radio, TV, Electronics, Hi-Fi	74
Remailing Service	87A
Rubber Stamps & Office Supplies	36
Science & Chemistry	41
Spec. Services	31
Sports, Goods, Guns, Fishing Tackle, Etc.	15
Stamp Collecting	28
Swap	70B
Tobacco & Pipes	88
Treasure, Purses & Gelzer Counters	77
Trees, Shrubs, Roots & Herbs	20
Wanted To Buy	72
Watch Repairing	74
Welding, Soldering	4
Western Merchandise	70C

'RING-Valve Job' while driving \$8.00 postpaid. Guaranteed. Nothing like it! Lasts 100,000 miles. Motoloy, Cranham 27 Penna.

AUTO Safety Belt, Nylon, Tests 4000 Lbs. Fits Any Auto, Complete With Anchors. Blue, Red, Green, Black, Tan \$8.95. Postpaid. General Safety, 657 W. Mason, Green Bay Wisc.

AUTOMOTIVE Electrical Circuit Tester locates wiring trouble with power Off test light complete with batteries \$1.95. Burnworth Tracer Company, 613 Pomona, El Cerrito El, California.

SPARK Plugs, Air-Oil Filters, 30% Discount, New Top Brands. Ext. Sales, 5229 Grove, Skokie, Ill.

TRANSISTORIZED Electronic Ignition Systems. The Greatest Improvement Since The Original Kettering 1910 Ignition Invention. Can Be Used On All 4 And 12 Volt Automobiles, Trucks, Race Cars, Boats. With Negative Ground. Dealers Wanted. For Low Prices And Literature, Write Bill Slep Company, Drawer 178PS, Ellenton, Florida.

CYLINDER Power Maintenance. Cpm500, 49c; Cpm1500, 98c; Cpm2500, \$1.49; Cpm4000, \$1.98. Box 4159, Los Angeles 64, California.

PARTS and Accessories Catalog for Ford Model A. Everything to renew, rebuild, and renovate your '28-'31 Model 'A' Ford. Send for J. C. Whitney, 1919-P88 Archer, Chicago 16, Ill.

3 AUTO TRAILERS

BUILD Expanding eight foot trailer. Accommodates five. Literature 10c. Framar Company, Wilmington Massachusetts.

4 MOTORCYCLES, BICYCLES AND SUPPLIES

RECONDITIONED Motorcycle Motors. Chrome accessories. Complete stock Indian parts. Expert rebuilding. Fast service. Indian Motorcycle Sales, Kansas City 27, Missouri.

BMW Motorcycles, shaftdrive, U.S. Distributor. Butler & Smith, Inc., 180 West 43 St., New York 24, N. Y.

GO Cart \$30. Motorscooter \$20. Motorbike \$20. less engines. Engines \$2 up. Motorbike \$25. Doodlebug \$35. Flat Chassis \$75. (Mail order only). Send 25c, (35c. for First Class Mailing) for 32-page Directory-Catalogue Number 103 listing these and hundreds of other bargains in Go Carts, Motorscooters, War Surplus homebuilders, parts, parts etc. Midget Motors Directory, Athens, Ohio.

DEALERS wanted for 'Peugeot' Motorcycles and Motorbikes, also Vespa's. Motorbikes. Prices start at \$129.85. List, P.O. B. assembly plant Fort Lauderdale, Florida. International Cycle Imports, Inc., 1041 N.E. 20th Court, Fort Lauderdale, Florida.

IMPORTED 1962 motorcycles \$500.00. Everett Cooksey, Route 3, Choctaw, Okla.

SCARCE Bicycle Parts—Tires. We have them. Northern Wheel Goods, Box 3100, Madison, Wisconsin.

POPULAR SCIENCE OPPORTUNITIES

5 AVIATION

PROPELLERS Plans Supplies for airplanes, Snowplanes. 125 H.P. Lycoming engines \$135.00 Prompt Delivery Catalog 25c Banks-Maxwell Propeller Co., Box 33010 Ft. Worth 5, Texas

HARTLETT Flying Saucer" M2 Amazing Aircraft Lawn mower engine flies 300 lbs over land water Easily built and flown. Info 25c. Plans \$5.00 Kits \$49.95 Write Herb Hartlett, Box 88A, Silverdale, Washington.

6 BATTERIES, GENERATORS, ETC.

REACTIVATE ordinary flashlight and radio batteries over and over Service your neighbors' batteries. No gimmick but a proven electronic method. Send \$1.00 for fully illustrated instructions and simple circuits. Write B.I. Electronics, P.O. Box 173, Outremont, Quebec, Canada

7 ELECTRICAL SUPPLIES & EQUIPMENT

RECTIFIERS, Electroplating Equipment And Supplies. Free Catalog. Hot Wood Bronze Supply Dept. N7, 1824 East First, Los Angeles 13, Calif.

LAMP — Appliance — Vacuum — parts wholesale catalogues 25c. Seco, 28 South 20th Street, Birmingham 3, Alabama.

8 WELDING, SOLDERING

ARC Welder Manual, . . . Only 50c regular \$1.00 value. Tells how to weld every job. Emerson Electric, 8100 Florissant, St. Louis Missouri.

WELDERS, 110-220. Welds 1/2" \$39.50 Morris, 1079 Inner Drive, Schenectady, New York

9 MACHINERY, TOOL SUPPLIES, ETC.

SHKET Metal brakes; 36"—\$27.00 Larger sizes, Benders, folders, shears. Free catalog Vyke Company, N4134 Jason, Denver 11, Colorado

10 ENGINES, MOTORS, ETC.

DIESEL Injector Parts and Fuel Pumps Wanted GM31-33 71-110. Mayer 7130 Carnegie Cleveland 3, Ohio.

REWIND Motors yourself. Complete instructions \$1.00 Lewis Manufacturing, Howell, 11, Michigan

PUT Your Three Phase Motors To Work On Single Phase Simple Hookup Does It! Instructions—\$1.00. Gregory, 1401 So Riverside, Rialto, California.

AIRBOAT Snowplane engines. Propellers. Supplies. 125 H.P. Lycoming engines \$135.00. Catalog 25c Banks-Maxwell, Box 33010H, Ft. Worth 5, Texas.

MOTORS, Pumps Generators. **EMCO** Atlantic Engines, 741 Ocean, Freeport, N. Y.

11 BOATS, OUTBOARD MOTORS

NEW used, rebuilt marine motors. Marine conversions, fittings. Free Catalog Stokes Marine Supply, Dept. 23, Coldwater Mich.

FULL size, cut-to-shape boat patterns. blueprints 7", 14 feet. Big new 64 pg illustrated Build a Boat Catalog of Naval architect-designed Catamarans, Cruisers, Runabouts, Skiffs, Outboard Boats, Sailing Racers, Houseboats 50c. How to Build a Boat" Booklet, \$2.50. Cleveland Boat Blueprint Co., Dept. A-77, Box 1431, Cleveland Ohio

BOAT Plans, Frame Kits, Full Size Patterns prepared specially for amateurs. Send 50c for new 80-page catalog illustrating over 40 Build-it Yourself power boats from 7' to 38'. Glen Marine, 8152 Rosecrans, Belvedere, Calif.

11A GOVERNMENT SURPLUS

GOVERNMENT Surplus—Jeeps, \$264.00 Radios, \$2.53. Boats, \$38.00; Guns, Airplanes, Walkie Talkies, Typewriters, Cameras; Tools, thousands of items. Buy direct from government at ridiculously low prices. Full details and procedure all yours complete by return mail, only \$1.00. Surplus Bargains, Dept. PS, P. O. Box 512, New Orleans, La.

BUY Government Surplus direct. Jeeps, boats, radios—everything from A to Z. Complete information by return mail Satisfaction guaranteed \$1.00 Surplus, Box 2434-S, Washington 13, D. C.

JEeps \$278. Airplanes \$158. Boats \$7.85. Generators \$2.48. Typewriters \$4.79 are typical government surplus sale prices. Buy 10,001 items wholesale direct. Full details, 827 locations and procedure only \$1.00. Surplus, Box 789-C2, York, Penna.

GOVERNMENT Surplus How and Where To Buy In Your Area. Send \$1.00. PS Surplus Information, Headquarters Building, Washington 6, D. C.

JEeps—\$223.62. Radios—\$2.47. Boats—\$4.18. Tires—\$1.74. Generators—\$1.38. Typewriters—\$4.48. Guns. Cameras. Binoculars. Typical Government Surplus Prices. Buy Direct Last Of Depots, Procedure Full Details. Only \$1.00 N.Y. Enterprises, International Airport, Box 402-58 Jamaica 30, New York.

BUY War Surplus Direct From the Government—Airplanes. Boats. Jeeps. Trucks, Tractors, Helicopters, Walkie-Talkies, Radar, Mac. Send for Brody's U.S. Depot Directory & Procedures" \$1.00. Box 425-PS, Nantuet, New York.

12 BODY-BUILDING COURSES, JIU JITSU & ATHLETIC EQUIPMENT

BUILD powerful arms, chest, shoulders! 22 exercises. \$1. Poonad, Box 601-C, 1100 Market, Wilmington 90, Delaware

30 JUDO, 10 Savate, 30 Karate lessons! Bodybuilding course! Boxing! Stunts! Yoga instructions! Charts Diagrams 125 illustrated lessons Everything \$1.00 Oxford A44 Bromfield, Boston 8, Massachusetts.

BIG Deal! 12 large, advanced muscle courses, health wisdom courses, valuable information. Over 50,000 words complete. Guaranteed Special only \$1.00. Ed & H. Stern, PS-C6, 8421-C Evergreen, Southgate, California

BECOME super muscular with world's best course! Win prizes! Free details! Samson, P.O. Box 43, Tremont Station, New York 57, N. Y.

PROP Wong's Karate Kung Fu Break bricks barehanded \$8.95. Oriental Book Sales, 142 Waverly Place, San Francisco 8 Calif.

OUTSTANDING Physical Development! Any Age. New Guaranteed Discovery! Use Only A Rope! Strength, Health, Muscle. Gain-Reduce. Free Booklet. Ropercus, 4814-A Art. San Diego 15, California

GIANT Arms" Dr. Young's, D. C. Revolutionary discovery. \$2. Satisfaction or refund. Gaucho, Box 8308-S6, Chicago 90

"KARATE" Jiu Jitsu fighting secrets. Fear no man knives, guns, clubs. Thirty-six knockout blows without hits. Forty lessons 66 photographic illustrations, copyrighted by world-famous Military and Official Police Instructor. Amazing simplified homestudy course, complete \$1.00. Jorgensen, Box 3823-598, Seattle 7, Wash.

PUSHED around? Don't take nonsense from bullies. Surprise them. Easy when you know Police Jiu Jitsu. Complete fully illustrated course in one volume as taught police and armed forces. Send \$1.00. Satisfaction guaranteed. Books Publishing Co., Amityville 29, New York.

14 FIELD GLASSES, TELESCOPES

FREE Catalogue! Thousands war surplus optical, bargains. Lenses, Prisms, Telescopes, Binoculars, etc. Send \$1.00 for 10 Lens Hobbyist Set and Project Booklet. G. Jagers, 681 West Merrick Road, Lyndbrook, New York

SCIENCE Bargains' Lenses, Telescopes, Binoculars, microscopes, kits parts war surplus. Send \$1.00 for beginner's 10-lens kit with instruction booklet. Order Stock 2-CN Request Free 144-page Catalog CN Edmund Scientific Co., Barrington, New Jersey

DYNASCOPE—Amazing world famous reflector telescopes. Request free brochure. Criterion, Dept. D8 38 Hartford 1 Conn.

REFLECTING Telescope completely assembled 80X. Guaranteed Observatory clearness. Free information, The Skyscope Co., P. O. Box 55, Brooklyn 28, New York.

BARGAINS, Binoculars, Telescopes, Riflescopes, Microscopes. Catalog Free. Adventure Sales, Box 2188, San Diego 12, California.

BUILD your own Reflector Telescopes. Complete kits, Mirrors, Eyepieces, Tripods, all other accessories. Request free illustrated literature. Criterion Manufacturing Dept. KP-81, Hartford 1 Conn.

TELESCOPE kits—direct from manufacturer. Other optical, hobby kits. Large selection. Free booklet. Ecco Products, Oakridge N. J.

TELESCOPES and telescope makers supplies. Free catalog. Suffolk Science, Mattituck, New York.

ASTRONOMICAL books, star-atlases, free list. Herbert Luft, 89-11 229th St., Flushing 64, N. Y.

15 SPORTING GOODS, GUNS, FISHING TACKLE, ARCHERY, TRAPPING

100,000 PRODUCTS Wholesale — Free catalog! Send postcard. Econ-O-Mart, Whippany 18, New Jersey

FREE Wholesale Catalog. Seeds, Spinners, Lure parts, Sinkers, molds, Jugs, Rera Finny sports, (P.E.), Toledo 14, Ohio.

3000 GUNS, Swords, War Relics. Catalog 50c. Smith Museum, Hunnemed N. J.

154 PAGE catalog—a real "Dream Book" for fishermen! It's free. Netcraft Company, Dept. A 2, Toledo 13 Ohio.

10,000 GUNS! — Antiques, Moderns, Swords, Armour, every description. Giant Catalog \$1.00. Agromonte's, Yonkers 7-A, N. Y.

HUNTING Guide Free! Experts tell you how to be crack shot, dress game, care for weapons, camp cookery and how to have convenient heat and light in the woods. Supplies limited. Write A. W. Thacker Co., Dept. PS, Clermont, Fla.

BUY Hunting And Fishing Equipment Direct And Save. Weaver Scopes K 1.5 or K 3 Retail \$27.50, Special \$23.95, K 4 Retail \$45.00 Special, \$26.75. Vari Power V 8 with mount Retail \$75.50 Special \$52.95, Redding Powder Scale, Retail \$14.00 Special, \$10.95. Redding Press, Retail \$16.00, Special \$11.95. Lyman 310 Tool with Dial, Retail \$16.50 Special \$13.20. Ruger Deerstalker Carbine Retail, \$108.00 Special \$81.75. Free Giant Fully Illustrated Catalogues featuring World's Finest Hunting and Fishing Equipment at Lowest Discount Prices (Spec'y Hunting, fishing or both) No money down Up to 10 months to pay. International Charge Credit Cards honored on all purchases—any amount. (Add postage and items 20¢ deposit on all C.O.D.'s). Parker, Duanebors (Dept. PS 981 3516 White Plains Road, New York 67, New York TUNP-1 1900

SURPLUS Guns, Rifles \$7.85, Revolvers \$6.95. Bargain list 25c. Consolidated, Box 34, Fulton, Calif.

CROSSBOWS Hunting—Bows! Factory Prices! Jayco Box 1255, Wichita, Kansas.

JAP rifles altering American shells 94.00. Jap shells \$3.95, catalog 10c. TP Shop, West Branch 10, Michigan.

16 CAMPING EQUIPMENT & TENTS

CAMPING Equipment, world's largest selection. Low prices. Send 25c (print name—address) for complete giant catalogue of Tents, Camping Equipment, National Camp Sites Guide & Camping Handbook. Morrison Tents, 10-150 both Ave. Long Island City 1, New York

TENTS, Government surplus, 5 man hexagonal, pyramidal. Cost \$140. Our price \$39.50. \$275 Paint Spray unit \$44.50. Free folder. Inasco, 1820 S. State, Chicago 14, Ill.

POPULAR SCIENCE OPPORTUNITIES

BUILD Your Pickup Camper Kits. Blueprints, Plans, Literature 10c. Camstock Plans, Patuxent, Kansas.

17 DOGS, BIRDS, HAMSTERS, RABBITS & PETS

RAISE Rabbits and Fishworms on \$300 month plan. Free details. White's Rabbitry, Mt. Vernon, Ohio.

BLOODHOUND Puppies: Registered. Write Richard Baylor, Hinton, West Va. Phone 245.

BABY Raccoons, skunks, monkeys, turtles, snakes, lizards, birds. Catalogue 10c. Thompson Zoo, Cleveland, Fla.

HAMSTERS—Ideal Pets. \$2.95 pair. Free literature. Jar-Pro's Hamsters, 1447 Apple, Muskegon 18 Michigan.

LIVE Seahorses. Mated Pair Direct To Door—Delivery \$3.50. Check Or C.O.D. Food And Instructions Included. Gift Shippers. Opalocks, Fla.

STOP That Chaser With Dog-It. Guaranteed to stop your dog's rat chasing. Completely harmless, no spray or clumsy devices. Only \$1.00. Dog-It, 2648 N.W. 58th, Seattle 7, Washington.

18 EARTHWORMS, CRICKETS, TREES

FREE Picture Folder. How to Make \$3,000 Yearly. Sparetime Backyard, Raising Earthworms! Oakhaven-121, Cedar Hill, Texas.

FREE Literature. Big money raising earthworms and crickets. Write to you how to raise and sell. Special Today. Hybrid red wigglers. 3000—\$5.95, 5000—\$8.95, 10,000—\$18.95. Postpaid, with raising and marketing instructions. Read our Life Magazine Story, Dec. 28, 1958 issue. Carter Farm-12, Plains, Georgia.

DEALER Fishermen's Grocers' Refuse buying fishworms. Write for low job of prices, free raising instructions! Fishworms-G, Cedar Hill, Texas.

HYBRID Redworms. 1000—\$1.00, 3000—\$3.00, 5000—\$5.00. Postpaid With Raising Instructions Worm Gardens. 324 David Drive, Waco, Texas.

LARGE African Night crawlers. 100—\$2.00, 500—\$7.00, 1000—\$12.50. Postpaid (Western mailed). Oak Worm Farm V. Willow Springs, Missouri.

19 FARMS, OTHER REAL ESTATE

CANADIAN Tax Sale Lands. Our 44th annual sale of land, just begun, deals in farms, timber lots, hunting and fishing camps. Average price five dollars an acre. Small monthly payments guaranteed. Write today for free sixteen page booklet containing full information. Tax Sale Service Room 411 N. 17th Street, Toronto 5, Canada.

CANADIAN Vacation Lands. Large acreage, low price \$9.90 per acre. Suitable for lake sites, hunting, fishing, recreation. Free information. Land Corporation 1700 D. Bathurst, Downsview, Ontario, Canada.

NEW Strout Fall Catalog Just Out! Free! Farms, Homes, Businesses, over 3,000 bargains, 36 States & Bermuda, established 81 years, World's Largest! Strout Realty, 231-235 Park Ave. South, New York 10 N.Y.

U.S. RESIDENTS eligible now. Amazing profits from recorded timber leases. Low cost, terms. Free information. Lismann, 130L Shaftesbury, Downsview, Ontario, Canada.

CAROLINA Coast \$3 down \$8 monthly. Buy large homesite 70x150 in beautiful setting. See & Lake. Satisfaction guaranteed. 16,000 acres, \$2 freshwater lakes. Excellent fishing, hunting. Free literature. Bowling Spring Lakes, Southport 2, North Carolina.

FLORIDA Campsites deep in the heart of the great Ocala National Forest. Abundance of game, best fishing. Warranty deed. Unrestricted—pitch tent, park trailer, build house. Free maps and photos. Winfree Vernon, Deland, Florida. AD-60086 Q-Q.

20 TREES, SHRUBS, ROOTS, HERBS

GINSENG bringing \$14 pound. Have seeds, plants. Or herbal. Full information. G. Collins, Viola, Iowa.

22 PROFITABLE OCCUPATIONS

INVESTIGATE Auto Accidents. Earn \$750 to \$1,000 monthly. More investigations urgently needed. Car furnished. Business expenses paid. No college education necessary. No selling of any kind. Pick your own job hours. Most interesting. Important people. We train you at home in spare time. You keep present job until ready to switch. Write for free book. No obligation. Liberty School, Dept. C-38, Libertyville, Illinois.

FREE Picture Folder. How to Make \$3,000 Yearly. Sparetime Backyard, Raising Earthworms. Oakhaven-7, Cedar Hill, Texas.

BYCOME independent with your own franchise business. Thousands earning handsome incomes. Request interest facts today. National Franchise Reporter, Y-328, 233 North Michigan, Chicago 1.

VENDING Machines—No Selling. Operate A Route of Coin Machines and Varn. Amazing Profits. 32-Page Catalog. Free. Parkway Machine Corporation, Dept. 17, 713 E. 10th Street, Baltimore 2, Maryland.

FREE Literature—Make Big Money Raising Fishworms and Crickets. Carter Farm-10, Plains, Ga.

INVESTIGATE Accidents. Earn \$750 to \$1,000 monthly. Men urgently needed. Car furnished. Business expenses paid. No selling. No college education necessary. Pick your own job hours. Most interesting. Important people. We train you at home in spare time. You keep present job until ready to switch. Write for free book. No obligation. Liberty School, Dept. C-38, Libertyville, Illinois.

END Money Worries. Bake new greaseless doughnuts in 10 min. Half price. Sell stores. Free recipe. Stephen, 2408 South 13th, Minneapolis 7, Minnesota.

SHARPEN—science pointers inexpensive. Lower sharpening supplies. Blackhawk, Stoughton, Iowa.

FREE Book. 100 Successful Little-Known Businesses. Write home. Plymouth 45H, Brooklyn 5, New York.

AUCTIONEERING—Resident and Home Study Courses. Diploma granted. Auction School, Ft. Smith, Ark.

23 BOOKS & MAGAZINES

GOOD Used Books. 10c-\$1. Free Lists. Editions, Dept. PS, Hempstead, New York.

BRITISH Book Bargains. Any subjects. Catalogue free. Transbooks, Wantagh 71, New York.

ATHLETIC Books Catalogue free. Truth Seeker Co., 38 Park Ave., New York 9.

THOUGHT Ray Broadcasting. Receiving with a thought. Amateurs. New books. Over 100 million different wave-lengths. Manual. Thought Broadcasting, 814 S. 22nd Street, St. Augustine, Florida.

NATIONAL Geographic Magazine. Any time, 1958-1960. Periodical Service, Box 463 PS, Wilmington, Delaware.

BOOKHUNTERS. All Subjects. Send Wantal. Jaber Book Service, 183 Woodwood Drive, Westbury, New York.

1,000 001 15c-BOOKS. Thousands Titles. Box to Sharepoint. Catalogs 10c. Bargains, 1523-Y8 Chaparral, Corpus Christi, Texas.

BOOKHUNTERS. Scarce. Many late books. Supplied. Atlantic Book Service, 18 Cedar Charlestown 20, Mass.

MAGAZINES Wholesale Retail. catalogue. Dr. Backdale, 1181 East Lombard, Baltimore 2, Maryland.

SURVIVE World War III. Read Civil Defense Magazine \$2.00 per year. Free shelter and survival manual with subscription. Box 1047C, Bloomington, Indiana.

RENT Technical Books. Reference And Textbooks Of All Subjects. Last Best Mention Particular Needs. H. J. Bush, 7234 Pine Street, Upper Darby, Penn.

24 HYPNOTISM

FREE Hypnotism, Self-Hypnosis, Sleep-Learning Case or Records Tapes, Books, Courses, Equipment. Drawer PS400, Redwood, New Mexico.

HYPNOTIZE Self Others while asleep with amazing hypnotic phonograph records. Catalog free. Research Association, Box 24-G, Olympia, Washington.

FREE Illustrated Hypnotism Self-Hypnosis Catalogue. Write H. H. H. H., 8721 Sunset, Hollywood 46P, California.

HYPNOTIZE Successfully! "One Word Instantaneous," "Against Will!" Methods Exposed! Complete Illustrated Course—Including "Secret Nerve Pressure Technique" \$1.00. Arthur Fowler, Box 4301, Woodbury, New Jersey.

HYPNOTISM Self-Hypnosis Guaranteed. Home study course. Diploma issued. Free brochure. School Hypnotism, 400 Robyn Pl., East Meadow 1, N.Y.

HYPNOTIC Training Kit. Now—amaze friends with your mental power. Force their neuro-muscular response. Complete with Optic Directional Chart, Weighted pendulum, ring instructions. Guaranteed. Only \$2.00. Allied Aids, Dept. CT-3, 1132 Broadway, N.Y.C. 10.

SELF-hypnosis may help you many ways. Proven new concept of learning quickly. See it. Book. "The Record." Free literature. M. Kiley Publishers, Audio Dept., Box 5618, San Bernardino, California.

FREE Illustrated Catalog Everything on Hypnotism. Merlin Enterprises, 1204 Lincoln Avenue, San Jose, California.

35 LESSONS! Complete course, 811 Satisfaction guaranteed! Scott, Box 240, Great Neck, New York.

HYPNOTIZE Unnoticed, quickly, effortlessly. Write for free literature. \$1.00. Intern, Box 244, Cedarburg, Wisconsin.

HYPNOTIZE One word. One finger snap. On stage. Satisfaction or refund. 62 Hypnomaster, Box 8100-40, Chicago 90.

SELF-Hypnosis, Hypnotism. Little Professional Method. Free. Brochure Dr. Ardan, 1035 N. Fulton Street, Fresno 4, California.

24A JOKES, GAMES, NOVELTIES, ETC.

2700 NOVELTIES. Jokes, tricks, funmakers, bubbles. World's biggest gadget catalog. 10c. Johnson, Box 10, Detroit 7.

25 MAGIC TRICKS, PUZZLES, ETC.

WORLD'S finest professional magic. Joke pointers, Giant illustrated catalog 10c. Top Hat Entertainment, 13 Detroit.

500 TRICKS. Famous Douglas catalog of magical tricks and supplies now available just 10c. Fastest service. Douglas Macdonald, Dept. 62, Dallas, Texas.

3000 TRICKS. pocket parlor stage. World's Finest Magic Catalog (400 pages). \$2.50. Kanter's, 4-1211 Walnut, Philadelphia 7.

INDIA Rope Trick And Magic Catalog. 25c. Hocus Focus, 200 West Capitol, Jackson, Mississippi.

50 SPICY Cards \$1.00, 10-25c Different! Excelsior, 387-A, Lynnwood, Washington.

26 COINS & CURRENCY

INDIAN Head Cents, two different only. 25c. Approvals. Littleton Coin Co., Littleton R2, New Hampshire.

\$12.50 FOR One Silver Dollar. Amazing new 1961 U.S. Coin Book by Jacques Del. More & everything on every silver coin minted, worth value how to sell, speculate, investment, other valuable facts. Cloth bound, 150 illustrations. Send no money. Pay postman \$2.00 (plus postage) or \$2.00 postpaid. (Refundable). Arden Book Co., 300-CP Fourth Ave., N.Y.C. 10.

3 INDIAN Cents Plus Liberty Nickel 50c. Hutchinson's, Box 8254, Philadelphia, Penna.

POPULAR SCIENCE OPPORTUNITIES

TRUNKFUL 20 000 Liberty-Buffalo Nickels Wild pack grab-bag style 100 mixed \$50 sample bag of 10-\$3 Money back guarantee Mrs. Fischer, Dept. BB, 3 Centre St. Hempstead, N. Y.

COIN Collectors Largest Newspaper Twice Monthly, 10 issues \$1.00, \$2.00 yearly. Numismatic News, Washington St., Iowa, Wisc.

COIN Magazine, 100 pages, Sample 50c. Numismatic, 7120 Milwaukee, Chicago 31.

FREE Coin Supplies Giant Coin list 10c (refundable). Economy Sales, Mansfield, Massachusetts.

BRILLIANT Proof sets (in cases)—Cyprus \$10.50; Ghana \$10.50; Quetzal \$5.50; Pakistan \$5.25; South Africa \$4.25; World Coin Book \$4.25. Organic Bargain Co. catalogue \$1.00. Free with \$10.00 order. Books \$4.14 North 30th, Omaha 11, Nebraska.

BARGAIN List U.S. Coins Accessories. Stamp plates. Hugh A. Hickory N. C.

RAKE 1874 CC Mint Dollar Uncirculated \$5.00 100 pg. coin catalogue 50c. Shurtz Salt Lake City 10, Utah.

INTRODUCTORY Free Confederate Dime Year 40 and medal catalog. Send 25c for postage etc. Hobbies, Box 71 B Rockaway 44, N. Y.

LINCOLN 40 Different 1908 40 Plus 1960L Small Date 1, 25 25 Different 4. Including Hare 1935H \$1.50. Harrison, Box 6.93, San Francisco, California.

40 PAGE Illustrated United States and Canadian coin list 10c. Steady, 260 Wash. D.C.

TWENTY page 1961 retail price list of U.S.A. and Canadian coins for 19c. Our selling prices on thousands of coins and coin collectors supplies. Bryson Incorporated 438 White, Toledo 3, Ohio.

7 INDIAN Cents \$1.00. Liberty Nickels 6-\$1.00 14 \$2.50. Doktor, P.O. Box 25151, Los Angeles 33 Calif.

25 DIFFERENT Indian And Lincoln Pennies \$3.00, 11c, \$5.00. Wesley Road, Hawatha 5, Iowa.

TWO Brilliant Uncirculated Mexican Silver Dollars—\$1.00 (Refunded) Universal Services, Box 266, San Antonio 8-A, Texas.

28 STAMP COLLECTING

AMAZING Offer! 200 U.S. stamps—including commemoratives, airmails, high denominations to \$1.00—only 10c to Approval Applicants! Illustrated Bargain List free. Mystic Stamp Co., Dept. 36, Camden New York.

EXCEPTIONAL 125 different cataloging \$3.00 includes triangles commemoratives 10c approvals. Reeves, Box 27547F, Miami 37, Florida.

UNITED States commemorative collection containing 33 different—10c. Approvals. White, 516-W Avenue L, Brooklyn 30 New York.

WORLDWIDE, 50 all different, absolute free just to introduce our incomparable approvals. Kent Stamp Company GPO Box 17 Brooklyn New York.

TWO \$5.00 United States Stamps, twenty others 10c with United States approvals. Irwin, Box 1100, Brooklyn 30.

NUDES set (4)—Unusual Approvals 10c. Atlas Fairfield Racine Wisconsin.

ALBUM Hundreds of Spaces! Only 25c. Fox paid Stampcraft, Hartford 1, Connecticut.

MYSTERY Bag Stamp Collection, Only 10c. Hill Company Defiance, Ohio.

225 STAMPS For only 10c! This mammoth value includes Airmails. Plus rare stamps from strange Countries cataloging up to 25c each! Also Approvals. Mystic Stamp Company, Camden 35, N. Y.

25 DIFFERENT Large American Commemoratives, 10c with approvals. Linstamp, St. Catharines 103, Ontario.

100 DISSIMILAR British Colony stamps 10c Approvals. Crown Stamp Company, Virgil 402, Ontario.

1 000 DIFFERENT Worldwide Stamps \$1.00 Valued over \$20.00 To introduce our unique services Universal, Box 4, Menasha 4, Wisconsin.

307 WORLDWIDE Different Stamps only 25c Approvals. Niagara Stamps, St. Catharines 202, Ontario.

STAMP Jungle including Zebu, Kookburra, Komabur, Kangaroo, Rhinoceros. 10c Approvals. Crown Stamp Company, Virgil 402, Ontario.

100 DIVERSIFIED British Empire stamps, 10c. Approvals. Niagara Stamps, St. Catharines 502, Ontario.

107 DISTINCT British Colonial Stamps, 10c Approvals. Linstamp, St. Catharines 402, Ontario.

25 DIFFERENT Commemoratives 1961 up 10c U.S. Approvals. E. & B. Box 211 Brooklyn 22, N. Y.

UNITED Nations 15th Anniversary Sheet With first day cancel, as commemorated by Russia. Free While they last with approvals. Philadelphia, P-J. New Paltz, N. Y.

U.S. STAMPS Giant Discount Catalog—20c. Rayman, 27-VX Maiden Lane, N. Y. C. 14.

FREE! Giant Bargain Catalog—New Edition listing thousands of bargains in such as U.S. and N.A. Stamps, packets, m-stamps, albums, accessories and supplies sent with beautiful approvals. Adults only! Jamestown Stamps, Dept. E-1-P5 Jamestown N. Y.

100 DIFFERENT Stamps, 10c with approvals. Smith, 306U Brooks, College Station Texas.

50 DIFF U.S. Stamps Includes 15th Century Commemoratives. High values. Plus 143 Flag Stamp of Occupied Nations. All for only 25c Approvals included. Willett Co., Box 234-Y, Yorktown Heights, N. Y.

WOW! 110 All Different Germany 10c Zeppelins, Semi Postals, Airmails. High values, etc. Giant Catalog bargain lists included with beautiful approvals. Adults only! Jamestown Stamps, Dept. A-1-P5, Jamestown, N. Y.

21 000 All Different, only pennies a day using our systematic payment plan. Details Free. Spoult 1435 A Cherrydale San Jose 28, California.

U.S. Mini Specials! Flag Set Complete \$1.00 1c, 2c 3c Famous Americans 21 different, \$1.00 Free list B. Box 2323 Avenue K Brooklyn 25, New York.

1002 COSMOPOLITAN 40c Contains U.S.A., Russia, First L.N. Summit Conference Olympics, Space Satellites, hundreds more. Approval request references required. Horace Oakwood, Winston-Salem North Carolina.

AMERICA'S Biggest Stamp Bargain \$10.00 Catalog Value Only \$ 6.00 Jean Husak, 342 Liberty Syracuse 4, N. Y.

50 DIFFERENT stamps free with attractive approvals. Patton 2, 600 Cal Boulder City Nevada.

"OLD Glory" In Flaming Colors!! USA Flag sent beauty from Honduras. 1. ornous U.S. led Nations Mexican Stamp Plus 5 rarest Gorkus issue Duke of Windsor Morning Jersey Macao towers Wild Buffalo stamp & others 10c with approvals. Sunny Stamps, Apopka 10, Florida.

FANTASTIC Fish Triangles!! Valuable Ben Franklin on Canal Zone. Flaming bi-colored Volcano Triangle!! Lovely Olympics Triangle!! Plus Icy Greenland, Weird Wild Beast issue and others, 10c with approvals. Roseland Stamps, Spring Lake 10, Michigan.

500 DIFFERENT World-wide from Formosa, Morocco Indonesia etc. cataloging over \$15. only 35c Offer to Adults only Approvals. Littleton Stamp Co., Littleton CO, N. E.

GIGANTIC Collection Free—Includes Triangles—Early United States—Animals—Commemoratives—British Colonies—High Value Portraits, etc. Complete Collection plus Big Illustrated Magazine all free. Send 5c for postage. G. & S. Stamp Company Dept. PR Toronto Canada.

WEIRD Diamond Shape Coffee Stamps—Lovely Flower Triangle First Amer. on big commemorative Green and 10c Dancer etc 10c with approvals. Capital Stamp Co. Ferrysburg 10, Mich.

715 DIFFERENT Worldwide 25c Flame Korea Japan Russia Transvaal Approvals. Bob's Box 2045, Saint Louis 20, Missouri.

FREE 400 genuine postage stamps! Worth \$10.00 at catalogue prices Africa—British Empire—Asia—Europe and Bonus, Russia honoring "Man in Space" Yuri Gagarin beautiful stamps with Tab signed by Khrushchev—a fascinating valuable mixture from foreign continents banks, etc. Who knows what you will find. Also free valuable book et Adults only Approvals enclosed. Frazer Co. P80, White Plains, N. Y.

ROOSEVELT Giant Diamond Red Cross Triangle, 25 others, 4c Approvals. Frisch, 428 Main, Northampton, Penna.

SEVENTY Different United States Obsolete and Current, 25c. Ed Kallier, Library 2, Penna.

100 DIFFERENT United States Commemoratives, 1/2c to 10c values, \$1.00. Adults may request approvals. Gil, Box 12C, Brooklyn, N. Y.

200 DIFFERENT U.S. Stamps \$1.00 Approvals included. Shelton, Box 207-26, New York 8 N. Y.

FREE 50 Different stamps Approvals. Werkhovet, 6545 Alascadero, Santa Barbara Calif.

TRIANGLE Flowers Set "Olympics Triangle!! African Flag!! 25 others, 4c. Approvals. W. Kert, 1430 Oakland, Petersburg Virginia.

DIAMOND Roosevelt Pope Triangle, Green and Ang. a 1, others 5c Approvals. Loughorn Box 1048P Lubbock, Tex.

2000 STAMPS \$2.00 On and off paper. Good variety World wide, Many pictures. No approvals follow. Satisfaction guaranteed. Whalen, 1435 First Ave., Oakland 6 Calif.

GIANT Approvals Thousands Different 1c and 2c ea. h. Wahl's Stamp Exchange, 7004K Farragut Chicago 31 Ill.

TRIANGLES, Diamond set of Butterflies, Flowers, 25 others, 4c. Approvals. Benson Box 77 Ocean New York.

FREE! 25 Different New Zealand; colorful, inexpensive approvals. Ekhart, Box 22, Ekhart, Indiana.

FREE! 6 Rainbow colored Flag Stamps!! Approvals. C & R Stamps, Box 222 Hicksville, New York.

AIRMAILS: World-Wide collection, Many Complete sets, Bargain lists, Approvals. This done promptly mailed. Charles Boger Box 142, North Wales, Pa.

FREE! Exotic Mint Polynesian Nuts Girl stamps Giant bargain lists included with approvals. Alpha Stamp, 1010-P6 Terrill Drive Dallas 24 Texas.

FREE magnifying glass with order for 25 different large U.S. commems, 25c. Manning, 21 Lakeside, Freeport, N. Y.

50 DIFFERENT U.S. (36 Commemoratives) 25c, 80 approvals. Seidenberg, Astoria Wis.

TONGA, Ruanda, Congo, etc. Free with approvals. Devel, P.O. Box 142, Palmyra, New Jersey.

THREE Mini Sets Free with Approvals. Ross, 1171 Nichols, Stratford, Conn.

300 DIFFERENT 25c with foreign approvals. Robert E. Bedford, Box 611, Minneapolis 24, Minnesota.

UNITED NATIONS, Five different 10c. Approvals. Anderson, 1334 Delaware, Santa Cruz California.

340 DIFFERENT world cataloging to 25c each 10c to approvals applicants. Winchester Stamps, 43 Winchester Rd., Mansfield, Ohio.

14 000 DIFFERENT! Amazing new plan builds your collection systematically country by country. Only 50c weekly. Free details L. L. Ware, Stegney 70, Conn.

FREE Mini Set—Approvals Accompany. Mintco, Box 137, Memphis 1, Tennessee.

TERRIFIC Beauties! 2c-10c Approvals. Marshall, Box 552-R, Pacific Grove, Calif.

151 DIFFERENT U.S. commemoratives \$1.00, Carstamps, 725-B Ordway, Freeport, Illinois.

100 WORLDWIDE Includes Airs, midgets triangles 10c Approvals Premiums. Faith, 29 1/2 Bushnell, Alhambra, Calif.

POPULAR SCIENCE OPPORTUNITIES

50 DIFFERENT U.S. 10c with U.S. Approvals. Desert Stamps. Box 1024. Scottsdale, Arizona.

100 OLD U.S. Stamps between 1861 and 1935 \$1.00. Housch Stamps. 31 Chestnut. Mansfield, Ohio.

U.S., U.N., Confederate States Illustrated catalog free. Stone, 340 Washington, Boston 8, Mass.

PENNY Approvals! Regardless Catalogue. Kloster, 4164-42nd St., San Diego 8, California.

MILLION Foreign Stamps! 3c each! Send for free 4 giant approvals! ABC Stamps. Box 4000 HQ, San Francisco 1, California.

FREE Mystery stamp packet. Premiums. Antonsen-Dancer. 875-143. Mansfield, Ohio.

THIS outstanding system brings you hundreds of stamps each and every week. Gives your duplicates real value. Obtaining stamps otherwise hard to find. Complete or a la carte. One year's membership \$1.00. Las Vegas Stamp Service, 438 Oakley Blvd., Las Vegas 7, Nevada.

500 MIXED U.S. various issues. 25c. Munz, Farmington, Cincinnati 14, Ohio.

50 DIFFERENT Stamps Free with approvals. Beach Stamps. Box 218a, Pompano Beach, Florida.

WORLDWIDE Large pictorial commemoratives 50 to 1000 diff. prices each. 75 large foreign from 75 countries \$1.00. Philatelic supplies, albums, catalogs and premiums. 25c. orders \$1.00. discounts. Rudin. Box 323, Amherstville N.Y.

HUNGARY "Zoo Parade" Elephants, Tigers—given with approvals. Williams Deems, Ravenwood, West Virginia.

100 DIFFERENT Sweden, 35c! Bargain Approvals Catalog. 35c. H. Howard City Michigan.

SENSATIONAL Penny Approvals! Pictorials, Topicals, Etc. Write Today! Schmidt, Box 1128 Richmond, Calif.

SOUTH Sea Island Magic. Free Mnt. Commemorative from Cook Islands, New Guinea, New Hebrides, Papua New Guinea & postage. Request Approvals. Valerys. Box 4148 Spring Valley, California.

SPAIN'S (long Nude) stamp 30c. Approvals Royal Stamp Company. Tamaqua 3, Penna.

1000 DIFFERENT \$1.00 with approvals. Golems. 8721 Eastwood, Philadelphia 48 Penna.

UNITED STATES, Canada, British Colonies or Global Foreign, Quality Approval Collections, Enclose 10c. Peterson, Box 81 St. Paul 3, Minn.

ENORMOUS variety old U.S. Baga, famous Americana. Commemorative with approvals. surprise packet 10c handling. Metropolitan Stamps. Box 212 PS, Jackson Heights 72, N.Y.

25 QUEEN Elizabeth 10c Approvals. Vail. Box 801, Columbus, Mississippi.

U.S. Collection 125 Different 50c. Ray Worth, 321 South Cicero, Chicago 44.

1000 DIFFERENT Worldwide \$1.00 With approvals only. Jacobsen, Crompond, New York.

LARGE French Pictorials! 25 Different 10c With Approvals. H. Coster, 434 36th Street, Union City, New Jersey.

SCREWBALL Fish in natural colors. Pan the g at mail. Egg of Mother's Day. Crawley bugs set, Jets, Bombs and flower garden, French Model, U.S. Revolutionary War, Etc. Free with approval purchases. Stamp Farm 85-38, Oxford, Wisc.

PENNY Approvals — Bargains — Gifts. Stamp Nook, 3110 West 12nd, Anderson, Indiana.

50 LARGE Pictorials 25c With Fascinating Approvals. Roberts, Box 5173, Colo. Springs, Colorado.

FREE Sample! Interesting, Informative, Illustrated. National Stamp News. Anderson, South Carolina.

FREE!!! Beautiful stamps Gold, Silver, others. Approvals. Delor, 20224 Westphalia, Detroit 5, Michigan.

FREE 25 thrilling airmail jet airplane rocket outer space stamps. Send for handling. 3c approvals included. ABC World Stamps, Box 8000-SC, San Francisco 1, Calif.

FINE U.S. Air Mail on approval. Wilden Stamp Co., Cape Porpoise, Maine.

29 ANTIQUES, RELICS & INDIAN GOODS

GIANT Photo-Illustrated Indian Relic Catalog 25c (refundable). Indian Gallery. 8 Hester Avenue. Merrick 3 New York.

3 WAR Arrowheads, Scraping Knife, Thunderbird \$4.00. Catalog Arrowhead, Glenwood, Arkansas.

SELLING 100,000 ancient Arrowheads, Spearheads, Tomahawks, etc. List free. Lear's, Glenwood, Arkansas.

30 MINERALS & PRECIOUS STONES

ROCKBOUNDS—Gem Cutters—Jewelry Makers. New Free catalog—just off the press. Biggest supply to hobbyists and craftsmen. Offers new tools, materials, equipment, introductory bargains and much more. Free catalog. Write: Grangers Dept. C-12, 1412 E. Walnut Pasadena, California.

EARTH Science — Rockbound's National Magazine subscription \$2.50 Sample 25c. Box 1337-PS Chicago 100, Ill.

IRKUTSK Gems Minerals catalogue—dms. 510 SE Wasmire, Milwaukee 22, Oregon.

FREE bargain gem list. New 1961 last-day and a year in tool catalog. 50c. O'Brien's. 1116M Wilcox, Hollywood 38, Calif.

31 HOBBIES, COLLECTIONS

INVENTING can be an interesting and profitable hobby. Write for complete particulars. Institute of American Inventors, Dept. 20-E, 633-P St., N.W., Washington 4, D.C.

COLLECTORS — Miniature engraving series starting. Send \$1.00 for first print. Satisfaction guaranteed. Palmer Studio, 602 South Michigan, Chicago 5, Illinois.

SOLDIERS—Over 1,000 sets. Including Civil War. Romans. Knights. Napoleonic. Catalog \$2-25c. Bomber, Box 107-E, Wollaston 10, Mass.

GOLD, Silver, Copper Plating supplies. Instructions. Free price circular. Crow's Craft Studio, Box 581, Rockaway, Oregon.

32 PHOTO FINISHING, PHOTOCOPIES, ETC.

TWELVE Exposure rolls 50c. Wallets 20 for \$1.00. Live in Studios. Dept. L, Box 12 Lincoln, Neb.

OIL Coloring Photographs—A fascinating hobby or profitable sideline for those with artistic talent. Learn at home. Easy simplified method. Free booklet. National Photo Coloring School. 233 Diversey Parkway. Dept. 1228, Chicago 14.

ENLARGEMENTS! Five Heavy 8x7's from negatives, \$1.00. Wilart, Box 973, Little Rock, Ark.

PHOTOCOPY of anything written, typed, printed. 50c copy. minimum order \$1.00. Richard Kapikian, 2218 21st Ave. Long Island City 5, N.Y.

33 MOTION PICTURES & COLOR SLIDES

SEE the World in Color 8mm-16mm Kolorchrome movies. Alaska, Hawaii, America, Europe, Africa, South Seas, U.S. National Parks, Also War and Rocket Test films. 165 subjects. Low prices. Write World in Color, Box 282-PS, Elmhurst, N.Y.

MOVIE Camera Film 8 mm roll \$1.50 16mm 100' \$3.00. Free processing. Better Films, 742 New Lots, Brooklyn, N.Y.

MOVIE Film! Free catalog! Eno-H, 47th Holly, Kansas City 13, Mo.

USED 16MM Sound Projectors, also sound films, rent, sale, exchange. Write for free catalog. National Cinema, 71 Day Street, New York City.

8MM-16MM Color and B&W film and supplies. Save \$44. Free Catalog Superior, 443 44th N. West, Chicago 10.

FREE Catalogues 5,000 8-16MM Films. International Films, Greentree New York.

8MM 16MM MOVIE Subjects silent, sound—new used—3"x2" color slides—biggest selection anywhere. Free each month, big 24-page newspaper size catalog. Blackhawk Films, Davenport 15, Iowa.

8 MM HOME Movies. Free Catalog. Midwest Film Sales, P.O. Box 2062, Milwaukee Wisconsin.

BIG money! Making short, simple, 8mm movies. Free details. Lagene's, Pocommet 4, Mass.

16MM SOUND Features—Laurel and Hardy, Charlie Chase, Jason Temple. 8mm Old Time Movies. Entertainment Films, P.S. 326 W55, N.Y.C.

SPECIAL Entertainment—8mm b&w 50 feet \$12.00. 16mm b&w 100 feet \$20.00. Tex, Box 348, Terminal A, Toronto, Canada.

34 CAMERAS, PHOTO SUPPLIES

PHOTOGRAPHY for pleasure or profit. Learn at home. Practical basic training. Long established school. Free booklet. American Bureau of Photography, 213 Diversey Parkway, Dept. 1724, Chicago 14.

164-PAGE Photographic Bargain Catalog. Giving thousands of photographic bargains. Send 10c for your copy. receive 25c credit on first order. Dept. 4-18 Central Camera Company, 210 So. Wabash Avenue Chicago 4, Illinois.

DISCOUNTS on Kodak and Polaroid films. Free Price List Thrifty Camera Co., Box 1623C, Saginaw, Michigan.

35 MUSICAL INSTRUMENTS AND SONG WRITERS

SONGS Into MONEY—Share \$32 million dollars yearly for New Songwriters. Song-poets. Any subject, songs composed, published, promoted by largest firm. International, expression Free. Send 10c to Music Publishers, 4000 Sunset, Hollywood 28PA, California.

POEMS Wanted for musical setting and recording. Send poems. Free examination. Crown Music Company, 49-P West 82 Street, New York 1.

SONGWRITERS Recording Company. Wants new songs. Royalty basis. National sales, promotion if selected. No charge for melodies. Send material. Music Makers, Dept. C-75, 4344 Melrose Hollywood, California.

POEMS Needed Immediately for New Songs and Records. Free Exam. nation and Approval. Send Poems. Songwriters, Arklen & Son, Nashville, Tenn.

SONGWRITERS, with publisher contacts, want song ideas. Share royalties. No fees. Send poems. Songwriters' Association, 1650 Broadway New York 19-P.

SONGPOEMS and songs wanted! Mail to Tim Pan Agency Inc., Box 460, Radio City Station, New York 18, N.Y.

GUITAR Making books, plans, imported tools. List 10c. Widdow 210 East 11th Street New York 9, N.Y.

SONGS And Songpoems Wanted. For Our Summer And Fall Program. Sincere Writers Only. Columbia Enterprises, Box 2488, Burbank, California.

SONGWRITERS! Protect your ideas! Hold all poems songs. Write for sale, correct procedure! Song Service Dept. PS 223 W 56th, New York 19, N.Y.

PIANO Tuning—Home Study Course. Diploma granted. American School of Tuning, Box 707, Gilroy Calif.

ACCORDION-O-RAMA, 874 Broadway New York 1 N.Y. Tremendous Discounts. Top Brands. Free Brochure.

SONGPOEMS Wanted! Collaborate with professional songwriters on equal basis. Share royalties. Songwriters Contact Co., 169-T Broadway, New York 18.

POPULAR SCIENCE OPPORTUNITIES

ACCORDIONS, Chord Organs, Guitars! Buy direct—save to 1/2. Famous makes. Free home trial. Easy terms. Trades. Free catalog. Mention instrument in correspondence. Music Mart Dept. P, 2003 Chicago Avenue, Chicago 22.

PLAY Guitar like Chet Atkins. Teach yourself. 4306 Erma Ball Guitars, Box 208PSM, Tarzana, California.

PLAYED Piano Rolls. Free Lst. Worth. Box 173, Muskegon 1, Mich.

ELECTRIC Guitars, amplifiers, wholesale. Free catalog. Carvin, PSM, Corona, California.

FORMS Wanted By America's Largest Song And Recording Studio. Free Examination. Five Star Music Masters, 648 Beacon Bldg., Boston.

MERCURY, Venus Banjos. Write Particulars, Garlipy, P.S. 263 E. Porhan St., Long Beach 5, California.

PLAY Guitar, teach yourself method. \$1.00. . . results guaranteed. Erma Ball Guitars, Box 208PSM Tarzana, California.

35A PHONOGRAPH RECORDS

RECORDS—Stereo, Monaural. Big Discounts, Noisison, Box 311, New York 8, N. Y.

36 RADIO, TELEVISION, ELECTRONICS, HI-FI

RADIO & TV Tubes at Manufacturers Prices! 100% Guaranteed Brand New! No re brands or pulled United Radio, Box 1000 Newark, New Jersey.

FIX Your Own TV. Save 50%! Send for Free Illustrated Chart showing how. We'll include Giant Electronics Catalog. Zyrtron, 220-B West 42nd Street, NYC.

DON'T Buy HI-FI Components. Etc. Tape Recorders until you get our low low return mail quotes. We guarantee Not To Be Under Sold. Wholesale Catalog Free. HI-Fide by Center 220-B E. 23rd Street, New York 10, New York.

TAPE recorders, HI-FI components. Sleep Learning Equipment tapes. Unusual values. Free Catalog. Dressner, 1523 Jericho Tpke., New Hyde Park, New York.

RECORDERS, HI-FI. Free Wholesale Catalogue. Carleton, 128-J East 88, New York City 28.

FREE: Giant wholesale catalog on electronics. In 4 languages. Also in baby, optics, photographic, housewares, jewelry, tools, novelties, toys. Write Lektro, 2418 Everett Ave., Chelsea 50, Mass.

DETECT police radar traps. Build Radar King. Kit or Auto buyers. Warren Smith.

CONVERT Car Radios to 120 Volt operation. Instructions. 50c. Hanson Electric, Northwood, Iowa.

GOVERNMENT Surplus Snooperscopes, Ham Gear, Mine Detectors, Parabolic Reflectors, Telescopes, Picture Catalog. 10c. Meshna, Malden 48, Mass.

TERRIFIC Bargains—Electronic Components—Books—Records. Free Lst. 5T Labs 438 I. & Ave. Newark 1, N. J.

CRYSTAL Radio Kit \$1.00. Amplifier and Speaker for same \$4.95. Catalogue Clearco, Box 1638, Stuart, Florida.

37 BUSINESS OPPORTUNITIES

START Your Own Business On Credit (U.S. Only). Your own boss. 1344 Dealers sold \$5,000 to \$25,000 in 1960. We supply stocks, equipment on credit. 200 home necessities. Spices. Paperware unnecessary. Perfect of stable business backed by world wide industry. Write Rawlatha, Dept. I-U PSC Freeport, Ill.

MAKE Extra Money—Big Cash Commission plus premiums for you and your customers. Sell Advertising Book. Meet new sensational new Tenoramas, Quamoz Girls. Hairdressing doctors others. All sizes. Quick daily sales. Big repeat business. Free Master Kit makes selling easy—no experience necessary. Super or Match. Dept. PX-861, 7539 Greenwood, Chicago 19, Illinois.

\$250.00 WEEK spare time profit possible. Earn at home with new fascinating Printing method. \$5 starts you—send no money now. Free Confidential Facts and Valuable sample. Screen-Print, BR, Los Angeles 61.

OPERATE profitable mail order business. Write Walter Service, 4138-B East 112th, Cleveland 5, Ohio.

BRONZE Baby Shoes Instructions. Equipment and Mountings for genuine Electropainting Process. Largest Supplier of all Painting Equipment Supplies. Free Catalog. No. Wood Bronze Supply Dept. B, 1624 East First, Los Angeles 23, California.

FREE Name Brands Catalog! Your own high profit business. Sell Name Brands, full or part time. No inventory, no investment. More than 2000 Name Brand items lowest wholesale prices. Watches, jewelry, cameras, hi-fi stereo radios, phonos, appliances, housewares, hardware, power tools, luggage, musical instruments, garden equipment, sports goods, toys, many others. 4 Floors of Name Brands. \$1.00 dollar inventory. Orders shipped complete within 24 hours. Send for Free beautifully illustrated catalog. Now! Separate wholesale price list. H. B. Davis Corp., Dept. PS, 144 West 15 St., New York 11, N. Y.

FREE Picture Folder, "How to Make \$3,000, Yearly, Sparetime, Backyard, Raising Earthworms." Oakhaven-42, Cedar Hill, Texas.

\$1.00 HOUR—home, sparetime, assembling pump lamps. Easy. Free Details. Oscar Caldwell, Arkansas.

BUY Direct From Factories—Appliances, Cameras, Watches! Free details. Cam Company, 4348 S. Bloomfield Ave. Verona, N. J.

IMPORT-Export opportunity profitable world-wide. mail-order business from home without capital or travel abroad. Established world trader shows instructions for no risk examination. Experience unnecessary. Free details. Manager 1554 South Sepulveda, Dept. T606, Los Angeles 25 Calif.

EXCEPTIONALLY profitable opportunity in Tape Recording. Free information. Baron & Lynden, Washington.

\$1.00 BIRDS. You \$12.00 Spare-Full Time Home Business opportunity. Amazing new level spray, transforms old ceramic lamps. TV radio, furniture, furniture, anything into \$1448 products. Free samples. 50 Business Opportunities Booklet. Send No Money. Flok Kraft, BR, Los Angeles 61.

\$100.00 WEEKLY spare room. Raise roommates. Solless way. Odorless. Charlie Morgan, Box 110C, Bushnell, Florida.

MAKE fabulous weekly profits clipping newspaper items for publishers. Some earnings worth \$5.00 each. Part-time free. National, 81-PS, Knickerbocker, New York City 2.

FRANCHISES make profits. Operate your own franchise. Free information. Write today for free information. National Franchise Reports, PS-325, 113 North Michigan, Chicago 1.

FREE Report "999 Odd, Successful Businesses." Box 1001-B, Evanston, Ill.

VENDING Machines—No Selling. Operate A Route of Coin Machines And Park Amusement. 12 Page Catalog Free. Parkway Machine Corporation, Dept. 18, 716 Enzor Street, Baltimore 2, Maryland.

I WANT A Man who wants a business of his own. I will train you, supply the equipment, help finance you start your business. This is not a risky get rich quick scheme. It is a legitimate business, a selected franchise, proved successful by hundreds throughout the country. An investment of \$995 is required. Send name, address and phone number to Marvin Wade 213 North Wayne, Dept. 475M, Chicago 16, Illinois.

IMMEDIATE Profits with no capital or experience. Take orders for all magazine subscriptions. Friends and neighbors are your prospects. Write now for complete free kit. McGregor Magazine Agency, Dept. 119B, Mount Morris, Illinois.

FREE Literature — Make Big Money Raising Fishworms and Crickets. Carter Farm, Plains, Georgia.

EARN \$3 hourly, spare, full time, looking up information at your local library. Details Free. Service, 81E, Knickerbocker Station, New York City.

YOUR Own Import Mail Order Business! Deal with over 400 manufacturers, exporters of the world. Complete import procedures, international drop-ship methods. Casual unnecessary. Free details. Associated, Box 104 RB, Lincoln, Nebraska.

DOLLS' Dolls! Dolls! We teach you to repair, make and sell all kinds of dolls and accessories including clothing. Study at home. Earn while you learn. Free catalog. Doll Hospital School, Studio PSC90, 11828 San Vicente Blvd., Los Angeles 48, Calif.

FREE How to Win Contests. ContestStar Box 51-A, Des Plaines, Illinois.

BIG Money—Operate own Fix-it Shop. Service household appliances, motors, lawnmowers, saws, skates, etc. Free Book, Christy Trades School, A-1601, 1214 Lawrence, Chicago 25.

SELL by Mail Profitably. Dealers invited. Not Pulp or Nickel, Dime circulars. Lucrative, Complete Set-up, Selling, Reprints. Mail Trade Contacts, Montrose 8, N. Y.

EARN cash from used flashlight batteries. See Classification & B. 1. Electrochemical.

WANTED—Honest intelligent people to investigate "best proposition on earth." Orinsteen, DuQuoin, Illinois.

MAKE durable building plastic easily. Waterproof, fireproof, economical. Ray Laboratory, Chino, Arizona.

WORLD'S Largest wholesale supply. Buy from 89 American, European, Japanese, Russian, Turkish made goods from Hong Kong. 123 drop-up catalog. Knockdown prices. Free details. International Buyers, 218-PS2 Jackson, Chicago 4, Illinois.

LEARN Candle Making—Decorating at home. Send for Free Facts on Famous Home Study Course. Candle, Dept. X-503, Encinitas, Calif.

SHARPEN saws, tools, knives, shears, scissors, clippers, twist drills, surgical instruments etc. Manual furnished. Trayon, N. Tonawanda 1, N. Y.

INVISIBLE Reweaving. \$5-\$10 per job possible. Reweaving burns, tears, moth-holes. Save full time. Free details. Skill-Weave Dept. HC-129, 135 W. Madison, Chicago 8, Illinois.

OPPORTUNITY New Home Business. County Franchise. Build Your Own Future. McNelly, 12 Susan Drive, Reading, Massachusetts.

MAKE Most Extra Cash with world's biggest line Christmas cards. Gifts. Illustrations. Free information. Over 150 Christmas cards. Every day box assortment. 500 big money makers. Pocket up to 50% profit plus big cash bonus. Free giant color catalog, samples on approval. Styleline, 431 Fifth Ave., 4, Dept. 84-E, Minneapolis, Minn.

MONEY in your mailbox every day. Fabulous home mail order business. Import from all over the world at ridiculously low prices. Cash prices. Come as \$4.24 watches, \$2.40 radios, \$2.67 5 ft items jewelry, novelties etc. Free to raise L.B. buyers at profit up to 500%. Thousands now doing it. Where to buy, how to buy, where to sell, etc. Everything complete by return mail. Satisfaction guaranteed or your expectations. Send \$2.00 to: Impex, Dept. PS, 714 Howard, New Orleans 12, La.

YOUR Own Baby shoe bronzing business. Instructions, equipment, supplies. Metalizing, glassing, pearling. Free booklet. Dept. C, Box 5036, Inglewood, Calif.

EXPORT-Import Business. Complete professional setup service. 20 lines delivered. Hermes, 152 West 42, New York City 36.

U.S. RESIDENTS eligible now. Amazing profits from recorded timber leases. No money spare time easy. Oldest, largest international corporation. Low investment. Free information. Zelman, 130-F Shaftesbury, Downsview, Ontario, Canada.

IMPORT Represent manufacturers. Details Free. Benko, Box 189-D, New York 21, N. Y.

POPULAR SCIENCE OPPORTUNITIES

WANTED Fishing Tackle Items for national distribution, exclusive manufacturing and sales. Our increasing sales force can handle 3 or 2 additional items for wholesale and retail distribution. Also want good mail order items for established customers. Send full details and samples to: **Axelsson Fishing Tackle Mfg. Co.** 1539H Placentia, Newport Beach, Calif.

MAILORDER America's Most Unique No Cost Beginner's Piano. A money saving 194-C Darrington & W., Washington 24, D.C.

LEARN Sewing Machine-Vacuum Cleaner Repairing. Excellent Field Gardner, Box 21 Jenkintown, Penna.

PIANO Tuning learned quickly at home. Tremendous field. Musical knowledge unnecessary. Information free. Empire School of Piano Tuning, Champaign, Illinois. (Founded 1925.)

PLASTERCRAFT molds, liquid rubber, plasters, socks, candle supplies. Catalog and manual free. Jayhawk Plasters, Blue Rapids, Kansas.

SELL Champion AC Automatic spark plugs. Record sales. Profitable and guaranteed 10,000 miles. 100% profit. Free sample. Lee Plugs 1608-K Roberts House, Igou 3 Texas.

SHARPEN saws and lawnmowers the profitable way. Send for free literature. Max Manufacturing Company, 118 Stockton Avenue, San Jose 26 California.

BAKE New Orleans Doughnuts in Kitchen. Sell stores. Free recipes. Summerville 3008 South 18th, Minneapolis 7, Minnesota.

OPPORTUNITY to earn \$15,000-\$30,000 annually. Franchise protected. Claimed on \$2,500 basis. Live at home. No money down to buy. Be famous. One of most exclusive and successful businesses in United States and Canada. Send for free explanatory booklet. Harte and Company, Box 6-D, Louisville, Indiana.

JAPAN Directory 145 Japanese manufacturing exporters. Japan and Hong Kong trade journal. Information Asia opportunities. Send \$1.00 today. Nippon Annual, Box 1184-PS, Spokane 10, Washington.

MARKETS Everywhere! Make Artistic concrete birdbaths, pottery. Best coloring. Home workshop. Hundred varieties. Free pictures. Hollywood Cementcraft, 4527-N Wonderland, Hollywood 44 California.

LANDSCAPING pays. Personalized home study. National Landscape Institute Dept. POC-91, Los Angeles 49, Calif.

\$300 WEEK, making signs. Sample signs, particulars, time (refunded). Cook Martin Avenue, Saratoga Springs, New York.

CARTOONING—good money in fields of Television Advertising. An mail order. Movies, Magazines. Famous Systems of Manual Teaching brings amazing new concept of art instruction at home. For profit or pleasure. Send for free details. Commercial Schools, Dept. R-18, 4201 S Broadway, Los Angeles 37, Calif.

OPERATE home Mail-order Business. Vascok Distributors, 4444S Uta, San Diego 17, Calif.

FREE Wholesale directory lists 750,000 items. Deans, Box 40-PS, Kiberton, Georgia.

CANDIED Popcorn and Potato Chip Equipment. Bakins, Box 222-B1, Springfield, Ohio.

LIQUID Molding Rubber. Free Sample. Shalcraft Supplies, Chapter's, 1907-C East Road, Jacksonville 14 Fla.

OPERATE Profitable Mail-order Business. Valuable Information Free. Colson, 721-PS2 Yates, Chicago 49.

MAILORDER Profitable beginners information. John's, Box 941PPS, Miami, Florida.

HOW To Operate A Collection Agency. Locate Shipy \$19.00. C.C.A., Box 374, Taylorville, Illinois.

FREE Book 999 Successes. 11th Known Businesses. Work home. P.O. Box 432H, Douglas 4, New York.

FREE Book Offer. Now I made over \$44,000.00 year on \$100 investment selling by mail. Torrey, Box 3546-F, Oklahoma City 6 Oklahoma.

DOLLAR Making Plans. Descriptions done. Bestmart, Box 12-303, Cincinnati 12 Ohio.

MAILORDER Laws and Regulations. \$1.00 Free Details. Joseph Anderson, 5-28 W. Highland Road, Stoneham 80, Mass.

BIG Volume, Big Profit. Home Mail Order Business. Security. Prospects. Yours. Dealers. Beginners. Unlimited. No money. Easy Operation. Hurry. Send Now For Free Information. Granada Press, Dept. 3784, 10427 Buicher, Granada Hills, Calif. 91344.

UNUSUAL (Wholesale) Import Catalog plus Directory listing hundreds of products. Supply & Bulk \$.00. Chem Distributors, P.O. Box 2842, Denver 18, Colorado.

HUGE profits selling jewelry, perfume, gifts. Valuable franchise free. Universal, 41 A West 8th, Charlotte 6, N.C.

CASH from Sawdust, Tin-Cans, Newspapers. Over 200 methods. Instructions \$.00. Charles Company, 42-DPK, Norwood, Ohio.

COLORGLAZED Concrete pottery made without molds. Patented method. Cement products, novelties, gifts. Basement brick building. Money making projects. Booklet details free. Mrs. W. L. Nozka, Fox Grove, Grand Rapids, Minnesota.

EXCEPTIONALLY Profitable Opportunity to operate your own Mail Order Business. Write for Free Details. Direct Mail-order Service. Riverside Station, Box 229, Dayton Ohio.

SCHOOL Seniors Earn big commissions during school hours. Unbelievably easy! Craft cards. P.O. Box 335, Pittsburgh 26, Pennsylvania.

MAILORDER Drop Ship Brochure Contains 75 items of goods that may be dropped at door under your label. Name method used by Jack and Mary Lutz since 1944 in building their own successful Mail Order Business. Send for details and Free Sample Brochure. Mail Order Methods (Division of Leslie Creations), Lafayette Hill 17 Pa.

BE Your Own Boss! Visit the 3rd Annual "Start Your Own Business Exposition" at the International Amphitheatre in Chicago, Oct. 21-23, 1961.

MAKE Figurines. Rubber for Molds. Kit a Trick. Free Sample. W. W. Woot, 915 N. North, Peoria 11.

LEARN Professional TV Servicing in one week. Fabulous new simplified system. No big expense. No stock. No tools or equipment. Spare 10' time. Own your own big profit business. Save Amazing \$11.95. Free W. L. TV Systems. Dept. 24, 100, 1028 So. La Brea, Los Angeles 19, Calif.

YOU too can make money through Popular Science Classified Advertising. If you have a product or service which can be sold by mail, send now for the amazing new booklet, "How to Make Money Through Classified Advertising." This booklet full of valuable suggestions, time-tested mail order formulas and lots of "how to" info. It tells you what where when and how to get the most out of your ad. Get your copy today and begin making money. Order now. C. K. K. Co., 379, Popular Science Monthly, 130 Lexington Avenue, New York 17, N.Y.

38 MONEYMAKING OPPORTUNITIES

DETECTIVES—Work home—Travel Experience unnecessary. Detective Particulars free. Write Wagoner, P-125 West 66th New York 24.

MAKE fabulous weekly profits clipping new paper items. Publishers. Some clippings worth \$5.00 each. Particulars free. National 61-PS, Knickerbocker New York City 3.

AMATEUR successes through franchise. Be home each day. Franchise holder your territory. Information rushed. National Franchise Reports, SP 328, 335 North Michigan, Chicago 1.

VENDING Machine—No Selling. Operate A Route of Coin Machines And Earn Amazing Profits. 21 Page Catalog Free. Parkway Machine Corporation, Dept. 19, 715 Ensor Street, Baltimore 3, Maryland.

FREE Literature — Make Big Money Raising Fishworms and Crickets. Carter Farm-11, Plains, Ga.

\$25 \$50 WEEKLY possible. Everything new. Home. Jobs. Poems. Recipes for publishers. Same with \$.00 each. Details Free. Write, P-31-P, Knickerbocker Station, New York City.

EASY to start rubber stamp business at home in spare time. Make up to \$3.00 an hour without experience. Facts free. Write to Robert's 1523 Jarvis, Mount Carmel 3-M, Chicago 28.

LEARN Plant fabrication for extra income. Low cost. Home. No experience. Write for free booklet. Interstate Lining Service, Dept. D-2, Portland 13 Oregon.

MEN Women! Start Money Making. Fantastic Earn a business at home in spare time. Make sal. that costs for brings to \$3.50. No canvassing or selling. But men orders bring \$20 a day. Write for full particulars free. Each name in postcard to Warner House CL-3-M, 1523 Jarvis, Chicago 28, Ill.

MINK Raising Information free. Complete Lake Superior Mink Farm. Superintendent EF Wagoner.

SECOND Income from Oil can and your toll. Free book and oil can. National Petroleum, Panamerican Building, P.O. Miami 12, Florida.

TEAR Out This Ad and mail with name and address for big box of home needs and cosmetics for Free Trial. To test in your home. Tell your friends. Make money. Rush name. Blair Dept. 667a, Lynchburg Va.

BECOME Advertising Copywriter! Exciting work. Fabulous pay. No experience. (Age 18+ Home used) Submit. Penman AA-1, N.Y.

HOW To Win Contests. Manual May bring you riches. Complete and useful formula professional writers use. Guaranteed 45 pages of equal free literature. Paragon Enterprises, 11 Mutt St., DT-48, New York 13, N.Y.

ANTIQU And Modern Planets For Your Profit. Complete Plans \$1.00. H. B. Harris, 433 Federal Terrace SE, Atlanta 13, Ga.

COMMISSION Credits. Good Profits. America's, Hutchinson, 4400 Hughes, Ft. Worth 18 Texas.

EARN \$100.00 Easily with one paid draw. Write Laughlin Specialties, 1924 West 44th Ave. Vancouver 13, B.C. Canada.

FREE Spare Time \$444. Professional Picking, 1617 Log Cabin Ave., Rock 10 Illinois.

GETTING Dollars In Your Mail. Send 10c for eye opening literature. Donovan, W-PS Greenbelt, Levittown, New York.

RENEATH good income and career in home. Make sal. \$3 Guaranteed. Free details. MacKenzie's 3240PX Southport Avenue, Chicago 13, Ill.

MINIATURE trees growing hobby \$1.00 for beginner's kit and instructions. Leeman Miniature Nurseries, Box 2092, Doneson, Tennessee.

GOOD cash as showing, installing. Home systems for businesses, homes. Hold private after departmental, house in garage. Free literature. Conversations. Reprints. Home. Free. Telephone Reprints 1740-N Elm, Chicago 28.

FREE Beginners Illustrated Folder—Amazing 31 ways for making money. Labco. P.O. Box 521, Scottsdale Arizona.

MEN! Women! Make money raising bait for catfish and bass. Live baited Market. We buy your crop. Details Free. Red Wigglers, Warsaw 3, Indiana.

LEARN the secrets of repairing junk batteries, generators, starters, profitable easy, at home. Free particulars. Batteryman, 3465 Forest, Santa Clara, California.

MAKE \$200.00 monthly spare time with jig saw. Free details. Elkhart, 346 N. Summit, Sioux Falls, So. Dakota.

POPULAR SCIENCE OPPORTUNITIES

CIGARETTES—Make 20 plain or filter-tips for 8c. Facts Free, Moberly, Box 4813, Owensboro, Kentucky

BE AN Interviewer! Earn to \$100.00 weekly. No Selling! Pleasant, dignified work asking questions, gathering information for Polls, Market Research, Radio and TV Surveys. Supervised home training. Details Free. Dept. 15.2, 1540 N. Highland, Los Angeles 28 Calif.

RAISE Nightcrawlers, Redworms Easy Soilless Method. Three Oaks Ranch, Dresden Tenn.

38A BUY IT WHOLESALE

PICTURE Frames of distinction, for every purpose. Imported and domestic woods, including Gold Metal Leaf. All sizes. Unmatchable savings. Free delivery in U.S.A. Write for free catalog. Cadillac Company, 8828 Fairview Avenue, Baltimore 15 Md. vland

LARGEST Wholesale Supply Source in U.S. Get free catalog. Furniture, clothing, appliances, autos and accessories, farm equipment, tools, housewares, hobby supplies. Free details. Associated Wholesale Box 108-C Lincoln, Nebr.

NEW Deluxe Multicolor below wholesale catalog automobile catalog, and others. Housewares, appliances, refrigerators, freezers, washers, dryers, televisions, and more for less. Clothing, luggage, binoculars, phonographs, recorders, cameras, picture books, tools, typewriters, watches, jewelry. Name brands. Huge discounts to 50%. Postcard Service. Dept. 16.1, 16.2

BUY Below Wholesale! Thousands of Nationally advertised products. Drugs, Clothing, Housewares, Cameras, Jewelry, Hardware, Sporting Goods, etc. Postcard buy. Price List showing actual factory cost. Buy-Rite, 310 Main, Bennington 3 Vermont.

WHOLESALE Catalog Every Brand \$1.00 Retailable. Write to 43 Station Street, Long Beach, Calif. New York

WORLD'S Largest wholesale supply Buy from 675 American, European, Japanese wholesalers. Customized suits from Hong Kong. 123 dropship catalog. Rock bottom prices. Free details. International Buyers, 215-PS Jackson, Chicago 8, Illinois.

JUST Out 156-page catalog save to 50% on auto parts accessories. All makes. Models. Send 25c. retail value on first order. Whitney, 1815 PB-9 Archer, Chicago 18.

FLYWOOD prefinished wall panels and Christmas Top quality 1001 uses. Home Bazaar. Hobbies etc. Price Company. Oriskany, VT.

FREE Money-Saving Catalog Surplus and newly manufactured equipment and tools for workshop, home, boat. Is in factory. Write Oriskany, 1130 South Washington, Chicago 8, Illinois.

2,000 PAGES Wholesale Catalogs! Write Mosser, Box 47-A, Newark, Ohio.

100,000 PRODUCTS Wholesale! Terrific Bargains! United Wholesalers, 1245 Broadway, New York 1, N.Y.

WINDBRAKER, Waterproof, 3 For \$1.00. Parker, Box 1593, Oakland, California.

ELECTRIC Outlets, amplifiers, wholesale. Free Catalog. Carvin, PSW, Covina, California.

BUY Wholesale — Free Information Hanco Industries, 1245 Wealthy, Muskegon, Mich.

DRUG Sundries. Complete line of Rubber Goods, Nationally Advertised Brands, Vitamins Etc. Write For Free Catalog. Federal Pharmacy Supply, Inc., Dept. PS 6652 North Western Avenue, Chicago 45 Illinois.

38B IMPORT-EXPORT

\$50.00 DAILY possible. No capital risk! Sell Japanese art service. David Teel International, Dept. PS-8, 217 Christopher, Florida, New Mexico.

RECEIVE catalogs, offers from 100 Foreign Exporters without contacting them. Importers, Enka, North Carolina.

39 FORMULAS, PLANS, ETC.

FORMULAS—All Kinds. Amazing Big Catalog 10c. Kemisco, Park Ridge 18, Illinois.

WINE and Beer Formulas One Dollar. R. B. McGuire, Box 23, Hayden Lake Idaho.

LATE Modern Manufacturing Formulas List Free. Chemical Service, Martine New York.

FREE Formula catalog. Anything and everything. Reasonable. Western Chemical, Salem, Oregon.

ANY Formula \$3.00. Catalog-Miscellaneous 10c. Belfort, 182 N. Clark, Chicago 1.

SPECIAL Formulas for latest money-making discoveries. New! Good! Profitable! Valuable Literature Free! Master Chemist 1511 N. Tampa, Florida.

MODERN Formulas. Satisfaction guaranteed. Jack, Consultant, Box 25157, Los Angeles 25, California.

40 PLASTICS

NEW Liquid casting plastic clear color. Embed 100, 2 sets butterfly, physics coins. Send 25c for two handbooks. How to Cast Liquid Plastics and How to Make Extra Money at Home. Catalogue Dept. K-102 Woodstock, Illinois.

MANY uses for plastic made from Free related to 25c. For information send \$1.00 to H.P.D. Products, Box 14 Paramus, N.Y.

NEW Plastic Vacuum Forming Machines. Hobby Easy Profitable. Details \$1.00. 230 East Centre, Kalamazoo, Michigan.

PLEXIGLAS — Any thickness — Clear Colors. Cut to size—Clear Red—Yellow—M. Clark Plastics, P.O. Box 188B, Hanover, Pennsylvania.

SEND only \$1.00 for new "Castcraft Instruction Manual" on plastics for casting, embedding, molding and jewelry or 25c for catalog only. Castcraft Corporation, Dept. 8-661, P.O. Box 535, Palo Alto, California.

PLASTIC Embedding for fun and profit no oven. Make beautiful jewelry, decorative panels, science specimen castings. Catalog 25c. Natrol Plastics, Box 444, Upland 4, California.

CELLULOSE wrap assortment \$4.00 postpaid. P.O. Box 313, Kearney, New Jersey.

41 SCIENCE & CHEMISTRY

AMAZING New Book Of Science Experiments 1 formula and Catalogue of Laboratory Supplies. Only 25c. National Scientific Co., Dept. PS 13 8 Park Avenue, Lombard, Illinois.

NEW Vortex theory for elementary particles and forces. 30 pages. 25 cents. C. F. Kraft, 4400 Columbia Road, Falls Church, Virginia.

UNUSUAL Chemistry books, courses. Buy. Rare chemicals. Cheap. Catalog 25c. National, Box 131 A, Palo Alto, Calif.

ILLUSTRATED Catalog, Chemistry, mineralogy, biology 25c. Tracey Laboratories, Evanston, Illinois.

CHEMICALS and apparatus for industrial, analytical and private laboratories. Catalog 25c. Dept. M 26, B. W. & Co., 1176 Mt. Hope Ave., Rochester 20, N.Y.

EXCITING Experiments Booklet And Catalog 25c. Haxthorn Laboratories, Manitowish, Wisconsin.

FREE! Write for new catalog soon available. Chemical bargains in science fair materials. Free Scientific, 273 Orange, Mansfield 1 Ohio.

ROCKET Model Supplies. Fuel Chemicals, Engines. New Catalog 25c. Central Rocket Company, 845 Waupaca, Wis.

FREE! Laboratory Item—With 25c Scientific Materials Catalog. Stuart Scientific, Madison, Wisconsin.

NON Nozzle Rocket Plans and Formulas. Price \$1.00. Satisfaction guaranteed. Vortex Research Labs, Box 861, Lodi, California.

MICROSCOPES. Surveying. Electron. Everything Japanese. Catalog 25c. Magnification Instrument, 2 East 45th, New York 17.

42 EMPLOYMENT INFORMATION

FOREIGN Employment Information. Work overseas. Travel, adventure. Europe, Africa, Asia, Canada, Alaska. Earn as much as \$1,000 monthly. Construction men, truck drivers, clerks, teachers, professionals, etc. Fabulous opportunities. Most complete information, application forms, etc. Sent by return mail same day received. Send \$2.00 to Dept. PS, Foreign Bureau, P.O. Box 512, New Orleans, Louisiana.

FOREIGN Jobs—Latin America, Alaska, Canada, up to \$1500 monthly. Up-to-date 1961 Foreign Service Directory gives complete information, hot list of firms hiring or Military and Civilian Construction, Air, Sea, Oil, Exporters-Importers, Maritime. How When Where to apply. 13th Successful year. \$1.00 Global Reports, P.O. Box 5201, Inglewood, California.

DIRECTORY Reports. Construction, aviation, shipping, oilfields, government, manufacturing, trucking, etc. Foreign—a code. Helpful information plus job-seeking tips on preparing application letters. Unconditional money-back guarantee of satisfaction. Act Today. Only \$2.00. (4225 A. Mail) (C.O.D. Accepted) Research Division, Maramec Building, St. Louis 3-PS, Missouri.

HIGH Paying foreign jobs. Far East, Europe, South America. Jobs on ships and civil service. For information, write to International Employment, P.O. Box 116, Boston 27, Mass.

CHOICE U.S. & Overseas Jobs. All Trades Firms, Addresses, Hiring Procedures. Free. Brock, Bennett, For info write World Wide Dept. C12, 155 N. Franklin St. Hempstead, N.Y.

OVERSEAS Jobs—High Salaries. Europe, South America, Far East. Worldwide. How to get complete information by return mail. Satisfaction guaranteed. \$2.00. Jobs, Box 2434-S, Washington 13 D.C.

FOREIGN Employment. If interested in good paying overseas work with travel expenses, write Foreign Service Bureau, Dept. PS, Bradenton Beach, Florida.

FREE Information—U.S.A. Overseas Jobs. High Pay Transportation, Futures, Dept. 8, 215 West 34th Street, New York City 1.

EUROPE Overseas High paying jobs. Full details \$2.00. North Sea Export, P.O. Box 548, Amsterdam, Holland, Europe.

OVERSEAS Job Fact Book 18 Big Pages. With Free Information Bureau, 41 Madison, 156 East 10, N.Y.C. 11.

FOREIGN Employment! High paying, tax exempt jobs of all types in all corners of the Free World are in our current listing. Send \$2.00 to Capital Services (PS), P.O. Box 1, Colonial Station, Sacramento, Calif.

WORK in beautiful Arizona. Information, Job listings, \$1.00. Thompson Enterprises, Box 4351, Phoenix 8, Arizona.

EXCELLENT Employment. California, Oregon, Washington, Nevada, Arizona, Alaska, Hawaii. All occupations needed. Immediate. Men, Women. Free Details. Employment Service-28, 2908 Hawthorn, Orange, California.

OVERSEAS jobs for everybody. Fabulous opportunities. Free list sent \$2.00. P.O. Box 481, Kenosha, Wis.

HOUSTON Texas is booming. Sunday paper with job and business opportunities. \$1.00. West, 8208 Grand Blvd., Houston 21, Texas.

43 AGENTS WANTED

IF You Sell Christmas Cards, make most extra cash with one of all leading companies from one firm. World's biggest line. Over 150 Christmas cards. Everyday box assortments. 400 best money-makers. Make up to 50¢ profit plus cash bonus. Free color catalog of all new samples on approval. Action Catalogs, 513 Fourth Ave. S. Dept. 84 E. Minneapolis, Minn.

POPULAR SCIENCE OPPORTUNITIES

EARN \$150 Weekly Mechanical, Electronics Drafting. Send \$2 First Lesson. \$25 Complete Home Study Course. Prior, Inc., Dept. 120, 23-08 140 Street, Whitestone 57, New York.

FREE General Catalog—100 Pages Text Vocational educational instructional subjects. Millions of volumes, new and used. Bargain prices. Books bought Oct 1902 Long's College Book Co., Dept. PS, Columbus 1, Ohio.

BRITISH Study Courses, Sciences, Divinity, Literature, Theology Etc Diplomas. Free Information, St. Andrew's 421 Wain Street, New Westminster, Canada.

PENMANSHIP Corrector Improve poor penmanship quickly. Details free. Cement Box 685 15 St. Louis, Mo.

CALCULATING Made Fast Easy 10' Slide Rule Instruction Book. Complete \$2.00. Cash, 7731-PS2 Yates, Chicago 48.

LEARN Abreviatix Shorthand in four simple lessons enables you to take notes rapidly prepares you for job in just weeks \$2.98. Complete satisfaction guaranteed. Broadway Enterprises, 66 Broadway, Hagerstown, Maryland.

DON'T Every College Graduate. Get detailed guide to free home cultural training. Box 55865, Washington 14, D. C.

MEN wanted. Learn Auto Diesel Mechanics in our shop. Learn with tools on real equipment. Earn While You Learn. Many of our graduates earn \$35 a week and up. Write for free bulletin. Auto-Diesel College, Dept. 362, Nashville 9, Tenn.

46 CONTESTS

WIN contest money. General Contest Bulletin gives hundreds of tips. Lists current contests, rules. Sample magazine 25c. General Contests, 1609-A East 8th, Duluth 12, Minnesota.

MONTHLY Puzzle Contest! Cash Prizes! Details Free! Spence, Box 11840, St. Petersburg, Fla.

WIN Tricky Crosswords, Jingles, Etc. Green, 25 East, Red Bank, N. J.

47 DETECTIVES

DETECTIVE Training. Phillips Secret Service Systems, 1917-C North Kenneth, Chicago 39, Ill.

DETECTIVES—Work home—Travel Experience unnecessary. Detective Particulars free. Write Wagoner, P-125 West 86th, New York 24.

DETECTIVE Profession. Home Study Badge Certificate Future. 4547-C York, Los Angeles 41, Calif.

DETECTIVE Course. Credentials Diploma. Free Information. Southwestern Institute of Criminology, 619-B Iowa, Geronimo, Oklahoma.

48 LANGUAGE OUTFITS

INTERLANGUAGE approved by Unesco. Teach each other. \$1.25c Esperanto. Dept. PS, Middleton, Wis.

49 GIFTS

"APACHE Tears" Arizona natural black stone pendant. Sterling silver, \$1.75. Tax postage included. Helix Enterprises, Box 124, Spring Valley, California.

FAMOUS Handpainted Delit Windmill Table Lights From Holland. 7"—\$3.95, 9"—\$4.95, 17"—\$7.95. Nov-Ban, Bowling Virginia.

51 SPECIAL SERVICES

PERSONALIZED address labels. Free samples. Charles Diamond, 55 Larkspur Ave., Merrick, N. Y.

COUNSELLING—Budgets Debts. Invest merit. Submit Data Family \$15.00. Small Businesses \$25.00. Norman, Box 147, Hancock Michigan.

52 AUTHORS SERVICE

WANT Your Book Published? Learn how we publish, advertise, promote, distribute. Many successes. Free booklet PS, Vantage, 120 West 31, New York.

WANT your book published? Details Free. Pan Press, Tahlequah 3, Oklahoma.

53 ADVERTISING, AGENCIES, ETC., FOR ADVERTISERS

FREE expert assistance for mailorder advertisers. Ratebook leading newspapers, magazines. 10c. Chicago Advertising Agency 28 E Jackson, Chicago 4.

FREE Red hot book. More Profit From Your Advertising. Lists best Mail Order Magazine Newspapers. Advertiser, 518A Cornelia, Chicago 12.

NOW Available Amazing new booklet. How to Make Money Through Classified Advertising. This booklet is must reading for all mail order men. It tells you what where when and how to advertise. Contains scores of valuable hints on buying ads, writing copy, analyzing results, etc. If you advertise now or ever plan to, don't fail to study this booklet. For your copy just send .0c to cover postage and handling to O K Kelly Classified Adv. 3 or Dept. 328 Popular Science 355 Lexington Ave. New York 17, N. Y.

SOMETHING to sell? Write us about it and let us help you with a classified ad which will reach 7 million potential customers in the classified Opportunities section of this magazine. Include literature or samples if possible. Write today to O K Kelly, Classified Adv. 3 or Popular Science Monthly, 355 Lexington Ave., New York 17, N. Y.

54 ART INSTRUCTION, CARTOONING, SIGN PAINTING

"HOW to Make Money With Simple Cartoons"—A book everyone who likes to draw should have. It is free. No obligation. Simply address Cartoonists Exchange, Dept. 198 Pleasant Hill, Ohio.

LEARN Sign Painting. Fascinating System. Straley, 418-F South Western, Springfield, Ohio.

CARTOONING—good money in fields of Television Advertising Animation Movies. Magazine Famous System of Manual Training brings amazing new concept of art instruction at home. For profit or pleasure. Send for free details. Continental Schools, Dept. E 11 4201 S Broadway, Los Angeles 17, Calif.

CARTOONERAMA Teaches you cartooning in a new 24 Lesson Course. Free. B. Shore CPA, Box 28033, Branford, Connecticut.

SURE You Can Draw Portraits Of Relatives And Friends. Make Money Too With Our Don Snyder's "Art-Aids." Write Him 520 North Paulina St., Chicago 23, Ill.

56 RUBBER STAMPS & OFFICE SUPPLIES

FOUR line deluxe metal pocket stamp \$2.00; four line pocket, \$1.00; four line cushion handle \$1.00. Remora R. Box 6, 2175 East 12th Street, Brooklyn 33, N. Y.

BUY Rubber Stamps Wholesale. Send For Free Specimen And Price Catalog. Star Stamp, 746 South Wells, Chicago, Illinois.

QUALITY Pocket (self-inking) 3 or 4 lines \$1.00; deluxe (metal) \$2.00. Free literature. Adirondack Printers, Tupper Lake 2, New York.

FREE literature. Rubber Stamp Service, 108 North Hyatt Street, Tipp City, Ohio.

FREE Catalog Rubber Stamps, Business Cards, Printing. Martins 1425 Major Drive, Jefferson City Missouri.

FREE Rubber Stamp Catalog. Signature Stamps \$1.40. Free Printing Catalog. Youngers Stamp Shop, Princeton Iowa.

DELUXE Rubber Stamps, \$1.00. 1000 Name-Address Stickers, \$1.00. Prompt Service! Catalogue Johnson, 443 McDonough, Brooklyn 33, N. Y.

RUBBER Stamp—Free with \$5.00 order or more. Write for Price List. Kays, P.O. Box 10331, Riviera Beach, Fla.

THREE line pocket rubber stamp, self-inking, \$1.00. L. Watson, P.O. Box 162, St. Charles, Illinois.

THREE line pocket stamp with pad or office type, \$1.00. W. Atherton, Box 51, Randolph, Massachusetts.

57 PRINTING, MULTIGRAPHING, ETC.

1,000 BUSINESS Cards. "Raised Letters" \$3.95. Samples Pioneer, P88, Island Park, New York.

FREE Catalogs. Postpaid printing. Rubber stamp. D. M. Press. Schenectady, Calif.

100 EACH Printed 4 1/2 Envelopes, 5 1/2 x 3 1/2, Letterheads—\$2.35. M. Fortney, R3, Dillsburg, Pa.

LETTERHEADS, Circulars, etc. Price list. Valatta, 1705 South 2nd, Phila. 10, Pa.

1,000 GUMMED Name & Address Labels \$1.00. Perle's, Essex, Mass.

HIGH Quality Printing. Lowest Prices. Free Samples. Tuff 4378-S Viola, Phila. 4, Pa.

1,000 NAME Address labels 8c. Rubber pocket stamp 18c. Printing Rubber stamp catalog. Jordan's, 833 West O'Connor, Lima, Ohio.

MIMEOGRAPHING Offset Printing. Free samples. Pennaway, Drawer 1140, Scranton, Pa.

1,000 BUSINESS Cards (embossed) \$3.95. Samples. Thompson, 18105 Delroy, Cleveland 28, Ohio.

PERSONALIZED Stationery. Printed 100 \$1.98. Letterheads .100 \$1. Envelopes, \$2.35. DRJ Studios 1811 W. Lowell Avenue, Chicago 39, Illinois.

MIMEOGRAPHING—Offset Printing. Lowest Prices. BSB, 4732 So. Campbell, Chicago 29.

58 PRINTING OUTFITS, SUPPLIES

RUBBER Stamp Presses, Hydraulic Operated. Electrically heated. Sizes 8"x8", 8"x12", 10"x12" starting outfits, supplies. Printing Presses, Custom Manufacturing, 807 N. Jefferson, Springfield 2, Missouri.

PRINTING Outfits, type, supplies. Send dime for illustrated supply book and samples. Kelsey, Inc., E-S, Meriden, Conn.

PRINTING Presses, Type, Supplies. Lists & Turnbaugh Service, Mechanicsburg, Pa.

RUBBER Stamp Presses, Supplies. Write 3036 Barney Road, Kalamazoo, Michigan.

FOUNDRY cast type and supplies for printers and rubber stamp makers. Satisfaction guaranteed. Send \$1.00 for big 66 page catalog and printers' tweezers. Send this when first order. Acme Foundry, 433 Plymouth Court, Chicago 6, Ill.

MAKE Your Own self-molding rubber stamps and printing gals. Flexastamping, Argyle 2, Wisconsin.

TYPE case catalog. Manufacturer, King McKay Company, 22179 Telegraph, Southfield, Michigan.

60 FOR INVENTORS

WE have the markets if you have the ideas. Harvey Engineering, Cambridge 1, Maryland.

INVENTORS If you have an invention for sale, patented or unpatented, write in duplicate of American Inventors, Dept. 28A, 435 F St. N.W. Washington 4, D. C.

INVENTIONS needed immediately for manufacturers. For additional information write Kessler Corporation, C-78-FL, Fremont, Ohio.

INVENTORS Save time and money. Prepare and file your own patent application. Our complete Patent Kit makes it easy. Includes detailed instructions and all necessary material. Only \$8.95. Money back guarantee. Don't delay. Send check or money order today to National Inventors Service, Box 88, Ben. Franklin Station, Washington, D. C.

PATENT Drawings. Your Inventions Made So. Our Expert Illustrators At Reasonable Cost. Patent Service Associates, Haverhill, New Hampshire.

WRITE for information about our new concept in developing and promoting ideas and inventions. Taylor-Garner Corp., 1113 Hraley Bldg., Atlanta 3, Georgia.

POPULAR SCIENCE OPPORTUNITIES

INVENTIONS Wanted for immediate promotion. Patented, unpatented. Outright cash, royalties. Casco, Mills Building, Washington 5, D. C.

INVENTORS Let us publish description of your issued or pending patents. No charge. Manufacturers constantly seeking new products. Answers go direct to you. Write Inventions Report, 3500 Greenville, Dallas 6, Texas.

PATENT Searches including copies of nearest patents. \$4.00. Rep. is airmail with 24 hours. More than 300 registered patent attorneys have used my service. For free invention protection forms, write Miss Ann Hastings, P. O. Box 178, Washington 4, D. C.

U. S. Patent Office Searches—\$3.00. Free Invention Record. Patents Engineered. Patent Office Searches, 319 Broadway Room 3615 New York.

U. S. Patent Office Former Examiner's Invention Service. Patent Office searches. Free commercial invention evaluation. Cash Royalty on production. Patent engineering development. Free invention protection certificates. George Specter, Licensed Patent Engineer, Woolworth Building, New York.

PROTECT Inventions (ideas without patent). Quare, used. Proten. McNeil 5.00. C. Tyner, 23022 Gault, Canada Park, Calif.

PROFESSIONAL Patent searches. \$5.00 complete with comprehensive report and Official copies of related patents. Prompt dependable Airmail service. For free protective Invention Record Folio and "Information Every Inventor Should Have" write Congress Invention Institute, 1142 McKim Building, Washington 6, D. C.

PATENT Searches. \$5.00. complete with comprehensive report and Official Patent Office copies of related patents. Certified. Airmail. For free Invention Protection Form and Patent Information write U. S. Invention Service Bureau, Headquarters Building, Washington 5, D. C.

PATENT Searches including complete copies of related patents. \$4.00. Invention attorneys. Manufacturers use my service. World Wide Airmail service. Proof of Invention protection forms and Information Every Inventor Needs sent free. Miss Jane Hayward, 1629 Vermont Avenue N. W. Washington 5, D. C.

SAVE High fees! Apply for your Patent yourself. New Do-It-Yourself Patent Kit. Now makes it easy. Free Kestrel and Form. Miss Suzanne Blaine, 304 Carry Building, Washington 6, D. C.

PATENTS Skillfully Prepared for maximum commercial value with useful product development. High record of success in proving and claiming patentability. Valuable market service. Patents prepared and filed for service fee as low as \$10.00. Send for self protecting Invention record forms free. Patent search with valuable engineering report \$15.00. Foreign patents filed at lower cost. Thirty Years established. Joseph O'Brien, Patent & Development Engineer, 132 Nassau Street, New York 38, N. Y.

INVENTORS! Sell your invention for cash or royalties! Our client manufacturers constantly seeking new items. Patented. Unpatented. For free information write Gilbert Adams, Patent Broker, 30 Wall St., Financial District, New York, N. Y.

PATENTS Professionally Prepared for maximum commercial value. Patent Searches including report \$4.00. Patents prepared as low as \$10.00. Valuable market service with cash or royalty sales. 10 years dependable service. For free self protecting Record of Invention forms write M. Lawrence Blaisius Patent and Development Engineer, 15 Park Row, New York 38, N. Y.

INVENTORS Consider our offer first before selling or licensing your invention on a cash or royalty basis. Patented. Unpatented. Write Invention on Demand, 75 Wall Street, New York 5, N. Y.

DON'T pay high fees! Obtain U. S. Patent yourself. It's easy with Professional Kit with Fill-In Forms. Free Registration Form. Patent Protection Institute, 15 Park Row, New York 38, N. Y.

PATENT Searches including full airmail report and complete patent copies. \$4.00. Quality searches. Expertly administered. Free protection forms. Write Professional Patent Office Search Bureau, 700 Albee Building, Washington 5, D. C.

PROFESSIONAL Searches of the Patent Office. Dependable—Reliable \$6.00 including airmail report and related patents. For free protection forms write—Trans-World Patent Service, 308 Walker Building, Washington 5, D. C.

INVENTORS! Outright cash sale or royalties for your inventions. Patented. Unpatented. Constant demand from our clients. Manufacturers. Write United States Invention Brokerage, 75 Wall Street, New York 5, N. Y.

INVENTORS! Searches of the Patent Office. Administered Professionally. \$4.00 including airmail comprehensive report and related patent copies. For free Invention Protection Forms. Dependable Service. Write Washington Patent Office Search Bureau, 1426 G Street, N. W. Washington, Washington 5, D. C.

PATENTS professionally prepared. Quality work at lowest prices. Established 1923. Adams, 15 Park Row, New York City.

61 INVENTIONS WANTED

INVENTORS Hundreds of manufacturers have requested our assistance in locating marketable new products. Complete information free. Instructions of Agents. Invention Dept. 30C, 434-F Street, N. W. Washington 4, D. C.

ARE you interested in offers from reliable manufacturers for your invention? Patented, unpatented. Harvey Engineering, Cambridge, Maryland.

INVENTIONS wanted. Patented, unpatented. Tremendous Manufacturers line. Global Marketing Service, 3420 7th, Oakland 5, Calif.

INVENTIONS wanted immediately for promoting on cash or royalty. Patented, unpatented. Free booklet outlines royalty rates, requirements. Write Kestrel Corporation, C-75 1W, Fremont, Ohio.

NAMES of Manufacturers Wanting Invention. Burside, Dept. 107, Box 1682, Rapid City, South Dakota.

INVENTIONS Wanted for immediate promotion! Patented, unpatented. Outright cash, royalties! Casco, Mills Building, Washington 5, D. C.

INVENTIONS Promoted For Cash. Royalty Sales with Manufacturer. Charles George Specter, Licensed Invention Engineer, Woolworth Building, New York.

WANTED Inventions all kinds, patented or unpatented, Engineer, Box 113, Hampton, N. H.

CASH or royalties for Inventions! Consider our offer first before licensing or selling your patented or unpatented invention. Write—A. Edwin Industries, 30 Wall Street, New York 5, N. Y.

INVENTORS! Sell your invention for cash or royalties! Our client manufacturers constantly seeking new items. Patented. Unpatented. For free information write Gilbert Adams, Patent Broker, 30 Wall St., Financial District, New York, N. Y.

INVENTORS! Consider our offer first before selling or licensing your invention on a cash or royalty basis. Patented. Unpatented. Write Invention on Demand, 75 Wall Street, New York 5, N. Y.

INVENTORS Needing Help with any problem, financial, development, securing manufacturer, obtaining patent. Write the organization that delivers action and results. Not promoters. Pioneer Invention Institute, 136 Broadway, New York, 38, N. Y.

INVENTORS! Outright cash sale or royalties for your inventions. Patented. Unpatented. Constant demand from our client manufacturers. Write United States Invention Brokerage, 75 Wall Street, New York 5, N. Y.

INVENTORS Want to sell your invention for cash or royalty? Write Allen Dept. D, 3100 So. Buckner, Dallas 27, Texas.

HIGHEST Cash, Royalties, Inventions. Learn what's needed, protect, sell. Inventions Creative Service, P. O. Box 154 South Spring, Los Angeles 11, California.

INVENTIONS Sold, Licensed, Outright. Royalty basis. Inventions International, 15 Park Row, New York City.

62 PATENTS FOR SALE

GAUGE for 5th nets. easy work making nets & hammocks. stops error with slipper nylon. Newark, 2852 W. 27 St., Newark 24, N. Y.

63 MANUFACTURING

MODEL Building For Inventors. Manufacturing Research. Mechanical. Chemical. Electrical. Weld. Parker, 33 Westminster, Worcester 5, Mass.

64 MODELS, MODEL SUPPLIES

"POWER Drive Handbook"—36 pages. Illustrations. Shows types motor drives for model engine, boats, airplanes, turntables, etc. Mar. 23 cert. cash refundable first order \$1.00 or more. Write of Cleveland, Dept. PS, P. O. Box 8004, Ft. Lauderdale, Fla.

SHIP Models. Most complete line in New England. Also fittings, plans, books, etc. See motors. Illustrated catalog. 156, James Hill and Co. Inc. Dept. PS, 342 Atlantic Avenue, Boston 18, Massachusetts.

SHIP and yacht model fittings, blueprints. Send 40¢ for illustrated catalog listing hundreds of items. A. J. Fisher, Inc., 1902 E. Atowan Ave., Royal Oak, Michigan.

LIVE Steam Engine Castings, Fittings. Plans Catalog 20¢. Ship Models Ltd. Vancouver, B. C.

CASTINGS and finished Steam and engine parts. Full size. 1/2 size. 1/4 size. 1/8 size. Finest materials and fittings. Catalog \$1.00. Denison Live Steam Models, 1404 Denison Ave., Cleveland 9, Ohio.

SHIP Model Kits and fittings; clippers, frigates, etc. 1/4 size. 1/8 size. 1/16 size. 1/32 size. Model Shipways, Box 65, Norwalk, New Jersey.

POWER Models. Unusual Steam Gasoline and Turbine Engines. Plans, Kits, etc. 13 Years Model Business. Reasonable. Catalog \$1.00. Charles Cow Venture, Calif.

MODEL Engineering Supplies. Plans. Castings. Books, tools, fittings. Ignition coils. Boiler kits, etc. Largest selection of model gasoline and steam engine castings kits. Illustrated catalog only 25¢.ature Models, Dept. A, 8148 N. Milwaukee Ave., Niles 48, Ill.

MOCKET supplies 1961 catalog now available 20¢. Sky Mfg. Co. Mineral Point, Pa.

65 HOME CRAFTSMAN

POUNDRYPTTE 2400" P. 17, 18 48 lb capacity. Free Circular. Kansas City Specialties Co., P. O. Box 11, Dept. 8-8, Wymore, Nebr.

FREE Do It Yourself Leathercraft Catalog. Tandy Leather Company, Box 791, R41, Fort Worth, Texas.

FREE Sample Perma-Flex new one coat concrete formula. Cures in moisture. Problems on base & brick. Stucco, stone, etc. is added and a 1/2 inch wide trim is added to your home. Less than one cent per square foot applied. Perma-Stone Co., Desk 18, Columbus 11, Ohio.

FREE New Catalog. 3447 Plans, Patterns. World's greatest selection things to do. Make. Fun. Profit. Craftplans, 1222-B Wabash, Chicago 5.

101 PATTERNS of smart Gifts, Novelties, Shelves, Action windmills plus "Make Money Jig Sawing" \$1.00. Mastercraft 358, 7041 Oakliff, Chicago 31.

GRANDFATHER clock movements, case plans, kits. Catalog 25¢. Mason Sullivan, Noroton 2, Conn.

This One



96YA-L2Q-JKGY

POPULAR SCIENCE OPPORTUNITIES

WOODWORKING Catalog and Manual. Brand New 150th Anniversary Edition! World's largest selection of domestic, imported woods—materials, tools, supplies, do-it-yourself plans, projects. 133 pages, many full color. More than 2,000 items. Send 25c for postage and packing. Act now! Constantine, 3050 Eastchester Road, Dept. M-102, New York 61, N. Y.

LEATHERCRAFT catalog. Hundreds of new items. Write MacPherson Bros. Leather Company, Dept. A, 730 Mission St., San Francisco 3, Calif.

SQUAREKNOTTERS: Make belts, handbags, lanyards, dog leashes, etc. Special offer! Beginner's book, catalog and quality cord samples 25c. P. C. Herwig Co., Dept. 71-P7, 39 Henry St., Brooklyn 1, New York.

KNOCKDOWN cedar chest and lumber. Catalog 25c. Bedford Lumber Company, Shelbyville, Tennessee.

PICTURE Frame Moulding, Squares and lumber. Kiln Dried Walnut, Cherry, Silver Maple, Midland Lumber Co., Box 262, Savannah, Mo.

66 DO IT YOURSELF

NEW Arc Welding Method! 1/16"-1/8", Plate, 30-45 Amperes. Hobbyists, Mechanics. Equipment Locally Under \$5.00! Assembled 5 Minutes! No Skill Required. Discovered By Electrical Engineer. Details \$1.00. McWhirter, Box 447, East Pittsburgh, Pa.

BUILD Automatic Garage Door Opener. Proven Design. No special tools required. Plans, Instructions, \$1.00. Robert's Design Company, 3920 Eighth Street, Muskegon Heights, Michigan.

RESILVER mirrors; plate. Literature catalog 25c. Microcrafts, 18514 Winthrop, Detroit 35.

"ART Of Making Whiskies", Complete Instructions \$2.00. Dominas, Box 584, Fort Wayne, Ind.

"35 HOMEMADE Recipes", Beers, Wines, \$1.00. Dominas, Box 584, Ft. Wayne, Indiana.

67 OLD GOLD, JEWELRY, WATCHES, ETC.

USED and new watches \$3 up. Free Catalogue. Southern Watches, 8-PS 8c, Wabash, Chicago 3.

HIGHEST Cash For Old Gold, Jewelry, Gold Teeth, Watches, Diamonds, Silverware, Spectacles, Platinum, Mercury. Free information. Rose Refiners, Heyworth Bldg., Chicago 2.

COSTUME Jewelry Supplies. Settings, Rhinestones, etc. 38 page illustrated catalog. 30c. Milady, Box 1228 G.P.O., New York (1).

HIGHEST Cash Paid for Old Gold, Jewelry, Gold Teeth, Rings, Diamonds, Watches, Silver, Platinum, Mail Articles Today. Information Free. Chicago Gold Co., 6 E. Monroe, Dept. 3157, Chicago 3.

WE Buy It! Gold, Silver And Platinum Scrap. Send It To Electro Company, 1043 Highland Avenue, Buffalo 23, New York.

SWISS watches, all kinds, fabulous import prices, 17 jewel calendar, \$12.48. Send \$1.00 for complete catalog (refundable). Olympic Imports, 40 Oakridge Drive, Binghamton, N. Y.

68 TOBACCO & PIPES

100 PIPE Cleaners 50c. King, 330 Alexander, Kamloops, B. C., Canada

70 OF INTEREST TO WOMEN

LEARN Candle Making—Decorating at home. Send for free facts on famous Home Study Course. Candle, Dept. X-504, Fallbrook, Calif.

HOME Typing: \$45 week possible! Details, \$1. Treasury, 700 Webster, New Rochelle PS-8, N. Y.

EARN a good income typing at home! Detailed information \$1. Refundable. Rycro Service, 310-Q Fifth Ave., Suite 1103, New York 10, N. Y.

LADIES: Earn up to \$2.00 hour sewing babywear! No house selling! Send postcard to Cuties, Warsaw 14, Indiana.

DRESSES 24c! Shoes 39c! Men's suits \$4.95; trousers \$1.20. Better used clothing. Free catalog. Transworld, 164-H Christopher, Brooklyn 12, N. Y.

71 FOR SALE MISCELLANEOUS

JUST Out! 354-page catalog—save to 50% on auto parts, accessories. All makes, models. Send 25c—refundable on first order. Whitney, 1918 EB-8 Archer, Chicago 16.

72 WANTED TO BUY

WANTED, gold, silver, platinum, scrap (any form), coins. Information free. Wilmet's, 1087-PS Bridge St., Grand Rapids 4, Michigan.

QUICKSILVER, platinum, silver, gold. Ores analyzed. Mercury Terminal, Norwood, Massachusetts.

OLD Copies of Popular Science wanted—any issue from 1890 to 1915. Condition not too important provided books are complete with no pages removed. Write to Room 531, 353 Lexington Avenue, New York 17, N. Y.

77 TREASURE FINDERS & GEIGER COUNTERS

TRANSISTOR Treasure Detectors, underwater detectors. Many models. Free catalog. Gardiner Electronics Co., Dept. 1, 25-45 East Indian School, Phoenix, Arizona.

DISCOVER buried loot, sunken treasure, gold, silver, coins; battlefield and ghost town relics, with powerful transistorized locators pioneered and perfected by Goldak. Low as \$79.50. Free, exciting information; literature on maps. The Goldak Co., 1540 West Glenoaks Blvd., Glendale 1, California.

TRANSISTOR M-Scope locates buried coins, gold, relics. From \$58.50; terms. Booklet, interesting customer comments free. Fisher Research, Dept. D-1, Palo Alto, Calif.

SCIENTIFIC Gift for teenagers and adults. Electronic Treasure Finder—Easy to make kit or assembled models available; Geiger Counters and Mineralights. Free Literature. Electronic Applications Co., Dept. C, P. O. Box 8, Arlington 10, Virginia.

78 WATCH REPAIRING

WATCH and clock repairing books. Free catalog. North American, 3320-BK, Milwaukee, Chicago 47, Illinois.

WATCHES repaired, cleaned, \$3.95 guaranteed. Lan's, 17 South Center, American Fork, Utah.

79 MISCELLANEOUS

WESTERN powerful wine beer formulas \$1.00. Bufta, Box 354, Lyons, Kansas.

"HOMEBREW Guide" illustrated instruction Manual, \$1.00. Hydrometers \$3.85 up. Free Catalog. Calbrew Supplies, 1226-G Luzern, Seaside, California.

MAKE Wines, Brandies, Cordials, Beer. Full Instructions. Trade Secrets \$1.00. Rorick, Cincinnati 26, Ohio.

PLAY that new card game Speculation. Special Cards and rules \$2.00. S.P.S. Co., Box 241, Columbus, Nebr.

FREE Catalog. Your family health needs. Bishop's Health Products, Box 704-E, Ojai, California.

RECEIVE Mails—Offers From Everywhere. Samples, Catalogues, Magazines, Bargains. Get Listed 25c. Rorick's, Cincinnati 26, Ohio.

STOP Leaky Faucets \$1. Details Free! River Sales, P. O. Box 301, Hatboro, Pa.

UNUSUAL Books—Every Subject! 10c up! Catalogs Free! Mailway, Box 124, Stuyvesant Sta., N.Y.C. 9.

DANDRUFF? Read Experiment using materials already found in most households. Send stamped self addressed envelope and 50c to Dandruff Experiment, P.O. Box 88, Crum Lynne, Pa. Refund within 15 days if dissatisfied.

HYDROMETERS for beer making. Free recipe and price list. Specialty Products, P.O. Box 462, Eugene, Oregon.

"HOMEBREWED Wines, Beers." Highest powered Instructions—\$1.00. Testers (Hydrometers)—\$3.85. Dean's, 188-PS West 42nd, New York 36, N. Y.

RECEIVE Mailorder. Hobby Magazines, Catalogs, Opportunities, 10c. Starr, Adkins, Texas.

COOKS: Make perfect meat balls in seconds—without handling the meat! Aluminum meat ball mold has scissor-action handles; forms a 1 1/2 inch ball between two vented molding cups. \$1.00. Bentley, 1435 Frances Road, San Pablo, California.

ELECTRONIC police radar detector gives advance warning of radar zones. Free information. Dee Company, Box 7263, Houston 2, Texas.

79A WESTERN MERCHANDISE

HANDMADE Western Boots. Free Catalog. Yuleta Boots, 815B Yuleta Station, El Paso, Texas.

79B SWAP

READ "Trading Post Magazine" 10c. Thorne's, 525 Dewey, Jackson 35, Michigan.

80 PERSONAL

MEXICAN Legal Matters. A. Kapejo, Box 317-F, Tijuana, Mexico.

LOANS by mail, \$100-\$400. Anywhere. Confidential. Write Union Finance, Dept. PS, 323 E. Camelback, Phoenix, Arizona.

WANT beautiful girl friend? Win: Popularity! Confidence! Dates! Exciting book offer. Write: Guide, Box 363-83, Mohagan Lake, New York.

LOSING Hair? Balding? Dandruff? Free Authoritative Information. Dr. Shiffer's Laboratories, Suite 235C, 1110 Euclid, Cleveland 15, Ohio.

MEXICAN legal Matters. F. Flores, Box 637, Cd. Juarez, Mexico.

"RULE Others with your Thoughts." Telepathy. (Adults.) Write: Clarion, Box 8300-58, Chicago 99.

TWO "Will" Forms and "Booklet on Wills", \$1.00. National, Box 48313H, Los Angeles 48, Calif.

"WHO, Me?" Yes, you! Surprising new facts on how to get what you want in life—sent free. Rush request to: President, Box 1924-O, Louisville 1, Ky.

MEXICAN Law. Attorney Centocron, Apto. 79-Cd. Juarez, Chih., Mexico.

SUPER memory overnight! Success guaranteed! Bijou, Box 1727-V, Hollywood 28, Calif.

80A REMAILING SERVICE

LETTERS Forwarded 25c. \$1.00 forwards your letter and we remain one answering letter to your return. Two-Way Remails, Box 840, Blinnett, Texas.

NEW YORK City confidential remails, 25c. Receiving, forwarding, \$3.00 monthly. Reiss, P.O. Box 129-E, New York 18, N. Y.

SECRET Mail Address. \$3 Month. Hedgpath, Box 630, Alhambra 24, California.

REMAILS, Confidential, 25c. \$2.50 monthly. De Graff, 9763 Innadale, Spring Valley, California.

LETTERS remailed from important, historic, Washington, D. C. 25c each, P.O. Box 7812 Benjamin Franklin Station, Washington, D. C.

FLORIDA Confidential Address \$2.50 per month, remails 25c. Box A-853, Ft. Lauderdale, Florida.

80B LOANS BY MAIL

BORROW \$100 to \$400 by Mail. Quick, Easy, Private. No Co-Signers. Repay in 24 small monthly payments. For the amount you want write today to Dial Finance Co., 410 Kilpatrick Bldg., Dept. I-1, Omaha 2, Nebraska.

NEW! Borrow \$500. Anywhere. Increased Loan Limit. Air Mail Service. Postal Finance, 374 New Brotherhood Building, Dept. 11B, Kansas City, Kansas.

LOANS By Air Mail, \$100 to \$500. Anywhere. Confidential. Write Security Finance Co., 898 Van Ness Avenue, Dept. PS, San Francisco 8, California.

MAIL Loans—Borrow \$50-\$500 confidentially. Repay 34 small monthly payments. State Supervised. Write: World Finance Co., Dept. 81-J, 620 Symes Bldg., Denver 2, Colo.



IT TAKES A REAL MAN TO WIN AN I.C.S. DIPLOMA!

Here's training for the man who can take it "straight"—without the fancy trimmings.

With I.C.S., your "classroom" is your home. Your "laboratory" or "shop" is the place you work. Every minute you spend is productive—no commuting, no long-winded discussion groups, no waiting for slower students to catch up.

You gauge your progress not by marks and grades alone but by pay boosts and promotions. And these are likely to come fast.

This is the most demanding kind of training. You select your own subjects, set your own pace, apply what you learn to your own specific needs—all while holding down a full-time job and possibly supporting a family.

Is it any wonder that men who can win I.C.S. diplomas often turn out to be leaders in their fields? I.C.S. has more of its former students now in supervisory and management positions than any other school.

It takes a real man to win an I.C.S. diploma. And the first step is mailing the coupon. Such a simple act sounds easy. Actually, it's the one thing that separates the "planners" from the "plodders." If you're the man we think you are, you'll mail the coupon NOW.

For Real Job Security—Get an I. C. S. Diploma!

I. C. S., Scranton 15, Penna.

Accredited Member,
National Home Study Council

INTERNATIONAL CORRESPONDENCE SCHOOLS



BOX 97065J, SCRANTON 15, PENNA.

(In Hawaii, reply P.O. Box 418, Honolulu)

(Partial list of courses)

Without cost or obligation, send me "HOW to SUCCEED" and the opportunity booklet about the field BEFORE which I have marked X (plus sample lesson):

ARCHITECTURE and BUILDING CONSTRUCTION

- ☐ Air Conditioning
- ☐ Architecture
- ☐ Arch. Drawing and Designing
- ☐ Building Contractor
- ☐ Building Estimator
- ☐ Carpenter Builder
- ☐ Carpentry and Millwork
- ☐ Heating
- ☐ Painting Contractor
- ☐ Plumbing
- ☐ Reading Arch. Blueprints

ART

- ☐ Commercial Art
- ☐ Magazine Illus.
- ☐ Sign Painting and Design's
- ☐ Sketching and Painting

AUTOMOTIVE

- ☐ Automobile
- ☐ Auto Body Rebuilding and Refinishing
- ☐ Auto Engine Tuneup
- ☐ Auto Electrical Technician
- ☐ Diesel Engines

AVIATION

- ☐ Aero-Engineering Technology
- ☐ Aviation English Read.
- ☐ Reading Aircraft Blueprints

BUSINESS

- ☐ Accounting
- ☐ Advertising
- ☐ Bookkeeping and Cost Accounting
- ☐ Business Administration
- ☐ Business Management
- ☐ Clerk Typist
- ☐ Creative Salesmanship
- ☐ Managing a Small Business
- ☐ Professional Secretary
- ☐ Public Accounting
- ☐ Purchasing Agent
- ☐ Real Estate Salesmanship
- ☐ Salesmanship
- ☐ Salesmanship and Management
- ☐ Traffic Management

CHEMICAL

- ☐ Analytical Chemistry
- ☐ Chemical Engineering
- ☐ Chem. Lab. Technician
- ☐ General Chemistry

- ☐ Oil Field Technology
- ☐ Pulp and Paper Making

CIVIL ENGINEERING

- ☐ Civil Engineering
- ☐ Construction Engineering
- ☐ Highway Engineering
- ☐ Professional Engineer (Civil)
- ☐ Reading Struc. Blueprints
- ☐ Sanitary Engineer
- ☐ Sewage Plant Operator
- ☐ Structural Engineering
- ☐ Surveying and Mapping
- ☐ Water Works Operator

DRAFTING

- ☐ Aircraft Drafting
- ☐ Architectural Drafting
- ☐ Drafting & Machine Design
- ☐ Electrical Drafting
- ☐ Electrical Engineer Drafting
- ☐ Industrial Piping Drafting
- ☐ Mechanical Drafting
- ☐ Sheet Metal Drafting

ELECTRICAL

- ☐ Electrical Appliance Servicing
- ☐ Electrical Engineering

- ☐ Electric Motor Repairman
- ☐ Elec. Engr. Technician
- ☐ Elec. Light and Power
- ☐ Practical Electrician
- ☐ Practical Lineman
- ☐ Professional Engineer

HIGH SCHOOL

- ☐ Good English
- ☐ High School Diploma
- ☐ High School General
- ☐ H. S. College Prep. (Eng'g & Science)
- ☐ High School Math
- ☐ High School Science
- ☐ Short Story Writing

LEADERSHIP

- ☐ Industrial Foremanship
- ☐ Industrial Supervision
- ☐ Personnel-Labor Relations
- ☐ Supervision

MECHANICAL and SHOP

- ☐ Diesel Engines
- ☐ Gas-Elec. Welding
- ☐ Heating and Air Conditioning
- ☐ Industrial Engineering
- ☐ Industrial Instrumentation

- ☐ Industrial Safety
- ☐ Machine Shop Practice
- ☐ Mechanical Engineering
- ☐ Plumbing and Heating
- ☐ Professional Engineer
- ☐ Quality Control
- ☐ Reading Shop Blueprints
- ☐ Refrigeration and Air Conditioning
- ☐ Tool Design ☐ Tool Making

RADIO, TELEVISION

- ☐ General Electronics Tech.
- ☐ Industrial Electronics
- ☐ Practical Radio-TV Eng'g
- ☐ Radio-TV Servicing
- ☐ TV Technician

RAILROAD

- ☐ General Railroad

STEAM and DIESEL POWER

- ☐ Combustion Engineering
- ☐ Power Plant Engineer
- ☐ Stationary Diesel Engr.
- ☐ Stationary Steam Engines

TEXTILE

- ☐ General

Name _____ Age _____ Home Address _____
City _____ Zone _____ State _____ Working Hours _____ A.M. to P.M. _____
Occupation _____
Canadian residents send coupon to International Correspondence Schools, Canadian, Ltd., Montreal, Canada. . . . Special low monthly tuition rates to members of the U. S. Armed Forces.

CHIEF
44 Color
Pattern


Wave
Reversib
for Doub
Wear
Luxu

An
Size
A Wee

Have Better
RUGS
& Wall to Wall
CARPET
The Famous
OLSON
MAGIC WAY

Like Millions of Olson Customers, You, Too, Can
SAVE UP TO 1/2—FACTORY-TO-YOU
Send Us Your Old Rugs, Carpets, Clothing

FREE Beautiful New OLSON Catalog in
Color, Model Rooms—Gift Coupon



I GUARANTEE to send you the
finest, longest-wearing Broad-
loom Rugs or wall-to-wall Car-
peting you ever had for so little
money. You can send your ma-
terials AFTER your rugs arrive.
Walter E. Olson, Pres

This "Business Reply"-coupon requires NO stamp
or envelope. Please write name and address clearly
in space provided—then cut out and drop in mailbox. Pay no atten-
tion to printing on back of coupon.

Write Your Name and Address — Cut Out and Mail

FROM:—

YOUR
NAME

ADDRESS

TOWN STATE

FIRST CLASS
Permit No. 66
Chicago, Ill.

BUSINESS REPLY MAIL
NO POSTAGE STAMP NECESSARY IF MAILED IN THE UNITED STATES

6¢ Postage Will Be Paid By—
OLSON RUG CO. Dept. P-11
2800 N. Pulaski at Diversey

Catalog
Division

Chicago 41, Illinois

By the Famous Olson Process, the good-
seasoned materials in customers' discar-
ed carpets, rugs, clothing are scientifi-
cally reclaimed like new, sterilized,
bleached, merged, re-dyed—then respu-
with choice new materials and woven
Within One Week into the loveliest, de-
textured, *permanently Moth-proofed* Re-
versible Broadloom Rugs or Carpeting
you have ever seen for so little money.

MAIL TODAY! WE
PAY THE POSTAGE

NO RISK OFFER: Send materials at no
expense. Satisfaction guaranteed. Monthly
payments if you wish. Our 87th year.

LOVELY NEW COLORS, PATTERNS
Any size you want in a
week—up to 38 feet
wide, seamless, any
length, 19 width looms.
No wasted yardage.
Smart TWEEDS
Solid Colors
Textured Effects
Early American
Oriental Designs
Modern
Casual
Floral
Scrolls
Ovals

OLSON RUG CO. Chicago New York San Francisco

AMAZING 5-IN-1 POWER TOOL!



SCROLL SAW



SANDER



SHAPER



POWER PLANE

Porter-Cable Model 155 Router

A heavy-duty job, too! Rugged 4-amp., ball-bearing 23,000-RPM power pack specifically designed to power this unit as a Router, Power Plane, Shaper, Scroll Saw, or Finishing Sander. You change from one tool to another in just **seconds** . . . and **save** the cost of 4 complete motor units! Why it's practically a whole toolshop. Get an exciting demonstration of what **you** can do with it today. Your Porter-Cable dealer will give you a free 10-day home trial!

FREE CATALOG shows the complete line of Porter-Cable tools and accessories. Write: Rockwell Manufacturing Company, Porter-Cable Division, N. Lexington Ave., Pittsburgh 8, Pa.

PORTER-CABLE MACHINE COMPANY

Subsidiary of Rockwell Manufacturing Company
Pittsburgh 8, Pennsylvania

In Canada: Porter Cable Ltd., Box 817, Kingston, Ont. Canadian prices slightly higher.

LIMITED OFFER!

\$8.95 SCROLL SAW **FREE**

Yes, until Dec. 24, 1961, your dealer will give you **FREE** a Porter-Cable Scroll Saw attachment (\$8.95 value) with your purchase of an amazing Model 155 Router unit. Does inside, outside curves, cuts openings without a starter hole, contour curves of every kind!

Porter-Cable

another fine product by

ROCKWELL 